

## 6. Electrical Parts List

### 6-1 TXM3298HFX/XAA

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
<b>ASSY CHASSIS</b>				...3	AA97-07229F	ASSY AUTO-WOOFER;CT-29Z7HR,K55A	S.N.A
1	*	AA91-04860P ASSY CHASSIS;TXM3298HFX/XAA		...4	CNW02	3711-002642 CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH	
..2	C-BLOC	6003-000333 SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A	...4	CW01	2401-002216 C-AL;2200uF,20%,35V,GP,TP,16x25,7.5	
..2	D-FOCU	6003-000333 SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A	...4	CW02	2305-000665 C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0mm	
..2	MP+HC	6003-000333 SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A	...4	CW04	2305-000665 C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0mm	
..2	TBA+HC	6006-001095 SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	S.N.A	...4	CW05	2401-000603 C-AL;1uF,20%,50V,GP,TP,5x11,5	
..2	WP+HC	6003-000333 SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A	...4	CW06	2401-000365 C-AL;100uF,20%,50V,WT,TP,10x12.5mm,	
..2		AA94-08584N ASSY PCB MISC-A/V SIDE;TXM3298HFX/XAA,K5		...4	CW07	2401-000603 C-AL;1uF,20%,50V,GP,TP,5x11,5	
...3	CN701	AA39-20071G LEAD CONNECTOR ASSY;K55A/VVT-32Z7HR,UL100		...4	CW09	2301-000289 C-FILM,PEF;5.6nF,5%,50V,TP,7x6x3,5	
...3	CN703	AA39-20069A LEAD CONNECTOR-ASSY;5PYBNH025-05,67096		...4	CW10	2305-000665 C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0mm	
...3	CN704	AA39-00070B LEAD CONNECTOR-ASSY;4PYBNH250-04,35184		...4	CW12	2305-000665 C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0mm	
...3	CPC+CC	6003-001268 SCREW-TAPTITE;TH,+,B,M4,0,L12,0,ZPC(YEL)	S.N.A	...4	EYW01	AA60-40011A EYELET;ID2,0,OD2.8,-,BST,-	S.N.A
...3	JA701	3722-001164 JACK-PIN;3P,3.4mm,SN,WH;YE,RE,#16-22		...4	EYW02	AA60-40011A EYELET;ID2,0,OD2.8,-,BST,-	S.N.A
...3	JK04	3722-000544 JACK-VHS;4P,11.5mm,AG,BLK,N		...4	PCB	AA41-00588A PCB-WOOFER;CT-29M8HR,FR-1,1L,A,1.6T,330X	S.N.A
...3	JKH701	3722-001061 JACK-PHONE;1P,3.6P,AG,BLK,N		...4	RW01	2001-001088 R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
...3		AA96-00918B ASSY COVER P-COVER A/V;34Z7, TXM3298HFX,HI		...4	RW02	2001-001071 R-CARBON(S);12KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4		AA63-00560B COVER-AV;34Z7,HIPS,VO,G4309,DGN-1189		...4	RW05	2001-001050 R-CARBON(S);1.5KOHM,5%,1/2W,AA,TP,2.4X6.	
...4		AA64-02667C INLAY-AV;Z7,PS SHEET,TO.3,DGN-K189,K55A		...4	RW06	2001-000085 R-CARBON(S);100KOHM,5%,1/2W,AA,TP,2.4X6.	
...4		AA97-07229H ASSY AUTO-A/V SIDE;CT-29Z7HR,K55A	S.N.A	...4	RW07	2001-001088 R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
...4	C701	2202-000121 C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP		...4	RW08	2001-001088 R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
...4	C702	2202-000121 C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP		...4	RW09	2001-000085 R-CARBON(S);100KOHM,5%,1/2W,AA,TP,2.4X6.	
...4	C707	2202-000231 C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP		...4	RW10	2001-001146 R-CARBON(S);4.7OHM,5%,1/2W,AA,TP,2.4X6.4	
...4	C708	2202-000231 C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP		...4	RW11	2001-001146 R-CARBON(S);4.7OHM,5%,1/2W,AA,TP,2.4X6.4	
...4	DZ701	0403-000563 DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500m		...3	3301-001201	CORE-FERRITE;AE,21x11x32mm,1500,280G	
...4	DZ702	0403-000708 DIODE-ZENER;MTZJ13B,13V,12.55-13.21V,500		...3	0202-000187	SOLDER-WIRE FLUX;-RS60S,D1.2,63Sn/37Pb	S.N.A
...4	DZ703	0403-000708 DIODE-ZENER;MTZJ13B,13V,12.55-13.21V,500		..2	AA94-11752A	ASSY PCB CRT;TXM3297HFX/XAA,K55A	
...4	L701	2701-000114 INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm		...3	C522	2201-002117 C-CERAMIC,DISC;4.7nF,20%,3kV,Y5U,TP,16x6	
...4	L702	2701-000114 INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm		...3	C523	2301-001192 C-FILM,MPPF;820nF,5%,400V,TP,29x18.5x25.	
...4	L705	2701-000168 INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm		...3	CNC01	3711-003974 CONNECTOR-HEADER;BOX,12P,1R,2.5mm,STRAIG	
...4	L706	2701-000168 INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm		...3	CNC01A	AA39-00088A LEAD CONNECTOR-ASSY;HERCULES,UL1007/1185	
...4	L707	3301-000287 CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,		...3	CNC02A	AA39-20030B LEAD CONNECTOR-ASSY;8P,67096-008,S,400,	
...4	L708	3301-000287 CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,		...3	GT503S	AA39-20010B LEAD CONNECTOR-ASSY;1PYFH800-01,S,500,	
...4	PCB	AA41-00620B PCB-A/V SIDE(Z7);CT-29Z7HR,FR-1,1L,B,1.6	S.N.A	...3	IC501	AA96-50311L ASSY H/S;-AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
...4	R701	2001-000028 R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4		...3	IC502	AA96-50311L ASSY H/S;-AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
...4	R702	2001-000028 R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4		...3	IC503	AA96-50311L ASSY H/S;-AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
...3		3301-001201 CORE-FERRITE;AE,21x11x32mm,1500,280G		...4	1201-001131	IC-VIDEO AMP;6111,SIF9P,-,SINGLE,-,PLAS	
...3		0202-000187 SOLDER-WIRE FLUX;-RS60S,D1.2,63Sn/37Pb	S.N.A	...4	6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
..2	AA94-08584R	ASSY PCB MISC-CONTROL;TXM3298HFX/XAA,K55		...4	AA62-30175D	HEAT-SINK,PS;-SECC,T1.0,-,33X15X30 FT-2	S.N.A
...3	AV+CV	6003-001268 SCREW-TAPTITE;TH,+,B,M4,0,L12,0,ZPC(YEL)	S.N.A	...3	IC504	BH99-00038E ASSY HEAT/SINK;TDA2030,AMP,HERCULES,BH62	S.N.A
...3	CN01	AA39-00100E LEAD CONNECTOR-ASSY;4PYBNH250-04,35155		...4	CIS	0205-001027 OIL-SILICON;G746,-,-	S.N.A
...3	SW01	3404-000176 SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST		...4	CIS	1201-000010 IC-OP AMP;2030,PENTAWATT,5P,-,SINGLE,-,C	
...3	SW02	3404-000176 SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST		...4	BH61-00004A	SPRING-TR;CDA,CDB,SUS304,-,-,-,-,TO.5,	S.N.A
...3	SW03	3404-000176 SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST		...4	CIS	BH62-00041A HEAT SINK-TR;PN17LT,A1050S,T1.0,50,23,-,	S.N.A
...3	SW04	3404-000176 SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST		...3	QF09	AA96-00243M ASSY H/S;-AMP,AA62-000450A,2SA1011,HERC	S.N.A
...3	SW05	3404-000176 SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST		...4	0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
...3	SW06	3404-000176 SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST		...4	0502-000131	TR-POWER;2SA1011-D,PNP,1.2W,TO-220,-,60	
...3		AA96-00920B ASSY COVER P-COVER CONTROL;34Z7, TXM3298H		...4	6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
...4	KC+CC	6003-001019 SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	S.N.A	...4	AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,DREAM,-,-,-,-,	S.N.A
...4		AA63-00559B COVER-CONTROL;34Z7,HIPS,VO,G4309,DGN-118		...3	QF10	AA96-00243L ASSY H/S;-CRT,AA62-000450A,2SC2344,HERC	S.N.A
...4		AA64-02662A KNOB-CONTROL;Z7,ABS,HB,G3676,S104M+W971		...4	0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
...3		AA97-07229G ASSY AUTO-CONTROL;CT-29Z7HR,K55A	S.N.A	...4	0502-000153	TR-POWER;2SC2344-D,NPN,1.2W,TO-220,-,60	
...4	LC01	2701-000114 INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm		...4	6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
...4	PCB	AA41-00618A PCB-CONTROL(Z4);CT-20MH8,FR-1,1L,A,1.6T,	S.N.A	...4	AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,DREAM,-,-,-,-,	S.N.A
...4	RC01	2001-000281 R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		...3	SC01	3722-001503 JACK-PIN;1P,1PI,Ni,RED,SCR-JACK	
...4	RC02	2001-000577 R-CARBON;2KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...3	V999S	3704-001032 SOCKET-CRT;8P,29PI,35.5PI,UA30U	
...4	RC03	2001-000878 R-CARBON;6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C501	AA97-12699B ASSY AUTO-CRT;TXM3297HFX/XAA,K55A	
...4	RC04	2001-000009 R-CARBON;20KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C502	2201-000247 C-CERAMIC,DISC;0.015nF,5%,50V,NP0,TP,5x3	
...4	RC06	2001-000007 R-CARBON;3KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C503	2201-000662 C-CERAMIC,DISC;0.007nF,0.25pF,50V,NP0,TP	
...3		0202-000187 SOLDER-WIRE FLUX;-RS60S,D1.2,63Sn/37Pb	S.N.A	...4	C504	2301-000016 C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
..2	AA94-11567A	ASSY PCB MISC-WOOFER;TXM2798HFX/XAA,K55A		...4	C505	2301-000016 C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
...3	CNW01	AA39-20055B LEAD CONNECTOR-ASSY;6PYBNH025-06,67096		...4	C506	2301-000016 C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
...3	ICW01	AA96-50367D ASSY H/S;-POWER,AA62-30181D,TDA7269,ZES	S.N.A	...4	C507	2301-000016 C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
...4		0205-000129 GREASE-SILICON;SC102,JAPAN	S.N.A	...4	C508	2301-001211 C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
...4		1201-001385 IC-POWER AMP;7269A,ZIP,11,19.6,DUAL,13,P		...4	C509	2301-000016 C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
...4		6003-000333 SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A	...4	C510	2201-000291 C-CERAMIC,DISC;1nF,10%,500V,Y5P,TP,7.5x3	
...4		AA62-30181D HEAT-SINK,ES;-AL6063 EXTR.,2,WHT,70MM,-	S.N.A	...4	C511	2301-001211 C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
...4				...4	C512	2301-001211 C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
...4				...4	C513	2201-000600 C-CERAMIC,DISC;0.56nF,10%,50V,Y5P,TP,5x3	

## Electrical Parts List

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
....4	C514	2201-000599 C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.		....4	LF08	2901-000297 FILTER-EMI ON BOARD;-3A,-,-,3.5x5,TP,-	
....4	C515	2201-000599 C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.		....4	LF09	2901-000297 FILTER-EMI ON BOARD;-3A,-,-,3.5x5,TP,-	
....4	C520	2401-000703 C-AL;2200uF,20%,25V,GP,-,12.5x25mm,		....4	LF11	2702-001092 INDUCTOR-RADIAL;2.2uH,10%,6x4mm	
....4	C526	2301-001211 C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm		....4	PCB	AA41-00578B PCB-CRT;CT-29Z7HR,FR-1,1LB,1.6T,330X245	S.N.A
....4	C528	2401-000832 C-AL;220uF,20%,25V,GP,TP,8x11.5,5		....4	Q501	0501-000283 TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	C531	2401-002264 C-AL;100uF,20%,350V,GP,TP,10x20mm,5m		....4	Q502	0501-000283 TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	C532	2401-001563 C-AL;47uF,20%,400V,GP,TP,16x25,7.5		....4	Q503	0501-000283 TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	C533	2305-000665 C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		....4	Q504	0501-000283 TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	C534	2401-000832 C-AL;220uF,20%,25V,GP,TP,8x11.5,5		....4	QF02	0501-000389 TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	C535	2401-000914 C-AL;22uF,20%,16V,GP,TP,5x11,5		....4	QF03	0501-000389 TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	C536	2202-000121 C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP		....4	QF04	0501-000283 TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	C537	2202-000121 C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP		....4	QF05	0501-000389 TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	C538	2202-000121 C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP		....4	R501	2001-000241 R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C539	2202-000632 C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP		....4	R502	2001-000241 R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	CF01	2401-000360 C-AL;100uF,20%,50V,GP,TP,8x11.5,5		....4	R503	2001-001088 R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	CF02	2201-000292 C-CERAMIC,DISC;1nF,10%,50V,Y5P,TP,5x3.5,		....4	R504	2001-001045 R-CARBON(S);1.2KOHM,5%,1/2W,AA,TP,2.4X6	
....4	CF03	2201-000192 C-CERAMIC,DISC;0.01nF,0.25pF,500V,NP0,TP		....4	R505	2001-001045 R-CARBON(S);1.2KOHM,5%,1/2W,AA,TP,2.4X6	
....4	CF04	2201-000516 C-CERAMIC,DISC;4.7nF,+100-0%,500V,Y5U,TP		....4	R506	2004-005055 R-METAL(S);86KOHM,1%,1/2W,AA,TP,2.4X6.4M	
....4	CF05	2301-000261 C-FILM,PEF;4.7nF,5%,100V,TP,10.5x12.5x6		....4	R507	2001-000472 R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	CF06	2201-000192 C-CERAMIC,DISC;0.01nF,0.25pF,500V,NP0,TP		....4	R508	2001-000958 R-CARBON;7500HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	CF07	2201-000604 C-CERAMIC,DISC;0.056nF,+100-0%,500V,SL,T		....4	R509	2008-000205 R-FUSIBLE(S);10ohm,5%,1/2W,AF,TP,2.5x6.5	
....4	CF71	2401-000832 C-AL;220uF,20%,25V,GP,TP,8x11.5,5		....4	R510	2004-005055 R-METAL(S);86KOHM,1%,1/2W,AA,TP,2.4X6.4M	
....4	CF73	2401-000927 C-AL;22uF,20%,250V,GP,TP,13x20,5		....4	R511	2004-005055 R-METAL(S);86KOHM,1%,1/2W,AA,TP,2.4X6.4M	
....4	CF74	2401-001840 C-AL;100uF,20%,16V,GP,TP,6.3x11,5		....4	R512	2004-001369 R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	CF75	2401-000045 C-AL;100uF,20%,160V,GP,TP,10x16,5		....4	R513	2002-001017 R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
....4	CNC02	3711-002647 CONNECTOR-HEADER;BOX,8P,1R,2.5mm,STRAIGH		....4	R514	2002-001017 R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
....4	D501	0401-000005 DIODE-SWITCHING;1N4148,100V,200mA,DO-35,		....4	R515	2002-001017 R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
....4	D502	0402-000546 DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T		....4	R516	2001-001153 R-CARBON(S);470HM,5%,1/2W,AA,TP,2.4X6.4M	
....4	D509	0402-000546 DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T		....4	R518	2001-001095 R-CARBON(S);2.2MOHM,5%,1/2W,AA,TP,2.4X6	
....4	D510	0402-000546 DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T		....4	R519	2001-000786 R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	D511	0402-000546 DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T		....4	R520	2001-001015 R-CARBON;9.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	D512	0402-000546 DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T		....4	R522	2001-000290 R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	D513	0402-000546 DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T		....4	R523	2001-000890 R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	D514	0402-000546 DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T		....4	R525	2002-001006 R-COMPOSITION;4.7KOHM,15%,1/2W,AA,TP,3.7	
....4	DF01	0401-000005 DIODE-SWITCHING;1N4148,100V,200mA,DO-35,		....4	R527	2001-000241 R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	DF02	0401-000005 DIODE-SWITCHING;1N4148,100V,200mA,DO-35,		....4	R528	2003-000458 R-METAL OXIDE(S);100ohm,5%,2W,AF,TP,4x12	
....4	DF05	0401-000005 DIODE-SWITCHING;1N4148,100V,200mA,DO-35,		....4	R529	2008-001129 R-FUSIBLE(S);1.5ohm,5%,1/2W,AF,TP,2.5x6	
....4	DF06	0401-000005 DIODE-SWITCHING;1N4148,100V,200mA,DO-35,		....4	R530	2001-000273 R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	DF07	0402-000546 DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T		....4	R531	2001-000539 R-CARBON;24KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	DF08	0402-000546 DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T		....4	R540	2001-000429 R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	DZ501	0403-000708 DIODE-ZENER;MTZJ13B,13V,12.55-13.21V,500		....4	R541	2008-001053 R-FUSIBLE;22ohm,5%,1/2W,AF,TP,2.5x6.5mm	
....4	DZ502	0403-000708 DIODE-ZENER;MTZJ13B,13V,12.55-13.21V,500		....4	R554	2001-000429 R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	DZ504	0403-000698 DIODE-ZENER;TZP12A,12V,11.4-12.6V,1W,DO-		....4	R555	2001-000429 R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	DZ510	0403-000734 DIODE-ZENER;TZP15B,15V,14.7-16.5V,1W,DO-		....4	R556	2001-000429 R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	DZF01	0403-001039 DIODE-ZENER;MA2560,56V,52-60V,1W,DO-41,T		....4	R560	2001-000052 R-CARBON(S);3.3KOHM,5%,1/2W,AA,TP,2.4X6	
....4	DZF02	0403-001039 DIODE-ZENER;MA2560,56V,52-60V,1W,DO-41,T		....4	R561	2001-001126 R-CARBON(S);3000HM,5%,1/2W,AA,TP,2.4X6.4	
....4	DZF03	0403-000508 DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500		....4	R562	2001-000273 R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	EL100	AA60-40011B EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A	....4	R563	2001-000273 R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	EL80	AA60-40011B EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A	....4	R564	2001-000290 R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	EL81	AA60-40011B EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A	....4	R565	2001-001071 R-CARBON(S);12KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	EL82	AA60-40011B EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A	....4	R566	2001-001040 R-CARBON(S);0.680HM,5%,1/2W,AA,TP,2.4X6	
....4	EL83	AA60-40011B EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A	....4	RF13	2008-001014 R-FUSIBLE(S);22ohm,5%,1W,AF,TP,3.2x10mm	
....4	EL84	AA60-40011B EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A	....4	RF14	2003-002276 R-METAL OXIDE(S);2.2KOHM,5%,2W,AG,TP,12X	
....4	EL85	AA60-40011B EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A	....4	RF15	2003-002276 R-METAL OXIDE(S);2.2KOHM,5%,2W,AG,TP,12X	
....4	EL86	AA60-40011B EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A	....4	RF16	2003-002276 R-METAL OXIDE(S);2.2KOHM,5%,2W,AG,TP,12X	
....4	EL87	AA60-40011B EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A	....4	RF17	2001-000019 R-CARBON(S);100HM,5%,1/2W,AA,TP,2.4X6.4M	
....4	EL88	AA60-40011B EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A	....4	RF18	2001-001079 R-CARBON(S);150HM,5%,1/2W,AA,TP,2.4X6.4M	
....4	EL89	AA60-40011B EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A	....4	RF19	2001-001079 R-CARBON(S);150HM,5%,1/2W,AA,TP,2.4X6.4M	
....4	EL92	AA60-40011B EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A	....4	RF20	2001-000331 R-CARBON;12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	EL94	AA60-40011B EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A	....4	RF21	2001-000258 R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	EL95	AA60-40011B EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A	....4	RF22	2001-000241 R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	EL96	AA60-40011B EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A	....4	RF23	2001-000554 R-CARBON;2700HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	EL97	AA60-40011B EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A	....4	RF24	2003-001018 R-METAL OXIDE(S);220ohm,5%,2W,AF,TP,3.9x	
....4	EL98	AA60-40011B EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A	....4	RF25	2001-000241 R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	EL99	AA60-40011B EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A	....4	RF26	2001-001179 R-CARBON(S);68KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	FN1	3711-002643 CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGH		....4	RF27	2001-001179 R-CARBON(S);68KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	FV1	3711-002642 CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH		....4	RF28	2001-000241 R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	GT501	AA60-40014A PIN-GT,ASSY;1P,-,-,AUTO	S.N.A	....4	RF29	2001-001071 R-CARBON(S);12KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	GT502	AA60-40014A PIN-GT,ASSY;1P,-,-,AUTO	S.N.A	....4	RF30	2001-000221 R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	GT503	AA60-40014A PIN-GT,ASSY;1P,-,-,AUTO	S.N.A	....4	RF31	2001-000221 R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	GT504	AA60-40014A PIN-GT,ASSY;1P,-,-,AUTO	S.N.A	....4	RF32	2003-000746 R-METAL OXIDE(S);56ohm,5%,2W,AF,TP,4x12m	
....4	L502	2701-000178 INDUCTOR-AXIAL;33uH,10%,3x7mm		....4	RF33	2001-001053 R-CARBON(S);1.50HM,5%,1/2W,AA,TP,2.4X6.4	
....4	LF01	2901-000297 FILTER-EMI ON BOARD;-3A,-,-,3.5x5,TP,-		....4	RF34	2001-001100 R-CARBON(S);2.70HM,5%,1/2W,AA,TP,2.4X6.4	
....4	LF02	2901-000297 FILTER-EMI ON BOARD;-3A,-,-,3.5x5,TP,-		....4	RF35	2003-000746 R-METAL OXIDE(S);56ohm,5%,2W,AF,TP,4x12m	
....4	LF03	2701-000112 INDUCTOR-AXIAL;100uH,10%,3x7mm		....4	RF36	2003-000652 R-METAL OXIDE(S);330ohm,5%,2W,AF,TP,4x12	
....4	LF04	2901-000297 FILTER-EMI ON BOARD;-3A,-,-,3.5x5,TP,-		...3		2202-000632 C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	LF06	2901-000297 FILTER-EMI ON BOARD;-3A,-,-,3.5x5,TP,-		...3		2202-000121 C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
...2	AA96-00908F	ASSY COVER P-TERMINAL BOARD;29Z7,TXM2798		△ ...3	T801S	AA26-00010B TRANS SWITCHING;EER5345,K55A ,90-264V,PM	
...3	PCB	AA41-00641A PCB-WOOFER JACK;CT-29Z7HR,FR-1,1L,A,1.6T	S.N.A	△ ...3	TU02S	AA40-00041A TUNER-F/S;TCPN3081PC09C(S),NTSC,181CH,45	
...3	WB01	3301-000287 CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,		...3	AA97-12698F	ASSY ROBOT-MAIN;TXM3298HFX/XAA,K55A	
...3	WB02	3301-000287 CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,		...4	C423	2301-001296 C-FILM,MPPF;720nF,5%,400V,BK,26X15.5X20M	
...3	WCN01	AA39-20005D LEAD CONNECTOR-ASSY;3P,YBNH250-03,67096		...4	C426	2306-001004 C-FILM,MPPF;300nF,5%,400V,TP,26x14x21mm,	
...3	WJ01	3722-001813 JACK-PIN;1P(3P),8.3MM,AU,BLK,-		...4	C803	2401-001676 C-AL;820uF,20%,250V,GP,-,35x40mm,10	
...3	WP+TBA	6006-001095 SCREW-ASSY TAPT;WP,BH,+,M4,L12,ZPC(YEL)	S.N.A	...4	C815	2401-003024 C-AL;220uF,20%,200V,WT,TP,22x35,10	
...3	AA64-02822D	INLAY-T/BOARD;Z6,PS SHEET,T0.5,KS4A PAL		...4	CN702	3711-003641 CONNECTOR-HEADER;BOX,12P,1R,2.5mm,STRAIG	
...3	AA65-00025A	TERMINAL-BOARD,ANT, HIPS V0,G4309	S.N.A	...4	CN902	3711-003043 CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGH	
△ ...2	AA96-20129B	ASSY-POWER,CORD;-EP2/YES,H/C400,ME301P,	S.N.A	...4	CR405S	2301-001583 C-FILM,PPF;3nF,5%,2KV,TP,25X13X7MM,20	
...3	3811-000401	WIRE-PVC CU;BCWA,300V,ROLL,17/0.16mm,#22	S.N.A	△ ...4	CR406S	2301-001583 C-FILM,PPF;3nF,5%,2KV,TP,25X13X7MM,20	
...3	AA39-10007Y	POWER-CORD;-EP2/YES,SPT-2 18AWGx2C,2.4m		...4	CR407S	2301-001398 C-FILM,MPPF;3.3nF,5%,2KV,TP,29x8.5x1.5mm	
...3	AA61-20284A	HOLDER-P-CORD,PP,-,-,BLK,VO,KE-002	S.N.A	...4	CX801S	2306-000318 C-FILM,MPPF;220nF,20%,250V,TP,-,22.5mm	
...2	AA94-08533Y	ASSY PCB MAIN;TXM3298HFX/XAA,K55A		△ ...4	CX802S	2306-000318 C-FILM,MPPF;220nF,20%,250V,TP,-,22.5mm	
...3	C-BLOC	AA26-00069A TRANS FBT;FUJ-29C002C(S),DREAM3,4,-,-,-,		...4	CY801S	2201-002002 C-CERAMIC,DISC;4.7nF,20%,400V,Y5U,TP,16x	
...3	C415	2301-001124 C-FILM,PPF;3.3nF,5%,800V,TP,20x6.5x13.5,		△ ...4	FP801S	3601-000293 FUSE-CARTRIDGE;250V,5A,SLOW-BLOW,GLASS,5	
...3	C806	2306-000112 C-FILM,MPPF;100nF,20%,250V,BK,-,15mm		△ ...4	IC401	1202-000103 IC-VOLTAGE COMP;393,DIP,8P,300MIL,DUAL,	
...3	C820	2401-003419 C-AL;2200uF,20%,50V,WT,TP,16X35.5mm		...4	IC601	1204-001972 IC-SOUND PROCESSOR;MSP3420G-P0-B10,DIP5	S.N.A
...3	CABLE	AA39-30007B IF-CABLE;-T,150mm,1365#26		△ ...4	IC803	1203-001225 IC-POSIFIXED REG;78R09,TO-220,4P,-,PLA	
△ ...3	D801S	AA96-00276C ASSY H/S;-BRIDGE,AA62-00052A,GSIB660,K	S.N.A	...4	IC902	1103-001177 IC-EEPROM;24WC16,2048x8BIT,DIP8P,-,Z	
...4	AA62-00052A	HEAT SINK-PS;-,-,SILVER,HOLE 18.5mm, 2	S.N.A	...4	L808	AA27-00098A COIL CHOKE;-,-,24uH,10%,0.1,3.0A,DR10X	
...4	AA60-30003A	WASHER;-,-,T1.5,-,SBHG-1,-	S.N.A	△ ...4	LR405S	AA27-00096A COIL HORIZ. WIDTH;-,-,10.0mH,DR15 X 27.5,U	
...4	6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A	△ ...4	LX801S	AA29-00011A FILTER LINE NOISE;CZ32W8,-,0.20MAX,1.5KV	
...4	0402-001399	DIODE-BRIDGE;GSIB660,600V,6A,SIP-4,BK		△ ...4	LX802S	AA29-00012A FILTER LINE NOISE;CS29A6PF8X/HAC,-,0.1MA	
...4	0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A	△ ...4	NT802S	1404-001045 THERMISTOR-NTC;4.7ohm,15%,2900K,35.0mW,T	
△ ...3	GT804S	AA39-20010B LEAD CONNECTOR-ASSY;1P,YFH800-01,S,500,		△ ...4	PC801S	0604-001038 PHOTO-COUPLER;TR,130-260V,200mW,DIP-4,ST	
...3	HC401	AA96-00275G ASSY H/S;SCREW,OIL,AA62-00051B,FJL6920YD	S.N.A	△ ...4	PT801S	1404-001276 THERMISTOR-PTC;1.50HM,+30/-20%,110V,140V	
...4	0502-001230	TR-POWER;FJL6920YDTU,N,200000MW,TO-264 F		△ ...4	TU01S	AA40-00020A TUNER-F/S;TCLN3181PA09A(S),NTSC,TR,181CH	
...4	AA62-00051B	HEAT SINK-PS;-,-,SILVER,HOLE 34mm,ALL	S.N.A	...4	C101	AA97-12699H ASSY AUTO-MAIN;TXM3298HFX/XAA,K55A	
...4	AA60-30001A	WASHER-PLATE;M3,ID3.5,15X8.5,T1.0,-,SBHG	S.N.A	...5	C102	2305-000665 C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
...4	0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A	...5	C103	2401-001840 C-AL;100uF,20%,16V,GP,TP,6.3x11.5	
...4	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A	...5	C103	2305-000665 C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
...4	0402-001296	DIODE-RECTIFIER;FMP-3FU,1.5KV,5A,TO-3PF,		...5	C104	2401-003578 C-AL;1000uF,20%,10V,GP,TP,8x20mm,5	
...3	HC801	AA96-00475A ASSY H/S;-REGULATOR,AA62-00066B,FML-G12	S.N.A	...5	C105	2305-000665 C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
...4	AA62-00066B	HEAT SINK-D2,D3,AL ,T1.0,89.70,-,AA62-00	S.N.A	...5	C106	2401-000480 C-AL;10uF,20%,50V,GP,TP,5x11.5	
...4	6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	S.N.A	...5	C107	2305-000665 C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
...4	1203-001006	IC-VOLTAGE REGULATOR;78R05,TO-220F,4P,-		...5	C108	2401-003578 C-AL;1000uF,20%,10V,GP,TP,8x20mm,5	
...4	0402-001230	DIODE-RECTIFIER;FMG-G2CS,1000V,3A,TO-220		...5	C109	2202-000216 C-CERAMIC,MLC-AXIAL;027NF,5%,50V,SL,TP	
...4	0402-000233	DIODE-RECTIFIER;FML-G12S,200V,5A,-,-		...5	C110	2202-000216 C-CERAMIC,MLC-AXIAL;027NF,5%,50V,SL,TP	
...4	0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A	...5	C111	2401-000480 C-AL;10uF,20%,50V,GP,TP,5x11.5	
...3	HIC401	AA13-00094A IC HYBRID;-DDR1001A,SIP5P,-,TP		...5	C112	2305-000665 C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
...3	IC301	AA96-50381A ASSY H/S;-,-,AA62-30180B,LA7845,-	S.N.A	...5	C113	2202-000216 C-CERAMIC,MLC-AXIAL;027NF,5%,50V,SL,TP	
...4	0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A	...5	C116	2202-002037 C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
...4	1204-000517	IC-VERTICAL DEF;LA7845,SIP,7P,-,PLASTIC		...5	C201	2305-000665 C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
...4	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A	...5	C202	2401-002463 C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
...4	AA62-30180B	HEAT-SINK,ES;-A6063 EXTR.,2,WHT,70MM,-	S.N.A	...5	C206	2305-000665 C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
...3	IC602	AA96-50369D ASSY H/S;-SOUND,AA62-30181F,TDA7269,HER	S.N.A	...5	C207	2401-002235 C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
...4	0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A	...5	C239	2401-002235 C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
...4	1201-001385	IC-POWER AMP;7269A,ZIP,11,19.6,DUAL,13,P		...5	C240	2305-000665 C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
...4	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A	...5	C302	2401-000365 C-AL;1000uF,20%,50V,WT,TP,10x12.5mm,	
...4	AA62-30181F	HEAT-SINK,ES;-AL6063 EXTR.,2,WHT,50MM,-	S.N.A	...5	C303	2201-000132 C-CERAMIC,DISC;0.1nF,10%,500V,Y5P,TP,6.5	
△ ...3	IC801S	AA96-50371H ASSY H/S;-SMPs,AA62-30181H,5Q1565RF,HER	S.N.A	...5	C304	2305-000285 C-FILM,MPEF;220nF,5%,100V,TP,10.5X5.5X15	
...4	AA61-11028A	BRACKET;-SECC,T1.0,-,-,-	S.N.A	...5	C305	2305-000149 C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.5	
...4	AA62-30181H	HEAT-SINK,ES;-AL6063 EXTR.,2,WHT,50MM,-	S.N.A	...5	C306	2301-000160 C-FILM,PEF;12nF,5%,50V,TP,11.0x6.0x9.0mm	
...4	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A	...5	C307	2401-000365 C-AL;100uF,20%,50V,WT,TP,10x12.5mm,	
...4	1203-002512	IC-PWM CONTROLLER;KA5Q1565RF-YDTU,TO-3PF		...5	C308	2305-000411 C-FILM,MPEF;470nF,5%,50V,TP,7.3x4.8x5.5m	
...4	0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A	...5	C401	2201-000556 C-CERAMIC,DISC;0.47nF,10%,500V,Y5P,TP,5	
△ ...3	IC805	AA96-00243K ASSY H/S;-REGULATOR,AA62-000450A,KA78R0	S.N.A	...5	C402	2401-001397 C-AL;470uF,20%,25V,GP,TP,10x16,5	
...4	0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A	...5	C403	2201-000556 C-CERAMIC,DISC;0.47nF,10%,500V,Y5P,TP,5	
...4	6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A	...5	C404	2401-002288 C-AL;470uF,20%,25V,WT,TP,10x20,5	
...4	AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-	S.N.A	...5	C408	2301-001143 C-FILM,PPF;56nF,5%,400V,TP,20x10x17,7.5	
...4	1203-001006	IC-VOLTAGE REGULATOR;78R05,TO-220F,4P,-		...5	C409	2301-001268 C-FILM,PPF;33nF,5%,630V,TP,20x11x17,7.5	
...3	IC901	AA09-00041A IC-MCU;-SDA555X-OTP3.3V,-,128K,SDIP,-4	S.N.A	...5	C411	2301-000192 C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
...3	JA701	3722-001765 JACK-PIN;9P(9P)-,NI,YEL/GRN/WHT/BLU/RED		...5	C412	2301-000310 C-FILM,PEF;68nF,5%,50V,TP,8.0X8.5X4.0X5	
...3	JA702	3722-001766 JACK-PIN;7P(9P)-,NI,GN/WH/WH/BL/RD/R		...5	C413	2401-000493 C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
△ ...3	LR402S	AA27-10004F COIL-CHOKE;-56uH,K,-,2.5A,BK,-,DR12x15,		...5	C414	2401-002597 C-AL;220uF,20%,35V,GP,TP,10x12.5,5	
△ ...3	LR403S	AA27-30003Q COIL-LINEARLITY;-8.8uH,YL81 15x18,USTCO		...5	C416	2305-000665 C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
△ ...3	LR404S	AA27-00031A COIL-HORIZ WIDTH;-140UH,AR 8X20,0.8MM,B		...5	C417	2305-000665 C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
...3	Q402	0505-001116 FET-SILICON;BUZ73A,N,200V,22A,0.6ohm,40W		...5	C418	2401-002597 C-AL;220uF,20%,35V,GP,TP,10x12.5,5	
...3	Q804	BH99-00007S ASSY HEAT/SINK;KSC2073,MICOM,HERCULES,BH	S.N.A	...5	C419	2301-000192 C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
...4	CIS	0205-001027 OIL-SILICON;G746,-,-	S.N.A	...5	C420	2301-000213 C-FILM,PEF;220nF,5%,250V,TP,21.5x11,7.5	
...4	CIS	0502-001007 TR-POWER;KSC2073-H2,NPN,25W,TO-220,ST,6		...5	C421	2201-000556 C-CERAMIC,DISC;0.47nF,10%,500V,Y5P,TP,5	
...4	CIS	BH61-00004A SPRING-TR;CDA,CDB,SUS304,-,-,-,-,T0.5,	S.N.A	...5	C422	2401-001527 C-AL;47uF,20%,250V,HR,TP,13x25mm,5m	
...4	CIS	BH62-00007A HEAT SINK-TR;-T1.0,L20*H30,CDA	S.N.A	...5	C424	2201-000132 C-CERAMIC,DISC;0.1nF,10%,500V,Y5P,TP,6.5	
△ ...3	RL801S	3501-001053 RELAY-POWER;5Vdc,530mW,10A,1FormA,15mS,5		...5	C425	2301-001067 C-FILM,MPPF;82nF,5%,400V,TP,19x15.5x7.7	
△ ...3	T401	AA26-50001S TRANS-HORIZ.DRIVE;-,-,6.0mH,-,-,44uH,-		...5	C432	2301-000192 C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
△ ...3	T444S	AA26-00180A TRANS FBT;FUJ-34H002F,FUJ-34H002F,135V,3		...5	C601	2201-000558 C-CERAMIC,DISC;0.47nF,10%,50V,Y5P,TP,5x3	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
.....5 C602	2401-001026	C-AL;3.3UF,20%,50V,GP,TP,5X11,5		.....5 C827	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
.....5 C603	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm		.....5 C828	2201-000374	C-CERAMIC,DISC;0.22nF,5%,50V,NP0,TP,10.5	
.....5 C604	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5		.....5 C830	2201-000984	C-CERAMIC,DISC;0.68nF,10%,2kV,Y5P,TP,9x5	
.....5 C605	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		.....5 C831	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5 C606	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3		.....5 C832	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
.....5 C607	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3		.....5 C833	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
.....5 C608	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3		.....5 C834	2401-003034	C-AL;220uF,20%,16V,WT,TP,8x11.5,5	
.....5 C610	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm		.....5 C835	2401-000722	C-AL;2200uF,20%,25V,WT,TP,16x25,7.5	
.....5 C611	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm		.....5 C836	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5 C612	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5		.....5 C837	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5 C613	2401-000611	C-AL;1uF,20%,50V,WT,TP,5x11,5		.....5 C838	2401-001513	C-AL;47uF,20%,16V,WT,TP,5x11,5	
.....5 C614	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm		.....5 C840	2401-001513	C-AL;47uF,20%,16V,WT,TP,5x11,5	
.....5 C615	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3		.....5 C841	2401-000611	C-AL;1uF,20%,50V,WT,TP,5x11,5	
.....5 C619	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5		.....5 C843	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5 C620	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5		.....5 C844	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5 C621	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5		.....5 C901	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
.....5 C622	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5		.....5 C902	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
.....5 C623	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP		.....5 C903	2202-000719	C-CERAMIC,MLC-AXIAL;6.8nF,20%,16V,Y5R,TP	
.....5 C624	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP		.....5 C904	2401-000471	C-AL;10uF,20%,50V,BP,TP,5x11,5mm	
.....5 C625	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5		.....5 C905	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3	
.....5 C626	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5		.....5 C906	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
.....5 C627	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP		.....5 C907	2305-000411	C-FILM,MPEF;470nF,5%,50V,TP,7.3x4.8x5.5m	
.....5 C628	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5		.....5 C909	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
.....5 C629	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP		.....5 C910	2201-000980	C-CERAMIC,DISC;0.03nF,5%,50V,NP0,TP,5x3	
.....5 C630	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm		.....5 C911	2201-000980	C-CERAMIC,DISC;0.03nF,5%,50V,NP0,TP,5x3	
.....5 C631	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm		.....5 C912	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5 C632	2201-000370	C-CERAMIC,DISC;0.22nF,10%,50V,Y5P,TP,4x3		.....5 C913	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
.....5 C633	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP		.....5 C914	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5 C634	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5		.....5 C915	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
.....5 C635	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		.....5 C916	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5 C636	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP		.....5 C917	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
.....5 C637	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP		.....5 C918	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
.....5 C638	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP		.....5 C919	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
.....5 C639	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP		.....5 C920	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
.....5 C640	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5		.....5 C921	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
.....5 C641	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5		.....5 C922	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5 C642	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP		.....5 C923	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5 C643	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5		.....5 C924	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
.....5 C644	2401-000192	C-AL;1000uF,20%,50V,GP,TP,16x25,7.5		.....5 C925	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5 C645	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm		.....5 C927	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
.....5 C646	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		.....5 C928	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
.....5 C647	2202-000286	C-CERAMIC,MLC-AXIAL;56pF,5%,50V,SL,TP,1		.....5 CN502	3711-002647	CONNECTOR-HEADER;BOX,8P,1R,2.5mm,STRAIGH	
.....5 C648	2401-000192	C-AL;1000uF,20%,50V,GP,TP,16x25,7.5		.....5 CN601	3711-002644	CONNECTOR-HEADER;BOX,5P,1R,2.5mm,STRAIGH	
.....5 C649	2301-000108	C-FILM,PEF;1.5nF,5%,50V,TP,6.5x3.0x5.5mm		.....5 CN602	3711-002645	CONNECTOR-HEADER;BOX,6P,1R,2.5mm,STRAIGH	
.....5 C650	2401-001192	C-AL;33uF,20%,50V,GP,TP,6.3x11,5		.....5 CN901	3711-002645	CONNECTOR-HEADER;BOX,6P,1R,2.5mm,STRAIGH	
.....5 C651	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		.....5 CN904	3711-002647	CONNECTOR-HEADER;BOX,8P,1R,2.5mm,STRAIGH	
.....5 C652	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm		△.....5 CR01S	2201-000556	C-CERAMIC,DISC;0.47nF,10%,500V,Y5P,TP,5	
.....5 C653	2401-002216	C-AL;2200uF,20%,35V,GP,TP,16x25,7.5		△.....5 CR02S	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
.....5 C654	2201-000611	C-CERAMIC,DISC;0.056nF,5%,50V,NP0,TP,7x3		△.....5 CR03S	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
.....5 C655	2401-001026	C-AL;3.3UF,20%,50V,GP,TP,5X11,5		△.....5 CR04S	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-5mm	
.....5 C656	2201-000304	C-CERAMIC,DISC;0.001nF,0.25pF,50V,NP0,TP		.....5 CW901	2503-000156	C-NETWORK;100pF,20%,50V	
.....5 C657	2201-000304	C-CERAMIC,DISC;0.001nF,0.25pF,50V,NP0,TP		.....5 D201	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5 C658	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		.....5 D202	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5 C659	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		.....5 D207	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5 C660	2401-000962	C-AL;22uF,20%,50V,GP,TP,5x11,5		.....5 D301	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
.....5 C701	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3		.....5 D401	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-TP	
.....5 C801	2401-000287	C-AL;100uF,20%,16V,WT,TP,6.3x11,5		.....5 D402	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
.....5 C802	2301-000204	C-FILM,PEF;2.7nF,5%,50V,TP,7.4x3.9x13mm,		.....5 D403	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
.....5 C804	2201-000332	C-CERAMIC,DISC;2.2nF,20%,250V,Y5U,TP,9x4		.....5 D404	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
.....5 C805	2201-000332	C-CERAMIC,DISC;2.2nF,20%,250V,Y5U,TP,9x4		.....5 D405	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5 C807	2303-000163	C-FILM,PPF;2.2nF,5%,800V,TP,15x13x8.5,7		.....5 D406	0404-001056	DIODE-SCHOTTKY;RK16,60V,1.5A,DO-204AC,TP	
.....5 C808	2401-003046	C-AL;47uF,20%,50V,WT,TP,6.3x11,2.5		.....5 D408	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
.....5 C809	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5		.....5 D409	0402-000493	DIODE-RECTIFIER;1R5GU41,400V,1.5A,DO-15L	
.....5 C810	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5		.....5 D410	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5 C811	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5		.....5 D411	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
.....5 C812	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		.....5 D601	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6	
.....5 C814	2201-002028	C-CERAMIC,DISC;0.47nF,10%,2kV,Y5P,TP,7.5		.....5 D602	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6	
.....5 C816	2401-000262	C-AL;100uF,20%,160V,HR,TP,16x25,7.5		.....5 D603	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5 C817	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5		.....5 D604	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5 C818	2401-000722	C-AL;2200uF,20%,25V,WT,TP,16x25,7.5		.....5 D605	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6	
.....5 C819	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5		.....5 D606	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6	
.....5 C821	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5		.....5 D607	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
.....5 C822	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5		△.....5 D803	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
.....5 C823	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5		△.....5 D804	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
.....5 C824	2401-001513	C-AL;47uF,20%,16V,WT,TP,5x11,5		△.....5 D805	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5 C825	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		△.....5 D808	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
.....5 C826	2401-003034	C-AL;220uF,20%,16V,WT,TP,8x11.5,5		△.....5 D812	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	



Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
△	5 FA802S	3601-001086 FUSE-AXIAL LEAD;125V,5A,FAST-ACTING,GLAS		5 Q601	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,T0-92,T	
△	5 FA803S	3601-001228 FUSE-AXIAL LEAD;125V,10A,FAST-ACTING,EPO		5 Q603	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,T0-92,T	
5 GT101	AA60-40014A	PIN-GT,ASSY;1P,-,AUTO	S.N.A	5 Q801	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,T0-92,T	
5 GT102	AA60-40014A	PIN-GT,ASSY;1P,-,AUTO	S.N.A	5 Q802	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,T0-	
5 GT301	AA60-40014A	PIN-GT,ASSY;1P,-,AUTO	S.N.A	5 Q803	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,T0-92,T	
5 GT302	AA60-40014A	PIN-GT,ASSY;1P,-,AUTO	S.N.A	5 Q901	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,T0-92,T	
5 GT401	AA60-40014A	PIN-GT,ASSY;1P,-,AUTO	S.N.A	5 Q906	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,T0-92,T	
5 GT402	AA60-40014A	PIN-GT,ASSY;1P,-,AUTO	S.N.A	5 Q907	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,T0-92,T	
5 GT404	AA60-40014A	PIN-GT,ASSY;1P,-,AUTO	S.N.A	5 Q908	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,T0-92,T	
5 GT405	AA60-40014A	PIN-GT,ASSY;1P,-,AUTO	S.N.A	5 Q909	0505-000109	FET-SILICON;2N7000,N,60V,200mA,5ohm,400m	
5 GT406	AA60-40014A	PIN-GT,ASSY;1P,-,AUTO	S.N.A	5 Q910	0505-000109	FET-SILICON;2N7000,N,60V,200mA,5ohm,400m	
5 GT409	AA60-40014A	PIN-GT,ASSY;1P,-,AUTO	S.N.A	5 Q911	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,T0-92,T	
5 GT410	AA60-40014A	PIN-GT,ASSY;1P,-,AUTO	S.N.A	5 Q912	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,T0-92,T	
5 GT411	AA60-40014A	PIN-GT,ASSY;1P,-,AUTO	S.N.A	5 Q913	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,T0-92,T	
5 GT412	AA60-40014A	PIN-GT,ASSY;1P,-,AUTO	S.N.A	5 Q914	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,T0-92,T	
5 GT801	AA60-40014A	PIN-GT,ASSY;1P,-,AUTO	S.N.A	△	5 QR01S	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,T0-92,T
5 GT802	AA60-40014A	PIN-GT,ASSY;1P,-,AUTO	S.N.A	△	5 QR02S	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,T0-92,T
5 GT803	AA60-40014A	PIN-GT,ASSY;1P,-,AUTO	S.N.A	5 R101	2001-000869	R-CARBON;560HM,5%,1/8W,AA,TP,1.8X3.2MM	
5 GT804	AA60-40014A	PIN-GT,ASSY;1P,-,AUTO	S.N.A	5 R102	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5 GT805	AA60-40014A	PIN-GT,ASSY;1P,-,AUTO	S.N.A	5 R103	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5 GT806	AA60-40014A	PIN-GT,ASSY;1P,-,AUTO	S.N.A	5 R104	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5 IC202	1203-001944	IC-POSIX.FIXED REG.;78RM33,T0-220,3P,-,PL		5 R105	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
△	5 IC402	1203-000243 IC-POSIX.FIXED REG.;7812A,T0-220,3P,-,PLA		5 R106	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
△	5 IC804	1203-001217 IC-POSIX.ADJUST REG.;431,T0-92,3P,4.58MIL		5 R107	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5 IC903	1203-001944	IC-POSIX.FIXED REG.;78RM33,T0-220,3P,-,PL		5 R108	2001-000869	R-CARBON;560HM,5%,1/8W,AA,TP,1.8X3.2MM	
5 IC904	1203-001943	IC-VOL. DETECTOR;7025,T0-92,3P,-,PLASTIC		5 R203	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5 L101	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm		5 R204	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5 L102	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm		5 R301	2001-001163	R-CARBON(S);560OHM,5%,1/2W,AA,TP,2.4X6.4	
5 L103	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm		5 R302	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4	
5 L104	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm		5 R303	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4X6.4MM	
5 L106	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm		5 R304	2008-001108	R-FUSIBLE(S);1.2ohm,5%,2W,AG,TP,3.9x12mm	
5 L201	2701-000200	INDUCTOR-AXIAL;5.6uH,10%,4.2x9.8mm		5 R305	2003-002205	R-METAL OXIDE(S);330ohm,5%,2W,AG,TP,3.9X	
5 L203	2901-000297	FILTER-EMI ON BOARD;-3A,-,-,3.5x5,TP-		5 R306	2003-002205	R-METAL OXIDE(S);330ohm,5%,2W,AG,TP,3.9X	
5 L301	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm		5 R307	2008-001114	R-FUSIBLE(S);1.5ohm,5%,2W,AG,TP,3.9x12mm	
5 L402	2901-000299	FILTER-EMI ON BOARD;-6A,UL/CSA,-,9x7.5,		5 R308	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4	
△	5 L403	2701-001040 INDUCTOR-AXIAL;10uH,10%,4.5x14mm		5 R309	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5 L404	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,		5 R310	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5 L407	2901-000297	FILTER-EMI ON BOARD;-3A,-,-,3.5x5,TP-		5 R314	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
5 L410	2901-000299	FILTER-EMI ON BOARD;-6A,UL/CSA,-,9x7.5,		5 R315	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
5 L601	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm		5 R316	2001-001129	R-CARBON(S);330KOHM,5%,1/2W,AA,TP,2.4X6.	
5 L602	2701-000169	INDUCTOR-AXIAL;3.9uH,10%,2.5x3.4mm		5 R317	2001-000066	R-CARBON(S);10KOHM,5%,1/2W,AA,TP,2.4X6.4	
5 L603	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm		5 R401	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
5 L604	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm		5 R402	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
5 L605	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm		5 R403	2003-000532	R-METAL OXIDE(S);18ohm,5%,2W,AF,TP,4x12m	
5 L606	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm		5 R405	2008-001018	R-FUSIBLE(S);0.47ohm,10%,2W,AF,TP,3.9x10	
5 L607	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm		5 R409	2003-000998	R-METAL OXIDE;300ohm,5%,2W,AF,TP,3.9x10m	
5 L608	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm		5 R410	2003-000998	R-METAL OXIDE;300ohm,5%,2W,AF,TP,3.9x10m	
5 L609	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm		5 R412	2003-000592	R-METAL OXIDE(S);22ohm,5%,2W,AF,TP,4x12m	
5 L610	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,		5 R413	2008-001018	R-FUSIBLE(S);0.47ohm,10%,2W,AF,TP,3.9x10	
5 L612	2901-000297	FILTER-EMI ON BOARD;-3A,-,-,3.5x5,TP-		5 R414	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
5 L613	2901-000297	FILTER-EMI ON BOARD;-3A,-,-,3.5x5,TP-		5 R415	2004-005051	R-METAL(S);2.2KOHM,1%,1/2W,AA,TP,2.4X6.4	
5 L614	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,		5 R416	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
5 L615	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,		5 R418	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4	
5 L701	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm		5 R419	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
5 L702	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm		5 R420	2004-001406	R-METAL(S);8.2Kohm,1%,1/2W,AA,TP,2.4x6.4	
5 L703	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm		5 R421	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
5 L704	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm		5 R422	2008-001149	R-FUSIBLE(S);0.22OHM,5%,2W,AF,TP,3.8X11M	
5 L705	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm		5 R423	2004-005051	R-METAL(S);2.2KOHM,1%,1/2W,AA,TP,2.4X6.4	
5 L706	2701-000177	INDUCTOR-AXIAL;33uH,10%,2.5x3.4mm		5 R424	2008-001109	R-FUSIBLE(S);0.18ohm,10%,2W,AG,TP,3.9x12	
5 L801	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-		5 R425	2008-001109	R-FUSIBLE(S);0.18ohm,10%,2W,AG,TP,3.9x12	
5 L802	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-		5 R426	2003-000540	R-METAL OXIDE(S);1Kohm,5%,2W,AF,TP,4x12m	
5 L803	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-		5 R428	2004-000698	R-METAL;3.3Kohm,1%,1/4W,AA,TP,2.4x6.4m	
5 L804	2901-000297	FILTER-EMI ON BOARD;-3A,-,-,3.5x5,TP-		5 R430	2004-002016	R-METAL(S);15Kohm,1%,1/2W,AA,TP,2.5x6.5m	
5 L805	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,		5 R431	2004-002016	R-METAL(S);15Kohm,1%,1/2W,AA,TP,2.5x6.5m	
5 L806	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-		5 R432	2001-001179	R-CARBON(S);68KOHM,5%,1/2W,AA,TP,2.4X6.4	
5 L807	2901-000299	FILTER-EMI ON BOARD;-6A,UL/CSA,-,9x7.5,		5 R433	2003-000540	R-METAL OXIDE(S);1Kohm,5%,2W,AF,TP,4x12m	
5 L809	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,		5 R434	2901-000297	FILTER-EMI ON BOARD;-3A,-,-,3.5x5,TP-	
5 L811	2701-001030	INDUCTOR-AXIAL;43uH,10%,5x14mm		5 R435	2003-000784	R-METAL OXIDE(S);7.5Kohm,5%,2W,AF,TP,4x1	
5 L901	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm		5 R440	2004-005052	R-METAL(S);24KOHM,5%,1/2W,AA,TP,2.4X6.4M	
5 L902	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm		5 R601	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5 L903	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm		5 R602	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5 L904	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm		5 R603	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5 L907	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm		5 R604	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5 L908	2701-000191	INDUCTOR-AXIAL;47uH,10%,2.5x3.4mm		5 R605	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5 L909	2701-000191	INDUCTOR-AXIAL;47uH,10%,2.5x3.4mm		5 R606	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
5 PCB	AA41-00667A	PCB-MAIN;CT2927HR,FR-1,1L,A,1.6T,330X245	S.N.A	5 R607	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
5 Q404	0505-000156	FET-SILICON;IRF620,N,200V,5A,0.8ohm,50W,		5 R608	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
.....5 R609	2001-000780	R-CARBON;4700HM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 R917	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R610	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 R919	2001-000780	R-CARBON;4700HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R611	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 R920	2001-000780	R-CARBON;4700HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R612	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 R921	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R613	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 R922	2001-000924	R-CARBON;6800HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R614	2001-000780	R-CARBON;4700HM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 R923	2001-000924	R-CARBON;6800HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R615	2001-000780	R-CARBON;4700HM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 R924	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R616	2001-000780	R-CARBON;4700HM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 R925	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R617	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 R926	2001-000793	R-CARBON;470HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R618	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 R927	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R623	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 R928	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R624	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 R935	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R626	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M		.....5 R936	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R627	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M		.....5 R937	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R628	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 R938	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R629	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 R940	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R630	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 R941	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R631	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 R942	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R632	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 R945	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R633	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 R946	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R634	2001-001146	R-CARBON(S);4.7OHM,5%,1/2W,AA,TP,2.4X6.4		.....5 R947	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R635	2001-001146	R-CARBON(S);4.7OHM,5%,1/2W,AA,TP,2.4X6.4		.....5 R948	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R704	2001-000969	R-CARBON;750HM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 R949	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R710	2001-000938	R-CARBON;680HM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 R950	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R715	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 R951	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R716	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 R952	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R717	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 R953	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R718	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 R954	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R723	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 R955	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R801	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M		.....5 R958	2001-000780	R-CARBON;4700HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R802	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12		.....5 R960	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R803	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12		.....5 R961	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R804	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12		.....5 R962	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R805	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.4		.....5 R963	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R806	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.4		.....5 R965	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R808	2001-001197	R-CARBON(S);910OHM,5%,1/2W,AA,TP,2.4X6.4		.....5 R966	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R809	2001-000780	R-CARBON;4700HM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 R967	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R810	2001-000109	R-CARBON(S);4700HM,5%,1/2W,AA,TP,2.4X6.4		.....5 R968	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R811	2001-001188	R-CARBON(S);8.2KOHM,5%,1/2W,AA,TP,2.4X6.4		.....5 R972	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R812	2001-000780	R-CARBON;4700HM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 R973	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R813	2001-000780	R-CARBON;4700HM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 R974	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R815	2008-000284	R-FUSIBLE(S);0.1OHM,10%,2W,AF,TP,3.9X10M		.....5 R981	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R816	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 R982	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R817	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 R983	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R818	2001-001131	R-CARBON(S);33KOHM,5%,1/2W,AA,TP,2.4X6.4		.....5 R984	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R819	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4X6.4		.....5 R988	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R820	2001-001096	R-CARBON(S);2.2OHM,5%,1/2W,AA,TP,2.4X6.4		△.....5 RP802S	2002-001010	R-COMPOSITION;1.8Mohm,5%,1/2W,AA,TP,3.7x	
.....5 R821	2004-002015	R-METAL(S);140Kohm,1%,1/2W,AA,TP,2.4X6.4		△.....5 RR01S	2008-000264	R-FUSIBLE(S);1ohm,5%,1W,AF,TP,3.9x10mm	
.....5 R822	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM		△.....5 RR02S	2001-001149	R-METAL(S);43KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5 R823	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM		△.....5 RR03S	2004-005054	R-METAL(S);39KOHM,1%,1/2W,AA,TP,2.4X6.4M	
.....5 R824	2001-000319	R-CARBON;120KOHM,5%,1/8W,AA,TP,1.8X3.2MM		△.....5 RR04S	2001-000908	R-CARBON;62KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R827	2008-000284	R-FUSIBLE(S);0.1OHM,10%,2W,AF,TP,3.9X10M		△.....5 RR05S	2001-001103	R-CARBON(S);20KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5 R828	2008-001088	R-FUSIBLE(S);1ohm,5%,2W,AG,TP,3.9x12mm		△.....5 RR06S	2001-000977	R-CARBON;8.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R829	2008-001148	R-FUSIBLE;3.3OHM,5%,1W,AG,TP,3.9x12MM		△.....5 RR07S	2004-004029	R-METAL(S);10Kohm,1%,1/2W,AA,TP,2.5x6.5mm	
.....5 R830	2003-002157	R-METAL OXIDE;220OHM,5%,2W,AG,TP,6x16MM		△.....5 RR08S	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R833	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM		△.....5 RR09S	2001-000780	R-CARBON;4700HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R835	2003-002181	R-METAL OXIDE(S);68Kohm,5%,2W,AG,TP,3.9x		△.....5 RR10S	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 R838	2001-001050	R-CARBON(S);1.5KOHM,5%,1/2W,AA,TP,2.4X6.4		△.....5 RR430S	2004-001390	R-METAL(S);1Kohm,2%,1/2W,AA,TP,2.4x6.4mm	
.....5 R840	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		△.....5 RY801S	2002-001012	R-COMPOSITION;8.2Mohm,5%,1/2W,AA,TP,3.7x	
.....5 R841	2001-000800	R-CARBON;5.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		△.....5 VP801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
.....5 R842	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM		△.....5 VX801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
.....5 R901	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 X601	2801-003903	CRYSTAL-UNIT;18.432MHz,25ppm,28-AAM,12pF	
.....5 R902	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		.....5 X901	2801-003728	CRYSTAL-UNIT;6MHz,30ppm,28-AAM,20pF,40oh	
.....5 R903	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM		.....3	AA39-20015B	LEAD CONNECTOR-ASSY;3(2)P;67096-003,200	
.....5 R904	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM		.....3	0202-000187	SOLDER-WIRE FLUX;-RS60S,D1,2.63Sn/37Pb	S.N.A
.....5 R905	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM		.....3	AA95-02001H	ASSY SUB-PCB NTSC F-BOX;CT-2927HR,K55A	
.....5 R906	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM		.....4 BR01	AA61-10068A	BRACKET-PCB;M2160,SPTE,T0.3,-,-,-	S.N.A
.....5 R907	2001-000995	R-CARBON;820OHM,5%,1/8W,AA,TP,1.8X3.2MM		.....4 BR02	AA61-10068A	BRACKET-PCB;M2160,SPTE,T0.3,-,-,-	S.N.A
.....5 R908	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM		.....4 CN01	3711-003495	CONNECTOR-HEADER;NOWALL,34P,2R,2.54mm,AN	
.....5 R909	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM		.....4 CN02	3711-003495	CONNECTOR-HEADER;NOWALL,34P,2R,2.54mm,AN	
.....5 R910	2001-000534	R-CARBON;240OHM,5%,1/8W,AA,TP,1.8X3.2MM		.....4 CN03	3711-003601	CONNECTOR-HEADER;BOX,12P,1R,2.5mm,ANGLE,	
.....5 R911	2001-000628	R-CARBON;300OHM,5%,1/8W,AA,TP,1.8X3.2MM		.....4 CX01	2801-000199	CRYSTAL-UNIT;20MHz,50ppm,28-AAA,16pF,50o	
.....5 R912	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM		.....4 DC41	2309-000138	C-FILM,PE-PF;100nF,5%,50V,TP,20x16x8.5,	
.....5 R913	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM		.....4 DC51	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0m	
.....5 R914	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		.....4 DX01	2802-001177	RESONATOR-CERAMIC,2.696MHZ,0.4%,BK,10X4.	
.....5 R915	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM		.....4 EC48	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
.....5 R916	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM		.....4 EX01	2801-004019	CRYSTAL-UNIT;20.25MHz,30ppm,28-AAM,13pF,	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
....4 IC06	1203-002000	IC-VOL. DETECTOR;7027,TO-92,3P,-,PLASTIC		.....6CCQ08	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
....4 SX01	2802-001179	RESONATOR-CERAMIC;4MHZ,0.5%,BK,8X3X5.5MM		.....6CCQ09	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
....4	AA97-07506M	ASSY AUTO-NTSC F-BOX;CT-29Z7HR,K55A	S.N.A	.....6CCQ12	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
....5 EC49	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5		.....6CCQ13	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
....5	AA97-07233D	ASSY SMD-NTSC F-BOX;CT-29Z7HR,K55A	S.N.A	.....6CCQ14	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....6CC01	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4		.....6CCQ15	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6CC02	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6CCQ16	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....6CC03	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6CCQ17	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....6CC04	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4		.....6CCQ18	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6CC05	2203-001035	C-CERAMIC,CHIP;5.6nF,10%,50V,X7R,TP,2012		.....6CCQ19	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....6CC06	2402-000170	C-AL,SMD;1uF,20%,50V,GP,TP,4.3x4.3x5.4,		.....6CCQ20	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....6CC07	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6CCQ21	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....6CC08	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6CR01	2007-000094	R-CHIP;22Kohm,5%,1/16W,DA,TP,1608	
.....6CC09	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6CR02	2007-000088	R-CHIP;7.5Kohm,5%,1/16W,DA,TP,1608	
.....6CC10	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4		.....6CR03	2007-000309	R-CHIP;10ohm,5%,1/16W,DA,TP,1608	
.....6CC11	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6CR04	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6CC12	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4		.....6CR05	2007-000119	R-CHIP;560ohm,5%,1/16W,DA,TP,1608	
.....6CC13	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6CR06	2007-000086	R-CHIP;5.6Kohm,5%,1/16W,DA,TP,1608	
.....6CC14	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6CR07	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6CC15	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6CR08	2007-000119	R-CHIP;560ohm,5%,1/16W,DA,TP,1608	
.....6CC16	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6CR09	2007-001157	R-CHIP;750ohm,5%,1/16W,DA,TP,1608	
.....6CC17	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6CR10	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6CC18	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6CR11	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6CC19	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6CR12	2007-000094	R-CHIP;22Kohm,5%,1/16W,DA,TP,1608	
.....6CC20	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6CR13	2007-000088	R-CHIP;7.5Kohm,5%,1/16W,DA,TP,1608	
.....6CC21	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4		.....6CR14	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6CC22	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6CR15	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6CC23	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4		.....6CR16	2007-000119	R-CHIP;560ohm,5%,1/16W,DA,TP,1608	
.....6CC24	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6CR17	2007-000086	R-CHIP;5.6Kohm,5%,1/16W,DA,TP,1608	
.....6CC25	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6CR18	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6CC27	2203-000634	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,201		.....6CR19	2007-001093	R-CHIP;620ohm,5%,1/16W,DA,TP,1608	
.....6CC28	2203-000634	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,201		.....6CR20	2007-000119	R-CHIP;560ohm,5%,1/16W,DA,TP,1608	
.....6CC29	2203-001223	C-CERAMIC,CHIP;0.82nF,10%,50V,X7R,TP,201		.....6CR21	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6CC30	2203-001048	C-CERAMIC,CHIP;0.56nF,10%,50V,NP0,TP,201		.....6CR22	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6CC31	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012		.....6CR23	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
.....6CC32	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6CR24	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6CC33	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4		.....6CR25	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....6CC34	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4		.....6CR26	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
.....6CC35	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6CR27	2007-000106	R-CHIP;220Kohm,5%,1/16W,DA,TP,1608	
.....6CC36	2203-000634	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,201		.....6CR28	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....6CC37	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6CR29	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....6CC38	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4		.....6CR30	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6CC39	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6CR31	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6CC40	2203-000361	C-CERAMIC,CHIP;0.15nF,5%,50V,NP0,TP,2012		.....6CR32	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....6CC41	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4		.....6CR33	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
.....6CC42	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6CR34	2007-000799	R-CHIP;360ohm,5%,1/16W,DA,TP,1608	
.....6CC43	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6CR35	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
.....6CC44	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4		.....6CR36	2007-000309	R-CHIP;10ohm,5%,1/16W,DA,TP,1608	
.....6CC45	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4		.....6CR37	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....6CC46	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6CR38	2007-000119	R-CHIP;560ohm,5%,1/16W,DA,TP,1608	
.....6CC47	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6CR39	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....6CC48	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4		.....6CR40	2007-000086	R-CHIP;5.6Kohm,5%,1/16W,DA,TP,1608	
.....6CC49	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6CR41	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....6CC50	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4		.....6CR42	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6CC51	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4		.....6CR43	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....6CC52	2402-000170	C-AL,SMD;1uF,20%,50V,GP,TP,4.3x4.3x5.4,		.....6CR44	2007-000113	R-CHIP;33ohm,5%,1/16W,DA,TP,1608	
.....6CD01	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8		.....6CR45	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....6CF01	2909-001052	FILTER-LC;3.58MHz,3MHz,1.5dB,TP,11dB/1.0		.....6CR46	2007-000309	R-CHIP;10ohm,5%,1/16W,DA,TP,1608	
.....6CF02	2909-001051	FILTER-LC;6MHz,6MHz,0.8dB,TP,5dB/6MHz,30		.....6CR47	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....6CF03	2909-001051	FILTER-LC;6MHz,6MHz,0.8dB,TP,5dB/6MHz,30		.....6CR48	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6CF04	2909-001051	FILTER-LC;6MHz,6MHz,0.8dB,TP,5dB/6MHz,30		.....6CR49	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6CL01	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm		.....6CR50	2007-000096	R-CHIP;30Kohm,5%,1/16W,DA,TP,1608	
.....6CL02	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm		.....6CR51	2007-000125	R-CHIP;3.9Kohm,5%,1/16W,DA,TP,1608	
.....6CL03	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm		.....6CR52	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....6CL04	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm		.....6CR53	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....6CL05	2703-000389	INDUCTOR-SMD;5.6uH,5%,3.2x2.5x2.2mm		.....6CR54	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....6CL06	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm		.....6CR55	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6CL07	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm		.....6CR56	2007-000234	R-CHIP;1.3Kohm,5%,1/16W,DA,TP,1608	
.....6CL08	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm		.....6CR57	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....6CL11	3301-001324	CORE-FERRITE BEAD;AB,150OHM,2X1.25X0.9MM,		.....6CR58	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....6CQ01	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23		.....6CR59	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
.....6CQ02	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23		.....6CR60	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
.....6CQ03	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-		.....6DC01	2203-000444	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012,-	
.....6CQ04	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23		.....6DC02	2203-000444	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012,-	
.....6CQ05	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-		.....6DC03	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6CQ06	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23		.....6DC04	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6CQ07	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-		.....6DC05	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	



Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
.....6DC06	2402-000173	C-AL,SMD;4.7uF,20%,35V,GP,TP,4.3x4.3x5.		.....6DR05	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6DC07	2203-000495	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,2012		.....6DR06	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6DC08	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012		.....6DR07	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....6DC09	2402-000170	C-AL,SMD;1uF,20%,50V,GP,TP,4.3x4.3x5.4		.....6DR08	2007-000691	R-CHIP;3.3Mohm,5%,1/16W,DA,TP,1608	
.....6DC10	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP		.....6DR09	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6DC11	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP		.....6DR10	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6DC12	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4		.....6DR11	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6DC13	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4		.....6DR12	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6DC14	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP		.....6DR13	2007-000086	R-CHIP;5.6Kohm,5%,1/16W,DA,TP,1608	
.....6DC15	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP		.....6DR14	2007-000086	R-CHIP;5.6Kohm,5%,1/16W,DA,TP,1608	
.....6DC16	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP		.....6DR15	2007-000869	R-CHIP;4.7Kohm,1%,1/16W,DA,TP,1608	
.....6DC17	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP		.....6DR16	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6DC18	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP		.....6DR17	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6DC19	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP		.....6DR18	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6DC20	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012		.....6DR19	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6DC21	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP		.....6DR20	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6DC22	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012		.....6DR21	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6DC23	2402-000173	C-AL,SMD;4.7uF,20%,35V,GP,TP,4.3x4.3x5.		.....6DR23	2007-000052	R-CHIP;10Kohm,1%,1/16W,DA,TP,1608	
.....6DC24	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4		.....6DR24	2007-000092	R-CHIP;15Kohm,5%,1/16W,DA,TP,1608	
.....6DC25	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP		.....6DR25	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....6DC26	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP		.....6DR26	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6DC27	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP		.....6DR27	2007-000068	R-CHIP;470KOHM,5%,1/10W,DA,TP,2012	
.....6DC28	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP		.....6DR28	2007-000068	R-CHIP;470KOHM,5%,1/10W,DA,TP,2012	
.....6DC29	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP		.....6DR29	2007-000118	R-CHIP;390ohm,5%,1/16W,DA,TP,1608	
.....6DC30	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4		.....6DR30	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6DC31	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012		.....6DR31	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....6DC32	2203-000575	C-CERAMIC,CHIP;220nF,10%,25V,X7R,TP,2012		.....6DR32	2007-000081	R-CHIP;2.7Kohm,5%,1/16W,DA,TP,1608	
.....6DC33	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012		.....6DR33	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
.....6DC34	2203-000891	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,2012		.....6DR34	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....6DC35	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012		.....6DR35	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6DC36	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012		.....6DR36	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6DC37	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP		.....6DR37	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....6DC38	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP		.....6DR38	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....6DC39	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4		.....6DR39	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....6DC40	2203-000444	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012,-		.....6DR40	2007-000072	R-CHIP;47ohm,5%,1/16W,DA,TP,1608	
.....6DC43	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4		.....6DR41	2007-000072	R-CHIP;47ohm,5%,1/16W,DA,TP,1608	
.....6DC44	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP		.....6DR42	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6DC45	2203-000575	C-CERAMIC,CHIP;220nF,10%,25V,X7R,TP,2012		.....6DR43	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6DC49	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4		.....6DR44	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6DC50	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4		.....6DR45	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6DC52	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4		.....6DR46	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....6DD01	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8		.....6DR47	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....6DD02	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8		.....6DR49	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6DD03	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP		.....6DR50	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6DD04	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP		.....6DR51	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6DD05	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP		.....6DR52	2007-000210	R-CHIP;1.1KOHM,5%,1/10W,DA,TP,2012	
.....6DD06	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP		.....6DR53	2007-000210	R-CHIP;1.1KOHM,5%,1/10W,DA,TP,2012	
.....6DD07	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP		.....6DR54	2007-000210	R-CHIP;1.1KOHM,5%,1/10W,DA,TP,2012	
.....6DD08	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8		.....6DR55	2007-000210	R-CHIP;1.1KOHM,5%,1/10W,DA,TP,2012	
.....6DD09	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8		.....6DR56	2007-000210	R-CHIP;1.1KOHM,5%,1/10W,DA,TP,2012	
.....6DD10	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8		.....6DR57	2007-000210	R-CHIP;1.1KOHM,5%,1/10W,DA,TP,2012	
.....6DD12	0403-000746	DIODE-ZENER;RLZ3.9B,3.9V,3.89-4.16V,400m		.....6DR58	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6DD13	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8		.....6DR59	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6DD14	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8		.....6DR60	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6DD15	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8		.....6DR61	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....6DD16	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8		.....6DR62	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....6DD17	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8		.....6DR63	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....6DD18	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8		.....6DR64	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....6DD19	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8		.....6DR65	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6DD20	0403-000620	DIODE-ZENER;RLZ5.6B,5.6,500mW,LL-34,TP		.....6DR66	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
.....6DL01	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm		.....6DR67	2007-000080	R-CHIP;2Kohm,5%,1/16W,DA,TP,1608	
.....6DL02	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm		.....6DR68	2007-000080	R-CHIP;2Kohm,5%,1/16W,DA,TP,1608	
.....6DL03	2703-001070	INDUCTOR-SMD;100uH,10%,4.5x3.2x3.2mm		.....6DR69	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....6DQ01	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-		.....6DR70	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
.....6DQ02	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23		.....6DR71	2007-000094	R-CHIP;22Kohm,5%,1/16W,DA,TP,1608	
.....6DQ03	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23		.....6EC01	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP	
.....6DQ04	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23		.....6EC02	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP	
.....6DQ05	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23		.....6EC03	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP	
.....6DQ06	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-		.....6EC04	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP	
.....6DQ07	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-		.....6EC07	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
.....6DQ08	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-		.....6EC08	2203-000575	C-CERAMIC,CHIP;220nF,10%,25V,X7R,TP,2012	
.....6DQ09	0501-000727	TR-SMALL SIGNAL;BC848C,NPN,310mW,SOT-23		.....6EC09	2203-000575	C-CERAMIC,CHIP;220nF,10%,25V,X7R,TP,2012	
.....6DQ10	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23		.....6EC10	2203-000575	C-CERAMIC,CHIP;220nF,10%,25V,X7R,TP,2012	
.....6DQ11	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-		.....6EC11	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP	
.....6DR02	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608		.....6EC12	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP	
.....6DR03	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608		.....6EC13	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
.....6DR04	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608		.....6EC14	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
.....6EC15	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012		.....6GL01	3301-001184	CORE-FERRITE BEAD;AB,1.3kohm,4.5x3.2x1.3	
.....6EC16	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6GL02	3301-001184	CORE-FERRITE BEAD;AB,1.3kohm,4.5x3.2x1.3	
.....6EC17	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012		.....6IC01	1204-001938	IC-DECODER;VSP9407B-B11,MQFP;80P,14X14MM	
.....6EC18	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012		.....6IC02	1204-001814	IC-SELECTOR;CXA2151Q,QFP;48P,144MIL,PLAS	
.....6EC19	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012		.....6IC03	1001-001082	IC-VIDEO SWITCH;BA7657F,-,SOP24P,300MIL	
.....6EC20	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012		.....6IC04	1204-001989	IC-VIDEO PROCESS;CXA2165Q,QFP;64P,20X14MM	
.....6EC21	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012		.....6IC05	1203-002186	IC-POSIFIXED REG.;18,DPAK,3P,240MIL,PLA	
.....6EC22	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012		.....6IC07	1203-002351	IC-VOLTAGE REGULATOR;LF25C,DPAK,3P,240MI	
.....6EC23	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012		.....6IC08	1203-001419	IC-VOLTAGE REGULATOR;4931,TO-252,3P,6x6	
.....6EC24	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6IC09	1204-001935	IC-SEPARATOR;UPD64083GF,QFP;100P,14X20MM	
.....6EC26	2203-000784	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012		.....6IC10	1001-001177	IC-VIDEO SWITCH;TEA6425D,VIDEO SWITCH,S	
.....6EC27	2203-000784	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012		.....6IC11	0801-000662	IC-CMOS LOGIC;74HC123,MULTIVIBRATOR,SOP,1	
.....6EC29	2203-000683	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,201		.....6PCB	AA41-006368	PCB-FEATURE BOX;CT32W,FR-4,4L,B,1.6T,180	S.N.A
.....6EC30	2203-000683	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,201		.....6SC01	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6EC31	2203-000683	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,201		.....6SC02	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6EC32	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6SC03	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6EC33	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6SC04	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6EC34	2203-000634	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,201		.....6SC05	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6EC35	2203-000634	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,201		.....6SC06	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6EC36	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6SC07	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6EC37	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6SC08	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6EC38	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6SC09	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6EC39	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6SC10	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6EC40	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6SC11	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6EC41	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6SC12	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6EC42	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4		.....6SC13	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6EC43	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6SC14	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6EC44	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4		.....6SC15	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6EC45	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6SC16	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
.....6EC46	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6SC17	2203-0005809	C-CERAMIC,CHIP;1000nF,10%,16V,X7R,TP,201	
.....6EC47	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4		.....6SC18	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6EC50	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4		.....6SC19	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6EC51	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4		.....6SC20	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6EC52	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6SC21	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6EC53	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6SC22	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6EC54	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6SC23	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6EC55	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6SC24	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6EC56	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6SC25	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6EC57	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4		.....6SC26	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....6EC59	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4		.....6SC27	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6EC60	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,		.....6SC28	2203-000938	C-CERAMIC,CHIP;0.47nF,5%,50V,NP0,TP,2012	
.....6EL02	2703-000274	INDUCTOR-SMD;2.2uH,10%,1.25x2x0.85mm		.....6SC29	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
.....6EL03	2703-000274	INDUCTOR-SMD;2.2uH,10%,1.25x2x0.85mm		.....6SC30	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6EL04	3301-001082	CORE-FERRITE BEAD;AB,600HM,3.2X2.5X1.3MM		.....6SC31	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
.....6EL05	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm		.....6SC32	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6EL06	3301-001324	CORE-FERRITE BEAD;AB,150HM,2X1.25X0.9MM,		.....6SC33	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
.....6EL07	3301-001324	CORE-FERRITE BEAD;AB,150HM,2X1.25X0.9MM,		.....6SC34	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6EL08	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm		.....6SC35	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
.....6EL09	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm		.....6SC36	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6EL12	2703-000274	INDUCTOR-SMD;2.2uH,10%,1.25x2x0.85mm		.....6SC37	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
.....6EL13	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm		.....6SC38	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6EQ01	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-		.....6SC39	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
.....6EQ02	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-		.....6SC40	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6EQ03	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-		.....6SC41	2203-001002	C-CERAMIC,CHIP;0.047nF,5%,50V,NP0,TP,201	
.....6EQ04	0505-000110	FET-SILICON;2N7002,N,60V,115MA,7.50HM,0.		.....6SC42	2203-001002	C-CERAMIC,CHIP;0.047nF,5%,50V,NP0,TP,201	
.....6EQ05	0505-000110	FET-SILICON;2N7002,N,60V,115MA,7.50HM,0.		.....6SC43	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6EQ06	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-		.....6SC44	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6ER01	2007-001166	R-CHIP;750HM,5%,1/10W,DA,TP,2012		.....6SC50	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....6ER02	2007-001166	R-CHIP;750HM,5%,1/10W,DA,TP,2012		.....6SC51	2203-000495	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,2012	
.....6ER03	2007-001166	R-CHIP;750HM,5%,1/10W,DA,TP,2012		.....6SC52	2203-000495	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,2012	
.....6ER04	2007-001166	R-CHIP;750HM,5%,1/10W,DA,TP,2012		.....6SL01	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....6ER05	2007-001166	R-CHIP;750HM,5%,1/10W,DA,TP,2012		.....6SL02	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....6ER06	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608		.....6SQ01	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....6ER07	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608		.....6SR01	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6ER09	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608		.....6SR02	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6ER11	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608		.....6SR03	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6ER12	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608		.....6SR04	2007-001166	R-CHIP;750HM,5%,1/10W,DA,TP,2012	
.....6ER13	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608		.....6SR05	2007-001166	R-CHIP;750HM,5%,1/10W,DA,TP,2012	
.....6ER14	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608		.....6SR06	2007-001166	R-CHIP;750HM,5%,1/10W,DA,TP,2012	
.....6ER15	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608		.....6SR07	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6ER16	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608		.....6SR08	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6ER17	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608		.....6SR09	2007-001166	R-CHIP;750HM,5%,1/10W,DA,TP,2012	
.....6ER18	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608		.....6SR10	2007-001166	R-CHIP;750HM,5%,1/10W,DA,TP,2012	
.....6ER19	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608		.....6SR11	2007-001166	R-CHIP;750HM,5%,1/10W,DA,TP,2012	
.....6ER20	2007-001166	R-CHIP;750HM,5%,1/10W,DA,TP,2012		.....6SR12	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6ER21	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012		.....6SR13	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....6ER22	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012		.....6SR14	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
.....6SR15	2007-001166	R-CHIP;750HM,5%,1/10W,DA,TP;2012		....4 RC05	2001-000020	R-CARBON(S);220HM,5%,1/2W,AA,TP;2.4X6.4M	
.....6SR16	2007-001166	R-CHIP;750HM,5%,1/10W,DA,TP;2012		....4 RC07	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP;1.8X3.2MM	
.....6SR17	2007-001166	R-CHIP;750HM,5%,1/10W,DA,TP;2012					
.....6SR20	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP;1608					
.....6SR21	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP;1608					
.....6SR22	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP;1608					
.....6SR23	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP;1608					
.....6SR24	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP;1608					
.....6SR25	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP;1608					
.....6SR26	2007-000052	R-CHIP;10Kohm,1%,1/16W,DA,TP;1608					
.....6SR27	2007-000080	R-CHIP;2Kohm,5%,1/16W,DA,TP;1608					
.....6SR28	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP;1608					
.....6SR29	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP;1608					
.....6SR30	2007-000258	R-CHIP;1.6KOHM,5%,1/10W,DA,TP;2012					
.....6SR31	2007-000931	R-CHIP;470OHM,5%,1/10W,DA,TP;2012					
.....6SR32	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP;1608					
.....6TC01	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP;2012					
.....6TC02	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP;2012					
.....6TC03	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP;2012					
.....6TC04	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP;2012					
.....6TC05	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP;2012					
.....6TC06	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP;2012					
.....6TC07	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP;6.6x6.6x5.4					
.....6TC08	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP					
.....6TL01	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm					
.....6TQ01	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-					
.....6TQ02	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-					
.....6TR01	2007-001166	R-CHIP;750HM,5%,1/10W,DA,TP;2012					
.....6TR02	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP;1608					
.....6TR03	2007-001166	R-CHIP;750HM,5%,1/10W,DA,TP;2012					
.....6TR04	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP;1608					
.....6TR05	2007-001166	R-CHIP;750HM,5%,1/10W,DA,TP;2012					
.....6TR06	2007-001166	R-CHIP;750HM,5%,1/10W,DA,TP;2012					
.....6TR07	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP;1608					
.....6TR08	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP;1608					
.....6TR09	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP;1608					
.....6TR10	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP;1608					
....4	0202-000187	SOLDER-WIRE FLUX;-;RS60S,D1.2,63Sn/37Pb	S.N.A				
....4	0202-001167	SOLDER-CREAM;RX3603-2330HO,S45A,PASTE,SN	S.N.A				
....3	AA65-30110A	CLAMP-WIRE;ALL MODEL,NYLON 66,V2,-,BLK,P	S.N.A				
....3	AA65-30104C	CLAMP-WIRE;ALL MODEL,NYLON 66,V2,-,NTR,W	S.N.A				
....3	AA65-30018A	CLAMP-WIRE;DONG-A,NYLON-66,-,-,DATL-60	S.N.A				
....3	AA61-00707B	HOLDER-COVER;ALL MODEL,NYLON-66 T1.0 V2,	S.N.A				
....3	AA39-20536G	LEAD CONNECTOR ASSY;,1P,F,F,60MM,1617#22					
....2	AA61-01190A	HOLDER-CHASSIS;Z7,HIPS V0,G4309	S.N.A				
....2	AA65-30105A	CLAMP-WIRE;ALL MODEL,NYLON 66,V2,-,NTR,1	S.N.A				
....2	AA94-07792A	ASSY PCB MISC-DYNAMIC FOCUS;CT-29Z7HR,K5					
....3 LH01	AA26-90002C	TRANS-DUMMY;-,-,-,-,-,-,-,-,-,-,EER2					
....3 LH02	AA27-40003L	COIL-HORIZ.WIDTH;-;1.0mH,DR14x20,2UEW0.4					
....3 RH28	2008-001113	R-FUSIBLE(S);0.22ohm,10%,2W,AG,TP;3.9x12					
....3 WIRE3	AA39-20061C	LEAD CONNECTOR-ASSY;,3PYFH800-03,S,200,					
....3	0202-000187	SOLDER-WIRE FLUX;-;RS60S,D1.2,63Sn/37Pb	S.N.A				
....3	AA97-07229L	ASSY AUTO-DYNAMIC FOCUS;CT-29Z7HR,K55A	S.N.A				
....4 EY01	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A				
....4 EY02	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A				
....4 EY03	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A				
....4 EY04	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A				
....4 EY05	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A				
....4 EY06	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A				
....4 EY07	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A				
....4 EY08	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A				
....4 EY09	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A				
....4 GTH01	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A				
....4 GTH02	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A				
....4 GTH03	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A				
....4 PCB	AA41-00152C	PCB-DOUBLE FOCUS;CW29A6VN8X/XEF,FR-1,1L,	S.N.A				
....2	AA94-07799A	ASSY PCB MISC-TACT SWITCH;CT-29Z7HR,K55A	S.N.A				
....3 CN01	AA39-20055C	LEAD CONNECTOR-ASSY;,6P,YBNH025-06,67096					
....3 LD02	0601-000262	LED;ROUND,RED,5mm,700nm					
....3 RM01	AA32-00012A	MODULE REMOCON;ORC-50HF2,38KHZ,940NM,MES					
....3 SVW01	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST					
....3	0202-000187	SOLDER-WIRE FLUX;-;RS60S,D1.2,63Sn/37Pb	S.N.A				
....3	AA97-07229J	ASSY AUTO-TACH SWITCH;CT-29Z7HR,K55A	S.N.A				
....4 CC01	2401-002291	C-AL;47uF,20%,16V,GP,TP;6.3x5.5					
....4 DC01	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,					
....4 DC02	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,					
....4 PCB	AA41-00622A	PCB-TACT SWITCH(Z7);CT-29HMM,FR-1,1L,A,1	S.N.A				

## ASSY COVER FRONT

1	*	AA90-03202B	ASSY COVER FRONT;TXM3298HFX/XAA	
..2	C/F	AA65-00011C	CLAMP-WIRE;ALL MODEL,NYLON 66,V2,-,NTR,2	S.N.A
..2	CA+CF	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
..2	CB+CF	AA60-10050T	SCREW-TAPPING;-;SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2	CB+TBA	AA60-10050T	SCREW-TAPPING;-;SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2	CC+CF	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
..2	CRT+CF	AA60-10050V	SCREW-ASSY;-;SWRCH18A,M6,L30,HH,+,WC,-,Z	S.N.A
..2	CV+CB	AA60-10050T	SCREW-TAPPING;-;SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2	CV+CB+	AA60-10050T	SCREW-TAPPING;-;SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2	D-COIL	AA65-30113A	CLAMP-D,COIL;-;NYLON 66,V2,-,BLK,TVI 25-	S.N.A
..2	D-COIL	AA65-30017A	CLAMP-D,COIL;-;NYLON-66,VO,-,NTR,DADH300	S.N.A
..2	PP+CF	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
..2	TBA+RJ	AA60-10050T	SCREW-TAPPING;-;SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2	WOO+CB	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	S.N.A
..2		AA91-03960A	ASSY HOLDER SPK;-;80HM/25W,-,WOOFER SP	
..2		AA96-00916B	ASSY COVER P-CAINET FRONT;34Z7,TXM3298HF	
..3	GS+CF	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	S.N.A
..3	KNOPOW	AA61-60003J	SPRING-CS;-;SUS304,-,-,OD6,N7,OD6,-,-,-,	S.N.A
..3	LED+GS	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	S.N.A
..3	SPK+CF	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	S.N.A
..3		AA64-02665A	WINDOW-RMC;Z7,PC,VIOLET	
..3		AA64-02666A	INDICATOR LED;Z7,ACRYL,CLR	
..3		AA64-70124C	BADGE-BRAND;-;AL,-,-,L=70,SAMSUNG,SILVER	S.N.A
..3		AA65-00011C	CLAMP-WIRE;ALL MODEL,NYLON 66,V2,-,NTR,2	S.N.A
..3		AA91-03959A	ASSY HOLDER SPK;-;80HM/10W,-,FRONT SPE	
..3		AA65-30105A	CLAMP-WIRE;ALL MODEL,NYLON 66,V2,-,NTR,1	S.N.A
..3		AA64-02654B	CABINET-FRONT;TXM3298,HIPS,VO,W91499,SV0	
..3		AA64-02657B	GRILLE-SPEAKER;3Z27,HIPS,VO,G4309,DG-703	
..3		AA64-02663A	KNOB-POWER;Z7,PC,VIOLET	
..3		AA64-02664A	DECORATION-POWER;Z7,ABS,HB,NTR	
..2		AA73-00005B	RUBBER-CAP;FLAT,PRJ,SILICONE RUBBER,WHIT	
..2		AA61-01108A	SUPPORT-CRT;Z7,HIPS	S.N.A
..2		AA60-00055A	SPACER-GUM,CRT;ALL MODEL,NTR RUBBER,-,-,	S.N.A

## ASSY COVER REAR

1	*	AA90-03205B	ASSY COVER REAR;TXM3298HFX/XAA	
..2		AA65-30008A	CLAMP-CORD;-;PE,HB,-,BLK,-	S.N.A
..2		AA64-60421C	INLAY-COVER;-;PS,T0.3,-,-,BLK,SEA	S.N.A
..2		AA64-02655B	CABINET BACK;34Z7,HIPS,VO,G4309,SV012P	
..2		AA63-00567A	COVER-BACK,R;34Z7,ABS,HB,G4309,DGM2188	S.N.A
..2		AA63-00566A	COVER-BACK,L;34Z7,ABS,HB,G4309,DGM2188	S.N.A
..2		AA60-00091J	SPACER-FELT;-;FELT,330X10,-,-,BLK,T0.5,-	S.N.A

## ASSY CPT

1	*	AA91-03995U	ASSY CPT;A80QEAA891X,34,+380MG,ITC	
△..2		AA03-00357A	CRT COLOR;A80QEAA891X002,+380MG,0.35MH,9.	
..2		AA98-70011F	ASSY TBC WIRE(P);-,34inch,NTSC,2P-WH,KS4	S.N.A
..2		AA27-00275A	COIL DEGAUSSING;SDI 34,14MH,10%,60TS,1	
..2		AA27-00284A	COIL DEGAUSSING;CPTTV,48MH,10%,270TS,-,	

## ASSY LABEL

1	*	AA92-06243G	ASSY LABEL;TXM3298HFX/XAA,K55A	
---	---	-------------	--------------------------------	--

## ASSY P/MATERIAL

1	*	AA92-05219B	ASSY P/MATERIAL;TXM3298HFX/XAA	
---	---	-------------	--------------------------------	--

## Electrical Parts List

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
----------	----------	-----------------------------	--------	----------	----------	-----------------------------	--------

..2	AA60-40006A	PIN-STAPLE;-,-,H18,33X17.8X2.4,-,AUTO	S.N.A
-----	-------------	---------------------------------------	-------

### ASSY BOX

1	*	AA92-05216B	ASSY BOX;TXM3298HFX/XAA
---	---	-------------	-------------------------

### ASSY ACCESSORY

1	*	AA92-05394E	ASSY ACCESSORY;TXM2768HFX/XAA
---	---	-------------	-------------------------------

..2	AA68-02395A	MANUAL USERS;ENG,SEA,K55A,W/P100G B5	
..2	AA59-00254A	REMOCON;TM63,HERCULES,51,G6671B,S/S,E/X	

6-2 Dissimilar Parts List by Inch

NO	PART	L/C	TXM27** (SDI CRT)		TXM30** (LG CRT)		TXM32** (TSB CRT)		REMARK					
			CODE	SPEC	CODE	SPEC	CODE	SPEC						
1	MAIN	C405	-		2201-000259	C-C 500V 0.18nF	-							
2		C409	2301-001385	C-F 630V 30nF	2301-001385	C-F 630V 30nF	2303-001001	C-F 630V 22nF						
3		C412	2301-000254	C-F 50V 39nF	2301-000383	C-F 50V 10nF	2301-000310	C-F 50V 68nF						
4		C415	2301-000203	C-F 100V 2.7nF	2301-000203	C-F 100V 2.7nF	2301-000232	C-F 50V 3.3nF						
5		C423	2301-001192	C-F 400V 820nF	2301-001192	C-F 400V 820nF	2301-001193	C-F 400V 1uF						
6		C426	2306-000195	C-F 400V 360nF	2306-000204	430nF,5%, 400V	2306-000166	C-F 400V 220nF						
7		C425	2301-001259	C-F 400V 100nF	2301-001067	C-F 400V 82nF	2301-001249	C-F 400V 68nF						
8		C414	2401-002597	C-AL 35V 220UF	2401-000039	C-AL 16V 1000UF	2401-002597	C-AL 35V 220UF						
9		D406	0402-000132	1N4004	0404-001056	RK16	0404-001056	RK16						
10		D408	0402-000534	RG10V	-		0402-000534	RG10V						
11		DZ402	0401-000005	1N4148			0401-000005	1N4148						
12		J422	3812-000219	JUMPER	3812-000219	JUMPER	-							
13		J423												
14		J403	-		-		3812-000219	JUMPER						
15		J417												
16		J401			3812-000219	JUMPER	-							
17		L401			2001-001037	0.39oHM,5%, 1/2W								
18		L404	3301-000287	F-B AA	3812-000219	JUMPER	3301-000287	F-B AA						
19		L409	2901-000297	F-B 3A	3812-000219	JUMPER	2901-000297	F-B 3A						
20		CR405S	2301-001343	C-F 2K 3.9nF	2301-001343	C-F 2K 3.9nF	2301-001583	C-C 2K 3NF						
21		CR406S												
22		LR402S	AA27-10004F	COIL-CHOKE 56UH	AA27-10004F	COIL-CHOKE 56UH	AA27-00175A	COIL-H 82UH						
23		LR403S	AA27-00070A	COIL-L 7uH	AA27-00022A	COIL-L 7.5uH	AA27-00251A	COIL-L 10uH						
24		LR404S	AA27-40001S	COIL-H 110uH	AA27-40003P	COIL-H 120uH	AA27-40003P	COIL-H 120uH						
25		Q903	-		3711-004386	C-HEADER 3P	-							
26		R304	2008-001088	R-F 2W 1ohm AG	2008-001114	R-F 2W 1.5ohm AG	2008-001108	R-F 2W 1.2ohm						
27		R305	2003-002157	R-M 220oHM 2W	2003-002205	R-M 330oHM 2W	2003-002205	R-M 330oHM 2W						
28		R306												
29		R307	2008-001088	R-F 2W 1ohm AG	2008-001114	R-F 2W 1.5oHM AG	2008-001114	R-F 2W 1.5ohm						
30		R403	2003-002064	R-M 2W 7.5oHM	2003-000713	R-M 2W 47oHM	2003-000532	R-M 2W 18ohm						
31		R405	2008-001011	R-F 2W 0.18oHM	2008-001018	R-F 2W 0.47oHM	2008-001018	R-F 2W 0.47oHM						
32		R415	2004-001983	R-M 1/2W 2.49K	2004-001379	R-M 1/2W 12K	2004-001983	R-M 1/2W 2.49K						
33		R418	2001-001114	R-C 1/2W 270oHM	2001-001107	R-C 1/2W 220oHM	2001-001114	R-C 1/2W 270oHM						
34		R420	2004-001987	R-M 1/2W 4.3K	2004-004029	R-M 1/2W 10K	2004-001987	R-M 1/2W 4.3K						
35		R422	2008-000251	R-F 2W 0.27oHM	2008-001011	R-F 2W 0.18oHM	2008-001149	0.22OHM,5%,2W						
36		R423	2001-001055	R-C 1/2W 1.8K	2004-001983	R-M 1/2W 2.49K	2001-001093	R-C 1/2W 2.2K						
37		R432	2001-001164	R-C 1/2W 56K	2001-001164	R-C 1/2W 56K	2001-001179	R-C 1/2W 68K						
38		R434	2003-002064	R-M 2W 7.5oHM	2901-000297	F/B 3A	2901-000297	F/B 3A						
39		R435	2003-001042	R-M 2W 5.6K	2003-001042	R-M 2W 5.6K	2003-000784	R-M 2W 7.5K						
40		R440	2004-001893	R-M 1/2W 22K	2001-001112	R-C 1/2W 24K	2004-002019	R-M 1/2W 33K						
41		R821	2004-001891	R-M 1/2W 133K	2004-002015	R-M 1/2W 140K	2004-002015	R-M 1/2W 140K						
42		T444S	AA26-00170A	FUJ-29H002F	AA26-00180A	FUJ-34H002F	AA26-00173A	FUJ34H001F						
43		VM3P	-		-		AA39-10015B	3(2)P						
1	CRT	C501	2201-000193	50V 0.01NF	[32" LG, SDI Refer to differences]		2201-000247	50V 0.015NF						
2		C502	-				2201-002031	50V 0.005PF						
3		C503					2201-000662	50V 0.007NF						
4		C510	2201-000291	500V 1NF			-							
5		C523	2301-001192	400V 820NF										
6		C539	2202-000121	50V 100PF			2202-000632	50V 100NF						
7		J506	3812-000219	JUMPER			-							
8		J507												
9		J509	-				3812-000219	JUMPER						
10		J513												
11		R503	2001-001088	R-C 1/2W 1K			-							
12		R516	2001-001153	R-C 1/2W 47oHM										
13		R519	-				2001-000786	R-C 1/8W 47K						
14		R520	2001-000563	R-C 1/8W 27K			2001-001015	R-C 1/8W 9.1K						
15		R521	-				3812-000219	JUMPER						
16		R524					2002-001012	R-C-P 1/2W 8.2M						
17		R529	2008-000204	R-F 1/2W 0.22oHM			2008-000264	R-F 1W 1oHM						
18		R531	2001-000009	R-C 1/8W 20K			2001-000539	R-C 1/8W 24K						
19		V999S	3704-001032	SOCKET 8P			3704-000114	SOCKET 14P						

6-3 Dissimilar Assy List by Model

ASS'Y		KOREAN						USA			
		Z7 CABINET			Z6 CABINET			M9 CABINET			
		CT-29Z7HR	WT-32Z7HR	CT-34Z7HR	CT-29Z6HR	WT-32Z6HR	CT-34Z6HR	TXM3297HFX/XAA	TXM2796HFX/XAA	TXM2797HFX/XAA	TXM3097WHFXXAA
MAIN	Manual injection	AA94-07670A	AA94-08282J	AA94-08282H	AA94-08533C	AA94-08533E	AA94-08533B	AA94-07669A	AA94-08282Y	←	AA94-08282X
	AUTO	AA97-07229N	AA97-07230Q	AA97-07230P	AA97-07506R	AA97-07608C	AA97-07506S	AA97-07229B	AA97-07506T	←	AA97-07506J
	ROBOT	AA97-07232L	AA97-07232N	AA97-07232M	AA97-07560D	AA97-07560H	AA97-07560E	AA97-07232K	AA97-07560F	←	AA97-07560A
CRT	Manual injection	AA94-08273G	AA94-07791A	AA94-07790A	AA94-08273G	AA94-07791A	AA94-07790A	AA94-07790A	AA94-08273G	←	AA94-07791A
	AUTO	AA97-07230R	AA97-07229M	AA97-07230D	AA97-07230R	AA97-07229M	AA97-07230D	AA97-00230D	AA97-07230R	←	AA97-07229M
	PCB	AA41-00578A	AA41-00639B	AA41-00578B	AA41-00578A	AA41-00639B	AA41-00578B	AA41-00578B	AA41-00578A	←	AA41-00639A
FOCUS	Manual injection	AA94-07792A	←	←	←	←	←	←	←	←	←
	AUTO	AA97-07229L	←	←	←	←	←	←	←	←	←
CONTROL	Manual injection	AA94-07795A	←	AA94-08492A	AA94-08273W	AA94-08584E	AA94-08273U	AA94-07794A	←	←	←
	AUTO	AA97-07229G	←	←	←	←	←	AA97-07229D	←	←	←
	PCB	AA41-00618A	←	←	←	←	←	AA41-10856A	←	←	←
A/V SIDE	Manual injection	AA94-07796A	AA94-08584F	AA94-08493A	AA94-08273V	AA94-08584A	AA94-08273T	AA94-07797A	←	←	←
	AUTO	AA97-07229H	←	←	←	←	←	AA97-07229E	←	←	←
	PCB	AA41-00620A	←	←	←	←	←	AA41-00594A	←	←	←
WOOFER	Manual injection	AA94-07798A	←	←	Not applied						
	AUTO	AA97-07229F	←	←							
TACT SWITCH	Manual injection	AA94-07799A	←	←	AA94-08273S	←	←	Not applied			
	AUTO	AA97-07229J	←	←	AA97-07506L	←	←				
	PCB	AA41-00622A	←	←	AA41-00640A	←	←				
T-BOARD	Manual injection	AA96-00908A	←	←	AA96-00908B	←	←				
F-BOX	Manual injection	AA95-02001H	←	←	←	←	←	AA95-02001J	←	←	←
	SMD	AA97-07232N	←	←	←	←	←	AA97-07506H	←	←	←
	AUTO	AA97-07506M	←	←	←	←	←	AA97-07506N	←	←	←
POWER CODE		AA96-20107C	AA96-20107A	←	AA96-20107C	AA96-20107A	←	AA96-20129A	AA96-20129A	←	←
CPT CRT	ASS'Y	AA91-03134A	AA91-03309A	AA91-03394A	AA91-03134A	AA91-03309A	AA91-03394A	AA91-03394A	AA91-02623A	←	AA91-03309A
	CRT	AA03-00076A	AA03-00243A	AA03-00232A	AA03-00076A	AA03-00243A	AA03-00232A	AA03-00232A	AA03-00076A	←	AA03-00243A
	D-COIL	AA27-00128A	AA27-00019A	AA27-00060A	AA27-00128A	AA27-00019A	AA27-00060A	AA27-00060A	AA27-20002Q	←	AA27-00019A
	TBC-WIRE	AA98-70011D	AA98-70011G	AA98-70011F	AA98-70011D	AA98-70011G	AA98-70011F	AA98-70011F	AA98-70011D	←	AA98-70011G
ACCESSORY	ASS'Y	AA92-04062A	←	←	←	←	←	AA92-04061A	←	←	←
	IB	AA68-02394A	←	←	←	←	←	AA68-02395A	←	←	←
	REMOCON	AA59-00253B	←	←	←	←	←	AA59-00251A	←	←	←
WOOFER SPK		AA91-03960A	←	←	Not applied						
FRONT SPK		AA91-03959A	←	←	AA91-00507A	←	←	←	←	←	←

ASS'Y		USA			KOREAN			SDI CRT Launching Models	
		Z7 CABINET			Z4 CABINET			M9 CABINET	Z7 CABINET
		TXM2798HFX/XAA	TXM3098WFXXAA	TXM3298HFX/XAA	CT-29Z4HRH	WT-32Z4HRH	CT-34Z4HRH	SF-TXM3297HFX/XAA	WT-32Z7HRX/SPL
MAIN	Manual injection	AA94-08282Z	AA94-08533X	AA94-08533Y	AA94-11784A	AA94-11786A	AA94-11785A	AA94-08533S	AA94-08533W
	AUTO	AA97-07506K	AA97-12699G	AA97-12699H	AA97-12699J	AA97-12699L	AA97-12699K	AA97-12699A	AA97-12699F
	ROBOT	AA97-07560B	AA97-12698E	AA97-12698F	AA97-12698G	AA97-12698J	AA97-12698H	AA97-12698A	AA97-12698D
CRT	Manual injection	AA94-08273G	AA94-07791A	AA94-11752A	AA94-08273G	AA94-07791A	AA94-07790A	AA94-11752A	AA94-07791A
	AUTO	AA97-07230R	AA97-07229M	AA97-12699B	AA97-07230R	AA97-07229M	AA97-07230D	AA97-12699B	AA97-07229M
	PCB	AA41-00578B	AA41-00639C	AA41-00578B	AA41-00578B	AA41-00639C	AA41-00578B	AA41-00578B	AA41-00578B
FOCUS	Manual injection	AA94-07792A	←	←	←	←	←	←	←
	AUTO	AA97-07229L	←	←	←	←	←	←	←
CONTROL	Manual injection	AA94-08584J	←	AA94-08584R	AA94-08584T	←	←	AA94-07794A	AA94-07795A
	AUTO	AA97-07229G	←	←	AA97-07506Y	←	←	AA97-07229D	AA97-07229G
	PCB	AA41-00618A	←	←	AA41-00619A	←	←	AA41-10856A	AA41-00618A
A/V SIDE	Manual injection	AA94-11566A	←	AA94-08584N	AA94-08584S	←	←	AA94-07797A	AA94-08584F
	AUTO	AA97-07229H	←	←	AA97-07506V	←	←	AA97-07229E	AA97-07229H
	PCB	AA41-00620A	←	←	AA41-00616A	←	←	AA41-00594A	AA41-00620A
WOOFER	Manual injection	AA94-11567A	←	←	Not applied	AA94-07798A	Not applied		AA94-11567A
	AUTO	AA97-07229F	←	←		AA97-07229F			AA97-07229F
TACT SWITCH	Manual injection	AA94-07799A	←	←	AA94-08273R	←	←	Not applied	AA94-07799A
	AUTO	AA97-07229J	←	←	AA97-07506W	←	←		AA97-07229J
	PCB	AA41-00622A	←	←	AA41-00615A	←	←		AA41-00622A
T-BOARD	Manual injection	AA96-00908F	←	←	AA96-00908B	AA96-00908A	←	←	AA96-00908A
F-BOX	Manual injection	AA95-02001H	←	←	←	←	←	AA95-02001J	AA95-02001H
	SMD	AA97-07232N	←	←	←	←	←	AA97-07506H	AA97-07232N
	AUTO	AA97-07506M	←	←	←	←	←	AA97-07506N	AA97-07506M
POWER CODE		AA96-20129A	AA96-20129B	←	AA96-20107A	AA96-20107A	AA96-20107A	AA96-20129B	AA96-20107A
CPT CRT	ASS'Y	AA91-02623A	AA91-03995W	AA91-03995U	AA91-03134A	AA91-03309A	AA91-03394A	AA91-03995U	AA91-03995W
	CRT	AA03-00076A	AA03-00339A	AA03-00357A	AA03-00076A	AA03-00243A	AA03-00232A	AA03-00357A	AA03-00339A
	D-COIL	AA27-20002Q	AA27-00019A	AA27-00060A	AA27-00128A	AA27-00019A	AA27-00060A	AA27-00275A	AA27-00216A
	TBC-WIRE	AA98-70011D	AA98-70011G	AA98-70011F	AA98-70011D	AA98-70011G	AA98-70011F	AA98-70011F	AA98-70011G
ACCESSORY	ASS'Y	AA92-05394E	AA92-05394E	←	AA92-05394V	←	←	AA92-04061A	AA92-05394N
	IB	AA68-02395A	AA68-02395A	←	AA68-02394A	←	←	AA68-02395A	AA68-02394A
	REMOCON	AA59-00254A	AA59-00254A	←	AA59-00264A	←	←	AA59-00251A	AA59-00253B
K55A WOOFER SPK		AA91-03960A	←	←	Not applied			Not applied	AA91-03960A
K55A FRONT SPK		AA91-03959A	←	←				AA91-00507A	AA91-03959A
K54A COVER FRONT SPK		Not applied			Not applied	AA91-00487A	Not applied	Not applied	
K54A CABINT FRONT SPK					AA91-00486A	←	←		



6-4 Dissimilar Parts List of SDI TSB CRT

PART	L/C	KOREA (CT-29Z7HR)		USA (TXM2797HFX/XAA)		REMARK
		CODE	SPEC	CODE	SPEC	
MAIN	R807	2001-001103	1/2W 20K	Delete		Power Difference
	RX801S	2002-001011	3.3M			
	CY802S	2201-000446	400V 3.3NF			SPEC
	CY801S	Delete		2201-002002	400V 4.7NF	
	RP802S			2002-001010	1.8M	
	C803	2401-003031	450V 470UF	2401-001676	250V 820UF	
	RR01S	Delete		2008-000264	RF 1W 1 (AF)	X-RAY
	RR02S			2001-001149	RC 1/2W 43K	
	RR03S			2004-001897	RM 1/2W 43.2K-F	
	RR04S			2001-000908	RC 1/8W 62K	
	RR05S			2001-001103	RC 1/2W 20K	
	RR06S			2001-000977	RC 1/8W 8.2K	
	RR07S			2004-004029	RM 1/2W 10K-F	
	RR08S			2001-000429	RC 1/8W 1K	
	RR09S			2001-000780	RC 1/8W 470	
	RR10S			2001-000290	RC 1/8W 10K	
	DR01S			0402-000534	RG10V	
	DR02S			3812-000219	JUMPER	
	DZR01S			0403-001321	MTZJ6.8C	
	CR01S			2201-000556	500V 471	
	CR02S			2401-000480	10uF, 20%, 50V	
	CR03S			2401-002235	16V 10UF	
	CR04S			2305-000412	63V 474	
	QR01S			0501-000283	KSA539-Y	
	QR02S			0501-000389	KSC815-Y	
	IC601	1204-001970	MSP3421G-P0-B8	1204-001972	MSP3420G-P0-B10	
CPT CRT	-	AA91-03134A	KOREAN 29"	AA91-03394A	USA 29"	

6-5 Dissimilar Parts List of 32" SDI, TSB, CRT

PART	L/C	TSB CRT		SDI CRT		REMARK
		CODE	SPEC	CODE	SPEC	
MAIN	C426	2306-000166	C-FILM,220nF,400V	2306-000350	C-FILM,274, 400V	CS Capacitor
	LR402S	AA27-00175A	COIL HORIZ, 82uH	AA27-10004F	COIL-CHOKE,56uH	Double Correction Change
	LR403S	AA27-00251A	10uH	AA27-30003F	7.6uH	Improvement of image change (W/COIL)
	C409	2303-001001	22nF,5%,630V, TP	2301-001268	33nF,5%,630V, TP	
	C419	DELETE		2301-000192	1nF,5%,50V, TP	
	C425	2301-001249	C-FILM,68nF,400V	2301-001067	C-FILM,823,250V	CS Capacitor
	C423	2301-001193	C-FILM,1uF,400V	2301-001192	C-FILM,824,400V	
	J417	3812-000219	JUMPER	DELETE		E/W Correction
	J403	3812-000219	JUMPER			
	J422	DELETE		3812-000219	JUMPER	
	J423			3812-000219	JUMPER	
	R440	2004-002019	R-M,33Kohm,1/2W	2004-005052	R-C 1/2W 24K-F	ABL Current (1.8mA)
	T444S	AA26-00173A	FUJ34H001F(S)	AA26-00180A	FUJ-34H002F	32" FBT
	C415	2301-000232	C-FILM,3.3nF,50V	2301-000234	C-FILM,3.9nF,100V	E/W Margin
	R415	2004-001983	2.49Kohm,1%,1/2W	2004-005051	R-C,1/2W 2.2K-F	
	R420	2004-001987	4.3Kohm,1%,1/2W	2004-001406	8.2Kohm,1%,1/2W	
	R418	2001-001114	270OHM,1/2W	2001-001107	R-C 1/2W 220	
	DZ402	0401-000005	1N4148	DELETE		
	L409	2901-000297	EMI ON BOARD	3812-000219	JUMPER	Improvement of Ringing
	R415	2004-001983	R-M,2.49Kohm,1/2	2004-001394	R-M,1/2W 2K-F	E/W Margin
	RR03S	2004-001897	R-M 43.2Kohm	신규자재	R-C 1/2W 39K-F	Difference in Specification
	R423	2001-001093	R-C,1/2W 2.2K	2004-005051	R-C,1/2W 2.2K-F	Improvement of image change (W/COIL)
	PT801S	1404-001026	THERMISTOR,7ohm	1404-001276	THERMISTOR,1.5ohm	DEGAUSSING
CRT	R529	2008-000264	R-F,1ohm,1W	2008-001129	R-F,1.5ohm,1/2W	HEATER
	LF11	2901-000297	FILTER-EMI ON BOARD	2702-001092	2.2uH	
	V999S	3704-000114	SOCKET-CRT,14P	3704-001032	SOCKET-CRT,8P	DUBLE FOCUS
	J507	DELETE		3812-000219	JUMPER	
	R524	2002-001012	COMPOSITION,8.2Mohm,1/2W	DELETE		CRT Difference
	C523	DELETE		2301-001192	C-FILM,820nF,400V	EHT Correction
	J509	3812-000219	JUMPER	DELETE		
	J513	3812-000219	JUMPER			
	C510	DELETE		2201-000291	500V 1NF	
	R506	2001-001194	R-C 82KOHM,5%,1/2W	2001-001198 R-C 91KOHM,5%,1/2W		Shortage of AMP Gain
	R510					
	R511					
	R516	DELETE		2001-001153	R-C 1/2W 47ohm	
	J506			3812-000219	JUMPER	EHT Correction
	R503			2001-001088	R-C 1/2W 1K	
CPT CRT	단품 CRT	AA03-00232A	TSB CRT 34"	AA03-00357A	SDI CRT 34"	Use of SDI, CRT
	D-COIL	AA27-00060A	D-Coil for 34" TSB	AA27-00275A	D-Coil for 34" TSB	

6-6 Dissimilar Parts List of 30" SDI, TSB, CRT

PART	L/C	TSB CRT		SDI CRT		REMARK
		CODE	SPEC	CODE	SPEC	
M A I N	R304	2008-001114	R-C 1.5ohm,5%,2W,AG,TP	2003-002279	R-C 1.2OHM,5%,2W,AG,TP	VERTICAL SIZE
	R307					
	R415	2004-001379	R-M 12Kohm,1%,1/2W,AA	2004-001406	R-M 8.2Kohm,1%,1/2W,AA	EW Adjustment Magin
	R420	2004-004029	R-M 10Kohm,1%,1/2W,AA	2004-001983	R-M 2.49Kohm,1%,1/2W,AA	
CPT CRT	CRT	AA03-00243A	LG CRT	AA03-00339A	SDI CRT	
	D-COIL	AA27-00019A	LG CRT D-COIL	AA27-00216A	SDI CRT D-COIL	

6-7 PCB

PCB	PCB CODE	CABINET SERISE	Size of Single Alignment	Size of Serial Alignment	Request Code of a Single File	Request Code of a Serial File
MAIN	AA41-00667A	ALL CABINET	245X245X1.6T	245X245X1 EA	DP010926-0005	DP010926-0005
CRT	AA41-00639C	32" CABINT	154X195X1.6T	245X330X2 EA	DP011220-0016	DP020109-0003
CRT	AA41-00578B	29",34" CABINT	155x122x1.6T	245x330x4 EA	DP011027-0006	DP011010-0011
CONTROL	AA41-00619A	Z4 CABINT	46.5x90x1.6T	245x245x8 EA	DP020207-0007	DP020207-0008
CONTROL	AA41-00618A	Z7 CABINT	134.5x25x1.6T	245x330x12 EA	DP011206-0012	DP011208-0018
CONTROL	AA41-10856B	M9 CABINT	170.5x44.5x1.6T	245x245x5 EA	DP011030-0002	DP011101-0003
A/V SIDE	AA41-00616A	Z4 CABINT	115x41x1.6T	245x245x8 EA	DP011207-0017	DP011210-0017
A/V SIDE	AA41-00620A	Z7 CABINT	135x39x1.6T	245x330x8 EA	DP011206-0020	DP011207-0037
A/V SIDE	AA41-00594A	M9 CABINT	86x42x1.6T	245x245x8 EA	DP011101-0004	DP011106-0019
TACT SWITCH	AA41-00615A	Z4 CABINT	50x41x1.6T	245x245x12 EA	DP011203-0032	DP011204-0010
TACT SWITCH	AA41-00622A	Z7 CABINT	59x78x1.6T	245x245x6 EA	DP011206-0019	DP011208-0013
TACT SWITCH	AA41-00640A	Z6 CABINT	63x70x1.6T	245x245x9 EA	DP020109-0010	DP020109-0009
WOOFER	AA41-00588A	Z4,Z6,Z7 CABINT	74.5x101x1.6T	245x330x8 EA	DP011016-0015	DP011016-0016
WOOFER JACK	AA41-00641A	Z4,Z6,Z7 CABINT	50x23x1.6T	245x245x24 EA	DP020107-0004	DP020107-0005
F-BOX	AA41-00636B	ALL CABINET	200X122X1.6T	245X245X2 EA	-	-
FOCUS	AA41-00152C	ALL CABINET	-	245X330	-	-