

REPLACEMENT PARTS LIST

LOCA. NO	PART NO	DESCRIPTION	LOCA. NO	PART NO	DESCRIPTION
CAPACITORS					
CA01	181-026A	CAPACITOR C-ARRAY (9*100P)	C1278	0CH1103K516	CHIP CAPA CERAMIC M/L H.D F/S 0.01M 50V K B 2.0X1.25 R/TP
C01A	0CE476DF618	C,ELECTROLYTIC 47UF STD 16V M	C1279	0CE476DF618	C,ELECTROLYTIC 47UF STD 16V M
C01P	0CE107DF618	C,ELECTROLYTIC 100UF STD 16V M	C128	0CN1020K519	C,TUBULA(HIGH DIELE) 1000PF 50V K
C02A	0CN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M	C1280	0CH1103K516	CHIP CAPA CERAMIC M/L H.D F/S 0.01M 50V K B 2.0X1.25 R/TP
C02P	0CH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP	C1281	0CE476DF618	C,ELECTROLYTIC 47UF STD 16V M
C03P	0CH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP	C1282	0CH1103K516	CHIP CAPA CERAMIC M/L H.D F/S 0.01M 50V K B 2.0X1.25 R/TP
C04	0CQ1042K439	C,POLYESTER(MYLAR) 0.1UF S 50V J	C1283	0CH5221K406	CAPA,CHIP CERAMIC M/L T.C R/S 220P 50V J SL 2.0X1.25 R/TP
C04P	0CH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP	C1284	0CH1103K516	CHIP CAPA CERAMIC M/L H.D F/S 0.01M 50V K B 2.0X1.25 R/TP
C05P	0CE106DF618	C,ELECTROLYTIC 10UF STD 16V M	C1285	0CH1103K516	CHIP CAPA CERAMIC M/L H.D F/S 0.01M 50V K B 2.0X1.25 R/TP
C06	0CN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M	C1286	0CE224DK618	C,ELECTROLYTIC 0.22UF STD 50V M
C06P	0CH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP	C1287	0CH1103K516	CHIP CAPA CERAMIC M/L H.D F/S 0.01M 50V K B 2.0X1.25 R/TP
C07	0CN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M	C1288	0CK4720K515	CAPACITOR CERAMIC(HIGH DIELE) 4700P 50V K B TS
C07P	0CE107DD618	C,ELECTROLYTIC 100UF STD 10V M	C1289	0CH1103K516	CHIP CAPA CERAMIC M/L H.D F/S 0.01M 50V K B 2.0X1.25 R/TP
C08	0CN1020K519	C,TUBULA(HIGH DIELE) 1000PF 50V K	C129	0CE476DF618	C,ELECTROLYTIC 47UF STD 16V M
C08P	0CH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP	C1290	0CH5221K406	CAPA,CHIP CERAMIC M/L T.C R/S 220P 50V J SL 2.0X1.25 R/TP
C09P	0CH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP	C1292	0CE476DF618	C,ELECTROLYTIC 47UF STD 16V M
C10P	0CE107DD618	C,ELECTROLYTIC 100UF STD 10V M	C1293	0CH1103K516	CHIP CAPA CERAMIC M/L H.D F/S 0.01M 50V K B 2.0X1.25 R/TP
C101	0CE476DF618	C,ELECTROLYTIC 47UF STD 16V M	C1295	0CE475DK618	C,ELECTROLYTIC 4.7UF STD 50V M
C102	0CN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M	C1296	0CH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP
C103	0CE476DF618	C,ELECTROLYTIC 47UF STD 16V M	C1298	0CH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP
C104	0CK1030K945	C,CERAMIC(HIGH DIELE) 0.01MF 50V Z	C13	0CE105DK618	C,ELECTROLYTIC 1UF STD 50V M
C105	0CE476DF618	C,ELECTROLYTIC 47UF STD 16V M	C13P	0CH5101K406	CAPA,CHIP CERAMIC M/L T.C R/S 100P 50V J SL 2.0X1.25 R/TP
C106	0CN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M	C131	0CE335DK618	C,ELECTROLYTIC 3.3UF STD 50V M
C107	0CN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M	C14P	0CH5331K406	CAPA,CHIP CERAMIC M/L T.C R/S 330P 50V J SL 2.0X1.25 R/TP
C108	0CE475DK618	C,ELECTROLYTIC 4.7UF STD 50V M	C15P	0CH5331K406	CAPA,CHIP CERAMIC M/L T.C R/S 330P 50V J SL 2.0X1.25 R/TP
C109	0CN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M	C16	0CN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M
C11P	0CH5680K406	CAPA,CHIP CERAMIC M/L T.C R/S 68P 50V J SL 2.0X1.25 R/TP	C16P	0CE6849K538	C,ELECTROLYTIC 0.68UF KU 50V K
C110	0CE476DF618	C,ELECTROLYTIC 47UF STD 16V M	C1601	0CE108DJ618	C,ELECTROLYTIC 1000UF STD 35V M
C111	0CN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M	C1602	0CE108DJ618	C,ELECTROLYTIC 1000UF STD 35V M
C112	0CN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M	C1603	181-442Z	C,POLYESTER 0.1MF 50V K
C113	0CE476DF618	C,ELECTROLYTIC 47UF STD 16V M	C1604	0CE108DK61A	C,ELECTROLYTIC 1000UF STD 50V M
C114	0CN1040K949	C,TUBULA(HIGH DIELE) 0.1M 50V Z	C1605	0CK1030K945	C,CERAMIC(HIGH DIELE) 0.01MF 50V Z
C115	0CE105DK618	C,ELECTROLYTIC 1UF STD 50V M	C1606	0CQ1031N509	C,POLYESTER(MYLAR) 0.01U 100V K
C116	0CE225DK618	C,ELECTROLYTIC 2.2UF STD 50V M	C1607	181-442Z	C,POLYESTER 0.1MF 50V K
C117	0CN1040K949	C,TUBULA(HIGH DIELE) 0.1M 50V Z	C1608	0CE107DH618	C,ELECTROLYTIC 100UF STD 25V M
C118	0CE226DK618	C,ELECTROLYTIC 22UF STD 50V M	C1609	0CE106DH618	C,ELECTROLYTIC 10UF STD 25V M
C119	0CN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M	C1610	0CQ1031N509	C,POLYESTER(MYLAR) 0.01U 100V K
C12	0CN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M	C1611	0CE107DH618	C,ELECTROLYTIC 100UF STD 25V M
C12P	0CH5680K406	CAPA,CHIP CERAMIC M/L T.C R/S 68P 50V J SL 2.0X1.25 R/TP	C1612	0CE106DH618	C,ELECTROLYTIC 10UF STD 25V M
C120	0CN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M	C1613	0CQ1031N509	C,POLYESTER(MYLAR) 0.01U 100V K
C121	0CE225DK618	C,ELECTROLYTIC 2.2UF STD 50V M	C1614	0CE107DH618	C,ELECTROLYTIC 100UF STD 25V M
C122	181-444E	C,METALPOLYESTER 0.1MF 50V J	C1615	0CE106DH618	C,ELECTROLYTIC 10UF STD 25V M
C124	0CN4710K519	C,TUBULA(HIGH DIELE) 470PF 50V K	C1616	0CE106DH618	C,ELECTROLYTIC 10UF STD 25V M
C125	0CN1040K949	C,TUBULA(HIGH DIELE) 0.1M 50V Z	C1617	0CE228DJ650	C,ELECTROLYTIC 2200UF STD 35V M
C126	0CN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M	C1618	181-442Z	C,POLYESTER 0.1MF 50V K
C127	0CN1020K519	C,TUBULA(HIGH DIELE) 1000PF 50V K	C1619	0CE228DJ650	C,ELECTROLYTIC 2200UF STD 35V M
C1271	0CH1103K516	CHIP CAPA CERAMIC M/L H.D F/S 0.01M 50V K B 2.0X1.25 R/TP	C1620	0CE108DK61A	C,ELECTROLYTIC 1000UF STD 50V M
C1272	0CH4100K406	CHIP CAPA CERAMIC M/L T.C F/S 10P 50V J SL 2.0X1.2 R/TP	C1621	0CK1030K945	C,CERAMIC(HIGH DIELE) 0.01MF 50V Z
C1273	0CH4100K406	CHIP CAPA CERAMIC M/L T.C F/S 10P 50V J SL 2.0X1.2 R/TP	C1622	0CQ1031N509	C,POLYESTER(MYLAR) 0.01U 100V K
C1275	0CH1103K516	CHIP CAPA CERAMIC M/L H.D F/S 0.01M 50V K B 2.0X1.25 R/TP	C1623	181-442Z	C,POLYESTER 0.1MF 50V K
C1277	0CE226DF618	C,ELECTROLYTIC 22UF STD 16V M	C1624	0CE107DH618	C,ELECTROLYTIC 100UF STD 25V M

LOCA. NO	PART NO	DESCRIPTION	LOCA. NO	PART NO	DESCRIPTION
C1625	OCE106DH618	C,ELECTROLYTIC 10UF STD 25V M	C2021	OCK1030K945	C,CERAMIC(HIGH DIELE) 0.01MF 50V Z
C1626	OCQ6821N519	C,POLYESTER(MYLAR) 0.0068U 100V K	C203	181-444L	C,METALPOLYESTER 0.33MF 50V J
C1627	OCE107DH618	C,ELECTROLYTIC 100UF STD 25V M	C204	OCE105DK618	C,ELECTROLYTIC 1UF STD 50V M
C1628	OCE107DH618	C,ELECTROLYTIC 100UF STD 25V M	C205	OCE106DK618	C,ELECTROLYTIC 10UF STD 50V M
C1629	OCE106DH618	C,ELECTROLYTIC 10UF STD 25V M	C206	OCK1040K945	C,CERAMIC(HIGH DIELE) 0.1M 50V Z
C1630	OCE106DK618	C,ELECTROLYTIC 10UF STD 50V M	C207	OCE106DK618	C,ELECTROLYTIC 10UF STD 50V M
C1631	OCE106DH618	C,ELECTROLYTIC 10UF STD 25V M	C208	OCK1040K945	C,CERAMIC(HIGH DIELE) 0.1M 50V Z
C1632	OCE474DK618	C,ELECTROLYTIC 0.47UF STD 50V M	C209	OCQ2242K439	C,POLYESTER(MYLAR) 0.22UF S 50V J
C1633	OCE334DK618	C,ELECTROLYTIC 0.33UF STD 50V M	C21	OCN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M
C1634	OCQ5631N409	C,POLYESTER(MYLAR) 0.0560UF 100V J	C21P	OCQ2231N509	C,POLYESTER(MYLAR) 0.022MF 100V K
C1635	OCK1030K945	C,CERAMIC(HIGH DIELE) 0.01MF 50V Z	C210	OCK1040K945	C,CERAMIC(HIGH DIELE) 0.1M 50V Z
C1636	OCQ5631N409	C,POLYESTER(MYLAR) 0.0560UF 100V J	C211	OCE106DK618	C,ELECTROLYTIC 10UF STD 50V M
C1637	OCE334DK618	C,ELECTROLYTIC 0.33UF STD 50V M	C213	OCX5600K409	C,TUBULA(T.C) 56P 50V J
C1638	OCQ5621N419	C,POLYESTER(MYLAR) 5600P 100V J	C214	OCX5600K409	C,TUBULA(T.C) 56P 50V J
C1639	181-442Z	C,POLYESTER 0.1MF 50V K	C215	OCX5600K409	C,TUBULA(T.C) 56P 50V J
C1640	OCK1030K945	C,CERAMIC(HIGH DIELE) 0.01MF 50V Z	C216	OCE225DK618	C,ELECTROLYTIC 2.2UF STD 50V M
C1641	OCE107DF618	C,ELECTROLYTIC 100UF STD 16V M	C217	OCE476DF618	C,ELECTROLYTIC 47UF STD 16V M
C1667	OCE227DF618	C,ELECTROLYTIC 220UF STD 16V M	C218	OCK1030K945	C,CERAMIC(HIGH DIELE) 0.01MF 50V Z
C1668	OCE477DF618	C,ELECTROLYTIC 470UF STD 16V M	C219	OCQ3000K415	CAPACITOR CERAMIC(TEMP COMP) 30P 50V JNPO TP
C1669	OCQ3931N509	C,POLYESTER(MYLAR) 0.039UF 100V K	C22P	OCQ4721N509	C,POLYESTER(MYLAR) 0.0047U 100V K
C17P	OCQ3321N509	C,POLYESTER(MYLAR) 0.0033U 100V K	C220	OCQ3000K415	CAPACITOR CERAMIC(TEMP COMP) 30P 50V JNPO TP
C1701	OCH5101K406	CAPA,CHIP CERAMIC M/L T.C R/S 100P 50V J SL 2.0X1.25 R/TP	C221	OCK1040K945	C,CERAMIC(HIGH DIELE) 0.1M 50V Z
C1702	OCH5101K406	CAPA,CHIP CERAMIC M/L T.C R/S 100P 50V J SL 2.0X1.25 R/TP	C222	OCE106DK618	C,ELECTROLYTIC 10UF STD 50V M
C1703	OCH5101K406	CAPA,CHIP CERAMIC M/L T.C R/S 100P 50V J SL 2.0X1.25 R/TP	C223	OCK1040K945	C,CERAMIC(HIGH DIELE) 0.1M 50V Z
C1705	OCQ1810K475	CAPACITOR,CERAMIC(TEMP COMP) 180PF 50V J N750 TR	C2230	OCN4710K519	C,TUBULA(HIGH DIELE) 470PF 50V K
C1706	OCH4120K406	CAPA,CHIP CERAMIC M/L T.C F/S 12PF 50V J SL 2012 R/TP	C2231	OCN4710K519	C,TUBULA(HIGH DIELE) 470PF 50V K
C1707	OCH4120K406	CAPA,CHIP CERAMIC M/L T.C F/S 12PF 50V J SL 2012 R/TP	C2233	OCQ1031N509	C,POLYESTER(MYLAR) 0.01U 100V K
C1708	OCQ1010K465	CAPACITOR,CERAMIC(TEMP COMP) 100PF 50V J N470 TR	C2234	OCQ4731N509	C,POLYESTER(MYLAR) 0.047U 100V K
C1709	OCE477DF618	C,ELECTROLYTIC 470UF STD 16V M	C2237	OCN4710K519	C,TUBULA(HIGH DIELE) 470PF 50V K
C1710	OCH103K516	CHIP CAPA CERAMIC M/L H.D F/S 0.01M 50V K B 2.0X1.25 R/TP	C2238	OCN4710K519	C,TUBULA(HIGH DIELE) 470PF 50V K
C1711	OCE476DF618	C,ELECTROLYTIC 47UF STD 16V M	C224	OCE106DK618	C,ELECTROLYTIC 10UF STD 50V M
C1713	OCH103K516	CHIP CAPA CERAMIC M/L H.D F/S 0.01M 50V K B 2.0X1.25 R/TP	C225	OCE228DD618	CAPACITOR,ELECTROLYTIC 2200UF STD 10V M FL TP5
C1714	OCE476DF618	C,ELECTROLYTIC 47UF STD 16V M	C226	OCE107DF618	C,ELECTROLYTIC 100UF STD 16V M
C18	OCE476DF618	C,ELECTROLYTIC 47UF STD 16V M	C227	OCE106DK618	C,ELECTROLYTIC 10UF STD 50V M
C18P	OCE475DK618	C,ELECTROLYTIC 4.7UF STD 50V M	C228	OCN1810K519	C,TUBULA(HIGH DIELE) 180PF 50V K
C19P	181-444E	C,METALPOLYESTER 0.1MF 50V J	C229	181-444J	C,METALPOLYESTER 0.22MF 50V J
C20	OCK1040K945	C,CERAMIC(HIGH DIELE) 0.1M 50V Z	C23	OCN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M
C20P	OCH104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP	C23P	OCQ1500K415	C,CERAMIC(TEMP COMP) 15P 50V J
C2001	OCE106DK618	C,ELECTROLYTIC 10UF STD 50V M	C230	OCN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M
C2002	OCE107DH618	C,ELECTROLYTIC 100UF STD 25V M	C231	OCX2700K409	C,TUBULA(T.C) 27PF 50V J
C2003	OCE1066R618	C,ELECTROLYTIC 10UF SMS 250V M	C232	OCN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M
C2004	OCE2261P618	C,ELECTROLYTIC 22UF SM 160V M	C235	OCE107DF618	C,ELECTROLYTIC 100UF STD 16V M
C201	OCQ2200K415	C,CERAMIC(TEMP COMP) 22P 50V J	C236	OCQ2242K439	C,POLYESTER(MYLAR) 0.22UF S 50V J
C2010	OCN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M	C237	181-444J	C,METALPOLYESTER 0.22MF 50V J
C2014	OCN1010K519	C,TUBULA(HIGH DIELE) 100PF 50V K	C238	OCN3910K519	C,TUBULA(HIGH DIELE) 390P 50V K
C2015	OCN1010K519	C,TUBULA(HIGH DIELE) 100PF 50V K	C239	OCE476DF618	C,ELECTROLYTIC 47UF STD 16V M
C2016	OCK4720W510	C,CERAMIC(HIGH DIELE) 4700P 500V K	C24	OCE227DF618	C,ELECTROLYTIC 220UF STD 16V M
C2017	OCK4720W510	C,CERAMIC(HIGH DIELE) 4700P 500V K	C24P	OCQ1800K415	C,CERAMIC(TEMP COMP) 18P 50V J
C2018	OCE107DD618	C,ELECTROLYTIC 100UF STD 10V M	C240	OCN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M
C2019	OCE107DD618	C,ELECTROLYTIC 100UF STD 10V M	C241	181-444J	C,METALPOLYESTER 0.22MF 50V J
C202	OCQ2200K415	C,CERAMIC(TEMP COMP) 22P 50V J	C242	181-444J	C,METALPOLYESTER 0.22MF 50V J
C2020	OCK1020W515	C,CERAMIC(HIGH DIELE) 1000PF 500V K	C243	OCQ2242K439	C,POLYESTER(MYLAR) 0.22UF S 50V J

LOCA. NO	PART NO	DESCRIPTION	LOCA. NO	PART NO	DESCRIPTION
C244	181-444J	C,METALPOLYESTER 0.22MF 50V J	C408	181-010V	CAPACITOR PP 630V 0.0068UF J
C245	OCQ2242K439	C,POLYESTER(MYLAR) 0.22UF S 50V J	C409	0CE107DJ618	C,ELECTROLYTIC 100UF STD 35V M
C246	OCN1010K519	C,TUBULA(HIGH DIELE) 100PF 50V K	C41P	0CE475DK618	C,ELECTROLYTIC 4.7UF STD 50V M
C248	OCN4710K519	C,TUBULA(HIGH DIELE) 470PF 50V K	C411	181-060X	CAPACITOR PP 400V 0.15UF J
C249	OCN4710K519	C,TUBULA(HIGH DIELE) 470PF 50V K	C412	181-013T	CAPACITOR MPP 400V 0.70UF J
C25	0CE107DF618	C,ELECTROLYTIC 100UF STD 16V M	C413	181-013V	C,MPP 400V 0.39UF J
C25P	181-444E	C,METALPOLYESTER 0.1MF 50V J	C414	OCK4710K515	C,CERAMIC(HIGH DIELE) 470P 50V K
C250	OCN4710K519	C,TUBULA(HIGH DIELE) 470PF 50V K	C415	OCK1030K945	C,CERAMIC(HIGH DIELE) 0.01MF 50V Z
C251	OCN4710K519	C,TUBULA(HIGH DIELE) 470PF 50V K	C417	0CE6851K652	CAPACITOR,ELECTROLYTIC 6.8000UF SM 50V M FM7.5 BP(S)
C252	OCX1800K409	C,TUBULA(T.C) 18PF 50V J	C418	0CE6851K652	CAPACITOR,ELECTROLYTIC 6.8000UF SM 50V M FM7.5 BP(S)
C253	0CE476DF618	C,ELECTROLYTIC 47UF STD 16V M	C419	0CE476DH618	C,ELECTROLYTIC 47UF STD 25V M
C254	OCN4710K519	C,TUBULA(HIGH DIELE) 470PF 50V K	C42P	0CE107DD618	C,ELECTROLYTIC 100UF STD 10V M
C255	OCN4710K519	C,TUBULA(HIGH DIELE) 470PF 50V K	C420	OCK1020K515	C,CERAMIC(HIGH DIELE) 1000PF 500V K
C256	OCN3910K519	C,TUBULA(HIGH DIELE) 390P 50V K	C421	0CE105DK618	C,ELECTROLYTIC 1UF STD 50V M
C257	0CE477DF618	C,ELECTROLYTIC 470UF STD 16V M	C422	0CE2276Q650	C,ELECTROLYTIC 220UF SMS 200V M
C258	0CE476DF618	C,ELECTROLYTIC 47UF STD 16V M	C423	0CE3361R610	C,ELECTROLYTIC 33U SM 250V M
C26	0CE227DF618	C,ELECTROLYTIC 220UF STD 16V M	C424	OCK56101515	C,CERAMIC(HIGH DIELE) 560P 1KV K
C26P	0CE475DK618	C,ELECTROLYTIC 4.7UF STD 50V M	C425	OCQ2241N501	C,POLYESTER(MYLAR) 0.22MF 100V L
C261	0CE107DF618	C,ELECTROLYTIC 100UF STD 16V M	C426	OCQ3331N509	C,POLYESTER(MYLAR) 0.033U 100V K
C263	0CE106DK618	C,ELECTROLYTIC 10UF STD 50V M	C427	181-452H	CAPACITOR MPP 1.6KV 912H
C264	OCN3910K519	C,TUBULA(HIGH DIELE) 390P 50V K	C428	OCK56101515	C,CERAMIC(HIGH DIELE) 560P 1KV K
C265	OCN3910K519	C,TUBULA(HIGH DIELE) 390P 50V K	C429	OCK56101515	C,CERAMIC(HIGH DIELE) 560P 1KV K
C266	OCN3910K519	C,TUBULA(HIGH DIELE) 390P 50V K	C43P	0CH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP
C27P	0CE475DK618	C,ELECTROLYTIC 4.7UF STD 50V M	C430	0CE477DH618	C,ELECTROLYTIC 470UF STD 25V M
C28P	0CE475DK618	C,ELECTROLYTIC 4.7UF STD 50V M	C431	0CE108DJ618	C,ELECTROLYTIC 1000UF STD 35V M
C29P	0CH5101K406	CAPA,CHIP CERAMIC M/L T.C R/S 100P 50V J SL 2.0X1.25 R/TP	C432	0CE477DH618	C,ELECTROLYTIC 470UF STD 25V M
C3S	OCN4710K519	C,TUBULA(HIGH DIELE) 470PF 50V K	C433	OCQ1021N509	C,POLYESTER(MYLAR) 0.001U 100V K
C30P	0CH5101K406	CAPA,CHIP CERAMIC M/L T.C R/S 100P 50V J SL 2.0X1.25 R/TP	C434	OCX6800K409	C,TUBULA(T.C) 68P 50V J
C301	OCQ4741N501	CAPACITOR POLYESTER(MYLAR) 0.47U 100V K POLY F5	C435	OCK56101515	C,CERAMIC(HIGH DIELE) 560P 1KV K
C302	0CE107DJ618	C,ELECTROLYTIC 100UF STD 35V M	C436	0CE107DK618	C,ELECTROLYTIC 100UF STD 50V M
C303	0CE477DH618	C,ELECTROLYTIC 470UF STD 25V M	C438	181-014S	CAPACITOR MPP 2000V 0.0022UF J
C304	0CE477DH618	C,ELECTROLYTIC 470UF STD 25V M	C44P	0CE477DD618	C,ELECTROLYTIC 470UF STD 10V M
C305	OCQ4731N509	C,POLYESTER(MYLAR) 0.047U 100V K	C440	OCQ2721N409	C,POLYESTER(MYLAR) 2700PF 100V J
C306	OCK5610K515	C,CERAMIC(HIGH DIELE) 560P 50V K	C45P	0CH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP
C309	0CC2710K415	CAPACITOR CERAMIC(TEMP COMP) 270P 50V J NPO TP	C46P	0CH4470K406	CHIP CAPA CERAMIC M/L T.C F/S 47P 50V J SL 2.0X1.2 R/TP
C310	OCN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M	C47P	0CH4470K406	CHIP CAPA CERAMIC M/L T.C F/S 47P 50V J SL 2.0X1.2 R/TP
C32P	0CE475DK618	C,ELECTROLYTIC 4.7UF STD 50V M	C48P	0CH4470K406	CHIP CAPA CERAMIC M/L T.C F/S 47P 50V J SL 2.0X1.2 R/TP
C33P	0CH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP	C49P	0CH4470K406	CHIP CAPA CERAMIC M/L T.C F/S 47P 50V J SL 2.0X1.2 R/TP
C34P	0CH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP	C5S	OCN4710K519	C,TUBULA(HIGH DIELE) 470PF 50V K
C35P	0CE475DK618	C,ELECTROLYTIC 4.7UF STD 50V M	C50P	0CH4470K406	CHIP CAPA CERAMIC M/L T.C F/S 47P 50V J SL 2.0X1.2 R/TP
C36P	0CH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP	C501	OCK1030K945	C,CERAMIC(HIGH DIELE) 0.01MF 50V Z
C37P	0CE107DD618	C,ELECTROLYTIC 100UF STD 10V M	C502	0CE476DF618	C,ELECTROLYTIC 47UF STD 16V M
C38P	0CH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP	C503	OCQ1042K439	C,POLYESTER(MYLAR) 0.1UF S 50V J
C39P	0CE107DD618	C,ELECTROLYTIC 100UF STD 10V M	C504	OCQ1042K439	C,POLYESTER(MYLAR) 0.1UF S 50V J
C4S	OCN4710K519	C,TUBULA(HIGH DIELE) 470PF 50V K	C505	OCN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M
C40P	0CH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP	C506	0CE476DF618	C,ELECTROLYTIC 47UF STD 16V M
C401	0CE474DK618	C,ELECTROLYTIC 0.47UF STD 50V M	C507	0CE107DF618	C,ELECTROLYTIC 100UF STD 16V M
C403	OCK1020W515	C,CERAMIC(HIGH DIELE) 1000PF 500V K	C508	181-444J	C,METALPOLYESTER 0.22MF 50V J
C404	0CE225DP618	C,ELECTROLYTIC 2.2UF STD 160V M	C509	181-444E	C,METALPOLYESTER 0.1MF 50V J
C405	181-014S	CAPACITOR MPP 2000V 0.0022UF J	C51P	0CH4470K406	CHIP CAPA CERAMIC M/L T.C F/S 47P 50V J SL 2.0X1.2 R/TP
C406	OCK5610W515	C,CERAMIC(HIGH DIELE) 560PF 500V K	C510	OCN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M
C407	181-014X	CAPACITOR MPP 2KV 0.0077UF J	C511	0CE476DF618	C,ELECTROLYTIC 47UF STD 16V M

LOCA. NO	PART NO	DESCRIPTION	LOCA. NO	PART NO	DESCRIPTION
C512	OCN1010K519	C,TUBULA(HIGH DIELE) 100PF 50V K	C563	OCE107DF618	C,ELECTROLYTIC 100UF STD 16V M
C513	OCN1010K519	C,TUBULA(HIGH DIELE) 100PF 50V K	C564	OCX1500K409	C,TUBULA(T.C) 15PF 50V J
C514	181-444N	C,METALPOLYESTER 0.47MF 50V J	C565	OCX1500K409	C,TUBULA(T.C) 15PF 50V J
C515	181-444N	C,METALPOLYESTER 0.47MF 50V J	C566	OCN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M
C516	OCC6800K415	CAPACITOR CERAMIC(TEMP COMP) 68P 50V J NPO TP	C567	OCN1010K519	C,TUBULA(HIGH DIELE) 100PF 50V K
C517	OCC6800K415	CAPACITOR CERAMIC(TEMP COMP) 68P 50V J NPO TP	C568	OCN1010K519	C,TUBULA(HIGH DIELE) 100PF 50V K
C518	OCC3310K405	CAPACITOR CERAMIC(TEMP COMP) 330P 50V J SL TS	C569	OCN1020K519	C,TUBULA(HIGH DIELE) 1000PF 50V K
C519	OCC2210K415	CAPACITOR CERAMIC(TEMP COMP) 220P 50V J NPO TP	C57P	0CH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP
C52P	0CH4470K406	CHIP CAPA CERAMIC M/L T.C F/S 47P 50V J SL 2.0X1.2 R/TP	C570	OCN3310K519	C,TUBULA(HIGH DIELE) 330P 50V K
C520	OCC2210K415	CAPACITOR CERAMIC(TEMP COMP) 220P 50V J NPO TP	C58P	0CH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP
C521	181-444N	C,METALPOLYESTER 0.47MF 50V J	C59P	OCE107DD618	C,ELECTROLYTIC 100UF STD 10V M
C523	OCE107DF618	C,ELECTROLYTIC 100UF STD 16V M	C6S	OCN4710K519	C,TUBULA(HIGH DIELE) 470PF 50V K
C524	OCQ1042K439	C,POLYESTER(MYLAR) 0.1UF S 50V J	C60P	OCE475DK618	C,ELECTROLYTIC 4.7UF STD 50V M
C525	181-444E	C,METALPOLYESTER 0.1MF 50V J	C603	OCE476DF618	C,ELECTROLYTIC 47UF STD 16V M
C526	OCQ1042K439	C,POLYESTER(MYLAR) 0.1UF S 50V J	C604	OCQ3931N509	C,POLYESTER(MYLAR) 0.039UF 100V K
C527	OCE106DK618	C,ELECTROLYTIC 10UF STD 50V M	C605	OCQ1042K439	C,POLYESTER(MYLAR) 0.1UF S 50V J
C528	181-444E	C,METALPOLYESTER 0.1MF 50V J	C606	OCQ5621N509	C,POLYESTER(MYLAR) 5600PF 100V K
C529	OCQ1042K439	C,POLYESTER(MYLAR) 0.1UF S 50V J	C607	OCN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M
C53P	0CH4470K406	CHIP CAPA CERAMIC M/L T.C F/S 47P 50V J SL 2.0X1.2 R/TP	C608	OCE476DF618	C,ELECTROLYTIC 47UF STD 16V M
C530	181-444E	C,METALPOLYESTER 0.1MF 50V J	C609	OCQ1042K439	C,POLYESTER(MYLAR) 0.1UF S 50V J
C531	OCQ4731N509	C,POLYESTER(MYLAR) 0.047U 100V K	C61P	0CH2333K516	CAPA,CHIP CERAMIC M/L H.D R/S 33000P 50V K B 2.0X1.25 R/TP
C532	OCQ1042K439	C,POLYESTER(MYLAR) 0.1UF S 50V J	C610	OCQ5621N509	C,POLYESTER(MYLAR) 5600PF 100V K
C533	OCQ4731N509	C,POLYESTER(MYLAR) 0.047U 100V K	C611	OCQ3931N509	C,POLYESTER(MYLAR) 0.039UF 100V K
C534	OCK1040K945	C,CERAMIC(HIGH DIELE) 0.1M 50V Z	C612	OCE476DF618	C,ELECTROLYTIC 47UF STD 16V M
C535	OCE476DF618	C,ELECTROLYTIC 47UF STD 16V M	C613	OCE226DK618	C,ELECTROLYTIC 22UF STD 50V M
C536	181-444E	C,METALPOLYESTER 0.1MF 50V J	C614	OCE226DK618	C,ELECTROLYTIC 22UF STD 50V M
C537	OCE105DK618	C,ELECTROLYTIC 1UF STD 50V M	C615	OCE226DK618	C,ELECTROLYTIC 22UF STD 50V M
C538	OCE475DK618	C,ELECTROLYTIC 4.7UF STD 50V M	C616	OCE226DK618	C,ELECTROLYTIC 22UF STD 50V M
C539	OCQ1042K439	C,POLYESTER(MYLAR) 0.1UF S 50V J	C617	OCE106DK618	C,ELECTROLYTIC 10UF STD 50V M
C54P	0CH4470K406	CHIP CAPA CERAMIC M/L T.C F/S 47P 50V J SL 2.0X1.2 R/TP	C618	OCE476DF618	C,ELECTROLYTIC 47UF STD 16V M
C540	181-444E	C,METALPOLYESTER 0.1MF 50V J	C619	OCE106DK618	C,ELECTROLYTIC 10UF STD 50V M
C541	181-0321	C,TANTAL 1.0MF 25V K	C620	OCK1030K945	C,CERAMIC(HIGH DIELE) 0.01MF 50V Z
C542	OCQ4721N509	C,POLYESTER(MYLAR) 0.0047U 100V K	C621	OCE335DK618	C,ELECTROLYTIC 3.3UF STD 50V M
C543	OCQ3321N509	C,POLYESTER(MYLAR) 0.0033U 100V K	C622	OCQ1031N509	C,POLYESTER(MYLAR) 0.01U 100V K
C544	OCE107DF618	C,ELECTROLYTIC 100UF STD 16V M	C623	OCC4710K405	CAPACITOR CERAMIC(TEMP COMP) 470P 50V J SL TP
C545	OCN1040K949	C,TUBULA(HIGH DIELE) 0.1M 50V Z	C624	OCC4710K405	CAPACITOR CERAMIC(TEMP COMP) 470P 50V J SL TP
C546	OCQ1042K439	C,POLYESTER(MYLAR) 0.1UF S 50V J	C625	181-444L	C,METALPOLYESTER 0.33MF 50V J
C547	OCQ3921N409	CAPACITOR POLYESTER(MYLAR) 0.0039U 100V J POLY TP	C626	181-444L	C,METALPOLYESTER 0.33MF 50V J
C548	OCC2210K415	CAPACITOR CERAMIC(TEMP COMP) 220P 50V J NPO TP	C627	181-444L	C,METALPOLYESTER 0.33MF 50V J
C549	OCC1500K415	C,CERAMIC(TEMP COMP) 15P 50V J	C628	181-444L	C,METALPOLYESTER 0.33MF 50V J
C55P	0CH4470K406	CHIP CAPA CERAMIC M/L T.C F/S 47P 50V J SL 2.0X1.2 R/TP	C629	181-444L	C,METALPOLYESTER 0.33MF 50V J
C550	OCQ1042K439	C,POLYESTER(MYLAR) 0.1UF S 50V J	C630	181-444L	C,METALPOLYESTER 0.33MF 50V J
C551	OCQ1042K439	C,POLYESTER(MYLAR) 0.1UF S 50V J	C63P	OCE475DK618	C,ELECTROLYTIC 4.7UF STD 50V M
C552	OCN2710K519	C,TUBULA(HIGH DIELE) 270PF 50V K	C631	OCN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M
C553	OCQ1042K439	C,POLYESTER(MYLAR) 0.1UF S 50V J	C632	OCE106DK618	C,ELECTROLYTIC 10UF STD 50V M
C554	OCN5610K519	C,TUBULA(HIGH DIELE) 560P 50V K	C633	181-444L	C,METALPOLYESTER 0.33MF 50V J
C555	OCN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M	C634	OCE106DK618	C,ELECTROLYTIC 10UF STD 50V M
C556	OCQ1042K439	C,POLYESTER(MYLAR) 0.1UF S 50V J	C635	OCK1030K945	C,CERAMIC(HIGH DIELE) 0.01MF 50V Z
C557	OCQ2721N409	C,POLYESTER(MYLAR) 2700PF 100V J	C636	OCC5600K415	C,CERAMIC(TEMP COMP) 56P 50V J
C558	OCN2710K519	C,TUBULA(HIGH DIELE) 270PF 50V K	C637	OCC5600K415	C,CERAMIC(TEMP COMP) 56P 50V J
C56P	0CH4470K406	CHIP CAPA CERAMIC M/L T.C F/S 47P 50V J SL 2.0X1.2 R/TP	C638	OCC5600K415	C,CERAMIC(TEMP COMP) 56P 50V J
C562	OCN1040K949	C,TUBULA(HIGH DIELE) 0.1M 50V Z	C639	OCC1300K415	C,CERAMIC(TEMP COMP) 13P 50V J

The components identified by shading and mark Δ are critical for safety.
Replace only with part number specified.

LOCA. NO	PART NO	DESCRIPTION	LOCA. NO	PART NO	DESCRIPTION
C64P	OCH233K516	CAPA,CHIP CERAMIC M/L H.D R/S 33000P 50V K B 2.0X1.25 R/TP	C819	OCE337DH618	C,ELECTROLYTIC 330UF STD 25V M
C640	OCC1300K415	C,CERAMIC(TEMP COMP) 13P 50V J	C82P	OCH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP
C642	OCE335DK618	C,ELECTROLYTIC 3.3UF STD 50V M	C820	OCE108DH618	C,ELECTROLYTIC 1000UF STD 25V M
C645	OCK1030K945	C,CERAMIC(HIGH DIELE) 0.01MF 50V Z	C821	OCE477DJ618	C,ELECTROLYTIC 470UF STD 35V M
C646	OCE476DF618	C,ELECTROLYTIC 47UF STD 16V M	C822	OCE2286K610	CAPACITOR,ELECTROLYTIC 2200M SMS 50V M FL
C647	181-444N	C,METALPOLYESTER 0.47MF 50V J	C823	OCE477DK618	C,ELECTROLYTIC 470UF STD 50V M
C648	181-444N	C,METALPOLYESTER 0.47MF 50V J	C825	OCE107DD618	C,ELECTROLYTIC 100UF STD 10V M
C649	OCN3910K519	C,TUBULA(HIGH DIELE) 390P 50V K	Δ C826	181-093A	C, DE 7090B 102KVA 1MKC4-14
C65P	OCH5470K406	CAPA,CHIP CERAMIC M/L T.C R/S 47P 50V J SL 2.0X1.25 R/TP	C827	OCQ1041N509	C,POLYESTER(MYLAR) 0.1MF 100V L
C650	OCN3910K519	C,TUBULA(HIGH DIELE) 390P 50V K	C828	OCE106DK618	C,ELECTROLYTIC 10UF STD 50V M
C651	OCQ6821N509	C,POLYESTER(MYLAR) 0.0068U 100V K	C829	181-091C	C,DE0705 R 471K 1KV
C652	OCN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M	C83P	OCH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP
C653	OCQ1021N509	C,POLYESTER(MYLAR) 0.001U 100V K	C830	OCE108DF618	C,ELECTROLYTIC 1000UF STD 16V M
C654	OCQ1021N509	C,POLYESTER(MYLAR) 0.001U 100V K	C831	OCE108DF618	C,ELECTROLYTIC 1000UF STD 16V M
C655	OCQ1021N509	C,POLYESTER(MYLAR) 0.001U 100V K	C832	OCK1030K945	C,CERAMIC(HIGH DIELE) 0.01MF 50V Z
C656	OCQ1021N509	C,POLYESTER(MYLAR) 0.001U 100V K	Δ C833	181-035L	CAPACITOR ECK-DNS 472MEX
C657	OCN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M	Δ C834	181-459A	CAPACITOR 820M SHL 200V
C658	OCN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M	Δ C835	181-459A	CAPACITOR 820M SHL 200V
C659	OCE226DK618	C,ELECTROLYTIC 22UF STD 50V M	Δ C836	181-035L	CAPACITOR ECK-DNS 472MEX
C66P	OCE475DK618	C,ELECTROLYTIC 4.7UF STD 50V M	C837	181-445A	C,TANTAL 10MF 16V K
C660	OCE226DK618	C,ELECTROLYTIC 22UF STD 50V M	C838	181-064N	C,ELECTROLYTIC 4.7MF 16V
C661	OCN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M	C84P	OCE475DK618	C,ELECTROLYTIC 4.7UF STD 50V M
C662	OCN1030F679	C,TUBULA(HIGH DIELE) 0.01MF 16V M	C840	181-093A	C, DE 7090B 102KVA 1MKC4-14
C68P	OCE475DK618	C,ELECTROLYTIC 4.7UF STD 50V M	C841	OCE3386F61A	CAPACITOR,ELECTROLYTIC 3300M SMS 16V M TP7.5
C71P	OCH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP	C842	181-091C	C,DE0705 R 471K 1KV
C72P	OCE107DD618	C,ELECTROLYTIC 100UF STD 10V M	C843	OCE226DN618	C,ELECTROLYTIC 22UF STD 100V M
C73P	OCH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP	C85P	OCE475DK618	C,ELECTROLYTIC 4.7UF STD 50V M
C74P	OCE107DD618	C,ELECTROLYTIC 100UF STD 10V M	C86P	OCH1103K516	CHIP CAPA CERAMIC M/L H.D F/S 0.01M 50V K B 2.0X1.25 R/TP
C75P	OCE105DK618	C,ELECTROLYTIC 1UF STD 50V M	C861	OCQZVBK003B	CAPACITOR B1133-C1154-M000
C76P	OCE475DK618	C,ELECTROLYTIC 4.7UF STD 50V M	C87P	OCE477DD618	C,ELECTROLYTIC 470UF STD 10V M
C77P	OCE475DK618	C,ELECTROLYTIC 4.7UF STD 50V M	C901	OCE227DF618	C,ELECTROLYTIC 220UF STD 16V M
C78P	OCE475DK618	C,ELECTROLYTIC 4.7UF STD 50V M	C902	OCK1040K945	C,CERAMIC(HIGH DIELE) 0.1M 50V Z
C79P	OCE107DF618	C,ELECTROLYTIC 100UF STD 16V M	C903	OCE475DR618	C,ELECTROLYTIC 4.7UF STD 250V M
C80P	OCH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP	C905	OCE335DK618	C,ELECTROLYTIC 3.3UF STD 50V M
Δ C801	OCQZVBK003C	CAPACITOR B1133-C1224-M000	C906	OCE475DR618	C,ELECTROLYTIC 4.7UF STD 250V M
Δ C802	OCQZVBK003B	CAPACITOR B1133-C1154-M000	C907	181-434K	C,CERAMIC(HI-K) 2200PF 2KV
C804	181-091M	C,DE1710-798 4700PF 1K K	C908	OCE227DF618	C,ELECTROLYTIC 220UF STD 16V M
C805	181-091M	C,DE1710-798 4700PF 1K K	C909	OCE227DF618	C,ELECTROLYTIC 220UF STD 16V M
C806	181-091M	C,DE1710-798 4700PF 1K K	C91P	OCH1103K516	CHIP CAPA CERAMIC M/L H.D F/S 0.01M 50V K B 2.0X1.25 R/TP
C807	181-091M	C,DE1710-798 4700PF 1K K	C921	OCK1040K945	C,CERAMIC(HIGH DIELE) 0.1M 50V Z
C808	OCE227DJ618	C,ELECTROLYTIC 220UF STD 35V M FL TP5	C922	OCN4710K519	C,TUBULA(HIGH DIELE) 470PF 50V K
C809	OCE106DN618	C,ELECTROLYTIC 10UF STD 100V M	C924	OCK1010W515	C,CERAMIC(HIGH DIELE) 100PF 500V K
C81P	OCE107DF618	C,ELECTROLYTIC 100UF STD 16V M	C93P	OCE106DF618	C,ELECTROLYTIC 10UF STD 16V M
C810	OCE477DF618	C,ELECTROLYTIC 470UF STD 16V M	C94P	OCH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP
C811	OCK1020K515	C,CERAMIC(HIGH DIELE) 1000PF 500V K	C941	OCK1040K945	C,CERAMIC(HIGH DIELE) 0.1M 50V Z
C812	181-083A	CAPACITOR PP 1600V 0.003MF J	C942	OCN3310K519	C,TUBULA(HIGH DIELE) 330P 50V K
C813	181-091C	C,DE0705 R 471K 1KV	C944	OCK1010W515	C,CERAMIC(HIGH DIELE) 100PF 500V K
C814	181-091C	C,DE0705 R 471K 1KV	C95P	OCH5680K406	CAPA,CHIP CERAMIC M/L T.C R/S 68P 50V J SL 2.0X1.25 R/TP
C815	OCK4710W515	C,CERAMIC(HIGH DIELE) 470PF 500V K	C96P	OCE475DK618	C,ELECTROLYTIC 4.7UF STD 50V M
C816	181-091C	C,DE0705 R 471K 1KV	C961	OCK1040K945	C,CERAMIC(HIGH DIELE) 0.1M 50V Z
C817	181-075E	C,ELECTROLYTIC 470MF 200V	C962	OCN4710K519	C,TUBULA(HIGH DIELE) 470PF 50V K
C818	OCE226DN618	C,ELECTROLYTIC 22UF STD 100V M	C964	OCK1010W515	C,CERAMIC(HIGH DIELE) 100PF 500V K

The components identified by shading and mark **⚠** are critical for safety.
Replace only with part number specified.

LOCA. NO	PART NO	DESCRIPTION
C97P	OCE475DK618	C,ELECTROLYTIC 4.7UF STD 50V M
C98P	OCH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*125 R/TP
C99P	OCH5470K406	CAPA,CHIP CERAMIC M/L T.C R/S 47P 50V J SL 2.0X125 R/TP
VC1701	181-036A	CAPACITOR,PP 600V 0.0039MFJ
DIODES		
D104	0DD247109AA	DIODE 1S2471
D105	0DD859009AA	DIODE SILICON MA859 TAPING
D106	0DD859009AA	DIODE SILICON MA859 TAPING
D107	0DD859009AA	DIODE SILICON MA859 TAPING
D108	0DD247109AA	DIODE 1S2471
D1602	0DD247109AA	DIODE 1S2471
D1603	0DD247109AA	DIODE 1S2471
D1604	0DD247109AA	DIODE 1S2471
D1701	0DD247109AA	DIODE 1S2471
D1702	0DD247109AA	DIODE 1S2471
D1703	0DD247109AA	DIODE 1S2471
D1704	0DD247109AA	DIODE 1S2471
D1705	0DD247109AA	DIODE 1S2471
D1706	0DD247109AA	DIODE 1S2471
D1707	0DD247109AA	DIODE 1S2471
D1708	0DD247109AA	DIODE 1S2471
D1709	0DD247109AA	DIODE 1S2471
D1710	0DD247109AA	DIODE 1S2471
D1711	0DD247109AA	DIODE 1S2471
D1712	0DD247109AA	DIODE 1S2471
D1713	0DD247109AA	DIODE 1S2471
D1714	0DD247109AA	DIODE 1S2471
D2002	0DD247109AA	DIODE 1S2471
D2003	0DD247109AA	DIODE 1S2471
D2004	0DD200009AF	DIODE RU-2MV
D2005	0DD200009AF	DIODE RU-2MV
D301	0DD150009CE	DIODE GP15J (1.5A/600V)
D306	0DD247109AA	DIODE 1S2471
D401	0DD081500AA	DIODE ERD08M-15,DAMPER,FUJI
D402	0DD300000AD	DIODE FMS-3FU SANKEN
D403	0DD200009AF	DIODE RU-2MV
D406	0DD100009AU	DIODE EU1AV 600V 0.25A
D407	0DD200009AF	DIODE RU-2MV
D408	0DD200009AF	DIODE RU-2MV
D409	0DD100009AU	DIODE EU1AV 600V 0.25A
D410	0DD247109AA	DIODE 1S2471
D411	0DD247109AA	DIODE 1S2471
D412	0DD100009AU	DIODE EU1AV 600V 0.25A
D501	0DD247109AA	DIODE 1S2471
D503	0DD247109AA	DIODE 1S2471
D505	0DD247109AA	DIODE 1S2471
D506	0DD247109AA	DIODE 1S2471
D509	0DD247109AA	DIODE 1S2471
⚠ D801	0DD560000AA	DIODE D5SB60 BRIDGE (5A/600V)S.D.G
D802	0DD060009AC	DIODE TVR06J 0.6A/600V 250NS
D803	0DD100009AP	DIODE EG1ZV FR 0.8A//200V(TA)

LOCA. NO	PART NO	DESCRIPTION
D805	0DD060009AC	DIODE TVR06J 0.6A/600V 250NS
D806	0DD100009AM	DIODE EU1ZV
D808	0DD100009AL	DIODE EH-1ZV
D809	0DD247109AA	DIODE 1S2471
D810	0DD410000AD	DIODE RU4AM,LF-L1
D811	0DD060009AC	DIODE TVR06J 0.6A/600V 250NS
D812	0DD100009AU	DIODE EU1AV 600V 0.25A
D813	0DD420000BB	DIODE D4L20U
D814	0DD100009DA	DIODE RGP10J
D815	0DD420000BB	DIODE D4L20U
D819	0DD100009AM	DIODE EU1ZV
D824	0DD420000BB	DIODE D4L20U
D921	0DD247109AA	DIODE 1S2471
D924	0DD247109AA	DIODE 1S2471
D941	0DD247109AA	DIODE 1S2471
D944	0DD247109AA	DIODE 1S2471
D961	0DD247109AA	DIODE 1S2471
D964	0DD247109AA	DIODE 1S2471
LD01	0DL100000AE	DIODE,LED DL-1LO (DIFFUSION TYPE)
ZD01	0DZ560009AA	DIODE ZENER MTZ5.6B
ZD01P	0DZ560009AA	DIODE ZENER MTZ5.6B
ZD02	0DZ560009AA	DIODE ZENER MTZ5.6B
ZD03	0DZ560009AA	DIODE ZENER MTZ5.6B
ZD2001	0DZ180009AA	DIODE ZENER MTZ18B
ZD201	0DZ103009AA	DIODE ZENER Z10.3 (MTZJ11A)
ZD202	0DZ330009AN	DIODE,ZENER MTZ3.3A TP(52MM) TP ROHM
ZD204	0DZ560009AA	DIODE ZENER MTZ5.6B
ZD205	0DZ330009AN	DIODE,ZENER MTZ3.3A TP(52MM) TP ROHM
ZD206	0DZ180009AA	DIODE ZENER MTZ18B
ZD2220	0DZ620009AA	DIODE ZENER MTZ6.2B
ZD2221	0DZ620009AA	DIODE ZENER MTZ6.2B
ZD2222	0DZ620009AA	DIODE ZENER MTZ6.2B
ZD302	0DZ180009AA	DIODE ZENER MTZ18B
ZD303	0DZ180009AA	DIODE ZENER MTZ18B
ZD404	0DZ120009AA	DIODE ZENER Z12BM TA
ZD405	0DZ180009AA	DIODE ZENER MTZ18B
ZD410	0DZ820009AA	DIODE ZENER MTZ8.2B
ZD502	0DZ510009AB	DIODE ZENER MTZ5.1B
ZD504	0DZ750009AA	DIODE ZENER MTZ7.5B
ZD804	0DZ750009AA	DIODE ZENER MTZ7.5B
ZD812	0DZ330009BA	DIODE ZENER HZT33
ZD816	0DZ240009BB	DIODE ZENER MTZ24B
ZD820	0DZ110009AA	DIODE ZENER MTZ 11B
ZD901	0DZ750009AA	DIODE ZENER MTZ7.5B
FUSES		
⚠ FR850	131-096E	FUSE MICRO 125V 4.0A
⚠ FR851	131-096E	FUSE MICRO 125V 4.0A
⚠ FR852	131-096E	FUSE MICRO 125V 4.0A
⚠ F1601	131-096C	FUSE MICRO 125V 2.0A
⚠ F1602	131-096C	FUSE MICRO 125V 2.0A
⚠ F801	131-098B	FUSE 4A/250V HBC TIME DELAY 5X20

The components identified by shading and mark Δ are critical for safety.
Replace only with part number specified.

LOCA. NO	PART NO	DESCRIPTION	LOCA. NO	PART NO	DESCRIPTION
ICs					
IC01	0ISQ863801B	IC,SONY LG8638-01B(CXP85324A-192S)	L01	0LA0222K119	INDUCTOR 22UH K
IC01P	0IPH916030A	IC,PHILIPS TDA9160A/N3 32SD P/N/S DECODER	L01A	0LA0471K119	INDUCTOR 4.7UH K
IC02	0IKE780500P	IC,KEC KIA78L05BP(TA)3P 5V,150MA	L01P	0LA0102K119	INDUCTOR 10UH K
IC02P	0IPH466500B	IC,PHILIPS TDA4665-V4 16D 1H D/L	L02	0LA0681K119	INDUCTOR 6.8UH K
IC03	0ISG241600A	IC,SGS-THOMSON ST24C16 8D EEPROM(16K)	L02P	0LA0102K119	INDUCTOR 10UH K
IC03P	0ISA748000A	IC,SANYO LC7480M-TLM 24SOP A/DI(6BIT FLA	L03	0LA0102K139	INDUCTOR 10UH K
IC04	0IKE703300B	IC,KEC KIA7033P 3P 3.3V RESET(TAPING)	L03P	0LA0102K119	INDUCTOR 10UH K
IC04P	0ISA744200A	IC,SANYO LC7442E 64QFP PIP CNTR(PAL/NT	L04P	0LA0102K119	INDUCTOR 10UH K
IC05P	0IH1534251B	IC,HITACHI HM534251BZ-8 28ZIP 1M-VRAM	L05P	0LA0102K119	INDUCTOR 10UH K
IC06P	0IMA586000A	IC,MATSUSHITA AN5860 14D ANALOG RGB S/W	L06P	0LA0102K119	INDUCTOR 10UH K
IC07P	0IKE704200B	IC,KEC KIA7042P 3P 4.2V RESET	L07P	0LA0102K119	INDUCTOR 10UH K
IC08P	0ISA722200A	IC, SANYO LA7222 (1280 AUDIO)	L08P	0LA0102K119	INDUCTOR 10UH K
IC102	0IPH981500B	IC,PHILIPS TDA9815-V3 32SD MULTI IF	L09P	0LA0102K119	INDUCTOR 10UH K
IC1271	0IMA534200A	IC,MATSUSHITA AN5342K 30SD SHARPNESS CONTROL	L1S	0LA0102K119	INDUCTOR 10UH K
IC1272	0IMO145770E	IC,MOTOROLA MC14577CP 8D DUAL VIDEO AMP	L10P	0LA0102K119	INDUCTOR 10UH K
IC1273	0IKE780900E	IC,KEC KIA7809PI 3P(TO-220IS)1A,9V	L103	0LA0102K119	INDUCTOR 10UH K
IC1601	0ISA428200A	IC, SANYO LA4282	L104	0LA0470K119	INDUCTOR 0.47UH K
IC1602	0ISA428200A	IC, SANYO LA4282	L105	150-C01F	COIL CHOKE 0.85UH A 1105
IC1603	0IKE455800E	IC, KIA4558 8DIP DUAL OP AMP	L106	0LA0102K119	INDUCTOR 10UH K
IC1604	0IKE455800E	IC, KIA4558 8DIP DUAL OP AMP	L107	150-E05B	COIL VAR,07S 1B 77.8MHZ
IC1701	0IMO145380C	IC,MOTOROLA MC14538BCP 16D 2-MONO MUL.VIB.	L108	0LA0102K119	INDUCTOR 10UH K
IC201	0IHY534256A	IC, HYUNDAI HY534256AS-70	L109	0LA0102K119	INDUCTOR 10UH K
IC202	0ISM527300A	IC,SIEMENS SDA5273S(C24) 52SD MEGA TEXT	L11P	0LA0102K119	INDUCTOR 10UH K
IC203	0ISM803200A	IC,SIEMENS SAB8032B-P 40D MEGATEXT MCU	L110	0LA0102K119	INDUCTOR 10UH K
IC204	0IGS743730F	IC, GOLDSTAR ELECTRON GD74HC373 20D OCTAL D-LATCH	L111	0LA0102K119	INDUCTOR 10UH K
IC205	167-125A	IC MEGA TEXT ROM WF-32A10S	L112	0LA0102K119	INDUCTOR 10UH K
IC206	0ISG641500A	IC,SGS-THOMSON TEA6415C,20D,VIDEO MATRIX S/W	L113	0LA0102K119	INDUCTOR 10UH K
IC207	167-115A	IC GSH9311(GS-ALPS) 8PIN RGB BUF.	L114	0LA0102K119	INDUCTOR 10UH K
IC208	0IKE703300B	IC,KEC KIA7033P 3P 3.3V RESET(TAPING)	L115	0LA0102K139	INDUCTOR 10UH K
IC301	0ISA784500A	IC,SANYO LA7845 7SIP V/OUT(1.5A)	L116	0LA0102K139	INDUCTOR 10UH K
IC401	0IKE455800E	IC, KIA4558 8DIP DUAL OP AMP	L117	0LA0102K139	INDUCTOR 10UH K
Δ IC402	0ITO721400A	IC,TOSHIBA TLP721[D4-GR] 4D PHOTO(SEMKO)	L118	0LA0102K139	INDUCTOR 10UH K
IC501	0IPH466500B	IC,PHILIPS TDA4665-V4 16D 1H D/L	L119	125-022K	CORE FERRITE 1UH
IC502	0IPH839520A	IC,PHILIPS TDA8395P/N2 16D SECAM DETECT.	L12P	0LA0102K119	INDUCTOR 10UH K
IC503	0IPH456620A	IC,PHILIPS TDA4566/V2 18D CTI	L120	125-022K	CORE FERRITE 1UH
IC504	0IPH837600A	IC,PHILIPS TDA8376-N1 52SD MULTI VIDEO P.	L1201	150-B02A	COIL L/C FILTER(05W) EQF
IC602	0IKE455800E	IC, KIA4558 8DIP DUAL OP AMP	L1271	0LA0822K119	INDUCTOR 82UH K
IC603	0IIT341000C	IC,ITT MSP3410B-FP-F7	L1273	0LA0102K119	INDUCTOR 10UH K
IC604	0IKE703300B	IC,KEC KIA7033P 3P 3.3V RESET(TAPING)	L1274	0LA0822K119	INDUCTOR 82UH K
Δ IC801	0ISK670900A	IC,SANKEN STR/S6709 9S SMPS-CNTR	L1276	0LA0102K119	INDUCTOR 10UH K
Δ IC802	0ITO721400A	IC,TOSHIBA TLP721[D4-GR] 4D PHOTO(SEMKO)	L1277	0LA0102K119	INDUCTOR 10UH K
Δ IC804	0ISK140000A	IC,SANKEN SE140N 3P 130V ERROR AMP	L13P	0LA0102K119	INDUCTOR 10UH K
IC805	0ISH122100A	IC,SHARP PQ12RF21 4P(TO-220) 12V S/W RE	L1601	125-123A	CORE FERRITE BFD3565R2F
IC806	0ISH052100A	IC,SHARP PQ05RF21 4P(TO-220) 5V S/W REG	L1602	125-123A	CORE FERRITE BFD3565R2F
IC809	0IKE780800A	IC,KEC KIA7808PI 3P(TO-220IS) 1A,8V	L1603	125-123A	CORE FERRITE BFD3565R2F
COILS & TRANSFORMERS			L1701	0LA0102K119	INDUCTOR 10UH K
FB803	125-022K	CORE FERRITE 1UH	L2S	0LA0102K119	INDUCTOR 10UH K
FB805	125-022K	CORE FERRITE 1UH	L2003	125-022K	CORE FERRITE 1UH
FB806	125-022K	CORE FERRITE 1UH	L201	0LA0102K119	INDUCTOR 10UH K
			L202	0LA0681K119	INDUCTOR 6.8UH K
			L203	0LA0102K119	INDUCTOR 10UH K
			L204	0LA0102K119	INDUCTOR 10UH K

The components identified by shading and mark **▲** are critical for safety.
Replace only with part number specified.

LOCA. NO	PART NO	DESCRIPTION	LOCA. NO	PART NO	DESCRIPTION
L205	0LA0102K119	INDUCTOR 10UH K	Q02	0TR102009AB	TRANSISTOR KRC102M,TP(KRC1202),KEC
L2050	150-B05B	COIL L/C FILTER(07S) EQF	Q02P	0TR150400BA	TRANSISTOR CHIP 2SA1504S(ASY) KEC
L206	0LA0102K119	INDUCTOR 10UH K	Q03	0TR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
L207	0LA0102K119	INDUCTOR 10UH K	Q03P	0TR150400BA	TRANSISTOR CHIP 2SA1504S(ASY) KEC
L209	0LA0102K119	INDUCTOR 10UH K	Q04P	0TR150400BA	TRANSISTOR CHIP 2SA1504S(ASY) KEC
L210	125-022K	CORE FERRITE 1UH	Q05P	0TR387500AA	TRANSISTOR CHIP 2SC3875S(ALY) KEC
L211	0LA0102K119	INDUCTOR 10UH K	Q06P	0TR102009AG	TRANSISTOR CHIP KRC102S SOT-23 TP KEC
L212	0LA0102K119	INDUCTOR 10UH K	Q07P	0TR102009AG	TRANSISTOR CHIP KRC102S SOT-23 TP KEC
L213	0LA0681K119	INDUCTOR 6.8UH K	Q08P	0TR102009AG	TRANSISTOR CHIP KRC102S SOT-23 TP KEC
L214	0LA0681K119	INDUCTOR 6.8UH K	Q09P	0TR387500AA	TRANSISTOR CHIP 2SC3875S(ALY) KEC
L215	0LA0102K119	INDUCTOR 10UH K	Q10P	0TR387500AA	TRANSISTOR CHIP 2SC3875S(ALY) KEC
L216	0LA0102K119	INDUCTOR 10UH K	Q101	0TR126609AA	TRANSISTOR KTA1266-TP-Y (KTA1015) KEC
L217	0LA0102K119	INDUCTOR 10UH K	Q102	0TR319709AB	TRANSISTOR KTC3197,TP(KTC388A),KEC
L218	125-022K	CORE FERRITE 1UH	Q103	0TR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
L219	125-022K	CORE FERRITE 1UH	Q104	0TR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
L220	125-022K	CORE FERRITE 1UH	Q105	0TR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
L221	125-022K	CORE FERRITE 1UH	Q106	0TR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
L222	125-022K	CORE FERRITE 1UH	Q11P	0TR387500AA	TRANSISTOR CHIP 2SC3875S(ALY) KEC
L2230	0LA0102K119	INDUCTOR 10UH K	Q12P	0TR150400BA	TRANSISTOR CHIP 2SA1504S(ASY) KEC
L2231	0LA0102K119	INDUCTOR 10UH K	Q1271	0TR387500AA	TRANSISTOR CHIP 2SC3875S(ALY) KEC
L224	125-022K	CORE FERRITE 1UH	Q1273	0TR387500AA	TRANSISTOR CHIP 2SC3875S(ALY) KEC
L225	125-022K	CORE FERRITE 1UH	Q1274	0TR387500AA	TRANSISTOR CHIP 2SC3875S(ALY) KEC
L226	125-022K	CORE FERRITE 1UH	Q1275	0TR387500AA	TRANSISTOR CHIP 2SC3875S(ALY) KEC
L3S	0LA0102K119	INDUCTOR 10UH K	Q13P	0TR387500AA	TRANSISTOR CHIP 2SC3875S(ALY) KEC
L4S	0LA0102K119	INDUCTOR 10UH K	Q14P	0TR387500AA	TRANSISTOR CHIP 2SC3875S(ALY) KEC
▲ L401	150-716Q	COIL LINEARITY,WN-3200	Q15P	0TR150400BA	TRANSISTOR CHIP 2SA1504S(ASY) KEC
L403	150-309F	COIL CHOKE 3.6MH WN-3200	Q1601	0TR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
L404	150-717K	COIL CHOKE 1.1MH WN-3200	Q1602	0TR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
L405	150-717K	COIL CHOKE 1.1MH WN-3200	Q1603	0TR126609AA	TRANSISTOR KTA1266-TP-Y (KTA1015) KEC
L601	0LA0472K119	INDUCTOR 47UH K	Q17P	0TR150400BA	TRANSISTOR CHIP 2SA1504S(ASY) KEC
L602	0LA0102K119	INDUCTOR 10UH K	Q1701	0TR150400BA	TRANSISTOR CHIP 2SA1504S(ASY) KEC
L603	0LA1000K119	INDUCTOR 100UH K	Q1702	0TR150400BA	TRANSISTOR CHIP 2SA1504S(ASY) KEC
L604	0LA0102K119	INDUCTOR 10UH K	Q1703	0TR150400BA	TRANSISTOR CHIP 2SA1504S(ASY) KEC
L605	125-123A	CORE FERRITE BFD3565R2F	Q1704	0TR387500AA	TRANSISTOR CHIP 2SC3875S(ALY) KEC
L606	125-123A	CORE FERRITE BFD3565R2F	Q1705	0TR150400BA	TRANSISTOR CHIP 2SA1504S(ASY) KEC
L801	150-C02F	COIL CHOKE 82UH R1217	Q1706	0TR150400BA	TRANSISTOR CHIP 2SA1504S(ASY) KEC
L802	150-C02F	COIL CHOKE 82UH R1217	Q1707	0TR150400BA	TRANSISTOR CHIP 2SA1504S(ASY) KEC
L901	0LA0102K139	INDUCTOR 10UH K	Q18P	0TR150400BA	TRANSISTOR CHIP 2SA1504S(ASY) KEC
L921	0LA0682K139	INDUCTOR, 68UH K	Q19P	0TR387500AA	TRANSISTOR CHIP 2SC3875S(ALY) KEC
L941	0LA0682K139	INDUCTOR, 68UH K	Q20P	0TR150400BA	TRANSISTOR CHIP 2SA1504S(ASY) KEC
L961	0LA0682K139	INDUCTOR, 68UH K	Q2002	0TR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
▲ T401	151-C02F	TRANSFORMER H-DRIVE,EI-19,BULK	Q2004	0TR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
▲ T402	151-E06A	TRANSFORMER DBF,EER-2834,BULK	Q2005	0TR320209AA	TRANSISTOR KTC3202-TP-Y (KTC1959)KEC
▲ T801	150-982C	COIL LINE FILTER,23MH SQE	Q2006	0TR127009AA	TRANSISTOR KTA1270-TP-Y (KTA562TMI)KEC
▲ T803	151-A12A	TRANSFORMER SMPS COIL EER4954 STR-S6709 W	Q2008	0TR968000AA	TRANSISTOR KTA968A-Y KEC
▲ T804	150-982C	COIL LINE FILTER,23MH SQE	Q2009	0TR223800AA	TRANSISTOR KTC2238A-Y
▲ T861	150-982C	COIL LINE FILTER,23MH SQE	Q201	0TR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
Z02	125-123A	CORE FERRITE BFD3565R2F	Q202	0TR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
TRANSISTORS			Q203	0TR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
Q01	0TR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC	Q204	0TR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
Q01P	0TR150400BA	TRANSISTOR CHIP 2SA1504S(ASY) KEC	Q205	0TR126609AA	TRANSISTOR KTA1266-TP-Y (KTA1015) KEC
			Q206	0TR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC

The components identified by shading and mark Δ are critical for safety.
Replace only with part number specified.

LOCA. NO	PART NO	DESCRIPTION
Q207	OTR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
Q208	OTR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
Q21P	OTR150400BA	TRANSISTOR CHIP 2SA1504S(ASY) KEC
Q22P	OTR387500AA	TRANSISTOR CHIP 2SC3875S(ALY) KEC
Q301	OTR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
Q401	OTR223800AA	TRANSISTOR KTC2238A-Y
Δ Q402	OTR476000AA	TRANSISTOR 2SC4760 (W/M) TOSHIBA
Δ Q403	OTF910000AA	FET BUZ91A TQ-220AB SIEMENS
Q404	OTR126609AA	TRANSISTOR KTA1266-TP-Y (KTA1015) KEC
Q406	OTR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
Q407	OTR126609AA	TRANSISTOR KTA1266-TP-Y (KTA1015) KEC
Q408	OTR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
Q409	OTR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
Q410	OTR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
Q411	OTR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
Q412	OTR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
Q413	OTR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
Q414	OTR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
Q502	OTR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
Q503	OTR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
Q601	OTR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
Q602	OTR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
Q603	OTR126609AA	TRANSISTOR KTA1266-TP-Y (KTA1015) KEC
Q604	OTR126609AA	TRANSISTOR KTA1266-TP-Y (KTA1015) KEC
Q605	OTR126609AA	TRANSISTOR KTA1266-TP-Y (KTA1015) KEC
Q606	OTR126609AA	TRANSISTOR KTA1266-TP-Y (KTA1015) KEC
Q801	OTR385200AA	TRANSISTOR 2SC3852A SANKEN
Q802	OTR322709AA	TRANSISTOR KTC3227-Y,TP(KTC1627A),KEC
Q803	OTR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
Q804	OTR322809AA	TRANSISTOR KTC3228-0 TP(KTC2383),KEC
Q805	OTR421009CB	TRANSISTOR BF421L(AMMO)TQ-92 TP PHILIPS
Q806	OTR968000AA	TRANSISTOR KTA968A-Y KEC
Q807	OTR322809AA	TRANSISTOR KTC3228-0 TP(KTC2383),KEC
Q808	OTR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
Q809	OTR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
Q810	OTR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
Q811	OTR126609AA	TRANSISTOR KTA1266-TP-Y (KTA1015) KEC
Q812	OTR126609AA	TRANSISTOR KTA1266-TP-Y (KTA1015) KEC
Q813	OTR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
Q814	OTR127509AC	TRANSISTOR KTA1275-Y TP(KTA1013),KEC
Q816	OTR127600AA	TRANSISTOR KTA1276-Y(KTA473),KEC
Q817	OTR126609AA	TRANSISTOR KTA1266-TP-Y (KTA1015) KEC
Q818	OTR126609AA	TRANSISTOR KTA1266-TP-Y (KTA1015) KEC
Q901	OTR126609AA	TRANSISTOR KTA1266-TP-Y (KTA1015) KEC
Q921	OTR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
Q922	OTR322900AA	TRANSISTOR KTC3229 (KTC2068),KEC
Q923	OTR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
Q924	OTR422009CB	TRANSISTOR BF422L(AMMO)TQ-92
Q925	OTR421009CB	TRANSISTOR BF421L(AMMO)TQ-92
Q941	OTR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
Q942	OTR322900AA	TRANSISTOR KTC3229 (KTC2068),KEC
Q943	OTR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC

LOCA. NO	PART NO	DESCRIPTION
Q944	OTR422009CB	TRANSISTOR BF422L(AMMO)TQ-92
Q945	OTR421009CB	TRANSISTOR BF421L(AMMO)TQ-92
Q961	OTR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
Q962	OTR322900AA	TRANSISTOR KTC3229 (KTC2068),KEC
Q963	OTR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
Q964	OTR422009CB	TRANSISTOR BF422L(AMMO)TQ-92
Q965	OTR421009CB	TRANSISTOR BF421L(AMMO)TQ-92
RESISTORS		
Δ FR436	ORF0101K607	R,FUSIBLE 12W 5%
Δ FR440	ORF0101K607	R,FUSIBLE 12W 5%
Δ FR441	ORF0101K607	R,FUSIBLE 12W 5%
Δ FR445	ORF0301K607	R,FUSIBLE 3 2W 5% TA62
Δ FR848	ORF0470H609	R,FUSIBLE 0.47 1/2W 5
Δ FR849	ORF0470H609	R,FUSIBLE 0.47 1/2W 5
Δ FR901	180-D02L	R,RNF RND(S) CR 2W 2.0J
J1276	ORH0000D622	RESISTOR CHIP 0 1/10W 5 D.R/TP
J1701	ORH0000D622	RESISTOR CHIP 0 1/10W 5 D.R/TP
J1702	ORH0000D622	RESISTOR CHIP 0 1/10W 5 D.R/TP
J1710	ORH0000D622	RESISTOR CHIP 0 1/10W 5 D.R/TP
J1711	ORH0000D622	RESISTOR CHIP 0 1/10W 5 D.R/TP
J203	ORD0681F609	R,CARBON FILM 6.8 1/6W 5
J301	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5
J355	ORD4702F609	R,CARBON FILM 47K 1/6W 5
R01	ORD1002F609	R,CARBON FILM 10K 1/6W 5
R01A	ORD2200F609	R,CARBON FILM 220 1/6W 5
R01P	ORH2200D622	RESISTOR CHIP 220 1/10W 5 D.R/TP
R02	ORD3900F609	R,CARBON FILM 390 1/6W 5
R02P	ORH2200D622	RESISTOR CHIP 220 1/10W 5 D.R/TP
R03P	ORH1002D622	RESISTOR CHIP 10K 1/10W 5 D.R/TP
R04	ORD3301F609	R,CARBON FILM 3.3K 1/6W 5
R04P	ORH1001D622	RESISTOR CHIP 1.0K 1/10W 5 D.R/TP
R05	ORD1002F609	R,CARBON FILM 10K 1/6W 5
R05P	ORH2001D622	RESISTOR CHIP 2.0K 1/10W 5 D.R/TP
R06	ORD2200F609	R,CARBON FILM 220 1/6W 5
R06P	ORH2001D622	RESISTOR CHIP 2.0K 1/10W 5 D.R/TP
R07	ORD2200F609	R,CARBON FILM 220 1/6W 5
R07P	ORH1003D622	RESISTOR CHIP 100K 1/10W 5 D.R/TP
R08	ORD2200F609	R,CARBON FILM 220 1/6W 5
R08P	ORH1001D622	RESISTOR CHIP 1.0K 1/10W 5 D.R/TP
R09	ORD2200F609	R,CARBON FILM 220 1/6W 5
R09P	ORH3001D622	RESISTOR CHIP 3.0K 1/10W 5 D.R/TP
R1S	ORD0822F609	R,CARBON FILM 82 1/6W 5
R10P	ORH1001D622	RESISTOR CHIP 1.0K 1/10W 5 D.R/TP
R101	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5
R102	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5
R104	ORD2402F609	R,CARBON FILM 24K 1/6W 5
R105	ORD5602F609	R,CARBON FILM 56K 1/6W 5
R106	ORD3902F609	R,CARBON FILM 39K 1/6W 5
R107	ORD5602F609	R,CARBON FILM 56K 1/6W 5
R108	ORD2000F609	R,CARBON FILM 200 1/6W 5
R109	ORD1201F609	R,CARBON FILM 1.2K 1/6W 5
R110	ORD3601F609	R,CARBON FILM 3.6K 1/6W 5

LOCA. NO	PART NO	DESCRIPTION	LOCA. NO	PART NO	DESCRIPTION
R111	ORD0222F609	R,CARBON FILM 22 1/6W 5	R1290	ORH7501D622	RESISTOR CHIP 7.5K 1/10W 5 D.R/TP
R112	ORD6800F609	R,CARBON FILM 680 1/6W 5	R1291	ORH2201D622	RESISTOR CHIP 2.2K 1/10W 5 D.R/TP
R113	ORD5601F609	R,CARBON FILM 5.6K 1/6W 5	R1292	ORH6802D622	RESISTOR CHIP 68K 1/10W 5 D.R/TP
R114	ORD4702F609	R,CARBON FILM 47K 1/6W 5	R1293	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5
R115	ORD6801F609	R,CARBON FILM 6.8K 1/6W 5	R1294	ORH4701D622	RESISTOR CHIP 4.7K 1/10W 5 D.R/TP
R116	ORD4702F609	R,CARBON FILM 47K 1/6W 5	R1295	ORH4701D622	RESISTOR CHIP 4.7K 1/10W 5 D.R/TP
R117	ORD4700F609	R,CARBON FILM 470 1/6W 5	R1296	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5
R118	ORD1202F609	R,CARBON FILM 12K 1/6W 5	R1297	ORH1001D622	RESISTOR CHIP 1.0K 1/10W 5 D.R/TP
R119	ORD4702F609	R,CARBON FILM 47K 1/6W 5	R13	ORD1002F609	R,CARBON FILM 10K 1/6W 5
R12	ORD1002F609	R,CARBON FILM 10K 1/6W 5	R13P	ORH1001D622	RESISTOR CHIP 1.0K 1/10W 5 D.R/TP
R12P	ORH1502D622	RESISTOR CHIP 15K 1/10W 5 D.R/TP	R131	ORD4702F609	R,CARBON FILM 47K 1/6W 5
R120	ORD2202F609	R,CARBON FILM 22K 1/6W 5	R132	ORD6801F609	R,CARBON FILM 6.8K 1/6W 5
R121	ORD3001F609	R,CARBON FILM 3.0K 1/6W 5	R133	ORD4702F609	R,CARBON FILM 47K 1/6W 5
R122	ORD2202F609	R,CARBON FILM 22K 1/6W 5	R134	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5
R123	ORD2202F609	R,CARBON FILM 22K 1/6W 5	R135	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5
R125	ORD2202F609	R,CARBON FILM 22K 1/6W 5	R14	ORD1002F609	R,CARBON FILM 10K 1/6W 5
R1252	ORH5600D622	RESISTOR CHIP 560 1/10W 5 D.R/TP	R14P	ORH1001D622	RESISTOR CHIP 1.0K 1/10W 5 D.R/TP
R1255	ORH2700D622	RESISTOR CHIP 270 1/10W 5 D.R/TP	R15	ORD1002F609	R,CARBON FILM 10K 1/6W 5
R1256	ORH6800D622	RESISTOR CHIP 680 1/10W 5 D.R/TP	R15P	ORH5601D622	RESISTOR CHIP 5.6K 1/10W 5 D.R/TP
R1257	ORH1001D622	RESISTOR CHIP 1.0K 1/10W 5 D.R/TP	R16	ORD1002F609	R,CARBON FILM 10K 1/6W 5
R1258	ORH6800D622	RESISTOR CHIP 680 1/10W 5 D.R/TP	R16P	ORH5601D622	RESISTOR CHIP 5.6K 1/10W 5 D.R/TP
R1259	ORH1602D622	RESISTOR CHIP 16K 1/10W 5 TA	R1601	ORD0221H609	R,CARBON FILM 2.2 1/2W 5
R126	ORD2000F609	R,CARBON FILM 200 1/6W 5	R1602	ORD4701F609	R,CARBON FILM 4.7K 1/6W 5
R1260	ORH1500D622	RESISTOR CHIP 150 1/10W 5 D.R/TP	R1603	ORD0221H609	R,CARBON FILM 2.2 1/2W 5
R1261	ORH1001D622	RESISTOR CHIP 1.0K 1/10W 5 D.R/TP	R1604	ORD6200F609	R,CARBON FILM 620 1/6W 5
R1262	ORH1001D622	RESISTOR CHIP 1.0K 1/10W 5 D.R/TP	R1605	ORD1801F609	R,CARBON FILM 1.8K 1/6W 5
R1263	ORH1001D622	RESISTOR CHIP 1.0K 1/10W 5 D.R/TP	R1606	ORD3301F609	R,CARBON FILM 3.3K 1/6W 5
R1265	ORH1001D622	RESISTOR CHIP 1.0K 1/10W 5 D.R/TP	R1607	ORD1801F609	R,CARBON FILM 1.8K 1/6W 5
R1267	ORH2001D622	RESISTOR CHIP 2.0K 1/10W 5 D.R/TP	R1608	ORD3301F609	R,CARBON FILM 3.3K 1/6W 5
R1268	ORH2001D622	RESISTOR CHIP 2.0K 1/10W 5 D.R/TP	R1609	ORD6200F609	R,CARBON FILM 620 1/6W 5
R1270	ORH3901D622	RESISTOR CHIP 3.9K 1/10W 5 D.R/TP	R1610	ORD4700H609	R,CARBON FILM 470 1/2W 5
R1271	ORH4702D622	RESISTOR CHIP 47K 1/10W 5 D.R/TP	R1611	ORD4700H609	R,CARBON FILM 470 1/2W 5
R1272	ORH3301D622	RESISTOR CHIP 3.3K 1/10W 5 D.R/TP	R1612	ORD0221H609	R,CARBON FILM 2.2 1/2W 5
R1273	ORH4701D622	RESISTOR CHIP 4.7K 1/10W 5 D.R/TP	R1613	ORD4701F609	R,CARBON FILM 4.7K 1/6W 5
R1274	ORH8201D622	RESISTOR CHIP 8.2K 1/10W 5 D.R/TP	R1614	ORD0221H609	R,CARBON FILM 2.2 1/2W 5
R1275	ORH1001D622	RESISTOR CHIP 1.0K 1/10W 5 D.R/TP	R1615	ORD9101H609	R,CARBON FILM 9.1K 1/2W 5
R1276	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5	R1616	ORD0102F609	R,CARBON FILM 10 1/6W 5
R1277	ORH5100D622	RESISTOR CHIP 510 1/10W 5 D.R/TP	R1617	ORD6200F609	R,CARBON FILM 620 1/6W 5
R1278	ORH1001D622	RESISTOR CHIP 1.0K 1/10W 5 D.R/TP	R1618	ORD1601F609	R,CARBON FILM 1.6K 1/6W 5
R1279	ORD1002F609	R,CARBON FILM 10K 1/6W 5	R1619	ORD1500H609	R,CARBON FILM 150 1/2W 5
R128	ORD0472F609	R,CARBON FILM 47 1/6W 5	R1621	ORD1802F609	R,CARBON FILM 18K 1/6W 5
R1280	ORH1502D622	RESISTOR CHIP 15K 1/10W 5 D.R/TP	R1622	ORD4703F609	R,CARBON FILM 470K 1/6W 5
R1281	ORD4302F609	R,CARBON FILM 43K 1/6W 5	R1623	ORD3902F609	R,CARBON FILM 39K 1/6W 5
R1282	ORH2202D622	RESISTOR CHIP 22K 1/10W 5 D.R/TP	R1624	ORD3902F609	R,CARBON FILM 39K 1/6W 5
R1283	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5	R1625	ORD1002F609	R,CARBON FILM 10K 1/6W 5
R1284	ORH1001D622	RESISTOR CHIP 1.0K 1/10W 5 D.R/TP	R1626	ORD1802F609	R,CARBON FILM 18K 1/6W 5
R1285	ORH6801D622	RESISTOR CHIP 6.8K 1/10W 5 D.R/TP	R1627	ORD4703F609	R,CARBON FILM 470K 1/6W 5
R1286	ORH4703D622	RESISTOR CHIP 470K 1/10W 5 D.R/TP	R1628	ORD5102F609	R,CARBON FILM 51K 1/6W 5
R1287	ORD5101F609	R,CARBON FILM 5.1K 1/6W 5	R1629	ORD5102F609	R,CARBON FILM 51K 1/6W 5
R1288	ORH1001D622	RESISTOR CHIP 1.0K 1/10W 5 D.R/TP	R1630	ORD4702F609	R,CARBON FILM 47K 1/6W 5
R1289	ORD1801F609	R,CARBON FILM 1.8K 1/6W 5	R1631	ORD4702F609	R,CARBON FILM 47K 1/6W 5
R129	ORD6801F609	R,CARBON FILM 6.8K 1/6W 5	R1632	ORD6801F609	R,CARBON FILM 6.8K 1/6W 5

LOCA. NO	PART NO	DESCRIPTION	LOCA. NO	PART NO	DESCRIPTION
R1633	ORD1002F609	R,CARBON FILM 10K 1/6W 5	R202	ORD1002F609	R,CARBON FILM 10K 1/6W 5
R1634	ORD1002F609	R,CARBON FILM 10K 1/6W 5	R2020	ORD0822F609	R,CARBON FILM 82 1/6W 5
R1638	ORD1002F609	R,CARBON FILM 10K 1/6W 5	R2021	ORD1201H609	R,CARBON FILM 12K 1/2W 5
R1639	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5	R2022	ORD1501H609	R,CARBON FILM 1.5K 1/2W 5
R1640	ORD1002F609	R,CARBON FILM 10K 1/6W 5	R2023	ORD1201H609	R,CARBON FILM 12K 1/2W 5
R1641	ORD4701F609	R,CARBON FILM 4.7K 1/6W 5	R2024	ORD1501H609	R,CARBON FILM 1.5K 1/2W 5
R1642	ORD4701F609	R,CARBON FILM 4.7K 1/6W 5	R2025	ORD6802H609	RESISTOR, FIXED CARBON FILM 68K 1/2W 5 TA52
R1643	ORD5102F609	R,CARBON FILM 51K 1/6W 5	R2026	ORD6802H609	RESISTOR, FIXED CARBON FILM 68K 1/2W 5 TA52
R17	ORD1002F609	R,CARBON FILM 10K 1/6W 5	R2027	ORD0332H609	R,CARBON FILM 33 1/2W 5
R1701	ORH1002D622	RESISTOR CHIP 10K 1/10W 5 D.R/TP	R2028	ORD1200H609	R,CARBON FILM 120 1/2W 5
R1702	ORH1002D622	RESISTOR CHIP 10K 1/10W 5 D.R/TP	R2029	ORD0271H609	R,CARBON FILM 2.7 1/2W 5
R1703	ORH1002D622	RESISTOR CHIP 10K 1/10W 5 D.R/TP	R203	ORD1500F609	R,CARBON FILM 150 1/6W 5
R1704	ORH7501D622	RESISTOR CHIP 7.5K 1/10W 5 D.R/TP	R2030	ORD1200H609	R,CARBON FILM 120 1/2W 5
R1706	ORH1002D622	RESISTOR CHIP 10K 1/10W 5 D.R/TP	R2031	ORD0201H609	R,CARBON FILM 2.0 1/2W 5
R1707	ORN2103F409	RESISTOR, FIX METAL FILM 210K 1/6W 1% TA52	R2032	ORD3900H609	R,CARBON FILM 390 1/2W 5
R1708	ORN8202F409	R, METAL FILM 82K 1/6W 1%	R205	ORD1200F609	R,CARBON FILM 120 1/6W 5
R1709	ORH1002D622	RESISTOR CHIP 10K 1/10W 5 D.R/TP	R206	ORD1200F609	R,CARBON FILM 120 1/6W 5
R1710	ORH2700D622	RESISTOR CHIP 270 1/10W 5 D.R/TP	R207	ORD1200F609	R,CARBON FILM 120 1/6W 5
R1711	ORH0822D622	RESISTOR CHIP 82 1/10W 5 D.R/TP	R208	ORD4701F609	R,CARBON FILM 4.7K 1/6W 5
R1712	ORH0562D622	RESISTOR CHIP 56 1/10W 5 D.R/TP	R209	ORD8201F609	R,CARBON FILM 8.2K 1/6W 5
R1713	ORH1000D622	RESISTOR CHIP 100 1/10W 5 D.R/TP	R21	ORD1000F609	R,CARBON FILM 100 1/6W 5
R1714	ORH6800D622	RESISTOR CHIP 680 1/10W 5 D.R/TP	R21P	ORH2000D622	RESISTOR CHIP 200 1/10W 5 TA
R1715	ORH2201D622	RESISTOR CHIP 2.2K 1/10W 5 D.R/TP	R210	ORD0681F609	R,CARBON FILM 6.8 1/6W 5
R1718	ORH1000D622	RESISTOR CHIP 100 1/10W 5 D.R/TP	R211	ORD9100F609	R,CARBON FILM 910 1/6W 5
R1719	ORH1000D622	RESISTOR CHIP 100 1/10W 5 D.R/TP	R212	ORD1000F609	R,CARBON FILM 100 1/6W 5
R1720	ORH1000D622	RESISTOR CHIP 100 1/10W 5 D.R/TP	R213	ORD0102F609	R,CARBON FILM 10 1/6W 5
R1721	ORH4700D622	RESISTOR CHIP 470 1/10W 5 D.R/TP	R214	ORD0681F609	R,CARBON FILM 6.8 1/6W 5
R1722	ORH4700D622	RESISTOR CHIP 470 1/10W 5 D.R/TP	R215	ORD1000F609	R,CARBON FILM 100 1/6W 5
R1723	ORH4700D622	RESISTOR CHIP 470 1/10W 5 D.R/TP	R216	ORD2200F609	R,CARBON FILM 220 1/6W 5
R1727	ORH0752D622	RESISTOR CHIP 75 1/10W 5 D.R/TP	R217	ORD0681F609	R,CARBON FILM 6.8 1/6W 5
R1728	ORH0752D622	RESISTOR CHIP 75 1/10W 5 D.R/TP	R218	ORD1000F609	R,CARBON FILM 100 1/6W 5
R1729	ORH0752D622	RESISTOR CHIP 75 1/10W 5 D.R/TP	R219	ORD2200F609	R,CARBON FILM 220 1/6W 5
R1730	ORH0682D622	RESISTOR CHIP 68 1/10W 5 D.R/TP	R22	ORD1000F609	R,CARBON FILM 100 1/6W 5
R18	ORD1002F609	R,CARBON FILM 10K 1/6W 5	R22P	ORH2000D622	RESISTOR CHIP 200 1/10W 5 TA
R18P	ORH2001D622	RESISTOR CHIP 2.0K 1/10W 5 D.R/TP	R220	ORD0102F609	R,CARBON FILM 10 1/6W 5
R19	ORD1000F609	R,CARBON FILM 100 1/6W 5	R221	ORD1000F609	R,CARBON FILM 100 1/6W 5
R19P	ORH2701D622	RESISTOR CHIP 2.7K 1/10W 5 D.R/TP	R222	ORD0332F609	R,CARBON FILM 33 1/6W 5
R2S	ORD0752F609	R,CARBON FILM 75 1/6W 5	R223	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5
R20	ORD1000F609	R,CARBON FILM 100 1/6W 5	R224	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5
R20P	ORH2000D622	RESISTOR CHIP 200 1/10W 5 TA	R2267	ORD0102F609	R,CARBON FILM 10 1/6W 5
R2001	ORS1800J607	R, METAL FILM OXIDE 180 1W 5%	R2269	ORD0102F609	R,CARBON FILM 10 1/6W 5
R2002	ORS3900K607	R, METAL FILM OXIDE 390 2W 5%	R227	ORD2200F609	R,CARBON FILM 220 1/6W 5
R2007	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5	R228	ORD2200F609	R,CARBON FILM 220 1/6W 5
R2009	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5	R229	ORD1500F609	R,CARBON FILM 150 1/6W 5
R201	ORD1002F609	R,CARBON FILM 10K 1/6W 5	R2290	ORD2202F609	R,CARBON FILM 22K 1/6W 5
R2010	ORD4700F609	R,CARBON FILM 470 1/6W 5	R2291	ORD2202F609	R,CARBON FILM 22K 1/6W 5
R2011	ORD3002F609	R,CARBON FILM 30K 1/6W 5	R2292	ORD0752F609	R,CARBON FILM 75 1/6W 5
R2012	ORD2401F609	R,CARBON FILM 2.4K 1/6W 5	R2294	ORD0752F609	R,CARBON FILM 75 1/6W 5
R2015	ORD1501F609	R,CARBON FILM 1.5K 1/6W 5	R2295	ORD0752F609	R,CARBON FILM 75 1/6W 5
R2017	ORD1500F609	R,CARBON FILM 150 1/6W 5	R2296	ORD0102F609	R,CARBON FILM 10 1/6W 5
R2018	ORD0102F609	R,CARBON FILM 10 1/6W 5	R23	ORD1000F609	R,CARBON FILM 100 1/6W 5
R2019	ORD0822F609	R,CARBON FILM 82 1/6W 5	R23P	ORH2000D622	RESISTOR CHIP 200 1/10W 5 TA

LOCA. NO	PART NO	DESCRIPTION	LOCA. NO	PART NO	DESCRIPTION
R230	ORD0822F609	R,CARBON FILM 82 1/6W 5	R34P	ORH4701D622	RESISTOR CHIP 4.7K 1/10W 5 D.R/TP
R231	ORD0752F609	R,CARBON FILM 75 1/6W 5	R35	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5
R232	ORD2203F609	R,CARBON FILM 220K 1/6W 5	R35P	ORH1202D622	RESISTOR CHIP 12K 1/10W 5 D.R/TP
R233	ORD3300F609	R,CARBON FILM 330 1/6W 5	R36	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5
R234	ORD3300F609	R,CARBON FILM 330 1/6W 5	R36P	ORH1001D622	RESISTOR CHIP 1.0K 1/10W 5 D.R/TP
R235	ORD2203F609	R,CARBON FILM 220K 1/6W 5	R37	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5
R236	ORD0102F609	R,CARBON FILM 10 1/6W 5	R38	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5
R237	ORD4701F609	R,CARBON FILM 4.7K 1/6W 5	R38P	ORH1001D622	RESISTOR CHIP 1.0K 1/10W 5 D.R/TP
R238	ORD0102F609	R,CARBON FILM 10 1/6W 5	R39	ORD4701F609	R,CARBON FILM 4.7K 1/6W 5
R24	ORD1000F609	R,CARBON FILM 100 1/6W 5	R39P	ORH6802D622	RESISTOR CHIP 68K 1/10W 5 D.R/TP
R24P	ORH1002D622	RESISTOR CHIP 10K 1/10W 5 D.R/TP	R4S	ORD2202F609	R,CARBON FILM 22K 1/6W 5
R240	ORD0511F609	RESISTOR,FIXED CARBON FILM 5.1 1/6W 5% TA	R40	ORD2200F609	R,CARBON FILM 220 1/6W 5
R241	ORD2200F609	R,CARBON FILM 220 1/6W 5	R40P	ORH4702D622	RESISTOR CHIP 47K 1/10W 5 D.R/TP
R242	ORD3300F609	R,CARBON FILM 330 1/6W 5	R401	ORD1000F609	R,CARBON FILM 100 1/6W 5
R243	ORD3300F609	R,CARBON FILM 330 1/6W 5	R402	ORD3301F609	R,CARBON FILM 3.3K 1/6W 5
R244	ORD2000F609	R,CARBON FILM 200 1/6W 5	R403	ORD3301H609	R,CARBON FILM 3.3K 1/2W 5
R245	ORD1300F609	R,CARBON FILM 130 1/6W 5	R404	ORD0472H609	R,CARBON FILM 47 1/2W 5
R246	ORD4700F609	R,CARBON FILM 470 1/6W 5	R405	ORS1201K607	RESISTOR,FIX METAL FILM OXIDE 120K 2W 5% TA62
R247	ORD1000F609	R,CARBON FILM 100 1/6W 5	R406	ORS0470J607	R,METAL FILM OXIDE 0.47 1W 5%
R249	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5	R407	ORD5600H609	R,CARBON FILM 560 1/2W 5
R25	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5	R408	ORD2200F609	R,CARBON FILM 220 1/6W 5
R25P	ORH3301D622	RESISTOR CHIP 3.3K 1/10W 5 D.R/TP	R409	ORD1303H609	R,CARBON FILM 130K 1/2W 5
R250	ORD2200F609	R,CARBON FILM 220 1/6W 5	R41P	ORH4701D622	RESISTOR CHIP 4.7K 1/10W 5 D.R/TP
R26	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5	R410	ORD1202F609	R,CARBON FILM 12K 1/6W 5
R26P	ORH1004D622	RESISTOR CHIP 1.0M 1/10W 5 D.R/TP	R411	ORS1002L667	RESISTOR,FIX METAL FILM OXIDE 10K 3W 5 SF30
R266	ORD2200F609	R,CARBON FILM 220 1/6W 5	R413	ORD7501F609	R,CARBON FILM 7.5K 1/6W 5
R267	ORD2200F609	R,CARBON FILM 220 1/6W 5	R414	ORD3602F609	R,CARBON FILM 36K 1/6W 5
R268	ORD0102F609	R,CARBON FILM 10 1/6W 5	R415	ORD1000F609	R,CARBON FILM 100 1/6W 5
R27	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5	R416	ORD5602F609	R,CARBON FILM 56K 1/6W 5
R27P	ORH1301D622	RESISTOR CHIP 1.3K 1/10W 5 D.R/TP	R417	ORD4700F609	R,CARBON FILM 470 1/6W 5
R28	ORD1000F609	R,CARBON FILM 100 1/6W 5	R418	ORD1002F609	R,CARBON FILM 10K 1/6W 5
R28P	ORH2202D622	RESISTOR CHIP 22K 1/10W 5 D.R/TP	R419	ORD1501F609	R,CARBON FILM 1.5K 1/6W 5
R29	ORD1000F609	R,CARBON FILM 100 1/6W 5	R42	ORD1000F609	R,CARBON FILM 100 1/6W 5
R29P	ORH6801D622	RESISTOR CHIP 6.8K 1/10W 5 D.R/TP	R42P	ORH6800D622	RESISTOR CHIP 680 1/10W 5 D.R/TP
R3S	ORD0102F609	R,CARBON FILM 10 1/6W 5	R421	ORD1002F609	R,CARBON FILM 10K 1/6W 5
R30P	ORH1301D622	RESISTOR CHIP 1.3K 1/10W 5 D.R/TP	R422	ORD1801H609	R,CARBON FILM 1.8K 1/2W 5
R304	ORN2001F409	R,METAL FILM 2K 1/6W 1%	R423	ORD2701H609	R,CARBON FILM 2.7K 1/2W 5
R305	ORD0101H609	R,CARBON FILM 1.0 1/2W 5	R424	ORS0102L667	RESISTOR,FIX METAL FILM OXIDE 10 3W 5 SF30
R306	ORN0121J607	RESISTOR,FIX METAL FILM 120 1W 5% TA62	R425	ORD1202F609	R,CARBON FILM 12K 1/6W 5
R307	ORS3300J607	R,METAL FILM OXIDE 330 1W 5%	R426	ORD1201H609	R,CARBON FILM 1.2K 1/2W 5
R308	ORD2001F609	R,CARBON FILM 2.0K 1/6W 5	R427	ORD1003F609	R,CARBON FILM 100K 1/6W 5
R31P	ORH3301D622	RESISTOR CHIP 3.3K 1/10W 5 D.R/TP	R428	ORD1201F609	R,CARBON FILM 1.2K 1/6W 5
R310	ORD1000F609	R,CARBON FILM 100 1/6W 5	R429	ORD1502F609	R,CARBON FILM 15K 1/6W 5
R312	ORD1002F609	R,CARBON FILM 10K 1/6W 5	R43	ORD1002F609	R,CARBON FILM 10K 1/6W 5
R314	ORD5601F609	R,CARBON FILM 5.6K 1/6W 5	R43P	ORH6801D622	RESISTOR CHIP 6.8K 1/10W 5 D.R/TP
R315	ORD2200F609	R,CARBON FILM 220 1/6W 5	R430	ORD1201F609	R,CARBON FILM 1.2K 1/6W 5
R316	ORD4701F609	R,CARBON FILM 4.7K 1/6W 5	R431	ORD1000H609	R,CARBON FILM 100 1/2W 5
R32	ORD1000F609	R,CARBON FILM 100 1/6W 5	R432	ORD6801H609	R,CARBON FILM 6.8K 1/2W 5
R32P	ORH1004D622	RESISTOR CHIP 1.0M 1/10W 5 D.R/TP	R433	ORD1502H609	R,CARBON FILM 15K 1/2W 5
R33	ORD1000F609	R,CARBON FILM 100 1/6W 5	R434	ORD1003F609	R,CARBON FILM 100K 1/6W 5
R33P	ORH4701D622	RESISTOR CHIP 4.7K 1/10W 5 D.R/TP	R435	ORD1003F609	R,CARBON FILM 100K 1/6W 5
R34	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5	R437	ORS0222H609	R,METAL FILM OXIDE 22 1/2W 5

LOCA. NO	PART NO	DESCRIPTION	LOCA. NO	PART NO	DESCRIPTION
R438	ORS5601J607	R,METAL FILM OXIDE 5.60K 1W 5% TA62	R524	ORD1000F609	R,CARBON FILM 100 1/6W 5
R44	ORD1502F609	R,CARBON FILM 15K 1/6W 5	R527	ORD3300F609	R,CARBON FILM 330 1/6W 5
R44P	ORH4701D622	RESISTOR CHIP 4.7K 1/10W 5 D.R/TP	R529	ORD2200F609	R,CARBON FILM 220 1/6W 5
R440	ORS1201K607	RESISTOR, FIX METAL FILM OXIDE 120K 2W 5% TA62	R53	ORD4701F609	R,CARBON FILM 4.7K 1/6W 5
R442	ORD1000H609	R,CARBON FILM 100 1/2W 5	R53P	ORH4701D622	RESISTOR CHIP 4.7K 1/10W 5 D.R/TP
R443	ORD3301H609	R,CARBON FILM 3.3K 1/2W 5	R530	ORD2200F609	R,CARBON FILM 220 1/6W 5
R444	ORD1002F609	R,CARBON FILM 10K 1/6W 5	R533	ORD2702F609	R,CARBON FILM 27K 1/6W 5
R449	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5	R534	ORD2001F609	R,CARBON FILM 2.0K 1/6W 5
R45	ORD4701F609	R,CARBON FILM 4.7K 1/6W 5	R535	ORD1502F609	R,CARBON FILM 15K 1/6W 5
R45P	ORH3901D622	RESISTOR CHIP 3.9K 1/10W 5 D.R/TP	R539	ORD5603F609	R,CARBON FILM 560K 1/6W 5
R450	ORD6800F609	R,CARBON FILM 680 1/6W 5	R54	ORD2200F609	R,CARBON FILM 220 1/6W 5
R451	ORD6801F609	R,CARBON FILM 6.8K 1/6W 5	R54P	ORH4701D622	RESISTOR CHIP 4.7K 1/10W 5 D.R/TP
R452	ORD5601F609	R,CARBON FILM 5.6K 1/6W 5	R540	ORN3902F409	R, METAL FILM 39K 1/6W 1%
R453	ORD9101F609	R,CARBON FILM 9.1K 1/6W 5	R541	ORD2702F609	R,CARBON FILM 27K 1/6W 5
R454	ORD4702F609	R,CARBON FILM 47K 1/6W 5	R542	ORD1003F609	R,CARBON FILM 100K 1/6W 5
R455	ORD1202F609	R,CARBON FILM 12K 1/6W 5	R543	ORD6200F609	R,CARBON FILM 620 1/6W 5
R456	ORD4702F609	R,CARBON FILM 47K 1/6W 5	R544	ORD1002F609	R,CARBON FILM 10K 1/6W 5
R457	ORD4702F609	R,CARBON FILM 47K 1/6W 5	R545	ORD1002F609	R,CARBON FILM 10K 1/6W 5
R458	ORD4702F609	R,CARBON FILM 47K 1/6W 5	R546	ORD5601F609	R,CARBON FILM 5.6K 1/6W 5
R459	ORD4701F609	R,CARBON FILM 4.7K 1/6W 5	R547	ORD6200F609	R,CARBON FILM 620 1/6W 5
R46	ORD1002F609	R,CARBON FILM 10K 1/6W 5	R548	ORD4701F609	R,CARBON FILM 4.7K 1/6W 5
R46P	ORH2700D622	RESISTOR CHIP 270 1/10W 5 D.R/TP	R549	ORD0471F609	R,CARBON FILM 4.7 1/6W 5
R460	ORD1201F609	R,CARBON FILM 12K 1/6W 5	R55	ORD4701F609	R,CARBON FILM 4.7K 1/6W 5
R461	ORD3301F609	R,CARBON FILM 3.3K 1/6W 5	R55P	ORH1000D622	RESISTOR CHIP 100 1/10W 5 D.R/TP
R47	ORD1502F609	R,CARBON FILM 15K 1/6W 5	R550	ORD1003F609	R,CARBON FILM 100K 1/6W 5
R47P	ORH1001D622	RESISTOR CHIP 1.0K 1/10W 5 D.R/TP	R551	ORD6200F609	R,CARBON FILM 620 1/6W 5
R48P	ORH6800D622	RESISTOR CHIP 680 1/10W 5 D.R/TP	R552	ORD6200F609	R,CARBON FILM 620 1/6W 5
R49P	ORH4701D622	RESISTOR CHIP 4.7K 1/10W 5 D.R/TP	R553	ORD1000F609	R,CARBON FILM 100 1/6W 5
R50	ORD2200F609	R,CARBON FILM 220 1/6W 5	R557	ORD4702F609	R,CARBON FILM 47K 1/6W 5
R50P	ORH1801D622	RESISTOR CHIP 1.8K 1/10W 5 D.R/TP	R558	ORD4702F609	R,CARBON FILM 47K 1/6W 5
R501	ORD0102F609	R,CARBON FILM 10 1/6W 5	R559	ORD4703F609	R,CARBON FILM 470K 1/6W 5
R502	ORD0102F609	R,CARBON FILM 10 1/6W 5	R56	ORD2200F609	R,CARBON FILM 220 1/6W 5
R503	ORD2200F609	R,CARBON FILM 220 1/6W 5	R56P	ORH1000D622	RESISTOR CHIP 100 1/10W 5 D.R/TP
R504	ORD0471F609	R,CARBON FILM 4.7 1/6W 5	R560	ORD3303F609	R,CARBON FILM 330K 1/6W 5
R505	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5	R561	ORD2200F609	R,CARBON FILM 220 1/6W 5
R506	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5	R563	ORD2200F609	R,CARBON FILM 220 1/6W 5
R507	ORD1000F609	R,CARBON FILM 100 1/6W 5	R565	ORD0471F609	R,CARBON FILM 4.7 1/6W 5
R508	ORD1000F609	R,CARBON FILM 100 1/6W 5	R57	ORD4701F609	R,CARBON FILM 4.7K 1/6W 5
R509	ORD0471F609	R,CARBON FILM 4.7 1/6W 5	R57P	ORH3902D622	RESISTOR CHIP 39K 1/10W 5 D.R/TP
R51	ORD4701F609	R,CARBON FILM 4.7K 1/6W 5	R58	ORD2200F609	R,CARBON FILM 220 1/6W 5
R51P	ORH3001D622	RESISTOR CHIP 3.0K 1/10W 5 D.R/TP	R58P	ORH2201D622	RESISTOR CHIP 2.2K 1/10W 5 D.R/TP
R510	ORD8200F609	R,CARBON FILM 820 1/6W 5	R59	ORD4701F609	R,CARBON FILM 4.7K 1/6W 5
R516	ORD6200F609	R,CARBON FILM 620 1/6W 5	R59P	ORH1001D622	RESISTOR CHIP 1.0K 1/10W 5 D.R/TP
R517	ORD6200F609	R,CARBON FILM 620 1/6W 5	R6S	ORD3300F609	R,CARBON FILM 330 1/6W 5
R518	ORD6200F609	R,CARBON FILM 620 1/6W 5	R60	ORD1003F609	R,CARBON FILM 100K 1/6W 5
R519	ORD1000F609	R,CARBON FILM 100 1/6W 5	R60P	ORH1001D622	RESISTOR CHIP 1.0K 1/10W 5 D.R/TP
R52	ORD2200F609	R,CARBON FILM 220 1/6W 5	R601	ORD4701F609	R,CARBON FILM 4.7K 1/6W 5
R52P	ORH1002D622	RESISTOR CHIP 10K 1/10W 5 D.R/TP	R602	ORD4700F609	R,CARBON FILM 470 1/6W 5
R520	ORD1002F609	R,CARBON FILM 10K 1/6W 5	R603	ORD7501F609	R,CARBON FILM 7.5K 1/6W 5
R521	ORD3300F609	R,CARBON FILM 330 1/6W 5	R604	ORD4700F609	R,CARBON FILM 470 1/6W 5
R522	ORD3300F609	R,CARBON FILM 330 1/6W 5	R605	ORD4700F609	R,CARBON FILM 470 1/6W 5
R523	ORD3300F609	R,CARBON FILM 330 1/6W 5	R606	ORD5102F609	R,CARBON FILM 51K 1/6W 5

The components identified by shading and mark Δ are critical for safety.
Replace only with part number specified.

LOCA. NO	PART NO	DESCRIPTION	LOCA. NO	PART NO	DESCRIPTION
R607	ORD5102F609	R,CARBON FILM 51K 1/6W 5	R76P	ORH1200D622	RESISTOR CHIP 120 1/10W 5 D.R/TP
R608	ORD4700F609	R,CARBON FILM 470 1/6W 5	R77	ORD1000F609	R,CARBON FILM 100 1/6W 5
R609	ORD4700F609	R,CARBON FILM 470 1/6W 5	R801	ORS4702L667	R,METAL FILM OXIDE 47K 3W 5
R61P	ORH1301D622	RESISTOR CHIP 1.3K 1/10W 5 D.R/TP	R802	180-A03H	RESISTOR RW RECT G 10W 1.0 J DOUBLE
R610	ORD4700F609	R,CARBON FILM 470 1/6W 5	R803	ORD1002H609	R,CARBON FILM 10K 1/2W 5
R611	ORD7501F609	R,CARBON FILM 7.5K 1/6W 5	R804	ORS0152K607	R,METAL FILM OXIDE 15 2W 5%
R612	ORD4701F609	R,CARBON FILM 4.7K 1/6W 5	R805	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5
R613	ORD5102F609	R,CARBON FILM 51K 1/6W 5	R806	ORD1801F609	R,CARBON FILM 1.8K 1/6W 5
R614	ORD5102F609	R,CARBON FILM 51K 1/6W 5	R807	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5
R618	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5	R808	180-A01D	R,RW ROUND G 2W 0.16 J
R619	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5	R809	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5
R62	ORD2200F609	R,CARBON FILM 220 1/6W 5	R810	ORD2001F609	R,CARBON FILM 2.0K 1/6W 5
R62P	ORH1001D622	RESISTOR CHIP 1.0K 1/10W 5 D.R/TP	R812	ORD2202F609	R,CARBON FILM 22K 1/6W 5
R620	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5	R813	ORD4702H609	R,CARBON FILM 47K 1/2W 5
R621	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5	R814	ORD4702F609	R,CARBON FILM 47K 1/6W 5
R622	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5	R816	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5
R623	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5	R817	180-A01F	RESISTOR RW ROUND G 2W 0.50 J TA31(63)
R624	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5	R818	ORD5100H609	R,CARBON FILM 510 1/2W 5
R625	ORD1002F609	R,CARBON FILM 10K 1/6W 5	R819	ORD3300F609	R,CARBON FILM 330 1/6W 5
R626	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5	R820	ORD5100H609	R,CARBON FILM 510 1/2W 5
R627	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5	R821	ORD2000F609	R,CARBON FILM 200 1/6W 5
R628	ORD1501F609	R,CARBON FILM 1.5K 1/6W 5	R822	ORD3300F609	R,CARBON FILM 330 1/6W 5
R63	ORD4701F609	R,CARBON FILM 4.7K 1/6W 5	R823	ORD3300F609	R,CARBON FILM 330 1/6W 5
R63P	ORH1001D622	RESISTOR CHIP 1.0K 1/10W 5 D.R/TP	Δ R824	180-C02H	RESISTOR RC 1/2W 8.2M K TA52
R630	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5	R825	ORD2201F609	R,CARBON FILM 2.2K 1/6W 5
R631	ORD3901F609	R,CARBON FILM 3.9K 1/6W 5	R826	ORD1803H609	R,CARBON FILM 180K 1/2W 5
R632	ORD3901F609	R,CARBON FILM 3.9K 1/6W 5	R827	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5
R633	ORD3901F609	R,CARBON FILM 3.9K 1/6W 5	R828	ORD4702F609	R,CARBON FILM 47K 1/6W 5
R634	ORD3901F609	R,CARBON FILM 3.9K 1/6W 5	R829	ORS6801K607	R,METAL FILM OXIDE 6.80K 2W 5%
R635	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5	R830	ORS8201K607	R,METAL FILM OXIDE 8.20K 2W 5%
R636	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5	R831	ORD8201H609	RESISTOR, FIXED CARBON FILM 8.2K 1/2W 5 TA52
R637	ORD2203F609	R,CARBON FILM 220K 1/6W 5	R834	ORS1001H609	R,METAL FILM OXIDE 1.0K 1/2W 5
R638	ORD2203F609	R,CARBON FILM 220K 1/6W 5	R836	ORS0562K607	RESISTOR, FIX METAL FILM OXIDE 56 2W 5% TA62
R639	ORD2203F609	R,CARBON FILM 220K 1/6W 5	R837	ORD1803H609	R,CARBON FILM 180K 1/2W 5
R64	ORD2200F609	R,CARBON FILM 220 1/6W 5	R838	ORN4701F409	RESISTOR, FIX METAL FILM 4.70K 1/6W 1% TA52
R64P	ORH2201D622	RESISTOR CHIP 2.2K 1/10W 5 D.R/TP	R839	ORS1002K607	R,METAL FILM OXIDE 10K 2W 5%
R640	ORD2203F609	R,CARBON FILM 220K 1/6W 5	R840	ORD0101H609	R,CARBON FILM 1.0 1/2W 5
R65	ORD4701F609	R,CARBON FILM 4.7K 1/6W 5	R841	ORD0101H609	R,CARBON FILM 1.0 1/2W 5
R66	ORD2200F609	R,CARBON FILM 220 1/6W 5	R842	ORD5601H609	R,CARBON FILM 5.6K 1/2W 5
R67P	ORH2700D622	RESISTOR CHIP 270 1/10W 5 D.R/TP	R843	ORD1000H609	R,CARBON FILM 100 1/2W 5
R68	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5	R844	ORD4702F609	R,CARBON FILM 47K 1/6W 5
R68P	ORH2001D622	RESISTOR CHIP 2.0K 1/10W 5 D.R/TP	R846	ORD2001F609	R,CARBON FILM 2.0K 1/6W 5
R69	ORD1002F609	R,CARBON FILM 10K 1/6W 5	Δ R847	180-C02L	RESISTOR 0.47M OHM 1/2W 10%
R7S	ORD3300F609	R,CARBON FILM 330 1/6W 5	R849	ORD0472H609	R,CARBON FILM 47 1/2W 5
R70	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5	R851	ORD4701F609	R,CARBON FILM 4.7K 1/6W 5
R71P	ORH2001D622	RESISTOR CHIP 2.0K 1/10W 5 D.R/TP	R853	ORS0470J607	R,METAL FILM OXIDE 0.47 1W 5%
R72	ORD0102F609	R,CARBON FILM 10 1/6W 5	R854	ORD3301H609	R,CARBON FILM 3.3K 1/2W 5
R72P	ORH1002D622	RESISTOR CHIP 10K 1/10W 5 D.R/TP	R855	ORD3302F609	R,CARBON FILM 33K 1/6W 5
R73	ORD1002F609	R,CARBON FILM 10K 1/6W 5	R856	ORD4702F609	R,CARBON FILM 47K 1/6W 5
R73P	ORH2001D622	RESISTOR CHIP 2.0K 1/10W 5 D.R/TP	R857	ORD4702F609	R,CARBON FILM 47K 1/6W 5
R74P	ORH1002D622	RESISTOR CHIP 10K 1/10W 5 D.R/TP	R9S	ORD2202F609	R,CARBON FILM 22K 1/6W 5
R75P	ORH2701D622	RESISTOR CHIP 2.7K 1/10W 5 D.R/TP	R901	ORD1000F609	R,CARBON FILM 100 1/6W 5

LOCA. NO	PART NO	DESCRIPTION
R902	ORD1201F609	R,CARBON FILM 12K 1/6W 5
R903	ORD1001F609	R,CARBON FILM 10K 1/6W 5
R904	ORD0562F609	R,CARBON FILM 56 1/6W 5
R905	ORD2000F609	R,CARBON FILM 200 1/6W 5
R908	ORD2003H609	R,CARBON FILM 200K 1/2W 5
R921	ORD1000F609	R,CARBON FILM 100 1/6W 5
R922	ORD0102F609	R,CARBON FILM 10 1/6W 5
R923	ORD1200F609	R,CARBON FILM 120 1/6W 5
R924	ORD8202F609	R,CARBON FILM 82K 1/6W 5
R925	ORS4700H609	R,METAL FILM OXIDE 470 1/2W 5
R928	ORS2200H609	R,METAL FILM OXIDE 220 1/2W 5
R929	ORD4700H609	R,CARBON FILM 470 1/2W 5
R941	ORD1000F609	R,CARBON FILM 100 1/6W 5
R942	ORD0102F609	R,CARBON FILM 10 1/6W 5
R943	ORD1200F609	R,CARBON FILM 120 1/6W 5
R944	ORD9102F609	R,CARBON FILM 91K 1/6W 5
R945	ORS4700H609	R,METAL FILM OXIDE 470 1/2W 5
R946	ORS6801L667	R,METAL FILM OXIDE 6.8K 3W 5
R948	ORS2200H609	R,METAL FILM OXIDE 220 1/2W 5
R949	ORD4700H609	R,CARBON FILM 470 1/2W 5
R961	ORD1000F609	R,CARBON FILM 100 1/6W 5
R962	ORD0102F609	R,CARBON FILM 10 1/6W 5
R963	ORD1200F609	R,CARBON FILM 120 1/6W 5
R964	ORD1003F609	R,CARBON FILM 100K 1/6W 5
R965	ORS4700H609	R,METAL FILM OXIDE 470 1/2W 5
R966	ORS6801L667	R,METAL FILM OXIDE 6.8K 3W 5
R968	ORS2200H609	R,METAL FILM OXIDE 220 1/2W 5
R969	ORD4700H609	R,CARBON FILM 470 1/2W 5
R99P	ORH4701D622	RESISTOR CHIP 4.7K 1/10W 5 D.R/TP
VR101	180-F03J	RESISTOR EVN-DJAY03 B203 SEMI-FIX
VR102	180-F03J	RESISTOR EVN-DJAY03 B203 SEMI-FIX
FILTERS & OSCILLATORS		
X01	166-E05A	FILTER RESO CST4.00MGW 4000-TF01
X01P	156-A05B	CRYSTAL 4.433619 SER.00262 TP PHILIPS
X02P	156-A01B	CRYSTAL 3.579545 16PF 90 OHM
X201	156-A02H	CRYSTAL 20.480000 18PF 20 OHM BULK
X202	156-A02B	CRYSTAL 12.000000 16PF 30 OHM BULK
X501	156-A01B	CRYSTAL 3.579545 16PF 90 OHM
X502	156-001B	CRYSTAL 4.433619MHZ(00384)PHILIPS
X601	156-A02R	CRYSTAL 18.432000 16PF 20 OHM BULK
Z01	166-F01G	FILTER EMI,DSS306-93FZ103N 100V TA
Z03	166-F01G	FILTER EMI,DSS306-93FZ103N 100V TA
Z101	166-250C	FILTER OFWVG3962M
Z102	166-A01B	FILTER OFWK3953M
Z103	166-A01L	FILTER OFWL9453M
Z104	166-C04C	FILTER TRAP TPWA02B-TF21(5.5/6.5)
Z105	166-C06A	FILTER MKT40.9MA110P-TF01
Z106	166-A01T	FILTER OFWVG9354M
Z107	166-274A	FILTER MKT40MA100P(40.4M TRAP)
Z108	166-274A	FILTER MKT40MA100P(40.4M TRAP)

LOCA. NO	PART NO	DESCRIPTION
Z110	166-F01G	FILTER EMI,DSS306-93FZ103N 100V TA
Z111	166-F01G	FILTER EMI,DSS306-93FZ103N 100V TA
Z112	166-F01G	FILTER EMI,DSS306-93FZ103N 100V TA
Z113	166-F01D	FILTER EMI,DS306-93 Y5S 271M 50V TA
Z114	166-F02A	FILTER EMI,NFV610-655 T2A 106 BK
Z1601	166-F01G	FILTER EMI,DSS306-93FZ103N 100V TA
BS PCB PARTS		
C03B	0CE227DH618	C,ELECTROLYTIC 220UF STD 25V M
C06B	0CE476DH618	C,ELECTROLYTIC 47UF STD 25V M
C07B	0CE476DH618	C,ELECTROLYTIC 47UF STD 25V M
C08B	0CH5101K406	CAPA,CHIP CERAMIC M/L T.C R/S 100P 50V J SL 2.0X1.25 R/TP
C09B	0CH5101K406	CAPA,CHIP CERAMIC M/L T.C R/S 100P 50V J SL 2.0X1.25 R/TP
C10B	0CE107DD618	C,ELECTROLYTIC 100UF STD 10V M
C11B	0CH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP
C12B	0CE105DK618	C,ELECTROLYTIC 1UF STD 50V M
C13B	0CH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP
C14B	0CE106DF618	C,ELECTROLYTIC 10UF STD 16V M
C15B	0CH5101K406	CAPA,CHIP CERAMIC M/L T.C R/S 100P 50V J SL 2.0X1.25 R/TP
C16B	0CH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP
C17B	0CH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP
C18B	0CE107DF618	C,ELECTROLYTIC 100UF STD 16V M
C19B	0CH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP
C20B	0CQ4731N509	C,POLYESTER(MYLAR) 0.047U 100V K
C21B	0CE106DF618	C,ELECTROLYTIC 10UF STD 16V M
C22B	0CH5471K406	CAPA,CHIP CERAMIC M/L T.C R/S 470P 50V J SL 2.0X1.25 R/TP
C23B	0CH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP
C25B	0CH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP
C26B	0CH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP
C27B	0CH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP
C28B	0CE106DF618	C,ELECTROLYTIC 10UF STD 16V M
C29B	0CE106DF618	C,ELECTROLYTIC 10UF STD 16V M
C30B	0CE107DF618	C,ELECTROLYTIC 100UF STD 16V M
C31B	0CH1104K946	CHIP CAPA CERAM 0.1M 50V Z 2.0*1.25 R/TP
C32B	0CE106DF618	C,ELECTROLYTIC 10UF STD 16V M
C33B	0CE106DF618	C,ELECTROLYTIC 10UF STD 16V M
D03B	0DD200009AF	DIODE RU-2MV
D04B	0DD200009AF	DIODE RU-2MV
IC01B	0ISM615150A	IC,SIEMENS TDA6151/5 20D BS IF
IC02B	0ISA701600A	IC, SANYO LA7016 ANALOG SW
IC03B	0ISK312000B	IC,SANKEN SI-3120C,5PIN,ON/OFF 12V REG.
L02B	0LA0102K119	INDUCTOR 10UH K
L03B	0LA0222K119	INDUCTOR 22UH K
L04B	0LA0102K119	INDUCTOR 10UH K
L05B	0LA0102K119	INDUCTOR 10UH K
Q01B	0TR387500AA	TRANSISTOR CHIP 2SC3875S(ALY) KEC
Q02B	0TR387500AA	TRANSISTOR CHIP 2SC3875S(ALY) KEC
Q03B	0TR127600AA	TRANSISTOR KTA1276-Y(KTA473),KEC
Q04B	0TR387500AA	TRANSISTOR CHIP 2SC3875S(ALY) KEC
Q05B	0TR150400BA	TRANSISTOR CHIP 2SA1504S(ASY) KEC
Q06B	0TR387500AA	TRANSISTOR CHIP 2SC3875S(ALY) KEC
Q07B	0TR127600AA	TRANSISTOR KTA1276-Y(KTA473),KEC

The components identified by shading and mark **△** are critical for safety.
Replace only with part number specified.

LOCA. NO	PART NO	DESCRIPTION
Q08B	OTR387500AA	TRANSISTOR CHIP 2SC3875S(ALY) KEC
Q09B	OTR387500AA	TRANSISTOR CHIP 2SC3875S(ALY) KEC
Q10B	OTR387500AA	TRANSISTOR CHIP 2SC3875S(ALY) KEC
Q11B	OTR150400BA	TRANSISTOR CHIP 2SA1504S(ASY) KEC
Q12B	OTR387500AA	TRANSISTOR CHIP 2SC3875S(ALY) KEC
Q13B	OTR387500AA	TRANSISTOR CHIP 2SC3875S(ALY) KEC
Q14B	OTR150400BA	TRANSISTOR CHIP 2SA1504S(ASY) KEC
Q15B	OTR387500AA	TRANSISTOR CHIP 2SC3875S(ALY) KEC
Q16B	OTR150400BA	TRANSISTOR CHIP 2SA1504S(ASY) KEC
Q17B	OTR387500AA	TRANSISTOR CHIP 2SC3875S(ALY) KEC
R01B	ORH1002D622	RESISTOR CHIP 10K 1/10W 5 D.R/TP
R02B	ORH4701D622	RESISTOR CHIP 4.7K 1/10W 5 D.R/TP
R03B	ORD1801H609	R,CARBON FILM 1.8K 1/2W 5
R04B	ORH3301D622	RESISTOR CHIP 3.3K 1/10W 5 D.R/TP
R05B	ORH1002D622	RESISTOR CHIP 10K 1/10W 5 D.R/TP
R06B	ORH1002D622	RESISTOR CHIP 10K 1/10W 5 D.R/TP
R07B	ORH1002D622	RESISTOR CHIP 10K 1/10W 5 D.R/TP
R08B	ORH1002D622	RESISTOR CHIP 10K 1/10W 5 D.R/TP
R09B	ORD1801H609	R,CARBON FILM 1.8K 1/2W 5
R10B	ORH3301D622	RESISTOR CHIP 3.3K 1/10W 5 D.R/TP
R11B	ORH1301D622	RESISTOR CHIP 1.3K 1/10W 5 D.R/TP
R12B	ORH2701D622	RESISTOR CHIP 2.7K 1/10W 5 D.R/TP
R13B	ORH3901D622	RESISTOR CHIP 3.9K 1/10W 5 D.R/TP
R14B	ORH2700D622	RESISTOR CHIP 270 1/10W 5 D.R/TP
R15B	ORH1500D622	RESISTOR CHIP 150 1/10W 5 D.R/TP
R16B	ORH1500D622	RESISTOR CHIP 150 1/10W 5 D.R/TP
R17B	ORH8200D622	RESISTOR CHIP 820 1/10W 5 D.R/TP
R18B	ORH2200D622	RESISTOR CHIP 220 1/10W 5 D.R/TP
R19B	ORH8200D622	RESISTOR CHIP 820 1/10W 5 D.R/TP
R20B	ORH1001D622	RESISTOR CHIP 1.0K 1/10W 5 D.R/TP
R21B	ORH4702D622	RESISTOR CHIP 47K 1/10W 5 D.R/TP
R22B	ORH1003D622	RESISTOR CHIP 100K 1/10W 5 D.R/TP
R23B	ORH1001D622	RESISTOR CHIP 1.0K 1/10W 5 D.R/TP
R24B	ORH4700D622	RESISTOR CHIP 470 1/10W 5 D.R/TP
R25B	ORH4700D622	RESISTOR CHIP 470 1/10W 5 D.R/TP
R26B	ORH3300D622	RESISTOR CHIP 330 1/10W 5 D.R/TP
R27B	ORH1501D622	RESISTOR CHIP 15K 1/10W 5 D.R/TP
R28B	ORH1501D622	RESISTOR CHIP 15K 1/10W 5 D.R/TP
R29B	ORH4701D622	RESISTOR CHIP 4.7K 1/10W 5 D.R/TP
R30B	ORH1801D622	RESISTOR CHIP 1.8K 1/10W 5 D.R/TP
R31B	ORH2200D622	RESISTOR CHIP 220 1/10W 5 D.R/TP
R32B	ORH0752D622	RESISTOR CHIP 75 1/10W 5 D.R/TP
R35B	ORH1003D622	RESISTOR CHIP 100K 1/10W 5 D.R/TP
R36B	ORH5102D622	RESISTOR CHIP 51K 1/10W 5 D.R/TP
R37B	ORH1002D622	RESISTOR CHIP 10K 1/10W 5 D.R/TP
R38B	ORH2701D622	RESISTOR CHIP 2.7K 1/10W 5 D.R/TP
R39B	ORH1001D622	RESISTOR CHIP 1.0K 1/10W 5 D.R/TP
R40B	ORH1002D622	RESISTOR CHIP 10K 1/10W 5 D.R/TP
R41B	ORH5601D622	RESISTOR CHIP 5.6K 1/10W 5 D.R/TP
R42B	ORH1500D622	RESISTOR CHIP 150 1/10W 5 D.R/TP
R43B	ORH4700D622	RESISTOR CHIP 470 1/10W 5 D.R/TP

LOCA. NO	PART NO	DESCRIPTION
R44B	ORH1000D622	RESISTOR CHIP 100 1/10W 5 D.R/TP
R45B	ORH1301D622	RESISTOR CHIP 1.3K 1/10W 5 D.R/TP
R46B	ORH1101D622	RESISTOR CHIP 1.1K 1/10W 5 TA
R47B	ORH1001D622	RESISTOR CHIP 1.0K 1/10W 5 D.R/TP
R48B	ORD1801H609	R,CARBON FILM 1.8K 1/2W 5
R49B	ORD1801H609	R,CARBON FILM 1.8K 1/2W 5
R50B	ORH3901D622	RESISTOR CHIP 3.9K 1/10W 5 D.R/TP
R52B	ORH4702D622	RESISTOR CHIP 47K 1/10W 5 D.R/TP
TU01B	113-248A	TUNER BSJE3-572A
T01B	166-285C	FILTER CDLP50
ZD05B	0DZ300009BA	DIODE ZENER MTZ30B
ZD06B	0DZ560009AA	DIODE ZENER MTZ5.6B
ZD07B	0DZ560009AA	DIODE ZENER MTZ5.6B
*** (BS PARTS OF THE MAIN1 PCB) ***		
C17	0CN1020K519	C,TUBULA(HIGH DIELE) 1000PF 50V K
C19	0CN1020K519	C,TUBULA(HIGH DIELE) 1000PF 50V K
Q04	OTR319809AA	TRANSISTOR KTC3198-TP-Y (KTC1815)KEC
R10	ORD1001F609	R,CARBON FILM 1.0K 1/6W 5
R11	ORD2200F609	R,CARBON FILM 220 1/6W 5
R30	ORD1000F609	R,CARBON FILM 100 1/6W 5
R31	ORD1002F609	R,CARBON FILM 10K 1/6W 5
R41	ORD4701F609	R,CARBON FILM 4.7K 1/6W 5
R48	ORD1000F609	R,CARBON FILM 100 1/6W 5
R49	ORD1000F609	R,CARBON FILM 100 1/6W 5
R71	ORD4701F609	R,CARBON FILM 4.7K 1/6W 5
MISCELLANEOUS		
PA001	109-010A	PCB ASSY RELAY DRAWER
PJ201	387-453E	CONNECTOR ASSY FOR DY(CBT-2870)
P202	106-049A	PRE-AMP LIM 9051-4(38.0KHZ),LITEON
P203	380-383A	JACK A/V IN,VERTICAL 2P
P204	380-363B	JACK S-VHS(TCS7953-14-211)HOSIDEN
P205	380-336B	JACK RCA WA6013A YL
△ RL801	380-336A	JACK RCA WA6013A WH
△ SG901	380-336C	JACK RCA WA6013A(RD)
△ SG921	141-018E	RELAY DG12D1-0(M)
△ SG941	165-004A	SPARK GAP AG20PT 152F-L3N/S-23
△ SG961	165-004A	SPARK GAP AG20PT 152F-L3N/S-23
SK1S	165-004A	SPARK GAP AG20PT 152F-L3N/S-23
SK202	165-004A	SPARK GAP AG20PT 152F-L3N/S-23
△ SK901	381-091A	SOCKET SCART JACK 21PIN
SW02	381-091A	SOCKET SCART JACK 21PIN
SW03	381-194A	SOCKET CPT,HPS0380-01-110 DOUBLEFOCUS
SW04	140-191A	SWITCH TACT,KHH-15910
SW05	140-191A	SWITCH TACT,KHH-15910
SW06	140-191A	SWITCH TACT,KHH-15910
SW07	140-191A	SWITCH TACT,KHH-15910
SW08	140-191A	SWITCH TACT,KHH-15910
△ SW801	140-191A	SWITCH TACT,KHH-15910
	6600VM2001A	SWITCH POWER SDDFC3

The components identified by shading and mark Δ are critical for safety.
Replace only with part number specified.

LOCA. NO	PART NO	DESCRIPTION
TH401	163-001A	THERMISTOR (YTD5-130)
Δ TH801	163-007F	THERMISTOR PTC PAQA57ROB270(7 OHM)UNIZON
TU101	113-234B	TUNER TUKE9C07DF
Δ T403	154-100C	FBT FCN1-32MP7RC
Δ VA801	164-003D	VARISTOR SVC 561D-14A
X601	156-A02R	CRYSTAL 18.432000 16PF 20
Z107	116-274A	FILTER MKT40MA100P(40.4M TRAP)
Z108	116-274A	FILTER MKT40MA100P(40.4M TRAP)
TRANSMITTER PARTS		
	0ISS518002A	IC,SAMSUNG SEMICONDUCTOR KS51800-24(OHS2209P)20SOP TX
	166-015U	FILTER KBR455BKT LR(WASHABLE)
	303-H73A	COVER BATTERY (105-212)
	303-H73T	COVER BATTERY (LG,105-229)
EXPLODED VIEW PARTS		
100	300-B33L	CABINET ASSY SWF32A12T PDGRN7
	300-B33T	CABINET ASSY SWF32A14T PDLRN7(NE-ESP)
	300-B33R	CABINET ASSY SWF32A12S PDGRT7 (FOR NE-SINGER)
100-01	315-616A	DOOR A/V (WN-3200)
100-02	316-511A	WINDOW DISPLAY(WF-32A10)
100-03	320-070D	SPRING COIL
100-04	441-520A	BUTTON POWER(WF-32A10)
100-05	444-139A	LEG RIGHT (WN-3200)
100-06	444-139B	LEG LEFT(WN-3200)
100-07	314-337A	GRILL JERSEY (WN-3200)
100-08	1PPF0403116	SCREW,PAN HEAD D4 L16
100-09	332-240B	SCREW ASSY,'P' TYPE+WASHER(4*16)
100-10	313-295B	PANEL ASSY(WF-32A10S)
	313-345A	PANEL ASSY(WF-32A14T)
100-11	470-861A	LOCK ASSY,DOOR KIFCO
101	317-003K	DRAWER ASSY,CONTROL(SWF32A12S)
101-01	316-435A	WINDOW COVER (DRAWER:WN-3200)
101-02	302-935A	CASE BOTTOM(DRAWER:WN-3200)
101-03	470-865A	LOCK ASSY DRAWER(KIFCO)
101-04	322-037B	DAMPER (KIFCO:P/N;DP802)
101-05	340-530A	BRACKET DRAWER (WN-3200)
101-07	1PWG0302616	SCREW,BRAZ WASH HD D3.0 L10.0
101-08	424-014A	GEAR DRAWER (WN-3200)
101-09	334-127A	WASHER STOPPER DRAWER
101-10	320-178A	SPRING COIL (DRAWER:WN-3200)
101-11	302-958C	CASE ASSY,TOP DRAWER(WF-32A10S)
101-12	109-009A	PCB ASSY CONTROL DRAWER
101-13	441-401A	BUTTON CONTROL (DRAWER:WN-3200)
102	122-185C	SPEAKER ASSY FRONT R (SWF32A12S)
102-01	302-732A	CASE BOTTOM (SPEAKER:WN-3200)
102-02	120-C77F	SPEAKER 8OHM 5W
102-03	1PTF0403016	SCREW,TRUSS HEAD D4 L14
102-04	302-731A	CASE TOP (SPEAKER:WN-3200)
102-05	1PTF0403116	SCREW,TRUSS HEAD D4 L16
103	122-185D	SPEAKER ASSY FRONT L (SWF32A12S)
104	109-550C	PCB ASSY PRE-AMP(MC52C SKD)

LOCA. NO	PART NO	DESCRIPTION
104-01	106-049A	PRE-AMP LIM 9051-4(38.0KHZ),LITEON
Δ 104-02	140-289B	SWITCH SDDF-3B(J-ALPS) TV-8
104-03	341-645A	HOLDER LED
104-04	351-008A	LINK POWER S/W FOR MC-97A CHASSIS
105	109-552D	PCB ASSY A/V-3(MC52C SKD)
105-01	380-363B	JACK S-VHS(TCS7953-14-211)HOSIDEN
105-02	380-336B	JACK RCA WA6013A YL
105-03	380-336A	JACK RCA WA6013A WH
105-04	380-336C	JACK RCA WA6013A(RD)
106	109-A35C	PCB ASSY LINE FILTER(MC52C SKD)
106-01	340-206A	BRACKET LINE FILTER
Δ 107	174-199J	CORD POWER,CBT-2170/2171
Δ	174-009Q	CORD POWER(W/HOLD HOUSING)L=300
Δ 200	112-C32C	CPT W76EWS001X11(NON-COATING)
Δ	6335V32002A (NE)	CPT ASSY W76ESF031X 14
Δ 200-01	150-201D	COIL D/G+MAGNETIC FIELD CANCEL COIL
200-02	332-229A	SCREW ASSY,HEXAGON HEAD SPECIAL
200-03	341-721B	HOLDER D-COIL (FOR AUTO,L=130)
200-04	342-101A	FIXER CPT (WN-3200)
200-05	343-975A	SUPPORTER CPT
	343-B43A	SUPPORTER CPT (WF-32A14T)
Δ 200-06	170-797V	LEAD SET CPT EARTH(WN-3200)
201	109-554E	PCB ASSY VM(MC52C)(SKD)
201-01	0TR223800AA	TRANSISTOR KTC2238A-Y
201-02	0TR968000AA	TRANSISTOR KTA968A-Y KEC
201-03	341-828A	HOLDER VM PCB
201-04	1PWG0302616	SCREW,BRAZ WASH HD D3.0 L10.0
300	3141VMN141C	CHASSIS ASSY MAIN (MC52C,WF-32A14S)
	3141VMN141B	CHASSIS ASSY MAIN (MC52C,WF-32A14T)
300-01	109-544U	PCB ASSY MAIN1 (MC52C)(FOR CE)
	109-544Y	PCB ASSY MAIN1 (MC-52C,WF-32A14S)
	109-544Z	PCB ASSY MAIN1 (WF-32A14T)
300-02	109-538G	PCB ASSY MAIN2 (MC52C,WF-32A14S)
	109-538F	PCB ASSY MAIN2 (MC52C,WF-32A14T)
300-03	312-391A	FRAME MAIN (WN-32A14T)
300-04	113-234B	TUNER TUKE9C07DF
300-05	380-383A	JACK A/V IN,VERTICAL 2P
300-07	109-542B	PCB ASSY PIP(MC52A)
300-08	109-556B	PCB ASSY BS(MC52A) *(FOR WF-32A12S ONLY)
300-09	109-548B	PCB ASSY SHARP & BLANK
300-10	113-248A	TUNER BSJE3-572A
300-11	109-558H	PCB ASSY SCART2(MC52C,W/O BS)
	109-558B	PCB ASSY SCART2(MC52A) *(FOR NE-AUF,32A12S)
300-12	381-091A	SOCKET SCART JACK 21PIN
300-13	109-540B	PCB ASSY CPT(MC52A)
	109-540C	PCB ASSY CPT(32" SUPER FLAT)
Δ 300-14	381-194A	SOCKET CPT,HPS0380-01-110 DOUBLEFOCUS
300-15	0TR322900AA	TRANSISTOR KTC3229 (KTC2068),KEC
300-16	109-548F	PCB ASSY AUDIO(MC52C)
300-17	0ISA428200A	IC, SANYO LA4282
300-18	343-A94A	SUPPORTER PCB
300-19	1PTF0403016	SCREW,TRUSS HEAD D4 L14

The components identified by shading and mark Δ are critical for safety.
Replace only with part number specified.

LOCA. NO	PART NO	DESCRIPTION
300-21	0ISH052100A	IC,SHARP PQ05RF21 4P(TO-220) 5V S/W REG
300-22	0ISH122100A	IC,SHARP PQ12RF21 4P(TO-220) 12V S/W RE
Δ 300-23	0DD560000AA	DIODE D5SB60 BRIDGE (5A/600V)S.D.G
300-24	0DD420000BB	DIODE D4L20U
Δ 300-25	0ISK670900A	IC,SANKEN STR/S6709 9S SMPS-CNTR
Δ 300-26	0TR476000AA	TRANSISTOR 2SC4760 (W/M) TOSHIBA
300-27	0DD300000AD	DIODE FMS-3FU SANKEN
300-28	0TR205900AA	TRANSISTOR KTD2059-Q,T0-220IS,100V,5A,KEC
300-29	0ISA784500A	IC,SANYO LA7845 7SIP V/OUT(1.5A)
Δ 300-30	154-100C	FBT FCN1-32MP7RC
300-31	381-091A	SOCKET SCART JACK 21PIN
300-32	343-A70C	SUPPORTER S/BOARD(MC-52A)
300-33	343-B41A	SUPPORTER SCART(WF-32A10)
300-34	401-745D	BOARD A/V(SWF32A12T,W/O BS.SCART)
	401-745A	BOARD A/V(WF-32A10) *(FOR NE-AUF,32A12S)
300-35	1BPF0302816	SCREW,PAN HEAD D3 L12
300-36	1PPF0403116	SCREW,PAN HEAD D4 L16
300-37	0ISK312000B	IC,SANKEN SI-3120C,5PIN,ON/OFF 12V REG.
300-38	302-A09A	CASE SHIELD(MC-52A,MICOM)
300-39	303-L14A	COVER SHIELD(MC-52A,MICOM)
300-41	407-U52A	PLATE SHIELD(MC52B,IF)
300-42	302-A88A	CASE SHIELD(MC-52C)
300-43	303-M42A	COVER SHIELD(MC-52C)
300-44	407-S36B	PLATE SHIELD(MC52B)
300-45	303-M72A	COVER SHIELD(MC52B,SAW FILTER)
400	303-H52J	COVER ASSY BACK(SWF32A12T PDGRN7)
	303-H52L	COVER ASSY BACK*(FOR NE-SINGER)
400-01	1PTF0403016	SCREW,TRUSS HEAD D4 L14
400-02	340-528A	BRACKET ASSY,GRILLE
400-03	314-331A	GRILL SPEAKER
400-04	1PTF0403316	SCREW,TRUSS HEAD TAP TITE + D4 L20 MSWR3/BK
401	122-184J	SPEAKER ASSY WOOFER(SWF32A12S)
401-01	302-730A	CASE TOP WOOFER SPK
401-02	302-936A	CASE BOTTOM WOOFER SPK
401-03	407-Q95A	PLATE SEPARATOR WOOFER SPK
401-04	120-D18B	SPEAKER SUPER WOOFER,80HM 20W 3P
401-05	1PTF0403116	SCREW,TRUSS HEAD D4 L16
401-06	1PTF0403316	SCREW,TRUSS HEAD TAP TITE + D4 L20 MSWR3/BK
500	105-212Q	TRANSMITTER MC52A,UNIFIED,W/PIP,W/TXT
	6710V00009A	TRANSMITTER MC52A,LG(W/PIP,TXT,VCR)
500-01	303-H73A	COVER BATTERY (105-212)

ADDRESS

LG Electronics North of England LTD.
BRITLEY ROAD, WASHINGTON
TYNE & WEAR NE38 9DE
UNITED KINGDOM

DEPARTMENT

LEGNE CTV SPARE PARTS DEPT.
TEL : (44-191) 418-3355
FAX : (44-191) 418-3351

We are supposed to supply the local parts for CTV spares to you from U. K.
In case of the local parts marked with "NE" on your SERVICE MANUAL.
Please place an order to the above address in U.K.