

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
ANODE COVER				
	262494		HV ANODE COVER FOR CRT	OPTICS ASSEMBLY
ANODE LEAD	240966		CABLE, CRT ANODE LEAD W/CAP	OPTICS ASSEMBLY
BA007	220343		CONNECTOR 8 PIN	SMALL SIGNAL BOARD
BA009	218515		CONNECTOR 3 PIN	SMALL SIGNAL BOARD
BA010	245051		CONNECTOR 6 PIN	SMALL SIGNAL BOARD
BBA200	258978		CONNECTOR, 4-PIN	MPEG CBA
BBA201	248839		CONNECTOR, 3-PIN	MPEG CBA
BA810	258982		CABLE, 4-CONDUCTOR 195MM	A/V INTERFACE
BA811	258978		CONNECTOR, 4-PIN	A/V INTERFACE
BA900	258985		CONNECTOR, 6-PIN	SMALL SIGNAL BOARD
BA980	215542		CONNECTOR	SMALL SIGNAL BOARD
BACK	259185		BACK, LOWER	INSTRUMENT ASSEMBLY
BACK PLATE	259205		FILLER PLATE, BACK	INSTRUMENT ASSEMBLY
BALLCATCH	258905		BALL CATCH	INSTRUMENT ASSEMBLY
BB01	239204		CONNECTOR 5 PIN	CONVERGENCE AMP BOARD
BBB101	227937		CONNECTOR	KINE DRIVER RED W/SVM
BBB103	259958		CONNECTOR, 9-PIN	KINE DRIVER RED W/SVM
BBB110	259316		SOCKET, KINE	KINE DRIVER RED W/SVM
BBB201	228338		CONNECTOR	KINE DRIVER GREEN W/SVM
BBB203	259488		CONNECTOR, 9-PIN	KINE DRIVER GREEN W/SVM
BBB210	259316		SOCKET, KINE	KINE DRIVER GREEN W/SVM
BBB301	259487		CONNECTOR, 7-PIN	KINE DRIVER BLUE W/SVM
BBB303	259858		CONNECTOR, 9-PIN	KINE DRIVER BLUE W/SVM
BBB310	259316		SOCKET, KINE	KINE DRIVER BLUE W/SVM
BD100	258980		CONNECTOR, 2-PIN	MPEG CBA
BD810A	258946		CABLE, 3-CONDUCTOR 1500MM	DVD CABLING & SUPPORT A
BD910	248839		CONNECTOR, 3-PIN	SPDIF OUTPUT
BG01	239204		CONNECTOR 5 PIN	CONVERGENCE AMP BOARD
BG103	232317		CONNECTOR 2 PIN	KINE DRIVER RED W/SVM
BG203	232317		CONNECTOR 2 PIN	KINE DRIVER GREEN W/SVM
BG303	232317		CONNECTOR 2 PIN	KINE DRIVER BLUE W/SVM
BJ010	257874		JACK	FRONT A/V IN
BJ011	259637		CONNECTOR, S-VIDEO	FRONT A/V IN
BJ300	211596		CONNECTOR 10 PIN	FRONT A/V IN
BK001	259030		CONNECTOR, 9-PIN	FRONT PANEL 1
BK002	247295		CONNECTOR, 4 PIN	FRONT PANEL 1
BK003	259034		CONNECTOR, 2-PIN	FRONT PANEL 1
BK004	237531		CONNECTOR, 3-PIN	FRONT PANEL 1
BK006	259040		CONNECTOR, 3-PIN	FRONT PANEL 1
BK007	256935		CONNECTOR, 8-PIN	FRONT PANEL 1
BK009	259041		CONNECTOR, 8-PIN	FRONT PANEL 2
BK009A	258945		CABLE, 8-CONDUCTOR/BK010-BK009	DVD CABLING & SUPPORT A
BK01	259633		CONNECTOR, RIBBON: 11-PIN	CONVERGENCE SIGNAL BOAR
BK010	259041		CONNECTOR, 8-PIN	FRONT PANEL 1
BK02	258685		CONNECTOR, 9-PIN	CONVERGENCE SIGNAL BOAR
BK04	259972		CONNECTOR, 12-PIN	CONVERGENCE SIGNAL BOAR
BK10	218515		CONNECTOR 3 PIN	CONVERGENCE SIGNAL BOAR
BK11	226977		CONNECTOR	CONVERGENCE SIGNAL BOAR
BK16	218375		CONNECTOR 7 PIN	CONVERGENCE SIGNAL BOAR
BK203	226977		CONNECTOR	IR PREAMP
BK225	256935		CONNECTOR, 8-PIN	MPEG CBA
BL111	259631		CONNECTOR, RIBBON: 21-PIN	P-S/DEFLECTION
BL200	232319		CONNECTOR 9 PIN	P-S/DEFLECTION
BL500	218375		CONNECTOR 7 PIN	P-S/DEFLECTION
BOOT	242724		BOOT, ANODE	P-S/DEFLECTION
BP005	258686		CONNECTOR, 25-PIN RIBBON-TYPE	P-S/DEFLECTION
BP130	245051		CONNECTOR 6 PIN	P-S/DEFLECTION
BP150	219160		CONNECTOR 5 PIN	P-S/DEFLECTION
BP302	256928		CONNECTOR, 14-PIN	SMPS - DVD
BP303	226978		CONNECTOR	SMPS - DVD
BP305	247295		CONNECTOR, 4 PIN	SMPS - DVD
BP500	258686		CONNECTOR, 25-PIN RIBBON-TYPE	SMALL SIGNAL BOARD
BP501	219160		CONNECTOR 5 PIN	SMALL SIGNAL BOARD
BP60	220343		CONNECTOR 8 PIN	CONVERGENCE PS / ADAPTE
BP601	218375		CONNECTOR 7 PIN	MAINS INPUT DOUBLER
BP602	258985		CONNECTOR, 6-PIN	MAINS INPUT DOUBLER

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
BP605	259966		CONNECTOR, 6-PIN	MAINS INPUT DOUBLER
BP611	258685		CONNECTOR, 9-PIN	MAINS INPUT DOUBLER
BP612	249133		CONNECTOR 2 PIN	MAINS INPUT DOUBLER
BQ009	225707		CONNECTOR	FRONT A/V IN
BQ012	257785		CONNECTOR, PHONE JACK: 3.5MM	FRONT A/V IN
BR001	218375		CONNECTOR 7 PIN	SMALL SIGNAL BOARD
BR002	218515		CONNECTOR 3 PIN	SMALL SIGNAL BOARD
BR004	258985		CONNECTOR, 6-PIN	SMALL SIGNAL BOARD
BR005	259966		CONNECTOR, 6-PIN	SMALL SIGNAL BOARD
BR006	259633		CONNECTOR, RIBBON: 11-PIN	SMALL SIGNAL BOARD
BR007	259967		CONNECTOR, 6-PIN	SMALL SIGNAL BOARD
BR01	239204		CONNECTOR 5 PIN	CONVERGENCE AMP BOARD
BR100	259633		CONNECTOR, RIBBON: 11-PIN	SMALL SIGNAL BOARD
BRACKET	259166		BRACKET, CONV SENS: 6-OCLOCK	INSTRUMENT ASSEMBLY
BRACKET	259203		SCREEN BRACKET, BOTTOM	INSTRUMENT ASSEMBLY
BRACKET	242739		BRACKET, HV SPLITTER	OPTICS ASSEMBLY
BRACKET	242738		BRACKET, FOCUS/SCREEN	OPTICS ASSEMBLY
BRACKET	259504		BRACKET, LED SUPPORT	FRONT PANEL 1
BRACKET	258904		BRACKET, SCREEN MOUNTING	INSTRUMENT ASSEMBLY
BRACKET	253469		BRACKET, LATCH MOUNTING	INSTRUMENT ASSEMBLY
BRACKET	258903		BRACKET FOR CONV SENSORS	INSTRUMENT ASSEMBLY
BRACKET	259204		SCREEN BRACKET, TOP	INSTRUMENT ASSEMBLY
BS02	248643		CONNECTOR, 2-PIN	CONVERGENCE SIGNAL BOAR
BT010	259983		CONNECTOR, 11-PIN	DIGITAL READY INTERFACE
BT100	259903		JACK, PHONO: 2-HIGH 3-WIDE	DIGITAL READY INTERFACE
BT110	259633		CONNECTOR, RIBBON: 11-PIN	DIGITAL READY INTERFACE
BT150	219160		CONNECTOR 5 PIN	DIGITAL READY INTERFACE
BT221	211596		CONNECTOR 10 PIN	MPEG CBA
BT222	232321		CONNECTOR, 4-PIN	MPEG CBA
BT400	259489		CONNECTOR, RIBBON: 21-PIN	DIGITAL READY INTERFACE
BT501	219160		CONNECTOR 5 PIN	DIGITAL READY INTERFACE
BT600	259952		DVI-HDTV JACK	DIGITAL READY INTERFACE
BT810	258983		CABLE, 10-CONDUCTOR 200MM	A/V INTERFACE
BT811	260031		CONNECTOR, 10-PIN	A/V INTERFACE
BT900	258985		CONNECTOR, 6-PIN	DIGITAL READY INTERFACE
BT940	259906		JACK, PHONO: 2-HIGH 3-WIDE	DIGITAL READY INTERFACE
BT960	258978		CONNECTOR, 4-PIN	DIGITAL READY INTERFACE
BT980	215542		CONNECTOR	DIGITAL READY INTERFACE
BT982	226525		CONNECTOR 2 PIN	DIGITAL READY INTERFACE
BT983	227394		CONNECTOR 2 PIN	DIGITAL READY INTERFACE
BT985	259500		CONNECTOR, EXTERNAL SPEAKER	DIGITAL READY INTERFACE
BU702	256830		CONNECTOR, RIBBON: 19-PIN	MPEG CBA
BU702A	258943		CABLE, RIBBON: 19-COND 145MM	DVD CABLING & SUPPORT A
BUTTON	258800		BUTTON CLUSTER, DVD	INSTRUMENT ASSEMBLY
BUTTON	258671		BUTTON CLUSTER	INSTRUMENT ASSEMBLY
BV001	259631		CONNECTOR, RIBBON: 21-PIN	SMALL SIGNAL BOARD
BV01	232319		CONNECTOR 9 PIN	CONVERGENCE PS / ADAPTE
BV010	259633		CONNECTOR, RIBBON: 11-PIN	SMALL SIGNAL BOARD
BV02	259958		CONNECTOR, 9-PIN	CONVERGENCE PS / ADAPTE
BV03	259858		CONNECTOR, 9-PIN	CONVERGENCE PS / ADAPTE
BV04	259488		CONNECTOR, 9-PIN	CONVERGENCE PS / ADAPTE
BV05	220145		CONNECTOR	CONVERGENCE PS / ADAPTE
BV06	227937		CONNECTOR	CONVERGENCE PS / ADAPTE
BV07	228338		CONNECTOR	CONVERGENCE PS / ADAPTE
BV08	259487		CONNECTOR, 7-PIN	CONVERGENCE PS / ADAPTE
BV11	218375		CONNECTOR 7 PIN	CONVERGENCE PS / ADAPTE
BV12	258685		CONNECTOR, 9-PIN	CONVERGENCE PS / ADAPTE
BV15	239202		CONNECTOR 5 PIN	CONVERGENCE PS / ADAPTE
BV16	239202		CONNECTOR 5 PIN	CONVERGENCE PS / ADAPTE
BV17	239202		CONNECTOR 5 PIN	CONVERGENCE PS / ADAPTE
BV300	220145		CONNECTOR	SMALL SIGNAL BOARD
BV810	258984		CABLE, 8-CONDUCTOR 65MM	A/V INTERFACE
BV811	258985		CONNECTOR, 6-PIN	A/V INTERFACE
BW04	220343		CONNECTOR 8 PIN	CONVERGENCE AMP BOARD
BW05	259972		CONNECTOR, 12-PIN	CONVERGENCE AMP BOARD
BW101	256928		CONNECTOR, 14-PIN	MPEG CBA

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
BW16	218375		CONNECTOR 7 PIN	CONVERGENCE AMP BOARD
BX100	259879		JACK, DUAL S-VIDEO	SMALL SIGNAL BOARD
BX200	259904		JACK, PHONO: 2-HIGH 3-WIDE	SMALL SIGNAL BOARD
BX300	211596		CONNECTOR 10 PIN	SMALL SIGNAL BOARD
BX400	259631		CONNECTOR, RIBBON: 21-PIN	SMALL SIGNAL BOARD
BX600	259902		JACK, PHONO: 2-HIGH 3-WIDE	SMALL SIGNAL BOARD
BX801	259966		CONNECTOR, 6-PIN	SMALL SIGNAL BOARD
BX802	259966		CONNECTOR, 6-PIN	SUB - DVD
BX803	259966		CONNECTOR, 6-PIN	SUB - DVD
BX900	248806		CONNECTOR 4 PIN	SMALL SIGNAL BOARD
BY218	256935		CONNECTOR, 8-PIN	MPEG CBA
C12101	224270		CAP LYTC 3.3UF M 50V	AUDIO CROSSOVER
CA001	259491		CAPCC .22UF 10% 50V X7R	SMALL SIGNAL BOARD
CA004	243372		CAPCC +/-5% 50V 100PF	SMALL SIGNAL BOARD
CA005	259569		CAPCC 3.3PF 10% 50V N750	SMALL SIGNAL BOARD
CA006	259569		CAPCC 3.3PF 10% 50V N750	SMALL SIGNAL BOARD
CA007	256817		CAPCC 47PF J NPO 50V	SMALL SIGNAL BOARD
CA008	243372		CAPCC +/-5% 50V 100PF	SMALL SIGNAL BOARD
CA009	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CA011	259362		CAP CD 220PF 10% 50V	SMALL SIGNAL BOARD
CA012	259362		CAP CD 220PF 10% 50V	SMALL SIGNAL BOARD
CA013	249036		CAPCC 220PF J NPO 50V	SMALL SIGNAL BOARD
CA014	249036		CAPCC 220PF J NPO 50V	SMALL SIGNAL BOARD
CA015	259561		CAP LYTC SMD 1UF 20% 50V 85C	SMALL SIGNAL BOARD
CA016	259561		CAP LYTC SMD 1UF 20% 50V 85C	SMALL SIGNAL BOARD
CA017	256817		CAPCC 47PF J NPO 50V	SMALL SIGNAL BOARD
CA018	256817		CAPCC 47PF J NPO 50V	SMALL SIGNAL BOARD
CA02	253796		CAPCC .1UF 10% 16V	CONVERGENCE AMP BOARD
CA021	259362		CAP CD 220PF 10% 50V	SMALL SIGNAL BOARD
CA022	259362		CAP CD 220PF 10% 50V	SMALL SIGNAL BOARD
CA023	249036		CAPCC 220PF J NPO 50V	SMALL SIGNAL BOARD
CA024	249036		CAPCC 220PF J NPO 50V	SMALL SIGNAL BOARD
CA025	259561		CAP LYTC SMD 1UF 20% 50V 85C	SMALL SIGNAL BOARD
CA026	259561		CAP LYTC SMD 1UF 20% 50V 85C	SMALL SIGNAL BOARD
CA027	256817		CAPCC 47PF J NPO 50V	SMALL SIGNAL BOARD
CA028	256817		CAPCC 47PF J NPO 50V	SMALL SIGNAL BOARD
CA03	253796		CAPCC .1UF 10% 16V	CONVERGENCE AMP BOARD
CA033	249036		CAPCC 220PF J NPO 50V	SMALL SIGNAL BOARD
CA034	249036		CAPCC 220PF J NPO 50V	SMALL SIGNAL BOARD
CA035	259561		CAP LYTC SMD 1UF 20% 50V 85C	SMALL SIGNAL BOARD
CA036	259561		CAP LYTC SMD 1UF 20% 50V 85C	SMALL SIGNAL BOARD
CA037	256817		CAPCC 47PF J NPO 50V	SMALL SIGNAL BOARD
CA038	256817		CAPCC 47PF J NPO 50V	SMALL SIGNAL BOARD
CA04	230980		CAP LYTC 47UF M 63V	CONVERGENCE AMP BOARD
CA043	249036		CAPCC 220PF J NPO 50V	SMALL SIGNAL BOARD
CA044	249036		CAPCC 220PF J NPO 50V	SMALL SIGNAL BOARD
CA045	259561		CAP LYTC SMD 1UF 20% 50V 85C	SMALL SIGNAL BOARD
CA046	259561		CAP LYTC SMD 1UF 20% 50V 85C	SMALL SIGNAL BOARD
CA047	256822		CAPCC 180PF 50V NPO	SMALL SIGNAL BOARD
CA048	256822		CAPCC 180PF 50V NPO	SMALL SIGNAL BOARD
CA05	247002		CAPCC .001UF 20% 50V X7R	CONVERGENCE AMP BOARD
CA050	259491		CAPCC .22UF 10% 50V X7R	SMALL SIGNAL BOARD
CA051	257823		CAP LYTC 470UF 20% 10V 85C	SMALL SIGNAL BOARD
CA052	247002		CAPCC 1000PF K X7R 50V	SMALL SIGNAL BOARD
CA053	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CA054	259628		CAP LYTC (SMD) 100UF 16V 85C	SMALL SIGNAL BOARD
CA056	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CA058	247002		CAPCC 1000PF K X7R 50V	SMALL SIGNAL BOARD
CA06	256814		CAPCC 22PF +5% -5% 50V NPO	CONVERGENCE AMP BOARD
CA061	253714		CAPCC 470PF 5% 50V	SMALL SIGNAL BOARD
CA062	253714		CAPCC 470PF 5% 50V	SMALL SIGNAL BOARD
CA063	259626		CAP LYTC (SMD) 22UF 16V 85C	SMALL SIGNAL BOARD
CA064	259626		CAP LYTC (SMD) 22UF 16V 85C	SMALL SIGNAL BOARD
CA065	253714		CAPCC 470PF 5% 50V	SMALL SIGNAL BOARD
CA066	253714		CAPCC 470PF 5% 50V	SMALL SIGNAL BOARD
CA067	198559		CAPCD .001UF K Y5S 50V	SMALL SIGNAL BOARD

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
CA068	198559		CAPCD .001UF K Y5S 50V	SMALL SIGNAL BOARD
CA07	253796		CAPCC .1UF 10% 16V	CONVERGENCE AMP BOARD
CA08	253796		CAPCC .1UF 10% 16V	CONVERGENCE AMP BOARD
CA082	258697		CAP LYTC-SMD 10UF 20% 16V 85C	SMALL SIGNAL BOARD
CA083	258697		CAP LYTC-SMD 10UF 20% 16V 85C	SMALL SIGNAL BOARD
CA084	258697		CAP LYTC-SMD 10UF 20% 16V 85C	SMALL SIGNAL BOARD
CA085	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CA09	256818		CAPCC 100PF 50V NPO	CONVERGENCE AMP BOARD
CA090	256817		CAPCC 47PF J NPO 50V	SMALL SIGNAL BOARD
CA092	256817		CAPCC 47PF J NPO 50V	SMALL SIGNAL BOARD
CA10	256818		CAPCC 100PF 50V NPO	CONVERGENCE AMP BOARD
CA100	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CA101	259629		CAP LYTC (SMD) 4.7UF 25V 85C	SMALL SIGNAL BOARD
CA102	258697		CAP LYTC-SMD 10UF 20% 16V 85C	SMALL SIGNAL BOARD
CA103	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CA11	256818		CAPCC 100PF 50V NPO	CONVERGENCE AMP BOARD
CA110	247002		CAPCC 1000PF K X7R 50V	SMALL SIGNAL BOARD
CA111	247002		CAPCC 1000PF K X7R 50V	SMALL SIGNAL BOARD
CA112	259629		CAP LYTC (SMD) 4.7UF 25V 85C	SMALL SIGNAL BOARD
CA113	259629		CAP LYTC (SMD) 4.7UF 25V 85C	SMALL SIGNAL BOARD
CA114	256821		CAPCC 330PF +/-5% 50V	SMALL SIGNAL BOARD
CA115	256821		CAPCC 330PF +/-5% 50V	SMALL SIGNAL BOARD
CA116	259626		CAP LYTC (SMD) 22UF 16V 85C	SMALL SIGNAL BOARD
CA117	259626		CAP LYTC (SMD) 22UF 16V 85C	SMALL SIGNAL BOARD
CA118	259645		CAP POLY .1UF 5% 63V	SMALL SIGNAL BOARD
CA119	259645		CAP POLY .1UF 5% 63V	SMALL SIGNAL BOARD
CA120	244141		CAPCC 3.3NF 10% 50V	SMALL SIGNAL BOARD
CA121	244141		CAPCC 3.3NF 10% 50V	SMALL SIGNAL BOARD
CA122	215555		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CA123	247002		CAPCC 1000PF K X7R 50V	SMALL SIGNAL BOARD
CA124	178836		CAP LYTC 470UF M 25V	SMALL SIGNAL BOARD
CA125	190552		CAPCC .1UF K X7R 50V	SMALL SIGNAL BOARD
CA127	178836		CAP LYTC 470UF M 25V	SMALL SIGNAL BOARD
CA128	190552		CAPCC .1UF K X7R 50V	SMALL SIGNAL BOARD
CA130	259491		CAPCC .22UF 10% 50V X7R	SMALL SIGNAL BOARD
CA131	215555		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CA132	247002		CAPCC 1000PF K X7R 50V	SMALL SIGNAL BOARD
CA15	243464		CAPCC 15PF 5% 50V	CONVERGENCE AMP BOARD
CA157	198559		CAPCD .001UF K Y5S 50V	SMALL SIGNAL BOARD
CA159	259629		CAP LYTC (SMD) 4.7UF 25V 85C	SMALL SIGNAL BOARD
CA16	243464		CAPCC 15PF 5% 50V	CONVERGENCE AMP BOARD
CA160	247002		CAPCC 1000PF K X7R 50V	SMALL SIGNAL BOARD
CA161	247002		CAPCC 1000PF K X7R 50V	SMALL SIGNAL BOARD
CA162	259629		CAP LYTC (SMD) 4.7UF 25V 85C	SMALL SIGNAL BOARD
CA163	259629		CAP LYTC (SMD) 4.7UF 25V 85C	SMALL SIGNAL BOARD
CA164	259629		CAP LYTC (SMD) 4.7UF 25V 85C	SMALL SIGNAL BOARD
CA165	259629		CAP LYTC (SMD) 4.7UF 25V 85C	SMALL SIGNAL BOARD
CA166	198559		CAPCD .001UF K Y5S 50V	SMALL SIGNAL BOARD
CA167	198559		CAPCD .001UF K Y5S 50V	SMALL SIGNAL BOARD
CA173	259491		CAPCC .22UF 10% 50V X7R	SMALL SIGNAL BOARD
CA174	259491		CAPCC .22UF 10% 50V X7R	SMALL SIGNAL BOARD
CA175	178836		CAP LYTC 470UF M 25V	SMALL SIGNAL BOARD
CA176	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CA177	178836		CAP LYTC 470UF M 25V	SMALL SIGNAL BOARD
CA178	178836		CAP LYTC 470UF M 25V	SMALL SIGNAL BOARD
CA179	243358		CAPCC 5PF +/- .5PF 50V	MPEG CBA
CA179	258697		CAP LYTC-SMD 10UF 20% 16V 85C	SMALL SIGNAL BOARD
CA180	243358		CAPCC 5PF +/- .5PF 50V	MPEG CBA
CA180	259629		CAP LYTC (SMD) 4.7UF 25V 85C	SMALL SIGNAL BOARD
CA181	243358		CAPCC 5PF +/- .5PF 50V	MPEG CBA
CA181	259629		CAP LYTC (SMD) 4.7UF 25V 85C	SMALL SIGNAL BOARD
CA182	259629		CAP LYTC (SMD) 4.7UF 25V 85C	SMALL SIGNAL BOARD
CA183	259629		CAP LYTC (SMD) 4.7UF 25V 85C	SMALL SIGNAL BOARD
CA184	259629		CAP LYTC (SMD) 4.7UF 25V 85C	SMALL SIGNAL BOARD
CA185	247002		CAPCC 1000PF K X7R 50V	SMALL SIGNAL BOARD
CA186	247002		CAPCC 1000PF K X7R 50V	SMALL SIGNAL BOARD

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
CA190	247002		CAPCC 1000PF K X7R 50V	SMALL SIGNAL BOARD
CA191	259629		CAP LYTC (SMD) 4.7UF 25V 85C	SMALL SIGNAL BOARD
CA194	243358		CAPCC 5PF +/- .5PF 50V	MPEG CBA
CA200	259628		CAP LYTC (SMD) 100UF 16V 85C	SMALL SIGNAL BOARD
CA201	259628		CAP LYTC (SMD) 100UF 16V 85C	SMALL SIGNAL BOARD
CA202	259254		CAP LYTC 100UF 20% 50V 85C	SMALL SIGNAL BOARD
CA203	258696		CAP LYTC 22UF 20% 63V 85C	SMALL SIGNAL BOARD
CA445	256775		CAPCC .01UF K X7R 50V	MPEG CBA
CA446	243359		CAPCC .1UF Z Y5V 16V	MPEG CBA
CA447	189981		CAP LYTC 10UF M 16V	MPEG CBA
CA448	230978		CAP LYTC 100UF M 16V	MPEG CBA
CA449	243359		CAPCC .1UF Z Y5V 16V	MPEG CBA
CA450	243359		CAPCC .1UF Z Y5V 16V	MPEG CBA
CA501	243359		CAPCC .1UF Z Y5V 16V	MPEG CBA
CA502	230978		CAP LYTC 100UF M 16V	MPEG CBA
CA503	243359		CAPCC .1UF Z Y5V 16V	MPEG CBA
CA504	189981		CAP LYTC 10UF M 16V	MPEG CBA
CA506	259994		CAPCC .001UF 5% 25V NPO	MPEG CBA
CA507	253714		CAPCC 470PF 5% 50V	MPEG CBA
CA508	259979		CAPCC 240PF 5% 50V NPO	MPEG CBA
CA509	256815		CAPCC 10PF 50V NPO	MPEG CBA
CA51	247002		CAPCC .001UF 20% 50V X7R	CONVERGENCE AMP BOARD
CA512	256821		CAPCC 330PF +/-5% 50V	MPEG CBA
CA513	259979		CAPCC 240PF 5% 50V NPO	MPEG CBA
CA514	189981		CAP LYTC 10UF M 16V	MPEG CBA
CA524	189981		CAP LYTC 10UF M 16V	MPEG CBA
CA526	259994		CAPCC .001UF 5% 25V NPO	MPEG CBA
CA527	253714		CAPCC 470PF 5% 50V	MPEG CBA
CA528	259979		CAPCC 240PF 5% 50V NPO	MPEG CBA
CA529	256815		CAPCC 10PF 50V NPO	MPEG CBA
CA532	256821		CAPCC 330PF +/-5% 50V	MPEG CBA
CA533	259979		CAPCC 240PF 5% 50V NPO	MPEG CBA
CA534	189981		CAP LYTC 10UF M 16V	MPEG CBA
CA54	175820		CAP LYTC 220UF M 25V	CONVERGENCE AMP BOARD
CA542	230978		CAP LYTC 100UF M 16V	MPEG CBA
CA545	243359		CAPCC .1UF Z Y5V 16V	MPEG CBA
CA55	175820		CAP LYTC 220UF M 25V	CONVERGENCE AMP BOARD
CA56	253796		CAPCC .1UF 10% 16V	CONVERGENCE AMP BOARD
CA59	256814		CAPCC 22PF +5% -5% 50V NPO	CONVERGENCE AMP BOARD
CA60	256818		CAPCC 100PF 50V NPO	CONVERGENCE AMP BOARD
CA61	243464		CAPCC 15PF 5% 50V	CONVERGENCE AMP BOARD
CA62	256818		CAPCC 100PF 50V NPO	CONVERGENCE AMP BOARD
CA66	256818		CAPCC 100PF 50V NPO	CONVERGENCE AMP BOARD
CA67	253796		CAPCC .1UF 10% 16V	CONVERGENCE AMP BOARD
CA68	243464		CAPCC 15PF 5% 50V	CONVERGENCE AMP BOARD
CABINET	258807		CABINET, UPPER	INSTRUMENT ASSEMBLY
CABINET	258783		CABINET, LOWER	INSTRUMENT ASSEMBLY
CABLE	258921		CABLE, AUDIO CROSSOVER	INSTRUMENT ASSEMBLY
CABLE	258945		CABLE, 8-CONDUCTOR/BK010-BK009	CHASSIS ASSEMBLY
CABLE	258944		CABLE, 8-CONDUCTOR 750MM	DVD CABLING & SUPPORT A
CABLE	258942		CABLE, 2-CONDUCTOR 120MM	DVD CABLING & SUPPORT A
CABLE	258951		CABLE, 14-CONDUCTOR 930MM	DVD CABLING & SUPPORT A
CABLE	258987		CABLE, 6-CONDUCTOR 900MM	A/V INTERFACE
CABLE	258986		CABLE, 4-CONDUCTOR 900MM	A/V INTERFACE
CASTER	261329		CASTER	INSTRUMENT ASSEMBLY
CB02	253796		CAPCC .1UF 10% 16V	CONVERGENCE AMP BOARD
CB03	253796		CAPCC .1UF 10% 16V	CONVERGENCE AMP BOARD
CB05	247002		CAPCC .001UF 20% 50V X7R	CONVERGENCE AMP BOARD
CB06	256814		CAPCC 22PF +5% -5% 50V NPO	CONVERGENCE AMP BOARD
CB07	253796		CAPCC .1UF 10% 16V	CONVERGENCE AMP BOARD
CB08	253796		CAPCC .1UF 10% 16V	CONVERGENCE AMP BOARD
CB09	256818		CAPCC 100PF 50V NPO	CONVERGENCE AMP BOARD
CB10	256818		CAPCC 100PF 50V NPO	CONVERGENCE AMP BOARD
CB109	256815		CAPCC 10PF 50V NPO	KINE DRIVER RED W/SVM
CB11	256818		CAPCC 100PF 50V NPO	CONVERGENCE AMP BOARD
CB110	258742		CAPCC 6.8PF 50V NPO	KINE DRIVER RED W/SVM

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
CB121	193043		CAP LYTC 47UF 25V	KINE DRIVER RED W/SVM
CB122	259590		CAPCC .022UF 10% 25V X7R	KINE DRIVER RED W/SVM
CB123	259360		CAP LYTC 4.7UF 20% 350V 85C	KINE DRIVER RED W/SVM
CB124	259381		CAP POLY .01UF 10% 400V	KINE DRIVER RED W/SVM
CB125	193043		CAP LYTC 47UF 25V	KINE DRIVER RED W/SVM
CB126	259590		CAPCC .022UF 10% 25V X7R	KINE DRIVER RED W/SVM
CB134	253798		CAPCC 12PF 5% 50V	KINE DRIVER RED W/SVM
CB140	253714		CAPCC 470PF 5% 50V	KINE DRIVER RED W/SVM
CB141	193043		CAP LYTC 47UF 25V	KINE DRIVER RED W/SVM
CB142	253796		CAPCC .1UF 10% 16V	KINE DRIVER RED W/SVM
CB144	243391		CAPCC 150PF 5% 50V	KINE DRIVER RED W/SVM
CB15	243464		CAPCC 15PF 5% 50V	CONVERGENCE AMP BOARD
CB151	256775		CAPCC .01UF K X7R 50V	KINE DRIVER RED W/SVM
CB152	256813		CAPCC 3.3PF 50V NPO	KINE DRIVER RED W/SVM
CB156	259590		CAPCC .022UF 10% 25V X7R	KINE DRIVER RED W/SVM
CB16	243464		CAPCC 15PF 5% 50V	CONVERGENCE AMP BOARD
CB161	247002		CAPCC .001UF 20% 50V X7R	KINE DRIVER RED W/SVM
CB162	193043		CAP LYTC 47UF 25V	KINE DRIVER RED W/SVM
CB166	259360		CAP LYTC 4.7UF 20% 350V 85C	KINE DRIVER RED W/SVM
CB167	244853		CAPCD 470PF K Y5R 3KV	KINE DRIVER RED W/SVM
CB171	198806		CAPCD .001UF FS Y5U 2KV	KINE DRIVER RED W/SVM
CB209	256815		CAPCC 10PF 50V NPO	KINE DRIVER GREEN W/SVM
CB210	258742		CAPCC 6.8PF 50V NPO	KINE DRIVER GREEN W/SVM
CB221	193043		CAP LYTC 47UF 25V	KINE DRIVER GREEN W/SVM
CB222	259590		CAPCC .022UF 10% 25V X7R	KINE DRIVER GREEN W/SVM
CB223	259360		CAP LYTC 4.7UF 20% 350V 85C	KINE DRIVER GREEN W/SVM
CB224	259381		CAP POLY .01UF 10% 400V	KINE DRIVER GREEN W/SVM
CB225	193043		CAP LYTC 47UF 25V	KINE DRIVER GREEN W/SVM
CB226	259590		CAPCC .022UF 10% 25V X7R	KINE DRIVER GREEN W/SVM
CB234	243464		CAPCC 15PF 5% 50V	KINE DRIVER GREEN W/SVM
CB239	193043		CAP LYTC 47UF 25V	KINE DRIVER GREEN W/SVM
CB240	247002		CAPCC .001UF 20% 50V X7R	KINE DRIVER GREEN W/SVM
CB241	193043		CAP LYTC 47UF 25V	KINE DRIVER GREEN W/SVM
CB242	253796		CAPCC .1UF 10% 16V	KINE DRIVER GREEN W/SVM
CB244	243391		CAPCC 150PF 5% 50V	KINE DRIVER GREEN W/SVM
CB251	256775		CAPCC .01UF K X7R 50V	KINE DRIVER GREEN W/SVM
CB252	256813		CAPCC 3.3PF 50V NPO	KINE DRIVER GREEN W/SVM
CB256	259590		CAPCC .022UF 10% 25V X7R	KINE DRIVER GREEN W/SVM
CB261	247002		CAPCC .001UF 20% 50V X7R	KINE DRIVER GREEN W/SVM
CB262	193043		CAP LYTC 47UF 25V	KINE DRIVER GREEN W/SVM
CB266	259360		CAP LYTC 4.7UF 20% 350V 85C	KINE DRIVER GREEN W/SVM
CB267	244853		CAPCD 470PF K Y5R 3KV	KINE DRIVER GREEN W/SVM
CB271	198806		CAPCD .001UF FS Y5U 2KV	KINE DRIVER GREEN W/SVM
CB309	256815		CAPCC 10PF 50V NPO	KINE DRIVER BLUE W/SVM
CB310	258742		CAPCC 6.8PF 50V NPO	KINE DRIVER BLUE W/SVM
CB321	193043		CAP LYTC 47UF 25V	KINE DRIVER BLUE W/SVM
CB322	259590		CAPCC .022UF 10% 25V X7R	KINE DRIVER BLUE W/SVM
CB323	259360		CAP LYTC 4.7UF 20% 350V 85C	KINE DRIVER BLUE W/SVM
CB324	259381		CAP POLY .01UF 10% 400V	KINE DRIVER BLUE W/SVM
CB325	193043		CAP LYTC 47UF 25V	KINE DRIVER BLUE W/SVM
CB326	259590		CAPCC .022UF 10% 25V X7R	KINE DRIVER BLUE W/SVM
CB334	256816		CAPCC 33PF 50V NPO	KINE DRIVER BLUE W/SVM
CB339	193043		CAP LYTC 47UF 25V	KINE DRIVER BLUE W/SVM
CB340	253714		CAPCC 470PF 5% 50V	KINE DRIVER BLUE W/SVM
CB341	193043		CAP LYTC 47UF 25V	KINE DRIVER BLUE W/SVM
CB342	253796		CAPCC .1UF 10% 16V	KINE DRIVER BLUE W/SVM
CB344	243391		CAPCC 150PF 5% 50V	KINE DRIVER BLUE W/SVM
CB351	256775		CAPCC .01UF K X7R 50V	KINE DRIVER BLUE W/SVM
CB352	256813		CAPCC 3.3PF 50V NPO	KINE DRIVER BLUE W/SVM
CB356	259590		CAPCC .022UF 10% 25V X7R	KINE DRIVER BLUE W/SVM
CB361	247002		CAPCC .001UF 20% 50V X7R	KINE DRIVER BLUE W/SVM
CB362	193043		CAP LYTC 47UF 25V	KINE DRIVER BLUE W/SVM
CB366	259360		CAP LYTC 4.7UF 20% 350V 85C	KINE DRIVER BLUE W/SVM
CB367	244853		CAPCD 470PF K Y5R 3KV	KINE DRIVER BLUE W/SVM
CB371	198806		CAPCD .001UF FS Y5U 2KV	KINE DRIVER BLUE W/SVM
CB50	230980		CAP LYTC 47UF M 63V	CONVERGENCE AMP BOARD

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
CB51	247002		CAPCC .001UF 20% 50V X7R	CONVERGENCE AMP BOARD
CB53	230980		CAP LYTC 47UF M 63V	CONVERGENCE AMP BOARD
CB54	175820		CAP LYTC 220UF M 25V	CONVERGENCE AMP BOARD
CB55	175820		CAP LYTC 220UF M 25V	CONVERGENCE AMP BOARD
CB56	253796		CAPCC .1UF 10% 16V	CONVERGENCE AMP BOARD
CB59	256814		CAPCC 22PF +5% -5% 50V NPO	CONVERGENCE AMP BOARD
CB60	256818		CAPCC 100PF 50V NPO	CONVERGENCE AMP BOARD
CB61	243464		CAPCC 15PF 5% 50V	CONVERGENCE AMP BOARD
CB62	256818		CAPCC 100PF 50V NPO	CONVERGENCE AMP BOARD
CB66	256818		CAPCC 100PF 50V NPO	CONVERGENCE AMP BOARD
CB67	253796		CAPCC .1UF 10% 16V	CONVERGENCE AMP BOARD
CB68	243464		CAPCC 15PF 5% 50V	CONVERGENCE AMP BOARD
CC530	243462		CAPCC 4.7PF +.25 -.25	SMALL SIGNAL BOARD
CC533	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CC534	259629		CAP LYTC (SMD) 4.7UF 25V 85C	SMALL SIGNAL BOARD
CC535	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CC536	253798		CAPCC 12PF 5% 50V	SMALL SIGNAL BOARD
CC551	244141		CAPCC 3.3NF 10% 50V	SMALL SIGNAL BOARD
CC552	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CC558	244141		CAPCC 3.3NF 10% 50V	SMALL SIGNAL BOARD
CC578	259561		CAP LYTC SMD 1UF 20% 50V 85C	SMALL SIGNAL BOARD
CC728	259590		CAPCC .022UF 10% 25V X7R	SMALL SIGNAL BOARD
CC730	243462		CAPCC 4.7PF +.25 -.25	SMALL SIGNAL BOARD
CC733	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CC734	259629		CAP LYTC (SMD) 4.7UF 25V 85C	SMALL SIGNAL BOARD
CC735	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CC736	253798		CAPCC 12PF 5% 50V	SMALL SIGNAL BOARD
CC751	244141		CAPCC 3.3NF 10% 50V	SMALL SIGNAL BOARD
CC752	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CC758	244141		CAPCC 3.3NF 10% 50V	SMALL SIGNAL BOARD
CC778	259561		CAP LYTC SMD 1UF 20% 50V 85C	SMALL SIGNAL BOARD
CC922	259590		CAPCC .022UF 10% 25V X7R	SMALL SIGNAL BOARD
CC950	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CC962	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CD100	189981		CAP LYTC 10UF M 16V	MPEG CBA
CD101	243359		CAPCC .1UF Z Y5V 16V	MPEG CBA
CD102	256775		CAPCC .01UF K X7R 50V	MPEG CBA
CD103	214015		CAP POLY 1UF J 63V	MPEG CBA
CD104	243359		CAPCC .1UF Z Y5V 16V	MPEG CBA
CD105	230978		CAP LYTC 100UF M 16V	MPEG CBA
CD902	230978		CAP LYTC 100UF M 16V	SPDIF OUTPUT
CE217	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CE218	243359		CAPCC .1UF Z Y5V 16V	MPEG CBA
CE219	230978		CAP LYTC 100UF M 16V	MPEG CBA
CE220	256816		CAPCC 33PF +/-5% 50V	MPEG CBA
CE223	256816		CAPCC 33PF +/-5% 50V	MPEG CBA
CE254	243358		CAPCC 5PF +/- .5PF 50V	MPEG CBA
CF003	241076		CAP POLY 4700PF K 100V	P-S/DEFLECTION
CF011	258720		CAP POLY .56UF 10% 63V	P-S/DEFLECTION
CF020	227248		CAP POLY .022UF K 100V	P-S/DEFLECTION
CF027	259353		CAP POLY .022UF 20% 63V	P-S/DEFLECTION
CF031	259354		CAP POLY .22UF 20% 63V	P-S/DEFLECTION
CF032	259354		CAP POLY .22UF 20% 63V	P-S/DEFLECTION
CG01	230980		CAP LYTC 47UF M 63V	CONVERGENCE AMP BOARD
CG02	253796		CAPCC .1UF 10% 16V	CONVERGENCE AMP BOARD
CG03	253796		CAPCC .1UF 10% 16V	CONVERGENCE AMP BOARD
CG05	247002		CAPCC .001UF 20% 50V X7R	CONVERGENCE AMP BOARD
CG06	157199		CAPCD 22PF J NP0 50V	CONVERGENCE AMP BOARD
CG07	253796		CAPCC .1UF 10% 16V	CONVERGENCE AMP BOARD
CG08	253796		CAPCC .1UF 10% 16V	CONVERGENCE AMP BOARD
CG09	256818		CAPCC 100PF 50V NPO	CONVERGENCE AMP BOARD
CG10	256818		CAPCC 100PF 50V NPO	CONVERGENCE AMP BOARD
CG101	243400		CAP LYTC 100UF 50V 105C	KINE DRIVER RED W/SVM
CG102	259590		CAPCC .022UF 10% 25V X7R	KINE DRIVER RED W/SVM
CG103	253796		CAPCC .1UF 10% 16V	KINE DRIVER RED W/SVM
CG104	253796		CAPCC .1UF 10% 16V	KINE DRIVER RED W/SVM

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
CG105	247002		CAPCC .001UF 20% 50V X7R	KINE DRIVER RED W/SVM
CG106	256775		CAPCC .01UF K X7R 50V	KINE DRIVER RED W/SVM
CG107	258718		CAP POLY .022UF 20% 250V	KINE DRIVER RED W/SVM
CG108	256783		RES CMF 0 OHM 0% 1/16W	KINE DRIVER RED W/SVM
CG109	258718		CAP POLY .022UF 20% 250V	KINE DRIVER RED W/SVM
CG11	256818		CAPCC 100PF 50V NPO	CONVERGENCE AMP BOARD
CG110	235816		CAP LYTC 22UF M 250V	KINE DRIVER RED W/SVM
CG112	258718		CAP POLY .022UF 20% 250V	KINE DRIVER RED W/SVM
CG114	247002		CAPCC .001UF 20% 50V X7R	KINE DRIVER RED W/SVM
CG131	259384		CAP POLY 1UF 5% 50V	KINE DRIVER RED W/SVM
CG132	243359		CAPCC .1UF Z Y5V 16V	MPEG CBA
CG141	193043		CAP LYTC 47UF 25V	KINE DRIVER RED W/SVM
CG148	157314		CAPCD 47PF K NP0 250V	KINE DRIVER RED W/SVM
CG149	194253		CAP LYTC 22UF M 16V	MPEG CBA
CG15	243464		CAPCC 15PF 5% 50V	CONVERGENCE AMP BOARD
CG154	243464		CAPCC 15PF 5% 50V	KINE DRIVER RED W/SVM
CG16	243464		CAPCC 15PF 5% 50V	CONVERGENCE AMP BOARD
CG160	230978		CAP LYTC 100UF M 16V	MPEG CBA
CG161	230978		CAP LYTC 100UF M 16V	MPEG CBA
CG162	230978		CAP LYTC 100UF M 16V	MPEG CBA
CG163	230978		CAP LYTC 100UF M 16V	MPEG CBA
CG165	243359		CAPCC .1UF Z Y5V 16V	MPEG CBA
CG182	243275		CAP LYTC 470UF M 10V	MPEG CBA
CG183	242829		CAP TANT, M,6.3V, 10UOF	MPEG CBA
CG186	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CG187	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CG189	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CG190	256775		CAPCC .01UF K X7R 50V	MPEG CBA
CG191	256775		CAPCC .01UF K X7R 50V	MPEG CBA
CG192	256775		CAPCC .01UF K X7R 50V	MPEG CBA
CG195	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CG196	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CG197	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CG200	230978		CAP LYTC 100UF M 16V	MPEG CBA
CG201	230978		CAP LYTC 100UF M 16V	MPEG CBA
CG201	243400		CAP LYTC 100UF 50V 105C	KINE DRIVER GREEN W/SVM
CG202	259590		CAPCC .022UF 10% 25V X7R	KINE DRIVER GREEN W/SVM
CG203	253796		CAPCC .1UF 10% 16V	KINE DRIVER GREEN W/SVM
CG204	253796		CAPCC .1UF 10% 16V	KINE DRIVER GREEN W/SVM
CG205	247002		CAPCC .001UF 20% 50V X7R	KINE DRIVER GREEN W/SVM
CG205	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CG206	256775		CAPCC .01UF K X7R 50V	KINE DRIVER GREEN W/SVM
CG206	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CG207	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CG207	258718		CAP POLY .022UF 20% 250V	KINE DRIVER GREEN W/SVM
CG208	256783		RES CMF 0 OHM 0% 1/16W	KINE DRIVER GREEN W/SVM
CG209	258718		CAP POLY .022UF 20% 250V	KINE DRIVER GREEN W/SVM
CG210	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CG210	235816		CAP LYTC 22UF M 250V	KINE DRIVER GREEN W/SVM
CG211	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CG212	258718		CAP POLY .022UF 20% 250V	KINE DRIVER GREEN W/SVM
CG212	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CG213	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CG214	247002		CAPCC .001UF 20% 50V X7R	KINE DRIVER GREEN W/SVM
CG215	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CG216	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CG217	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CG218	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CG219	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CG220	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CG221	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CG222	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CG231	259384		CAP POLY 1UF 5% 50V	KINE DRIVER GREEN W/SVM
CG241	193043		CAP LYTC 47UF 25V	KINE DRIVER GREEN W/SVM
CG248	157314		CAPCD 47PF K NP0 250V	KINE DRIVER GREEN W/SVM
CG254	243464		CAPCC 15PF 5% 50V	KINE DRIVER GREEN W/SVM

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
CG256	243358		CAPCC 5PF +/- .5PF 50V	MPEG CBA
CG257	243358		CAPCC 5PF +/- .5PF 50V	MPEG CBA
CG259	243359		CAPCC .1UF Z Y5V 16V	MPEG CBA
CG260	243359		CAPCC .1UF Z Y5V 16V	MPEG CBA
CG261	243275		CAP LYTC 470UF M 10V	MPEG CBA
CG262	243275		CAP LYTC 470UF M 10V	MPEG CBA
CG263	243359		CAPCC .1UF Z Y5V 16V	MPEG CBA
CG301	243400		CAP LYTC 100UF 50V 105C	KINE DRIVER BLUE W/SVM
CG302	259590		CAPCC .022UF 10% 25V X7R	KINE DRIVER BLUE W/SVM
CG303	253796		CAPCC .1UF 10% 16V	KINE DRIVER BLUE W/SVM
CG304	253796		CAPCC .1UF 10% 16V	KINE DRIVER BLUE W/SVM
CG305	247002		CAPCC .001UF 20% 50V X7R	KINE DRIVER BLUE W/SVM
CG306	256775		CAPCC .01UF K X7R 50V	KINE DRIVER BLUE W/SVM
CG307	258718		CAP POLY .022UF 20% 250V	KINE DRIVER BLUE W/SVM
CG308	256783		RES CMF 0 OHM 0% 1/16W	KINE DRIVER BLUE W/SVM
CG309	258718		CAP POLY .022UF 20% 250V	KINE DRIVER BLUE W/SVM
CG310	235816		CAP LYTC 22UF M 250V	KINE DRIVER BLUE W/SVM
CG312	258718		CAP POLY .022UF 20% 250V	KINE DRIVER BLUE W/SVM
CG314	247002		CAPCC .001UF 20% 50V X7R	KINE DRIVER BLUE W/SVM
CG331	259384		CAP POLY 1UF 5% 50V	KINE DRIVER BLUE W/SVM
CG341	193043		CAP LYTC 47UF 25V	KINE DRIVER BLUE W/SVM
CG348	157314		CAPCD 47PF K NP0 250V	KINE DRIVER BLUE W/SVM
CG354	243464		CAPCC 15PF 5% 50V	KINE DRIVER BLUE W/SVM
CG50	230980		CAP LYTC 47UF M 63V	CONVERGENCE AMP BOARD
CG500	243359		CAPCC .1UF Z Y5V 16V	MPEG CBA
CG501	243359		CAPCC .1UF Z Y5V 16V	MPEG CBA
CG502	243359		CAPCC .1UF Z Y5V 16V	MPEG CBA
CG507	256775		CAPCC .01UF K X7R 50V	MPEG CBA
CG508	189981		CAP LYTC 10UF M 16V	MPEG CBA
CG51	247002		CAPCC .001UF 20% 50V X7R	CONVERGENCE AMP BOARD
CG514	230978		CAP LYTC 100UF M 16V	MPEG CBA
CG53	230980		CAP LYTC 47UF M 63V	CONVERGENCE AMP BOARD
CG54	175820		CAP LYTC 220UF M 25V	CONVERGENCE AMP BOARD
CG55	175820		CAP LYTC 220UF M 25V	CONVERGENCE AMP BOARD
CG56	253796		CAPCC .1UF 10% 16V	CONVERGENCE AMP BOARD
CG59	256814		CAPCC 22PF +5% -5% 50V NPO	CONVERGENCE AMP BOARD
CG60	256818		CAPCC 100PF 50V NPO	CONVERGENCE AMP BOARD
CG61	243464		CAPCC 15PF 5% 50V	CONVERGENCE AMP BOARD
CG62	256818		CAPCC 100PF 50V NPO	CONVERGENCE AMP BOARD
CH001	257823		CAP LYTC 470UF 20% 10V 85C	SMALL SIGNAL BOARD
CH002	259590		CAPCC .022UF 10% 25V X7R	SMALL SIGNAL BOARD
CH010	259561		CAP LYTC SMD 1UF 20% 50V 85C	SMALL SIGNAL BOARD
CH011	247002		CAPCC 1000PF K X7R 50V	SMALL SIGNAL BOARD
CH020	256816		CAPCC 33PF +/-5% 50V	SMALL SIGNAL BOARD
CH021	256816		CAPCC 33PF +/-5% 50V	SMALL SIGNAL BOARD
CH030	259561		CAP LYTC SMD 1UF 20% 50V 85C	SMALL SIGNAL BOARD
CH032	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CH122	230978		CAP LYTC 100UF M 16V	MPEG CBA
CH125	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CH126	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CH128	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CH147	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CH500	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CH501	257823		CAP LYTC 470UF 20% 10V 85C	SMALL SIGNAL BOARD
CH502	259590		CAPCC .022UF 10% 25V X7R	SMALL SIGNAL BOARD
CH503	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CH511	247002		CAPCC 1000PF K X7R 50V	SMALL SIGNAL BOARD
CH520	256816		CAPCC 33PF +/-5% 50V	SMALL SIGNAL BOARD
CH521	256816		CAPCC 33PF +/-5% 50V	SMALL SIGNAL BOARD
CH530	259561		CAP LYTC SMD 1UF 20% 50V 85C	SMALL SIGNAL BOARD
CH531	247002		CAPCC 1000PF K X7R 50V	SMALL SIGNAL BOARD
CH532	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CI005	259561		CAP LYTC SMD 1UF 20% 50V 85C	SMALL SIGNAL BOARD
CI008	256821		CAPCC 330PF +/-5% 50V	SMALL SIGNAL BOARD
CI026	263132		CAPCC .68PF 50V NPO	SMALL SIGNAL BOARD
CI027	247002		CAPCC 1000PF K X7R 50V	SMALL SIGNAL BOARD

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
CI028	259384		CAP POLY 1UF 5% 50V	SMALL SIGNAL BOARD
CI029	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CI030	256825		CAPCC .047UF 16.0V	SMALL SIGNAL BOARD
CI031	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CI032	259629		CAP LYTC (SMD) 4.7UF 25V 85C	SMALL SIGNAL BOARD
CI033	256816		CAPCC 33PF +/-5% 50V	SMALL SIGNAL BOARD
CI035	258697		CAP LYTC-SMD 10UF 20% 16V 85C	SMALL SIGNAL BOARD
CI507	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CI508	247002		CAPCC 1000PF K X7R 50V	SMALL SIGNAL BOARD
CI526	263132		CAPCC .68PF 50V NPO	SMALL SIGNAL BOARD
CI527	247002		CAPCC 1000PF K X7R 50V	SMALL SIGNAL BOARD
CI528	259384		CAP POLY 1UF 5% 50V	SMALL SIGNAL BOARD
CI529	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CI530	256825		CAPCC .047UF 16.0V	SMALL SIGNAL BOARD
CI531	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CI532	258697		CAP LYTC-SMD 10UF 20% 16V 85C	SMALL SIGNAL BOARD
CI533	256816		CAPCC 33PF +/-5% 50V	SMALL SIGNAL BOARD
CI535	258697		CAP LYTC-SMD 10UF 20% 16V 85C	SMALL SIGNAL BOARD
CIRCUIT	258745		CIRCUIT, DIG READY INTERFACE	DIGITAL READY INTERFACE
CIRCUIT	258753		CIRCUIT, CONV SIGNAL BOARD	CONVERGENCE SIGNAL BOAR
CIRCUIT	258990		CIRCUIT, DVD A/V INTERFACE	A/V INTERFACE
CIRCUIT	258755		CIRCUIT, CONV P-S/ADAPTER CBA	CONVERGENCE PS / ADAPTE
CIRCUIT	258754		CIRCUIT, CONVERGENCE AMP BOARD	CONVERGENCE AMP BOARD
CIRCUIT	258758		CIRCUIT, GREEN KINE DR W/SVM	KINE DRIVER GREEN W/SVM
CIRCUIT	258751		CIRCUIT, MAINS INPUT DOUBLER	MAINS INPUT DOUBLER
CIRCUIT	258769		CIRCUIT, IR PREAMP	IR PREAMP
CIRCUIT	258767		CIRCUIT, P-S/DEFLECTION	P-S/DEFLECTION
CIRCUIT	258748		CIRCUIT, FRONT A/V IN	FRONT A/V IN
CIRCUIT	258820		CIRCUIT, FRONT PANEL: DVD	FRONT PANEL 2
CIRCUIT	258819		CIRCUIT, FRONT PANEL: TV	FRONT PANEL 1
CIRCUIT	258981		CIRCUIT, MPEG	MPEG CBA
CIRCUIT	258756		CIRCUIT, RED KINE DRIVE W/SVM	KINE DRIVER RED W/SVM
CIRCUIT	258757		CIRCUIT, BLUE KINE DR W/SVM	KINE DRIVER BLUE W/SVM
CIRCUIT	258817		CIRCUIT, DVD POWER SUPPLY	SMPS - DVD
CIRCUIT	258761		CIRCUIT, SMALL SIGNAL BOARD	SMALL SIGNAL BOARD
CIRCUIT	258818		CIRCUIT, DVD SPDIF OUTPUT	SPDIF OUTPUT
CIRCUIT	253485		CIRCUIT, AUDIO CROSSOVER	AUDIO CROSSOVER
CIRCUIT	258770		CIRCUIT, SUB-DVD	SUB - DVD
CJ003	259362		CAP CD 220PF 10% 50V	FRONT A/V IN
CJ004	259362		CAP CD 220PF 10% 50V	FRONT A/V IN
CK001	243372		CAPCC +/-5% 50V 100PF	FRONT PANEL 1
CK002	193043		CAP LYTC 47UF M 25V	FRONT PANEL 1
CK003	243372		CAPCC +/-5% 50V 100PF	FRONT PANEL 1
CK005	256817		CAPCC 47PF J NPO 50V	FRONT PANEL 1
CK006	256817		CAPCC 47PF J NPO 50V	FRONT PANEL 1
CK007	256817		CAPCC 47PF J NPO 50V	FRONT PANEL 1
CK009	243644		CAPCC 27PF K NPO 50V	FRONT PANEL 1
CK01	253796		CAPCC .1UF 10% 16V	CONVERGENCE SIGNAL BOAR
CK010	243644		CAPCC 27PF K NPO 50V	FRONT PANEL 1
CK011	243372		CAPCC +/-5% 50V 100PF	FRONT PANEL 1
CK012	244057		CAPCC 33NF +80% -20% 50V	FRONT PANEL 1
CK015	193043		CAP LYTC 47UF M 25V	FRONT PANEL 1
CK019	253796		CAPCC .1UF 10% 16V	FRONT PANEL 1
CK02	253796		CAPCC .1UF 10% 16V	CONVERGENCE SIGNAL BOAR
CK020	256817		CAPCC 47PF J NPO 50V	FRONT PANEL 1
CK021	256817		CAPCC 47PF J NPO 50V	FRONT PANEL 1
CK022	253796		CAPCC .1UF 10% 16V	FRONT PANEL 1
CK025	256817		CAPCC 47PF J NPO 50V	FRONT PANEL 1
CK03	256775		CAPCC .01UF K X7R 50V	CONVERGENCE SIGNAL BOAR
CK031	193043		CAP LYTC 47UF M 25V	FRONT PANEL 1
CK04	253633		CAPCC .0015UF 10% 50V	CONVERGENCE SIGNAL BOAR
CK05	253796		CAPCC .1UF 10% 16V	CONVERGENCE SIGNAL BOAR
CK06	253796		CAPCC .1UF 10% 16V	CONVERGENCE SIGNAL BOAR
CK07	256817		CAPCC 47PF 50V NPO	CONVERGENCE SIGNAL BOAR
CK08	253796		CAPCC .1UF 10% 16V	CONVERGENCE SIGNAL BOAR
CK09	253796		CAPCC .1UF 10% 16V	CONVERGENCE SIGNAL BOAR

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
CK10	247002		CAPCC .001UF 20% 50V X7R	CONVERGENCE SIGNAL BOAR
CK11	253796		CAPCC .1UF 10% 16V	CONVERGENCE SIGNAL BOAR
CK12	244062		CAPCC 2.2NF +/-10% 50V	CONVERGENCE SIGNAL BOAR
CK14	253796		CAPCC .1UF 10% 16V	CONVERGENCE SIGNAL BOAR
CK15	253796		CAPCC .1UF 10% 16V	CONVERGENCE SIGNAL BOAR
CK16	253796		CAPCC .1UF 10% 16V	CONVERGENCE SIGNAL BOAR
CK17	256818		CAPCC 100PF 50V NPO	CONVERGENCE SIGNAL BOAR
CK18	256775		CAPCC .01UF K X7R 50V	CONVERGENCE SIGNAL BOAR
CK19	247002		CAPCC .001UF 20% 50V X7R	CONVERGENCE SIGNAL BOAR
CK20	253796		CAPCC .1UF 10% 16V	CONVERGENCE SIGNAL BOAR
CK201	214073		CAP POLY .01UF K 100V	IR PREAMP
CK202	193643		CAP LYTC 22UF M 50V	IR PREAMP
CK21	253796		CAPCC .1UF 10% 16V	CONVERGENCE SIGNAL BOAR
CK23	259422		CAP LYTC 10UF 20% 63V 85C	CONVERGENCE SIGNAL BOAR
CK236	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CK237	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CK238	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CK24	259422		CAP LYTC 10UF 20% 63V 85C	CONVERGENCE SIGNAL BOAR
CK247	243359		CAPCC .1UF Z Y5V 16V	MPEG CBA
CK25	259422		CAP LYTC 10UF 20% 63V 85C	CONVERGENCE SIGNAL BOAR
CK26	253635		CAPCC .015UF 10% 50V	CONVERGENCE SIGNAL BOAR
CK31	256775		CAPCC .01UF K X7R 50V	CONVERGENCE SIGNAL BOAR
CK32	253796		CAPCC .1UF 10% 16V	CONVERGENCE SIGNAL BOAR
CK33	253632		CAPCC 680PF 10% 50V	CONVERGENCE SIGNAL BOAR
CK34	253632		CAPCC 680PF 10% 50V	CONVERGENCE SIGNAL BOAR
CK35	253632		CAPCC 680PF 10% 50V	CONVERGENCE SIGNAL BOAR
CK36	253796		CAPCC .1UF 10% 16V	CONVERGENCE SIGNAL BOAR
CK37	253796		CAPCC .1UF 10% 16V	CONVERGENCE SIGNAL BOAR
CK38	253632		CAPCC 680PF 10% 50V	CONVERGENCE SIGNAL BOAR
CK39	253632		CAPCC 680PF 10% 50V	CONVERGENCE SIGNAL BOAR
CK40	232368		CAP LYTC 1UF 100V	CONVERGENCE SIGNAL BOAR
CK41	253632		CAPCC 680PF 10% 50V	CONVERGENCE SIGNAL BOAR
CK42	253796		CAPCC .1UF 10% 16V	CONVERGENCE SIGNAL BOAR
CK43	253632		CAPCC 680PF 10% 50V	CONVERGENCE SIGNAL BOAR
CK44	253632		CAPCC 680PF 10% 50V	CONVERGENCE SIGNAL BOAR
CK45	253632		CAPCC 680PF 10% 50V	CONVERGENCE SIGNAL BOAR
CK46	253632		CAPCC 680PF 10% 50V	CONVERGENCE SIGNAL BOAR
CK47	253632		CAPCC 680PF 10% 50V	CONVERGENCE SIGNAL BOAR
CK48	253632		CAPCC 680PF 10% 50V	CONVERGENCE SIGNAL BOAR
CK50	256816		CAPCC 33PF 50V NPO	CONVERGENCE SIGNAL BOAR
CK53	259422		CAP LYTC 10UF 20% 63V 85C	CONVERGENCE SIGNAL BOAR
CK56	253632		CAPCC 680PF 10% 50V	CONVERGENCE SIGNAL BOAR
CK57	253632		CAPCC 680PF 10% 50V	CONVERGENCE SIGNAL BOAR
CK58	253632		CAPCC 680PF 10% 50V	CONVERGENCE SIGNAL BOAR
CK59	253632		CAPCC 680PF 10% 50V	CONVERGENCE SIGNAL BOAR
CK60	253796		CAPCC .1UF 10% 16V	CONVERGENCE SIGNAL BOAR
CK63	247002		CAPCC .001UF 20% 50V X7R	CONVERGENCE SIGNAL BOAR
CK64	247002		CAPCC .001UF 20% 50V X7R	CONVERGENCE SIGNAL BOAR
CK65	253796		CAPCC .1UF 10% 16V	CONVERGENCE SIGNAL BOAR
CK66	247002		CAPCC .001UF 20% 50V X7R	CONVERGENCE SIGNAL BOAR
CK67	259422		CAP LYTC 10UF 20% 63V 85C	CONVERGENCE SIGNAL BOAR
CK70	175820		CAP LYTC 220UF M 25V	CONVERGENCE SIGNAL BOAR
CK71	259422		CAP LYTC 10UF 20% 63V 85C	CONVERGENCE SIGNAL BOAR
CK72	175820		CAP LYTC 220UF M 25V	CONVERGENCE SIGNAL BOAR
CK73	253796		CAPCC .1UF 10% 16V	CONVERGENCE SIGNAL BOAR
CK74	253632		CAPCC 680PF 10% 50V	CONVERGENCE SIGNAL BOAR
CK75	256800		CAP LYTIC 100UF 25V 85C	CONVERGENCE SIGNAL BOAR
CK76	259645		CAP POLY .1UF 5% 63V	CONVERGENCE SIGNAL BOAR
CK77	253632		CAPCC 680PF 10% 50V	CONVERGENCE SIGNAL BOAR
CL004	232253		CAP LYTC 1UF 50V	P-S/DEFLECTION
CL005	259355		CAP LYTC 100UF 20% 25V 105C	P-S/DEFLECTION
CL006	157199		CAPCD 22PF J NP0 50V	P-S/DEFLECTION
CL007	243800		CAP POLY 3300PF K 100V	P-S/DEFLECTION
CL008	259645		CAP POLY .1UF 5% 63V	P-S/DEFLECTION
CL010	259645		CAP POLY .1UF 5% 63V	P-S/DEFLECTION
CL013	259352		CAP POLY .001UF 20% 63V	P-S/DEFLECTION

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
CL023	232253		CAP LYTC 1UF 50V	P-S/DEFLECTION
CL025	239175		CAP POLY .001UF M 100V	P-S/DEFLECTION
CL029	259285		CAP PROP 3.3UF 20% 63V	P-S/DEFLECTION
CL030	259307		CAP PROP 330PF 2.5% 2KV	P-S/DEFLECTION
CL031	259321		CAP PROP .0087UF 2.5% 2KV	P-S/DEFLECTION
CL032	259248		CAP PROP .022UF 5% 400KV	P-S/DEFLECTION
CL035	259268		CAP PROP .41UF 5% 400V	P-S/DEFLECTION
CL036	258698		CAP LYTC 2.2UF 20% 250V 105C	P-S/DEFLECTION
CL037	239175		CAP POLY .001UF M 100V	P-S/DEFLECTION
CL038	259305		CAP PROP .0022UF 2% 400V	P-S/DEFLECTION
CL039	259305		CAP PROP .0022UF 2% 400V	P-S/DEFLECTION
CL043	258717		CAP POLY .1UF 20% 250V	P-S/DEFLECTION
CL072	230979		CAP LYTC 100UF M 16V	P-S/DEFLECTION
CL075	230979		CAP LYTC 100UF M 16V	P-S/DEFLECTION
CL105	259306		CAP PROP .0047UF 5% 630V	P-S/DEFLECTION
CL107	210158		CAP POLY .047UF J 63V	P-S/DEFLECTION
CL110	230979		CAP LYTC 100UF M 16V	P-S/DEFLECTION
CL120	259304		CAP PROP .0016UF 2.5% 2KV	P-S/DEFLECTION
CL140	259280		CAP PROP .047UF 5% 400V	P-S/DEFLECTION
CL141	214073		CAP POLY .01UF K 100V	P-S/DEFLECTION
CL200	259253		CAP LYTC 10UF 20% 350V 85C	P-S/DEFLECTION
CL201	259623		CAPCD 470PF 10% 2KV	P-S/DEFLECTION
CL220	178836		CAP LYTC 470UF M 25V	P-S/DEFLECTION
CL221	259366		CAP CD 330PF 20% 1KV	P-S/DEFLECTION
CL230	258709		CAP LYTC 100UF 20% 100V 85C	P-S/DEFLECTION
CL231	259366		CAP CD 330PF 20% 1KV	P-S/DEFLECTION
CL250	178836		CAP LYTC 470UF M 25V	P-S/DEFLECTION
CL251	259366		CAP CD 330PF 20% 1KV	P-S/DEFLECTION
CL301	259255		CAP PROP .01UF 5% 400V	P-S/DEFLECTION
CL314	224271		CAP POLY .22UF K 63V	P-S/DEFLECTION
CLIP	259748		TRANSISTOR/IC MTG CLIP(BLACK)	KINE DRIVER BLUE W/SVM
CLIP	244842		CLIP, FUSEHOLDER	MAINS INPUT DOUBLER
CLIP	259748		TRANSISTOR/IC MTG CLIP(BLACK)	P-S/DEFLECTION
CLIP	259748		TRANSISTOR/IC MTG CLIP(BLACK)	KINE DRIVER GREEN W/SVM
CLIP	259748		TRANSISTOR/IC MTG CLIP(BLACK)	CONVERGENCE PS / ADAPTE
CLIP	259748		TRANSISTOR/IC MTG CLIP(BLACK)	KINE DRIVER RED W/SVM
CLIP	259846		TRANSISTOR/IC CLIP (BLUE)	P-S/DEFLECTION
CLIP	259845		TRANSISTOR/IC CLIP (BROWN)	P-S/DEFLECTION
CLIP	259846		TRANSISTOR/IC CLIP (BLUE)	CONVERGENCE AMP BOARD
CLIP	262082		CLIP, A/V-DVD DOOR RETAINER	INSTRUMENT ASSEMBLY
CLIP	259748		TRANSISTOR/IC MTG CLIP(BLACK)	SMALL SIGNAL BOARD
CONTROL	240623		CONTROL, FOCUS/SCREEN	OPTICS ASSEMBLY
COVER	259498		SHIELD COVER	DIGITAL READY INTERFACE
COVER	259165		COVER, CRT/KINE DRIVER ACCESS	INSTRUMENT ASSEMBLY
CP010	259262		CAP LYTC 220UF 20% 400V 85C	P-S/DEFLECTION
CP019	259677		CAPCD 220PF 20% 1KV 2B4	P-S/DEFLECTION
CP020	259367		CAP CD 100PF 20% 1KV	P-S/DEFLECTION
CP021	259335		CAP POLY .001UF 5% 400V	P-S/DEFLECTION
CP022	259677		CAPCD 220PF 20% 1KV 2B4	P-S/DEFLECTION
CP023	259355		CAP LYTC 100UF 20% 25V 105C	P-S/DEFLECTION
CP024	259354		CAP POLY .22UF 20% 63V	P-S/DEFLECTION
CP026	259645		CAP POLY .1UF 5% 63V	P-S/DEFLECTION
CP027	259356		CAP POLY .022UF 10% 63V	P-S/DEFLECTION
CP028	259353		CAP POLY .022UF 20% 63V	P-S/DEFLECTION
CP030	226501		CAP POLY 2200PF K 100V	P-S/DEFLECTION
CP031	153925		CAP POLY .1UF K 100V	P-S/DEFLECTION
CP034	153925		CAP POLY .1UF K 100V	P-S/DEFLECTION
CP049	259314		CAP CD .0015UF 20% 250V Y5U	P-S/DEFLECTION
CP050	259567		CAPCD 150PF 20% 400V Y5P	P-S/DEFLECTION
CP051	259368		CAPCD 470PF 10% 2KV 2C4	P-S/DEFLECTION
CP052	259960		CAP FILM .0022UF 20% 1KV	P-S/DEFLECTION
CP053	239175		CAP POLY .001UF M 100V	P-S/DEFLECTION
CP056	148067		CAPCD 470PF K Z5P 50V	P-S/DEFLECTION
CP061	259677		CAPCD 220PF 20% 1KV 2B4	P-S/DEFLECTION
CP062	175820		CAP LYTC 220UF M 25V	P-S/DEFLECTION
CP063	259645		CAP POLY .1UF 5% 63V	P-S/DEFLECTION

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
CP071	143871		CAPCD 100PF J NPO 50V	P-S/DEFLECTION
CP073	259362		CAP CD 220PF 10% 50V	P-S/DEFLECTION
CP110	259260		CAP LYTC 220UF 20% 200V 105C	P-S/DEFLECTION
CP111	259570		CAPCD 330PF 10% 2KV	P-S/DEFLECTION
CP112	259270		CAP PROP .0015UF 20% 1KV	P-S/DEFLECTION
CP113	259677		CAPCD 220PF 20% 1KV 2B4	P-S/DEFLECTION
CP12	259857		CAP LYTC 47UF 20% 450V 85C	CONVERGENCE PS / ADAPTE
CP120	259649		CAP LYTC 330UF 20% 35V 105C	P-S/DEFLECTION
CP121	259368		CAPCD 470PF 10% 2KV 2C4	P-S/DEFLECTION
CP130	259647		CAP LYTC 220UF 20% 35V 105C	P-S/DEFLECTION
CP131	259368		CAPCD 470PF 10% 2KV 2C4	P-S/DEFLECTION
CP135	259647		CAP LYTC 220UF 20% 35V 105C	P-S/DEFLECTION
CP136	259368		CAPCD 470PF 10% 2KV 2C4	P-S/DEFLECTION
CP140	259852		CAP LYTC 1000UF 20% 16V 105C	P-S/DEFLECTION
CP141	259368		CAPCD 470PF 10% 2KV 2C4	P-S/DEFLECTION
CP150	259848		CAP LYTC 2200UF 20% 16V 105C	P-S/DEFLECTION
CP151	259368		CAPCD 470PF 10% 2KV 2C4	P-S/DEFLECTION
CP152	214073		CAP POLY .01UF K 100V	P-S/DEFLECTION
CP162	143871		CAPCD 100PF J NPO 50V	P-S/DEFLECTION
CP170	256800		CAP LYTIC 100UF 25V 85C	P-S/DEFLECTION
CP171	210162		CAP POLY .01UF J 63V	P-S/DEFLECTION
CP172	153925		CAP POLY .1UF K 100V	P-S/DEFLECTION
CP175	143871		CAPCD 100PF J NPO 50V	P-S/DEFLECTION
CP179	247368		CAPCD 330PF K Y5R 50V	P-S/DEFLECTION
CP180	153925		CAP POLY .1UF K 100V	P-S/DEFLECTION
CP182	153925		CAP POLY .1UF K 100V	P-S/DEFLECTION
CP190	193043		CAP LYTC 47UF M 25V	P-S/DEFLECTION
CP195	214073		CAP POLY .01UF K 100V	P-S/DEFLECTION
CP196	153925		CAP POLY .1UF K 100V	P-S/DEFLECTION
CP197	153925		CAP POLY .1UF K 100V	P-S/DEFLECTION
CP199	193043		CAP LYTC 47UF M 25V	P-S/DEFLECTION
CP20	232368		CAP LYTC 1UF 100V	CONVERGENCE PS / ADAPTE
CP201	214073		CAP POLY .01UF K 100V	P-S/DEFLECTION
CP204	259354		CAP POLY .22UF 20% 63V	P-S/DEFLECTION
CP21	232368		CAP LYTC 1UF 100V	CONVERGENCE PS / ADAPTE
CP22	153925		CAP POLY .1UF K 100V	CONVERGENCE PS / ADAPTE
CP220	175820		CAP LYTC 220UF M 25V	P-S/DEFLECTION
CP221	214073		CAP POLY .01UF K 100V	P-S/DEFLECTION
CP23	193043		CAP LYTC 47UF 25V	CONVERGENCE PS / ADAPTE
CP230	259354		CAP POLY .22UF 20% 63V	P-S/DEFLECTION
CP240	259716		CAP LYTC 1000UF 20% 16V 105C	P-S/DEFLECTION
CP241	259350		CAP POLY .047UF 10% 63V	P-S/DEFLECTION
CP250	193043		CAP LYTC 47UF M 25V	P-S/DEFLECTION
CP28	247002		CAPCC .001UF 20% 50V X7R	CONVERGENCE PS / ADAPTE
CP29	247002		CAPCC .001UF 20% 50V X7R	CONVERGENCE PS / ADAPTE
CP30	259959		CAP FILM .0033UF 20% 1KV	CONVERGENCE PS / ADAPTE
CP301	256793		CAP PROP .1UF +20% -20%	SMPS - DVD
CP302	256793		CAP PROP .1UF +20% -20%	SMPS - DVD
CP304	259986		CAPCD .0047UF 20% 1KV 2E4	SMPS - DVD
CP305	198565		CAPCD 1500PF K Y5P 1KV	SMPS - DVD
CP306	198565		CAPCD 1500PF K Y5P 1KV	SMPS - DVD
CP308	260036		CAP LYTC 33UF 20% 200V 105C	SMPS - DVD
CP309	259990		CAP PROP .0022UF 20% 1KV	SMPS - DVD
CP31	239175		CAP POLY .001UF M 100V	CONVERGENCE PS / ADAPTE
CP315	260037		CAP .001UF 20% 275V RMS	SMPS - DVD
CP325	193643		CAP LYTC 22UF M 50V	SMPS - DVD
CP326	198571		CAPCD 2200PF K Y5R 50V	SMPS - DVD
CP327	230973		CAP LYTC 4.7UF M 50V	SMPS - DVD
CP328	259987		CAP POLY .1UF 5% 63V	SMPS - DVD
CP33	253633		CAPCC .0015UF 10% 50V	CONVERGENCE PS / ADAPTE
CP337	193043		CAP LYTC 47UF M 50V	SMPS - DVD
CP338	198559		CAPCD .001UF K Y5S 50V	SMPS - DVD
CP342	198559		CAPCD .001UF K Y5S 50V	SMPS - DVD
CP360	232380		CAP LYTC 1000UF M 16V	SMPS - DVD
CP361	193043		CAP LYTC 47UF M 50V	SMPS - DVD
CP362	232367		CAPCD .001UF M Y5R 1KV	SMPS - DVD

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
CP363	232367		CAPCD .001UF M Y5R 1KV	SMPS - DVD
CP364	227898		CAP LYTC 470UF M 16V	SMPS - DVD
CP365	232380		CAP LYTC 1000UF M 16V	SMPS - DVD
CP366	227898		CAP LYTC 470UF M 16V	SMPS - DVD
CP37	232734		CAP POLY 10NF K 100V	CONVERGENCE PS / ADAPTE
CP39	256772		CAPCC 470PF 20% 50V	CONVERGENCE PS / ADAPTE
CP390	178836		CAP LYTC 470UF M 25V	SMPS - DVD
CP392	232367		CAPCD .001UF M Y5R 1KV	SMPS - DVD
CP393	259987		CAP POLY .1UF 5% 63V	SMPS - DVD
CP394	175820		CAP LYTC 220UF M 25V	SMPS - DVD
CP396	178836		CAP LYTC 470UF M 25V	SMPS - DVD
CP40	256772		CAPCC 470PF 20% 50V	CONVERGENCE PS / ADAPTE
CP400	256793		CAP PROP .1UF +20% -20%	MAINS INPUT DOUBLER
CP402	259222		CAPCD .0047UF 1KV 20% Y5U	MAINS INPUT DOUBLER
CP403	259222		CAPCD .0047UF 1KV 20% Y5U	MAINS INPUT DOUBLER
CP410	259885		CAP LYTC 1000UF 20% 250V 105C	MAINS INPUT DOUBLER
CP411	259885		CAP LYTC 1000UF 20% 250V 105C	MAINS INPUT DOUBLER
CP412	259222		CAPCD .0047UF 1KV 20% Y5U	MAINS INPUT DOUBLER
CP42	259422		CAP LYTC 10UF 20% 63V 85C	CONVERGENCE PS / ADAPTE
CP46	257823		CAP LYTC 470UF 20% 10V 85C	CONVERGENCE PS / ADAPTE
CP49	259422		CAP LYTC 10UF 20% 63V 85C	CONVERGENCE PS / ADAPTE
CP503	259491		CAPCC .22UF 10% 50V X7R	SMALL SIGNAL BOARD
CP504	256800		CAP LYTIC 100UF 25V 85C	SMALL SIGNAL BOARD
CP511	259354		CAP POLY .22UF 20% 63V	SMALL SIGNAL BOARD
CP512	259647		CAP LYTC 220UF 20% 35V 105C	SMALL SIGNAL BOARD
CP513	259491		CAPCC .22UF 10% 50V X7R	SMALL SIGNAL BOARD
CP514	256800		CAP LYTIC 100UF 25V 85C	SMALL SIGNAL BOARD
CP521	259354		CAP POLY .22UF 20% 63V	SMALL SIGNAL BOARD
CP522	256772		CAPCC 470PF +10% -10% 50V	SMPS - DVD
CP522	259647		CAP LYTC 220UF 20% 35V 105C	SMALL SIGNAL BOARD
CP523	244062		CAPCC 2.2NF +/-10% 50V	SMPS - DVD
CP523	259491		CAPCC .22UF 10% 50V X7R	SMALL SIGNAL BOARD
CP524	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CP525	244062		CAPCC 2.2NF +/-10% 50V	SMPS - DVD
CP525	257823		CAP LYTC 470UF 20% 10V 85C	SMALL SIGNAL BOARD
CP527	259491		CAPCC .22UF 10% 50V X7R	SMALL SIGNAL BOARD
CP530	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CP533	259491		CAPCC .22UF 10% 50V X7R	SMALL SIGNAL BOARD
CP533	253633		CAPCC .0015UF 10% 50V	SMPS - DVD
CP534	257823		CAP LYTC 470UF 20% 10V 85C	SMALL SIGNAL BOARD
CP543	259491		CAPCC .22UF 10% 50V X7R	SMALL SIGNAL BOARD
CP544	256800		CAP LYTIC 100UF 25V 85C	SMALL SIGNAL BOARD
CP550	259491		CAPCC .22UF 10% 50V X7R	SMALL SIGNAL BOARD
CP551	253796		CAPCC .1UF 10% 16V	SMPS - DVD
CP552	256772		CAPCC 470PF +10% -10% 50V	SMPS - DVD
CP553	247002		CAPCC 1000PF K X7R 50V	SMPS - DVD
CP555	259491		CAPCC .22UF 10% 50V X7R	SMALL SIGNAL BOARD
CP556	257823		CAP LYTC 470UF 20% 10V 85C	SMALL SIGNAL BOARD
CP560	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CP561	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CP562	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CP563	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CP564	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CP565	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CP569	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CP570	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CP571	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CP60	259964		CAP LYTC 220UF 20% 100V 85C	CONVERGENCE PS / ADAPTE
CP61	227390		CAP LYTC 22UF M 100V	CONVERGENCE PS / ADAPTE
CP610	190523		CAP POLY .22UF K 100V	MAINS INPUT DOUBLER
CP621	153925		CAP POLY .1UF K 100V	MAINS INPUT DOUBLER
CP65	259964		CAP LYTC 220UF 20% 100V 85C	CONVERGENCE PS / ADAPTE
CP66	227390		CAP LYTC 22UF M 100V	CONVERGENCE PS / ADAPTE
CP70	232348		CAP LYTC 1000UF M 25V	CONVERGENCE PS / ADAPTE
CP71	175820		CAP LYTC 220UF M 25V	CONVERGENCE PS / ADAPTE
CP75	232348		CAP LYTC 1000UF M 25V	CONVERGENCE PS / ADAPTE

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
CP76	175820		CAP LYTC 220UF M 25V	CONVERGENCE PS / ADAPTE
CP86	227248		CAP POLY .022UF K 100V	CONVERGENCE PS / ADAPTE
CP87	232368		CAP LYTC 1UF 100V	CONVERGENCE PS / ADAPTE
CP90	227248		CAP POLY .022UF K 100V	CONVERGENCE PS / ADAPTE
CP91	232368		CAP LYTC 1UF 100V	CONVERGENCE PS / ADAPTE
CQ003	198559		CAPCD .001UF K Y5S 50V	FRONT A/V IN
CQ004	198559		CAPCD .001UF K Y5S 50V	FRONT A/V IN
CR001	259565		CAPCC 39PF 5% 50V NPO	SMALL SIGNAL BOARD
CR002	259565		CAPCC 39PF 5% 50V NPO	SMALL SIGNAL BOARD
CR003	253797		CAPCC .22UF 10% 10V	SMALL SIGNAL BOARD
CR005	258693		CAPCC .0012UF 10% 50V	SMALL SIGNAL BOARD
CR006	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CR007	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CR008	256825		CAPCC .047UF 16.0V	SMALL SIGNAL BOARD
CR009	256825		CAPCC .047UF 16.0V	SMALL SIGNAL BOARD
CR010	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CR011	258694		CAPCC .0039UF 10% 50V	SMALL SIGNAL BOARD
CR012	256934		CAPCC 820PF 10% 50V	SMALL SIGNAL BOARD
CR015	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CR016	258694		CAPCC .0039UF 10% 50V	SMALL SIGNAL BOARD
CR017	256934		CAPCC 820PF 10% 50V	SMALL SIGNAL BOARD
CR020	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CR021	258694		CAPCC .0039UF 10% 50V	SMALL SIGNAL BOARD
CR022	256934		CAPCC 820PF 10% 50V	SMALL SIGNAL BOARD
CR025	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CR026	258694		CAPCC .0039UF 10% 50V	SMALL SIGNAL BOARD
CR027	256934		CAPCC 820PF 10% 50V	SMALL SIGNAL BOARD
CR030	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CR031	258694		CAPCC .0039UF 10% 50V	SMALL SIGNAL BOARD
CR032	256934		CAPCC 820PF 10% 50V	SMALL SIGNAL BOARD
CR038	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CR039	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CR040	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CR041	258694		CAPCC .0039UF 10% 50V	SMALL SIGNAL BOARD
CR042	256934		CAPCC 820PF 10% 50V	SMALL SIGNAL BOARD
CR043	256825		CAPCC .047UF 16.0V	SMALL SIGNAL BOARD
CR049	259565		CAPCC 39PF 5% 50V NPO	SMALL SIGNAL BOARD
CR050	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CR051	258694		CAPCC .0039UF 10% 50V	SMALL SIGNAL BOARD
CR052	256934		CAPCC 820PF 10% 50V	SMALL SIGNAL BOARD
CR055	257823		CAP LYTC 470UF 20% 10V 85C	SMALL SIGNAL BOARD
CR057	259565		CAPCC 39PF 5% 50V NPO	SMALL SIGNAL BOARD
CR060	247002		CAPCC 1000PF K X7R 50V	SMALL SIGNAL BOARD
CR065	259628		CAP LYTC (SMD) 100UF 16V 85C	SMALL SIGNAL BOARD
CR066	259628		CAP LYTC (SMD) 100UF 16V 85C	SMALL SIGNAL BOARD
CR067	259628		CAP LYTC (SMD) 100UF 16V 85C	SMALL SIGNAL BOARD
CR068	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CR070	243372		CAPCC +/-5% 50V 100PF	SMALL SIGNAL BOARD
CR071	243372		CAPCC +/-5% 50V 100PF	SMALL SIGNAL BOARD
CR075	256825		CAPCC .047UF 16.0V	SMALL SIGNAL BOARD
CR081	259565		CAPCC 39PF 5% 50V NPO	SMALL SIGNAL BOARD
CR082	259565		CAPCC 39PF 5% 50V NPO	SMALL SIGNAL BOARD
CR083	256825		CAPCC .047UF 16.0V	SMALL SIGNAL BOARD
CR085	256825		CAPCC .047UF 16.0V	SMALL SIGNAL BOARD
CR090	259565		CAPCC 39PF 5% 50V NPO	SMALL SIGNAL BOARD
CR091	259565		CAPCC 39PF 5% 50V NPO	SMALL SIGNAL BOARD
CR092	259565		CAPCC 39PF 5% 50V NPO	SMALL SIGNAL BOARD
CR093	259565		CAPCC 39PF 5% 50V NPO	SMALL SIGNAL BOARD
CR094	259565		CAPCC 39PF 5% 50V NPO	SMALL SIGNAL BOARD
CR095	259565		CAPCC 39PF 5% 50V NPO	SMALL SIGNAL BOARD
CR096	259565		CAPCC 39PF 5% 50V NPO	SMALL SIGNAL BOARD
CR097	259565		CAPCC 39PF 5% 50V NPO	SMALL SIGNAL BOARD
CR110	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CR111	258694		CAPCC .0039UF 10% 50V	SMALL SIGNAL BOARD
CR112	256934		CAPCC 820PF 10% 50V	SMALL SIGNAL BOARD
CR113	256858		CAPCC 1UF 10% 6.3V X5R	SMALL SIGNAL BOARD

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
CR114	253797		CAPCC .22UF 10% 10V	SMALL SIGNAL BOARD
CR115	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CR116	258694		CAPCC .0039UF 10% 50V	SMALL SIGNAL BOARD
CR117	256934		CAPCC 820PF 10% 50V	SMALL SIGNAL BOARD
CR118	258695		CAPCC .0056UF 10% 50V	SMALL SIGNAL BOARD
CR130	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CR131	258694		CAPCC .0039UF 10% 50V	SMALL SIGNAL BOARD
CR132	256934		CAPCC 820PF 10% 50V	SMALL SIGNAL BOARD
CR150	256825		CAPCC .047UF 16.0V	SMALL SIGNAL BOARD
CR159	243372		CAPCC +/-5% 50V 100PF	SMALL SIGNAL BOARD
CR160	243372		CAPCC +/-5% 50V 100PF	SMALL SIGNAL BOARD
CR161	259565		CAPCC 39PF 5% 50V NPO	SMALL SIGNAL BOARD
CR162	259565		CAPCC 39PF 5% 50V NPO	SMALL SIGNAL BOARD
CR170	259565		CAPCC 39PF 5% 50V NPO	SMALL SIGNAL BOARD
CR171	259565		CAPCC 39PF 5% 50V NPO	SMALL SIGNAL BOARD
CR172	243372		CAPCC +/-5% 50V 100PF	SMALL SIGNAL BOARD
CR175	253797		CAPCC .22UF 10% 10V	SMALL SIGNAL BOARD
CR181	256817		CAPCC 47PF J NPO 50V	SMALL SIGNAL BOARD
CR182	256817		CAPCC 47PF J NPO 50V	SMALL SIGNAL BOARD
CR183	243372		CAPCC +/-5% 50V 100PF	SMALL SIGNAL BOARD
CR184	243372		CAPCC +/-5% 50V 100PF	SMALL SIGNAL BOARD
CR185	256825		CAPCC .047UF 16.0V	SMALL SIGNAL BOARD
CR187	256825		CAPCC .047UF 16.0V	SMALL SIGNAL BOARD
CR190	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CR194	243372		CAPCC +/-5% 50V 100PF	SMALL SIGNAL BOARD
CR196	243372		CAPCC +/-5% 50V 100PF	SMALL SIGNAL BOARD
CR250	257823		CAP LYTC 470UF 20% 10V 85C	SMALL SIGNAL BOARD
CR251	258694		CAPCC .0039UF 10% 50V	SMALL SIGNAL BOARD
CRT	263050		CRT ASSY, PROJECTION: GREEN	OPTICS ASSEMBLY
CRT	263116		CRT ASSY, PROJECTION: BLUE	OPTICS ASSEMBLY
CRT	263115		CRT ASSY, PROJECTION: RED	OPTICS ASSEMBLY
CS01	253634		CAPCC .0027UF 10% 50V	CONVERGENCE SIGNAL BOAR
CS02	253634		CAPCC .0027UF 10% 50V	CONVERGENCE SIGNAL BOAR
CS03	253634		CAPCC .0027UF 10% 50V	CONVERGENCE SIGNAL BOAR
CS04	253634		CAPCC .0027UF 10% 50V	CONVERGENCE SIGNAL BOAR
CS05	253634		CAPCC .0027UF 10% 50V	CONVERGENCE SIGNAL BOAR
CS06	253634		CAPCC .0027UF 10% 50V	CONVERGENCE SIGNAL BOAR
CS45	253796		CAPCC .1UF 10% 16V	CONVERGENCE SIGNAL BOAR
CS46	253797		CAPCC .22UF 10% 10V	CONVERGENCE SIGNAL BOAR
CS50	253797		CAPCC .22UF 10% 10V	CONVERGENCE SIGNAL BOAR
CS52	244141		CAPCC 3.3NF 10% 50V	CONVERGENCE SIGNAL BOAR
CS53	259384		CAP POLY 1UF 5% 50V	CONVERGENCE SIGNAL BOAR
CT001	259647		CAP LYTC 220UF 20% 35V 105C	DIGITAL READY INTERFACE
CT002	259354		CAP POLY .22UF 20% 63V	DIGITAL READY INTERFACE
CT003	256800		CAP LYTIC 100UF 25V 85C	DIGITAL READY INTERFACE
CT004	259491		CAPCC .22UF 10% 50V X7R	DIGITAL READY INTERFACE
CT005	259647		CAP LYTC 220UF 20% 35V 105C	DIGITAL READY INTERFACE
CT006	259354		CAP POLY .22UF 20% 63V	DIGITAL READY INTERFACE
CT007	256800		CAP LYTIC 100UF 25V 85C	DIGITAL READY INTERFACE
CT008	259491		CAPCC .22UF 10% 50V X7R	DIGITAL READY INTERFACE
CT009	256800		CAP LYTIC 100UF 25V 85C	DIGITAL READY INTERFACE
CT010	259491		CAPCC .22UF 10% 50V X7R	DIGITAL READY INTERFACE
CT011	256800		CAP LYTIC 100UF 25V 85C	DIGITAL READY INTERFACE
CT012	259491		CAPCC .22UF 10% 50V X7R	DIGITAL READY INTERFACE
CT202	259494		CAPCC .47UF 10% 6.3V X5R	DIGITAL READY INTERFACE
CT204	259494		CAPCC .47UF 10% 6.3V X5R	DIGITAL READY INTERFACE
CT206	259494		CAPCC .47UF 10% 6.3V X5R	DIGITAL READY INTERFACE
CT208	259494		CAPCC .47UF 10% 6.3V X5R	DIGITAL READY INTERFACE
CT210	259494		CAPCC .47UF 10% 6.3V X5R	DIGITAL READY INTERFACE
CT212	259494		CAPCC .47UF 10% 6.3V X5R	DIGITAL READY INTERFACE
CT214	259494		CAPCC .47UF 10% 6.3V X5R	DIGITAL READY INTERFACE
CT215	243372		CAPCC +/-5% 50V 100PF	MPEG CBA
CT216	243372		CAPCC +/-5% 50V 100PF	MPEG CBA
CT216	259494		CAPCC .47UF 10% 6.3V X5R	DIGITAL READY INTERFACE
CT217	259494		CAPCC .47UF 10% 6.3V X5R	DIGITAL READY INTERFACE
CT218	259494		CAPCC .47UF 10% 6.3V X5R	DIGITAL READY INTERFACE

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
CT219	259494		CAPCC .47UF 10% 6.3V X5R	DIGITAL READY INTERFACE
CT221	259494		CAPCC .47UF 10% 6.3V X5R	DIGITAL READY INTERFACE
CT222	259494		CAPCC .47UF 10% 6.3V X5R	DIGITAL READY INTERFACE
CT223	259494		CAPCC .47UF 10% 6.3V X5R	DIGITAL READY INTERFACE
CT224	259494		CAPCC .47UF 10% 6.3V X5R	DIGITAL READY INTERFACE
CT225	259494		CAPCC .47UF 10% 6.3V X5R	DIGITAL READY INTERFACE
CT226	259494		CAPCC .47UF 10% 6.3V X5R	DIGITAL READY INTERFACE
CT227	259494		CAPCC .47UF 10% 6.3V X5R	DIGITAL READY INTERFACE
CT228	259494		CAPCC .47UF 10% 6.3V X5R	DIGITAL READY INTERFACE
CT229	259494		CAPCC .47UF 10% 6.3V X5R	DIGITAL READY INTERFACE
CT231	256817		CAPCC 47PF J NPO 50V	DIGITAL READY INTERFACE
CT232	256817		CAPCC 47PF J NPO 50V	DIGITAL READY INTERFACE
CT233	256817		CAPCC 47PF J NPO 50V	DIGITAL READY INTERFACE
CT234	259494		CAPCC .47UF 10% 6.3V X5R	DIGITAL READY INTERFACE
CT235	256775		CAPCC .01UF K X7R 50V	DIGITAL READY INTERFACE
CT236	256858		CAPCC 1UF 10% 6.3V X5R	DIGITAL READY INTERFACE
CT237	256783		RES CMF 0 OHM 0% 1/16W	DIGITAL READY INTERFACE
CT238	256816		CAPCC 33PF +/-5% 50V	DIGITAL READY INTERFACE
CT241	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT242	259628		CAP LYTC (SMD) 100UF 16V 85C	DIGITAL READY INTERFACE
CT243	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT244	259628		CAP LYTC (SMD) 100UF 16V 85C	DIGITAL READY INTERFACE
CT245	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT246	259628		CAP LYTC (SMD) 100UF 16V 85C	DIGITAL READY INTERFACE
CT247	253714		CAPCC 470PF 5% 50V	DIGITAL READY INTERFACE
CT248	253714		CAPCC 470PF 5% 50V	DIGITAL READY INTERFACE
CT249	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT250	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT252	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT253	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT254	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT255	259494		CAPCC .47UF 10% 6.3V X5R	DIGITAL READY INTERFACE
CT261	259627		CAP LYTC (SMD) 47UF 16V 85C	DIGITAL READY INTERFACE
CT262	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT263	259634		CAPCC 22PF 1% 50V NPO	DIGITAL READY INTERFACE
CT264	259634		CAPCC 22PF 1% 50V NPO	DIGITAL READY INTERFACE
CT265	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT266	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT268	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT302	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT312	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT322	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT331	259628		CAP LYTC (SMD) 100UF 16V 85C	DIGITAL READY INTERFACE
CT332	259628		CAP LYTC (SMD) 100UF 16V 85C	DIGITAL READY INTERFACE
CT333	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT334	259628		CAP LYTC (SMD) 100UF 16V 85C	DIGITAL READY INTERFACE
CT335	246955		CAPCC 27PF J NPO 50V	DIGITAL READY INTERFACE
CT336	259628		CAP LYTC (SMD) 100UF 16V 85C	DIGITAL READY INTERFACE
CT337	253798		CAPCC 12PF 5% 50V	DIGITAL READY INTERFACE
CT338	259628		CAP LYTC (SMD) 100UF 16V 85C	DIGITAL READY INTERFACE
CT339	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT351	259628		CAP LYTC (SMD) 100UF 16V 85C	DIGITAL READY INTERFACE
CT352	259628		CAP LYTC (SMD) 100UF 16V 85C	DIGITAL READY INTERFACE
CT353	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT354	256813		CAPCC 3.3PF 50V NPO	DIGITAL READY INTERFACE
CT355	259628		CAP LYTC (SMD) 100UF 16V 85C	DIGITAL READY INTERFACE
CT356	259628		CAP LYTC (SMD) 100UF 16V 85C	DIGITAL READY INTERFACE
CT357	259628		CAP LYTC (SMD) 100UF 16V 85C	DIGITAL READY INTERFACE
CT358	246955		CAPCC 27PF J NPO 50V	DIGITAL READY INTERFACE
CT359	244022		CAPCC 2.7PF +/- .25PF 50V	DIGITAL READY INTERFACE
CT360	258742		CAPCC 6.8PF 50V NPO	DIGITAL READY INTERFACE
CT361	259628		CAP LYTC (SMD) 100UF 16V 85C	DIGITAL READY INTERFACE
CT362	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT371	259628		CAP LYTC (SMD) 100UF 16V 85C	DIGITAL READY INTERFACE
CT372	259628		CAP LYTC (SMD) 100UF 16V 85C	DIGITAL READY INTERFACE
CT373	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
CT374	256813		CAPCC 3.3PF 50V NPO	DIGITAL READY INTERFACE
CT375	259628		CAP LYTC (SMD) 100UF 16V 85C	DIGITAL READY INTERFACE
CT376	259628		CAP LYTC (SMD) 100UF 16V 85C	DIGITAL READY INTERFACE
CT377	246955		CAPCC 27PF J NPO 50V	DIGITAL READY INTERFACE
CT378	253798		CAPCC 12PF 5% 50V	DIGITAL READY INTERFACE
CT379	259628		CAP LYTC (SMD) 100UF 16V 85C	DIGITAL READY INTERFACE
CT380	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT401	256858		CAPCC 1UF 10% 6.3V X5R	DIGITAL READY INTERFACE
CT402	256858		CAPCC 1UF 10% 6.3V X5R	DIGITAL READY INTERFACE
CT403	256858		CAPCC 1UF 10% 6.3V X5R	DIGITAL READY INTERFACE
CT404	259628		CAP LYTC (SMD) 100UF 16V 85C	DIGITAL READY INTERFACE
CT405	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT406	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT407	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT408	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT409	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT410	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT411	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT412	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT413	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT414	259629		CAP LYTC (SMD) 4.7UF 25V 85C	DIGITAL READY INTERFACE
CT501	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT502	256815		CAPCC 10PF 50V NPO	DIGITAL READY INTERFACE
CT503	243464		CAPCC 15PF +5% -5%	DIGITAL READY INTERFACE
CT504	256814		CAPCC 22PF +5% -5%	DIGITAL READY INTERFACE
CT505	252354		CAP CD 68PF J 50V	DIGITAL READY INTERFACE
CT506	259565		CAPCC 39PF 5% 50V NPO	DIGITAL READY INTERFACE
CT507	256822		CAPCC 180PF 50V NPO	DIGITAL READY INTERFACE
CT508	259561		CAP LYTC SMD 1UF 20% 50V 85C	DIGITAL READY INTERFACE
CT509	259628		CAP LYTC (SMD) 100UF 16V 85C	DIGITAL READY INTERFACE
CT511	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT512	247002		CAPCC 1000PF K X7R 50V	DIGITAL READY INTERFACE
CT513	259561		CAP LYTC SMD 1UF 20% 50V 85C	DIGITAL READY INTERFACE
CT514	232768		CAP LYTC 470UF M 16V	DIGITAL READY INTERFACE
CT516	232768		CAP LYTC 470UF M 16V	DIGITAL READY INTERFACE
CT523	258697		CAP LYTC-SMD 10UF 20% 16V 85C	DIGITAL READY INTERFACE
CT528	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT529	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT530	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT531	246955		CAPCC 27PF J NPO 50V	DIGITAL READY INTERFACE
CT532	253637		CAPCC 91PF 5% 50V	DIGITAL READY INTERFACE
CT533	243371		CAPCC 82PF 5% 50V NPO	DIGITAL READY INTERFACE
CT534	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT541	246955		CAPCC 27PF J NPO 50V	DIGITAL READY INTERFACE
CT542	253637		CAPCC 91PF 5% 50V	DIGITAL READY INTERFACE
CT543	243371		CAPCC 82PF 5% 50V NPO	DIGITAL READY INTERFACE
CT544	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT546	232768		CAP LYTC 470UF M 16V	DIGITAL READY INTERFACE
CT548	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT551	232768		CAP LYTC 470UF M 16V	DIGITAL READY INTERFACE
CT561	256775		CAPCC .01UF K X7R 50V	DIGITAL READY INTERFACE
CT562	243391		CAPCC 150PF 5% 50V	DIGITAL READY INTERFACE
CT563	256815		CAPCC 10PF 50V NPO	DIGITAL READY INTERFACE
CT564	243391		CAPCC 150PF 5% 50V	DIGITAL READY INTERFACE
CT571	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT572	259628		CAP LYTC (SMD) 100UF 16V 85C	DIGITAL READY INTERFACE
CT602	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT604	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT607	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT608	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT611	258697		CAP LYTC-SMD 10UF 20% 16V 85C	DIGITAL READY INTERFACE
CT612	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT613	243372		CAPCC +/-5% 50V 100PF	DIGITAL READY INTERFACE
CT614	243372		CAPCC +/-5% 50V 100PF	DIGITAL READY INTERFACE
CT615	258697		CAP LYTC-SMD 10UF 20% 16V 85C	DIGITAL READY INTERFACE
CT616	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
CT617	243372		CAPCC +/-5% 50V 100PF	DIGITAL READY INTERFACE
CT618	258697		CAP LYTC-SMD 10UF 20% 16V 85C	DIGITAL READY INTERFACE
CT619	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT620	243372		CAPCC +/-5% 50V 100PF	DIGITAL READY INTERFACE
CT621	243372		CAPCC +/-5% 50V 100PF	DIGITAL READY INTERFACE
CT622	243372		CAPCC +/-5% 50V 100PF	DIGITAL READY INTERFACE
CT623	258697		CAP LYTC-SMD 10UF 20% 16V 85C	DIGITAL READY INTERFACE
CT624	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT625	243372		CAPCC +/-5% 50V 100PF	DIGITAL READY INTERFACE
CT626	243372		CAPCC +/-5% 50V 100PF	DIGITAL READY INTERFACE
CT631	256814		CAPCC 22PF +5% -5%	DIGITAL READY INTERFACE
CT632	256814		CAPCC 22PF +5% -5%	DIGITAL READY INTERFACE
CT633	256814		CAPCC 22PF +5% -5%	DIGITAL READY INTERFACE
CT634	256814		CAPCC 22PF +5% -5%	DIGITAL READY INTERFACE
CT635	256814		CAPCC 22PF +5% -5%	DIGITAL READY INTERFACE
CT636	256814		CAPCC 22PF +5% -5%	DIGITAL READY INTERFACE
CT642	259627		CAP LYTC (SMD) 47UF 16V 85C	DIGITAL READY INTERFACE
CT643	256775		CAPCC .01UF K X7R 50V	DIGITAL READY INTERFACE
CT644	258697		CAP LYTC-SMD 10UF 20% 16V 85C	DIGITAL READY INTERFACE
CT645	243372		CAPCC +/-5% 50V 100PF	DIGITAL READY INTERFACE
CT646	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT647	258697		CAP LYTC-SMD 10UF 20% 16V 85C	DIGITAL READY INTERFACE
CT648	243372		CAPCC +/-5% 50V 100PF	DIGITAL READY INTERFACE
CT649	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT650	258697		CAP LYTC-SMD 10UF 20% 16V 85C	DIGITAL READY INTERFACE
CT651	243372		CAPCC +/-5% 50V 100PF	DIGITAL READY INTERFACE
CT652	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT653	258697		CAP LYTC-SMD 10UF 20% 16V 85C	DIGITAL READY INTERFACE
CT654	243372		CAPCC +/-5% 50V 100PF	DIGITAL READY INTERFACE
CT655	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT656	258697		CAP LYTC-SMD 10UF 20% 16V 85C	DIGITAL READY INTERFACE
CT691	259628		CAP LYTC (SMD) 100UF 16V 85C	DIGITAL READY INTERFACE
CT692	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT710	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT715	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT717	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT718	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT719	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT720	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT721	259634		CAPCC 22PF 1% 50V NPO	DIGITAL READY INTERFACE
CT722	259634		CAPCC 22PF 1% 50V NPO	DIGITAL READY INTERFACE
CT724	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT725	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT726	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT727	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT735	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT736	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT737	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT738	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT745	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT747	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT749	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT752	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT900	259626		CAP LYTC (SMD) 22UF 16V 85C	DIGITAL READY INTERFACE
CT901	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT902	259626		CAP LYTC (SMD) 22UF 16V 85C	DIGITAL READY INTERFACE
CT903	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT912	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT913	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT914	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT915	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT916	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT917	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT918	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT919	253796		CAPCC .1UF 10% 16V	DIGITAL READY INTERFACE
CT940	259561		CAP LYTC SMD 1UF 20% 50V 85C	DIGITAL READY INTERFACE

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
CT941	259561		CAP LYTC SMD 1UF 20% 50V 85C	DIGITAL READY INTERFACE
CT942	256821		CAPCC 330PF +/-5% 50V	DIGITAL READY INTERFACE
CT943	256821		CAPCC 330PF +/-5% 50V	DIGITAL READY INTERFACE
CT944	249036		CAPCC 220PF J NPO 50V	DIGITAL READY INTERFACE
CT945	249036		CAPCC 220PF J NPO 50V	DIGITAL READY INTERFACE
CT950	259561		CAP LYTC SMD 1UF 20% 50V 85C	DIGITAL READY INTERFACE
CT951	259561		CAP LYTC SMD 1UF 20% 50V 85C	DIGITAL READY INTERFACE
CT952	256821		CAPCC 330PF +/-5% 50V	DIGITAL READY INTERFACE
CT953	256821		CAPCC 330PF +/-5% 50V	DIGITAL READY INTERFACE
CT954	249036		CAPCC 220PF J NPO 50V	DIGITAL READY INTERFACE
CT955	249036		CAPCC 220PF J NPO 50V	DIGITAL READY INTERFACE
CT960	259561		CAP LYTC SMD 1UF 20% 50V 85C	DIGITAL READY INTERFACE
CT961	259561		CAP LYTC SMD 1UF 20% 50V 85C	DIGITAL READY INTERFACE
CT962	256821		CAPCC 330PF +/-5% 50V	DIGITAL READY INTERFACE
CT963	256821		CAPCC 330PF +/-5% 50V	DIGITAL READY INTERFACE
CT964	249036		CAPCC 220PF J NPO 50V	DIGITAL READY INTERFACE
CT965	249036		CAPCC 220PF J NPO 50V	DIGITAL READY INTERFACE
CT970	259561		CAP LYTC SMD 1UF 20% 50V 85C	DIGITAL READY INTERFACE
CT971	259561		CAP LYTC SMD 1UF 20% 50V 85C	DIGITAL READY INTERFACE
CT972	247002		CAPCC 1000PF K X7R 50V	DIGITAL READY INTERFACE
CT973	247002		CAPCC 1000PF K X7R 50V	DIGITAL READY INTERFACE
CT982	244141		CAPCC 3.3NF 10% 50V	DIGITAL READY INTERFACE
CT983	244141		CAPCC 3.3NF 10% 50V	DIGITAL READY INTERFACE
CT984	244141		CAPCC 3.3NF 10% 50V	DIGITAL READY INTERFACE
CT985	244141		CAPCC 3.3NF 10% 50V	DIGITAL READY INTERFACE
CT990	259886		CAP NP LYTC 1000UF 20% 25V 85C	DIGITAL READY INTERFACE
CT991	259886		CAP NP LYTC 1000UF 20% 25V 85C	DIGITAL READY INTERFACE
CT992	259886		CAP NP LYTC 1000UF 20% 25V 85C	DIGITAL READY INTERFACE
CT993	259886		CAP NP LYTC 1000UF 20% 25V 85C	DIGITAL READY INTERFACE
CU001	259888		CAP LYTC (SMD) 100UF 6.3V 105C	SMALL SIGNAL BOARD
CU002	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CU003	245441		CAPCC 1UF K X7R 16V	SMALL SIGNAL BOARD
CU004	245441		CAPCC 1UF K X7R 16V	SMALL SIGNAL BOARD
CU005	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CU006	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CU007	259626		CAP LYTC (SMD) 22UF 16V 85C	SMALL SIGNAL BOARD
CU008	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CU009	259491		CAPCC .22UF 10% 50V X7R	SMALL SIGNAL BOARD
CU010	259491		CAPCC .22UF 10% 50V X7R	SMALL SIGNAL BOARD
CU011	259491		CAPCC .22UF 10% 50V X7R	SMALL SIGNAL BOARD
CU012	190552		CAPCC .1UF K X7R 50V	SMALL SIGNAL BOARD
CU013	243463		CAPCC 18PF +5% -5%	SMALL SIGNAL BOARD
CU014	243463		CAPCC 18PF +5% -5%	SMALL SIGNAL BOARD
CU015	259888		CAP LYTC (SMD) 100UF 6.3V 105C	SMALL SIGNAL BOARD
CU016	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CU017	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CU018	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CU019	190552		CAPCC .1UF K X7R 50V	SMALL SIGNAL BOARD
CU020	259491		CAPCC .22UF 10% 50V X7R	SMALL SIGNAL BOARD
CU021	259491		CAPCC .22UF 10% 50V X7R	SMALL SIGNAL BOARD
CU022	259491		CAPCC .22UF 10% 50V X7R	SMALL SIGNAL BOARD
CU023	243463		CAPCC 18PF +5% -5%	SMALL SIGNAL BOARD
CU024	243463		CAPCC 18PF +5% -5%	SMALL SIGNAL BOARD
CU025	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CU026	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CU027	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CU028	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CU029	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CU030	246955		CAPCC 27PF J NPO 50V	SMALL SIGNAL BOARD
CU031	246955		CAPCC 27PF J NPO 50V	SMALL SIGNAL BOARD
CU032	253635		CAPCC .015UF 10% 50V	SMALL SIGNAL BOARD
CU033	253634		CAPCC .0027UF 10% 50V	SMALL SIGNAL BOARD
CU034	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CU035	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CU037	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CU038	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
CU039	259627		CAP LYTC (SMD) 47UF 16V 85C	SMALL SIGNAL BOARD
CU040	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CU042	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CU043	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CU044	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CU045	253635		CAPCC .015UF 10% 50V	SMALL SIGNAL BOARD
CU046	253634		CAPCC .0027UF 10% 50V	SMALL SIGNAL BOARD
CU047	259627		CAP LYTC (SMD) 47UF 16V 85C	SMALL SIGNAL BOARD
CU048	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CU049	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CU051	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CU061	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CV005	243358		CAPCC 5PF +/- .5PF 50V	MPEG CBA
CV006	244063		CAPCC 20PF +/-5% 50V	MPEG CBA
CV011	243275		CAP LYTC 470UF M 10V	MPEG CBA
CV012	230978		CAP LYTC 100UF M 16V	MPEG CBA
CV001	243464		CAPCC 15PF +5% -5%	SMALL SIGNAL BOARD
CV002	244071		CAPCC 8.2PF +/- .5PF 50V	SMALL SIGNAL BOARD
CV003	252354		CAP CD 68PF J 50V	SMALL SIGNAL BOARD
CV004	243464		CAPCC 15PF +5% -5%	SMALL SIGNAL BOARD
CV005	252354		CAP CD 68PF J 50V	SMALL SIGNAL BOARD
CV006	259840		RES CMF 374 OHMS 1% 1/16W	SMALL SIGNAL BOARD
CV009	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CV01	189992		CE 4U7F +20% 100.0V 85C	CONVERGENCE PS / ADAPTE
CV011	259565		CAPCC 39PF 5% 50V NPO	SMALL SIGNAL BOARD
CV016	256814		CAPCC 22PF +5% -5%	SMALL SIGNAL BOARD
CV02	189981		CAP LYTC 10UF 16V	CONVERGENCE PS / ADAPTE
CV021	256822		CAPCC 180PF 50V NPO	SMALL SIGNAL BOARD
CV022	258693		CAPCC .0012UF 10% 50V	SMALL SIGNAL BOARD
CV03	189981		CAP LYTC 10UF 16V	CONVERGENCE PS / ADAPTE
CV030	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CV041	256822		CAPCC 180PF 50V NPO	SMALL SIGNAL BOARD
CV042	258693		CAPCC .0012UF 10% 50V	SMALL SIGNAL BOARD
CV050	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CV09	257823		CAP LYTC 470UF 20% 10V 85C	CONVERGENCE PS / ADAPTE
CV10	258709		CAP LYTC 100UF 20% 100V 85C	CONVERGENCE PS / ADAPTE
CV100	259628		CAP LYTC (SMD) 100UF 16V 85C	SMALL SIGNAL BOARD
CV101	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CV102	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CV11	153925		CAP POLY .1UF K 100V	CONVERGENCE PS / ADAPTE
CV112	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CV12	153925		CAP POLY .1UF K 100V	CONVERGENCE PS / ADAPTE
CV20	253796		CAPCC .1UF 10% 16V	CONVERGENCE PS / ADAPTE
CV200	259628		CAP LYTC (SMD) 100UF 16V 85C	SMALL SIGNAL BOARD
CV201	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CV202	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CV203	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CV204	259629		CAP LYTC (SMD) 4.7UF 25V 85C	SMALL SIGNAL BOARD
CV220	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CV221	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CV222	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CV230	246955		CAPCC 27PF J NPO 50V	SMALL SIGNAL BOARD
CV231	259560		CAPCC 10PF 50V N750	SMALL SIGNAL BOARD
CV240	256816		CAPCC 33PF +/-5% 50V	SMALL SIGNAL BOARD
CV241	256816		CAPCC 33PF +/-5% 50V	SMALL SIGNAL BOARD
CV250	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CV251	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CV252	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CV260	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CV261	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CV262	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CV270	258697		CAP LYTC-SMD 10UF 20% 16V 85C	SMALL SIGNAL BOARD
CV272	259629		CAP LYTC (SMD) 4.7UF 25V 85C	SMALL SIGNAL BOARD
CV279	259560		CAPCC 10PF 50V N750	SMALL SIGNAL BOARD
CV281	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CV30	253796		CAPCC .1UF 10% 16V	CONVERGENCE PS / ADAPTE

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
CV300	244059		CAPCC 5.6PF +/- .25PF 50V	SMALL SIGNAL BOARD
CV31	253796		CAPCC .1UF 10% 16V	CONVERGENCE PS / ADAPTE
CV310	244059		CAPCC 5.6PF +/- .25PF 50V	SMALL SIGNAL BOARD
CV32	189992		CE 4U7F +20% 100.0V 85C	CONVERGENCE PS / ADAPTE
CV320	244059		CAPCC 5.6PF +/- .25PF 50V	SMALL SIGNAL BOARD
CV33	189992		CE 4U7F +20% 100.0V 85C	CONVERGENCE PS / ADAPTE
CV340	243372		CAPCC +/-5% 50V 100PF	SMALL SIGNAL BOARD
CV400	259560		CAPCC 10PF 50V N750	SMALL SIGNAL BOARD
CV401	259560		CAPCC 10PF 50V N750	SMALL SIGNAL BOARD
CV50	259351		CAP POLY .33UF 10% 63V	CONVERGENCE PS / ADAPTE
CV505	247002		CAPCC 1000PF K X7R 50V	SMALL SIGNAL BOARD
CV511	247002		CAPCC 1000PF K X7R 50V	SMALL SIGNAL BOARD
CV513	243464		CAPCC 15PF +5% -5%	SMALL SIGNAL BOARD
CV52	259351		CAP POLY .33UF 10% 63V	CONVERGENCE PS / ADAPTE
CV521	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CV522	242831		CAP LYTC 220UF M 10V	SMALL SIGNAL BOARD
CV523	226503		CAPCC .001UF 5% 50V	SMALL SIGNAL BOARD
CV524	257772		CAP POLY .47UF J 63V	SMALL SIGNAL BOARD
CV526	226503		CAPCC .001UF 5% 50V	SMALL SIGNAL BOARD
CV527	243372		CAPCC +/-5% 50V 100PF	SMALL SIGNAL BOARD
CV528	247002		CAPCC 1000PF K X7R 50V	SMALL SIGNAL BOARD
CV53	253796		CAPCC .1UF 10% 16V	CONVERGENCE PS / ADAPTE
CV530	247002		CAPCC 1000PF K X7R 50V	SMALL SIGNAL BOARD
CV532	247002		CAPCC 1000PF K X7R 50V	SMALL SIGNAL BOARD
CV534	247002		CAPCC 1000PF K X7R 50V	SMALL SIGNAL BOARD
CV535	258720		CAP POLY .56UF 10% 63V	SMALL SIGNAL BOARD
CV54	259590		CAPCC .022UF 10% 25V X7R	CONVERGENCE PS / ADAPTE
CV541	210160		CAP POLY .033UF J 63V	SMALL SIGNAL BOARD
CV542	244072		CAPCC 4.7NF +/-10% 50V	SMALL SIGNAL BOARD
CV545	259283		CAP PROP .068UF 5% 63V	SMALL SIGNAL BOARD
CV546	253714		CAPCC 470PF 5% 50V	SMALL SIGNAL BOARD
CV55	258709		CAP LYTC 100UF 20% 100V 85C	CONVERGENCE PS / ADAPTE
CV550	256816		CAPCC 33PF +/-5% 50V	SMALL SIGNAL BOARD
CV554	244072		CAPCC 4.7NF +/-10% 50V	SMALL SIGNAL BOARD
CV556	244072		CAPCC 4.7NF +/-10% 50V	SMALL SIGNAL BOARD
CV56	253796		CAPCC .1UF 10% 16V	CONVERGENCE PS / ADAPTE
CV560	256816		CAPCC 33PF +/-5% 50V	SMALL SIGNAL BOARD
CV57	259590		CAPCC .022UF 10% 25V X7R	CONVERGENCE PS / ADAPTE
CV70	232734		CAP POLY 10NF K 100V	CONVERGENCE PS / ADAPTE
CV71	232734		CAP POLY 10NF K 100V	CONVERGENCE PS / ADAPTE
CV72	247002		CAPCC .001UF 20% 50V X7R	CONVERGENCE PS / ADAPTE
CV80	198806		CAPCD .001UF FS Y5U 2KV	CONVERGENCE PS / ADAPTE
CV81	259907		CAP PROP 820UF 2% 2KV	CONVERGENCE PS / ADAPTE
CV82	259908		CAP PROP 120PF 3.5% 2KV	CONVERGENCE PS / ADAPTE
CV83	232734		CAP POLY 10NF K 100V	CONVERGENCE PS / ADAPTE
CV85	259365		CAP CD .0047UF 20% 2KV	CONVERGENCE PS / ADAPTE
CV86	259365		CAP CD .0047UF 20% 2KV	CONVERGENCE PS / ADAPTE
CV90	178836		CAP LYTC 470UF M 25V	CONVERGENCE PS / ADAPTE
CV91	259366		CAP CD 330PF 20% 1KV	CONVERGENCE PS / ADAPTE
CW05	230979		CAP LYTC 100UF M 16V	CONVERGENCE AMP BOARD
CW06	253796		CAPCC .1UF 10% 16V	CONVERGENCE AMP BOARD
CW07	253796		CAPCC .1UF 10% 16V	CONVERGENCE AMP BOARD
CW138	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CW139	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CW140	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CW141	247002		CAPCC 1000PF K X7R 50V	MPEG CBA
CW142	256775		CAPCC .01UF K X7R 50V	MPEG CBA
CW146	230978		CAP LYTC 100UF M 16V	MPEG CBA
CW147	230978		CAP LYTC 100UF M 16V	MPEG CBA
CW19	253796		CAPCC .1UF 10% 16V	CONVERGENCE AMP BOARD
CX002	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX003	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CX010	258697		CAP LYTC-SMD 10UF 20% 16V 85C	SMALL SIGNAL BOARD
CX011	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX012	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CX100	174406		CAPCC 22PF J NPO 50V	SMALL SIGNAL BOARD

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
CX120	174406		CAPCC 22PF J NPO 50V	SMALL SIGNAL BOARD
CX130	257823		CAP LYTC 470UF 20% 10V 85C	SMALL SIGNAL BOARD
CX132	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX133	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CX200	174406		CAPCC 22PF J NPO 50V	SMALL SIGNAL BOARD
CX220	174406		CAPCC 22PF J NPO 50V	SMALL SIGNAL BOARD
CX300	174406		CAPCC 22PF J NPO 50V	SMALL SIGNAL BOARD
CX320	174406		CAPCC 22PF J NPO 50V	SMALL SIGNAL BOARD
CX409	243372		CAPCC +/-5% 50V 100PF	SMALL SIGNAL BOARD
CX410	243372		CAPCC +/-5% 50V 100PF	SMALL SIGNAL BOARD
CX500	259627		CAP LYTC (SMD) 47UF 16V 85C	SMALL SIGNAL BOARD
CX501	259627		CAP LYTC (SMD) 47UF 16V 85C	SMALL SIGNAL BOARD
CX502	259627		CAP LYTC (SMD) 47UF 16V 85C	SMALL SIGNAL BOARD
CX503	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX504	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX505	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CX506	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CX508	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX509	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CX511	256815		CAPCC 10PF 50V NPO	SMALL SIGNAL BOARD
CX515	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX520	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX530	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX540	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX555	245441		CAPCC 1UF K X7R 16V	SMALL SIGNAL BOARD
CX556	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX560	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX562	259590		CAPCC .022UF 10% 25V X7R	SMALL SIGNAL BOARD
CX565	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX570	190552		CAPCC .1UF K X7R 50V	SMALL SIGNAL BOARD
CX572	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX580	190552		CAPCC .1UF K X7R 50V	SMALL SIGNAL BOARD
CX582	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX585	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX586	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX588	190552		CAPCC .1UF K X7R 50V	SMALL SIGNAL BOARD
CX592	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX595	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX596	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX600	259627		CAP LYTC (SMD) 47UF 16V 85C	SMALL SIGNAL BOARD
CX601	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX602	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CX605	259627		CAP LYTC (SMD) 47UF 16V 85C	SMALL SIGNAL BOARD
CX606	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX607	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CX610	258697		CAP LYTC-SMD 10UF 20% 16V 85C	SMALL SIGNAL BOARD
CX611	259590		CAPCC .022UF 10% 25V X7R	SMALL SIGNAL BOARD
CX612	256817		CAPCC 47PF J NPO 50V	SMALL SIGNAL BOARD
CX620	258697		CAP LYTC-SMD 10UF 20% 16V 85C	SMALL SIGNAL BOARD
CX621	259590		CAPCC .022UF 10% 25V X7R	SMALL SIGNAL BOARD
CX622	256817		CAPCC 47PF J NPO 50V	SMALL SIGNAL BOARD
CX630	258697		CAP LYTC-SMD 10UF 20% 16V 85C	SMALL SIGNAL BOARD
CX631	259590		CAPCC .022UF 10% 25V X7R	SMALL SIGNAL BOARD
CX632	256817		CAPCC 47PF J NPO 50V	SMALL SIGNAL BOARD
CX650	259561		CAP LYTC SMD 1UF 20% 50V 85C	SMALL SIGNAL BOARD
CX651	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX656	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX671	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX673	253797		CAPCC .22UF 10% 10V	SMALL SIGNAL BOARD
CX676	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX700	259627		CAP LYTC (SMD) 47UF 16V 85C	SMALL SIGNAL BOARD
CX701	259627		CAP LYTC (SMD) 47UF 16V 85C	SMALL SIGNAL BOARD
CX702	259627		CAP LYTC (SMD) 47UF 16V 85C	SMALL SIGNAL BOARD
CX703	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX704	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX705	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
CX706	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CX708	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX709	256775		CAPCC .01UF K X7R 50V	SMALL SIGNAL BOARD
CX710	256815		CAPCC 10PF 50V NPO	SMALL SIGNAL BOARD
CX711	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX720	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX730	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX740	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX751	259590		CAPCC .022UF 10% 25V X7R	SMALL SIGNAL BOARD
CX760	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX762	259590		CAPCC .022UF 10% 25V X7R	SMALL SIGNAL BOARD
CX766	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX772	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX775	245441		CAPCC 1UF K X7R 16V	SMALL SIGNAL BOARD
CX776	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX781	259590		CAPCC .022UF 10% 25V X7R	SMALL SIGNAL BOARD
CX782	259590		CAPCC .022UF 10% 25V X7R	SMALL SIGNAL BOARD
CX785	259590		CAPCC .022UF 10% 25V X7R	SMALL SIGNAL BOARD
CX786	259590		CAPCC .022UF 10% 25V X7R	SMALL SIGNAL BOARD
CX787	259590		CAPCC .022UF 10% 25V X7R	SMALL SIGNAL BOARD
CX792	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX795	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX796	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX950	253796		CAPCC .1UF 10% 16V	SMALL SIGNAL BOARD
CX952	259590		CAPCC .022UF 10% 25V X7R	SMALL SIGNAL BOARD
CY500	230978		CAP LYTC 100UF M 16V	MPEG CBA
CY501	243359		CAPCC .1UF Z Y5V 16V	MPEG CBA
CY502	230978		CAP LYTC 100UF M 16V	MPEG CBA
CY503	243359		CAPCC .1UF Z Y5V 16V	MPEG CBA
CY617	232251		CAP LYTC 47UF M 16V	MPEG CBA
DA01	198589		DIODE 1N4148	CONVERGENCE AMP BOARD
DA02	198589		DIODE 1N4148	CONVERGENCE AMP BOARD
DA03	198589		DIODE 1N4148	CONVERGENCE AMP BOARD
DA05	244870		DIODE	CONVERGENCE AMP BOARD
DA06	244870		DIODE	CONVERGENCE AMP BOARD
DA08	223783		DIODE ZENER 6.2V .5W	CONVERGENCE AMP BOARD
DA09	223783		DIODE ZENER 6.2V .5W	CONVERGENCE AMP BOARD
DA10	198589		DIODE 1N4148	CONVERGENCE AMP BOARD
DA11	198589		DIODE 1N4148	CONVERGENCE AMP BOARD
DA110	259551		DIODE	SMALL SIGNAL BOARD
DA130	206077		DIODE	SMALL SIGNAL BOARD
DA131	206077		DIODE	SMALL SIGNAL BOARD
DA145	206077		DIODE	SMALL SIGNAL BOARD
DA170	219249		DIODE ZENER 5.1V .5W	SMALL SIGNAL BOARD
DA171	259215		IC, ESD PROTECTOR	SMALL SIGNAL BOARD
DA172	259215		IC, ESD PROTECTOR	SMALL SIGNAL BOARD
DA200	206077		DIODE	SMALL SIGNAL BOARD
DA201	206077		DIODE	SMALL SIGNAL BOARD
DA202	206077		DIODE	SMALL SIGNAL BOARD
DA203	258700		DIODE, SMD ZENER: 12V 1/2W	SMALL SIGNAL BOARD
DA204	206077		DIODE	SMALL SIGNAL BOARD
DA50	198589		DIODE 1N4148	CONVERGENCE AMP BOARD
DA51	198589		DIODE 1N4148	CONVERGENCE AMP BOARD
DA52	198589		DIODE 1N4148	CONVERGENCE AMP BOARD
DA53	244870		DIODE	CONVERGENCE AMP BOARD
DA56	223783		DIODE ZENER 6.2V .5W	CONVERGENCE AMP BOARD
DA57	223783		DIODE ZENER 6.2V .5W	CONVERGENCE AMP BOARD
DA58	244870		DIODE	CONVERGENCE AMP BOARD
DA59	198589		DIODE 1N4148	CONVERGENCE AMP BOARD
DA60	198589		DIODE 1N4148	CONVERGENCE AMP BOARD
DAMPER	259182		DOOR GEAR DAMPER	INSTRUMENT ASSEMBLY
DAMPER	CAP259184		CAP, DAMPER GEAR- A/V DOOR	INSTRUMENT ASSEMBLY
DB01	198589		DIODE 1N4148	CONVERGENCE AMP BOARD
DB02	198589		DIODE 1N4148	CONVERGENCE AMP BOARD
DB03	198589		DIODE 1N4148	CONVERGENCE AMP BOARD
DB05	244870		DIODE	CONVERGENCE AMP BOARD

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
DB06	244870		DIODE	CONVERGENCE AMP BOARD
DB08	223783		DIODE ZENER 6.2V .5W	CONVERGENCE AMP BOARD
DB09	223783		DIODE ZENER 6.2V .5W	CONVERGENCE AMP BOARD
DB10	198589		DIODE 1N4148	CONVERGENCE AMP BOARD
DB106	198589		DIODE 1N4148	KINE DRIVER RED W/SVM
DB11	198589		DIODE 1N4148	CONVERGENCE AMP BOARD
DB140	198589		DIODE 1N4148	KINE DRIVER RED W/SVM
DB151	230757		DIODE	KINE DRIVER RED W/SVM
DB152	230757		DIODE	KINE DRIVER RED W/SVM
DB153	230757		DIODE	KINE DRIVER RED W/SVM
DB154	230757		DIODE	KINE DRIVER RED W/SVM
DB160	198589		DIODE 1N4148	KINE DRIVER RED W/SVM
DB162	198589		DIODE 1N4148	KINE DRIVER RED W/SVM
DB164	230757		DIODE	KINE DRIVER RED W/SVM
DB166	259552		DIODE, ZENER: 100V 1.3W	KINE DRIVER RED W/SVM
DB167	259232		DIODE	KINE DRIVER RED W/SVM
DB168	259232		DIODE	KINE DRIVER RED W/SVM
DB206	198589		DIODE 1N4148	KINE DRIVER GREEN W/SVM
DB240	198589		DIODE 1N4148	KINE DRIVER GREEN W/SVM
DB251	230757		DIODE	KINE DRIVER GREEN W/SVM
DB252	230757		DIODE	KINE DRIVER GREEN W/SVM
DB253	230757		DIODE	KINE DRIVER GREEN W/SVM
DB254	230757		DIODE	KINE DRIVER GREEN W/SVM
DB260	198589		DIODE 1N4148	KINE DRIVER GREEN W/SVM
DB262	198589		DIODE 1N4148	KINE DRIVER GREEN W/SVM
DB264	230757		DIODE	KINE DRIVER GREEN W/SVM
DB266	259552		DIODE, ZENER: 100V 1.3W	KINE DRIVER GREEN W/SVM
DB267	259232		DIODE	KINE DRIVER GREEN W/SVM
DB268	259232		DIODE	KINE DRIVER GREEN W/SVM
DB306	198589		DIODE 1N4148	KINE DRIVER BLUE W/SVM
DB340	198589		DIODE 1N4148	KINE DRIVER BLUE W/SVM
DB351	230757		DIODE	KINE DRIVER BLUE W/SVM
DB352	230757		DIODE	KINE DRIVER BLUE W/SVM
DB353	230757		DIODE	KINE DRIVER BLUE W/SVM
DB354	230757		DIODE	KINE DRIVER BLUE W/SVM
DB360	198589		DIODE 1N4148	KINE DRIVER BLUE W/SVM
DB362	198589		DIODE 1N4148	KINE DRIVER BLUE W/SVM
DB364	230757		DIODE	KINE DRIVER BLUE W/SVM
DB366	259552		DIODE, ZENER: 100V 1.3W	KINE DRIVER BLUE W/SVM
DB367	259232		DIODE	KINE DRIVER BLUE W/SVM
DB368	259232		DIODE	KINE DRIVER BLUE W/SVM
DB50	198589		DIODE 1N4148	CONVERGENCE AMP BOARD
DB51	198589		DIODE 1N4148	CONVERGENCE AMP BOARD
DB52	198589		DIODE 1N4148	CONVERGENCE AMP BOARD
DB53	244870		DIODE	CONVERGENCE AMP BOARD
DB56	223783		DIODE ZENER 6.2V .5W	CONVERGENCE AMP BOARD
DB57	223783		DIODE ZENER 6.2V .5W	CONVERGENCE AMP BOARD
DB58	244870		DIODE	CONVERGENCE AMP BOARD
DB59	198589		DIODE 1N4148	CONVERGENCE AMP BOARD
DB60	198589		DIODE 1N4148	CONVERGENCE AMP BOARD
DD100	232709		DIODE	MPEG CBA
DD101	229644		DIODE	MPEG CBA
DD102	232709		DIODE	MPEG CBA
DD103	232710		DIODE, ZENER 6.8V .5W	MPEG CBA
DF011	259223		DIODE	P-S/DEFLECTION
DF031	244870		DIODE	P-S/DEFLECTION
DF033	244870		DIODE	P-S/DEFLECTION
DG01	198589		DIODE 1N4148	CONVERGENCE AMP BOARD
DG02	198589		DIODE 1N4148	CONVERGENCE AMP BOARD
DG03	198589		DIODE 1N4148	CONVERGENCE AMP BOARD
DG05	244870		DIODE	CONVERGENCE AMP BOARD
DG06	244870		DIODE	CONVERGENCE AMP BOARD
DG08	223783		DIODE ZENER 6.2V .5W	CONVERGENCE AMP BOARD
DG09	223783		DIODE ZENER 6.2V .5W	CONVERGENCE AMP BOARD
DG10	198589		DIODE 1N4148	CONVERGENCE AMP BOARD
DG101	198589		DIODE 1N4148	KINE DRIVER RED W/SVM

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
DG102	198589		DIODE 1N4148	KINE DRIVER RED W/SVM
DG11	198589		DIODE 1N4148	CONVERGENCE AMP BOARD
DG136	198589		DIODE 1N4148	KINE DRIVER RED W/SVM
DG137	198589		DIODE 1N4148	KINE DRIVER RED W/SVM
DG200	232219		DIODE	MPEG CBA
DG201	198589		DIODE 1N4148	KINE DRIVER GREEN W/SVM
DG201	232219		DIODE	MPEG CBA
DG202	198589		DIODE 1N4148	KINE DRIVER GREEN W/SVM
DG202	260032		DIODE	MPEG CBA
DG236	198589		DIODE 1N4148	KINE DRIVER GREEN W/SVM
DG237	198589		DIODE 1N4148	KINE DRIVER GREEN W/SVM
DG301	198589		DIODE 1N4148	KINE DRIVER BLUE W/SVM
DG302	198589		DIODE 1N4148	KINE DRIVER BLUE W/SVM
DG336	198589		DIODE 1N4148	KINE DRIVER BLUE W/SVM
DG337	198589		DIODE 1N4148	KINE DRIVER BLUE W/SVM
DG50	198589		DIODE 1N4148	CONVERGENCE AMP BOARD
DG501	229644		DIODE	MPEG CBA
DG502	229644		DIODE	MPEG CBA
DG504	232709		DIODE	MPEG CBA
DG51	198589		DIODE 1N4148	CONVERGENCE AMP BOARD
DG52	198589		DIODE 1N4148	CONVERGENCE AMP BOARD
DG53	244870		DIODE	CONVERGENCE AMP BOARD
DG56	223783		DIODE ZENER 6.2V .5W	CONVERGENCE AMP BOARD
DG60	198589		DIODE 1N4148	CONVERGENCE AMP BOARD
DDH010	259224		DIODE, SMD ZENER: 33V 1/2W	SMALL SIGNAL BOARD
DIAPHRAGM	254599		DIAPHRAGM,COOLANT: 7" PROJ CRT	OPTICS ASSEMBLY
DK005	198589		DIODE	FRONT PANEL 1
DK006	215488		DIODE ZENER 5.6V .5W	FRONT PANEL 1
DK08	206077		DIODE	CONVERGENCE SIGNAL BOAR
DK09	259973		DIODE, ZENER: 3.9V 1.3W	CONVERGENCE SIGNAL BOAR
DK10	206077		DIODE	CONVERGENCE SIGNAL BOAR
DL001	198589		DIODE	P-S/DEFLECTION
DL012	244834		DIODE	P-S/DEFLECTION
DL028	259231		DIODE	P-S/DEFLECTION
DL029	259238		DIODE	P-S/DEFLECTION
DL030	259875		DIODE	P-S/DEFLECTION
DL032	259638		DIODE	P-S/DEFLECTION
DL034	259601		DIODE	P-S/DEFLECTION
DL036	259601		DIODE	P-S/DEFLECTION
DL043	230757		DIODE	P-S/DEFLECTION
DL073	198589		DIODE	P-S/DEFLECTION
DL074	231865		DIODE ZENER 3.9V .5W	P-S/DEFLECTION
DL075	231865		DIODE ZENER 3.9V .5W	P-S/DEFLECTION
DL100	198589		DIODE	P-S/DEFLECTION
DL104	244870		DIODE	P-S/DEFLECTION
DL105	244870		DIODE	P-S/DEFLECTION
DL106	244870		DIODE	P-S/DEFLECTION
DL141	226463		DIODE, ZENER 18V .5W	P-S/DEFLECTION
DL201	258740		DIODE	P-S/DEFLECTION
DL221	259984		DIODE	P-S/DEFLECTION
DL222	259231		DIODE	P-S/DEFLECTION
DL231	259234		DIODE	P-S/DEFLECTION
DL251	259984		DIODE	P-S/DEFLECTION
DL252	259231		DIODE	P-S/DEFLECTION
DL301	259971		DIODE, ZENER: 24V 1.3W	P-S/DEFLECTION
DL302	244870		DIODE	P-S/DEFLECTION
DL303	244870		DIODE	P-S/DEFLECTION
DL306	NONSTK		WIRE JUMPER	P-S/DEFLECTION
DOOR	258664		DOOR, A/V IN	INSTRUMENT ASSEMBLY
DOOR	258801		DOOR, DVD	INSTRUMENT ASSEMBLY
DOOR LOCK	259187		DOOR LOCK	INSTRUMENT ASSEMBLY
DDP020	259234		DIODE	P-S/DEFLECTION
DDP021	256971		DIODE	P-S/DEFLECTION
DDP022	239132		DIODE ZENER 10V 1.3W	P-S/DEFLECTION
DDP023	230757		DIODE	P-S/DEFLECTION
DDP029	198589		DIODE	P-S/DEFLECTION

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
DP030	198589		DIODE	P-S/DEFLECTION
DP033	198589		DIODE	P-S/DEFLECTION
DP051	259865		DIODE	P-S/DEFLECTION
DP053	223694		DIODE ZENER 15V .5W	P-S/DEFLECTION
DP060	198589		DIODE	P-S/DEFLECTION
DP061	244834		DIODE	P-S/DEFLECTION
DP080	198589		DIODE	P-S/DEFLECTION
DP081	198589		DIODE	P-S/DEFLECTION
DP110	259646		DIODE	P-S/DEFLECTION
DP111	258740		DIODE	P-S/DEFLECTION
DP113	259865		DIODE	P-S/DEFLECTION
DP114	258740		DIODE	P-S/DEFLECTION
DP120	259868		DIODE	P-S/DEFLECTION
DP130	259868		DIODE	P-S/DEFLECTION
DP135	259868		DIODE	P-S/DEFLECTION
DP140	259632		DIODE	P-S/DEFLECTION
DP150	259632		DIODE	P-S/DEFLECTION
DP160	198589		DIODE	P-S/DEFLECTION
DP161	198589		DIODE	P-S/DEFLECTION
DP170	198589		DIODE	P-S/DEFLECTION
DP171	198589		DIODE	P-S/DEFLECTION
DP178	198589		DIODE	P-S/DEFLECTION
DP179	198589		DIODE	P-S/DEFLECTION
DP180	198589		DIODE	P-S/DEFLECTION
DP191	198589		DIODE	P-S/DEFLECTION
DP193	198589		DIODE	P-S/DEFLECTION
DP197	198589		DIODE	P-S/DEFLECTION
DP20	230757		DIODE	CONVERGENCE PS / ADAPTE
DP200	198589		DIODE	P-S/DEFLECTION
DP211	198589		DIODE	P-S/DEFLECTION
DP220	244834		DIODE	P-S/DEFLECTION
DP221	198589		DIODE	P-S/DEFLECTION
DP222	198589		DIODE	P-S/DEFLECTION
DP225	198589		DIODE	P-S/DEFLECTION
DP23	223694		DIODE	CONVERGENCE PS / ADAPTE
DP230	198589		DIODE	P-S/DEFLECTION
DP24	223694		DIODE	CONVERGENCE PS / ADAPTE
DP240	244834		DIODE	P-S/DEFLECTION
DP241	244834		DIODE	P-S/DEFLECTION
DP30	198589		DIODE 1N4148	CONVERGENCE PS / ADAPTE
DP301	259982		DIODE	SMPS - DVD
DP302	259982		DIODE	SMPS - DVD
DP303	259982		DIODE	SMPS - DVD
DP304	259982		DIODE	SMPS - DVD
DP31	259955		DIODE, ZENER: 16V 1.3W	CONVERGENCE PS / ADAPTE
DP32	259955		DIODE, ZENER: 16V 1.3W	CONVERGENCE PS / ADAPTE
DP320	260041		DIODE, ZENER: 15V 1.3W	SMPS - DVD
DP323	232545		DIODE ZENER 8.2V .5W	SMPS - DVD
DP324	244836		DIODE ZENER 24V .5W	SMPS - DVD
DP325	244834		DIODE	SMPS - DVD
DP330	232545		DIODE ZENER 8.2V .5W	SMPS - DVD
DP333	223694		DIODE ZENER 15V .5W	SMPS - DVD
DP337	244834		DIODE	SMPS - DVD
DP342	230757		DIODE	SMPS - DVD
DP359	244834		DIODE	SMPS - DVD
DP360	244834		DIODE	SMPS - DVD
DP361	244870		DIODE	SMPS - DVD
DP362	244834		DIODE	SMPS - DVD
DP363	244834		DIODE	SMPS - DVD
DP365	224903		DIODE	SMPS - DVD
DP368	198589		DIODE	SMPS - DVD
DP37	NONSTK		WIREBARE 22	CONVERGENCE PS / ADAPTE
DP38	226456		DIODE ZENER	CONVERGENCE PS / ADAPTE
DP39	198589		DIODE 1N4148	CONVERGENCE PS / ADAPTE
DP390	244834		DIODE	SMPS - DVD
DP392	198597		DIODE	SMPS - DVD

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
DP40	198589		DIODE 1N4148	CONVERGENCE PS / ADAPTE
DP400	259877		DIODE, FULL WAVE BRIDGE	MAINS INPUT DOUBLER
DP41	198589		DIODE 1N4148	CONVERGENCE PS / ADAPTE
DP410	257783		DIODE	MAINS INPUT DOUBLER
DP411	257783		DIODE	MAINS INPUT DOUBLER
DP44	198589		DIODE 1N4148	CONVERGENCE PS / ADAPTE
DP45	198589		DIODE 1N4148	CONVERGENCE PS / ADAPTE
DP46	198589		DIODE 1N4148	CONVERGENCE PS / ADAPTE
DP47	198589		DIODE 1N4148	CONVERGENCE PS / ADAPTE
DP48	198589		DIODE 1N4148	CONVERGENCE PS / ADAPTE
DP49	198589		DIODE 1N4148	CONVERGENCE PS / ADAPTE
DP501	206077		DIODE	SMALL SIGNAL BOARD
DP510	206077		DIODE	SMALL SIGNAL BOARD
DP520	259553		DIODE, ZENER(SMD): 10V 1/2W	SMALL SIGNAL BOARD
DP521	206077		DIODE	SMALL SIGNAL BOARD
DP530	206077		DIODE	SMALL SIGNAL BOARD
DP540	206077		DIODE	SMALL SIGNAL BOARD
DP60	244834		DIODE	CONVERGENCE PS / ADAPTE
DP601	198589		DIODE	MAINS INPUT DOUBLER
DP65	244834		DIODE	CONVERGENCE PS / ADAPTE
DP70	259246		DIODE	CONVERGENCE PS / ADAPTE
DP75	259246		DIODE	CONVERGENCE PS / ADAPTE
DP87	259226		DIODE, ZENER: 5.1V 1/2W	CONVERGENCE PS / ADAPTE
DRIP PAD	259163		DRIP PAD, 22" X 2.5"	INSTRUMENT ASSEMBLY
DRIP PAD	259164		DRIP PAD, 1.5" X 7"	INSTRUMENT ASSEMBLY
DT001	232709		DIODE	DIGITAL READY INTERFACE
DT161	232709		DIODE	MPEG CBA
DT201	259555		DIODE, ZENER(SMD): 6.8V 1/2W	DIGITAL READY INTERFACE
DT202	259555		DIODE, ZENER(SMD): 6.8V 1/2W	DIGITAL READY INTERFACE
DT203	259550		DIODE	DIGITAL READY INTERFACE
DT204	259555		DIODE, ZENER(SMD): 6.8V 1/2W	DIGITAL READY INTERFACE
DT205	259555		DIODE, ZENER(SMD): 6.8V 1/2W	DIGITAL READY INTERFACE
DT206	259550		DIODE	DIGITAL READY INTERFACE
DT207	259550		DIODE	DIGITAL READY INTERFACE
DT208	259550		DIODE	DIGITAL READY INTERFACE
DT501	232709		DIODE	DIGITAL READY INTERFACE
DT503	232709		DIODE	DIGITAL READY INTERFACE
DT601	232709		DIODE	DIGITAL READY INTERFACE
DT602	259555		DIODE, ZENER(SMD): 6.8V 1/2W	DIGITAL READY INTERFACE
DT603	259555		DIODE, ZENER(SMD): 6.8V 1/2W	DIGITAL READY INTERFACE
DT604	259555		DIODE, ZENER(SMD): 6.8V 1/2W	DIGITAL READY INTERFACE
DV01	244870		DIODE	CONVERGENCE PS / ADAPTE
DV02	244870		DIODE	CONVERGENCE PS / ADAPTE
DV03	244870		DIODE	CONVERGENCE PS / ADAPTE
DV110	206077		DIODE	SMALL SIGNAL BOARD
DV111	206077		DIODE	SMALL SIGNAL BOARD
DV20	198589		DIODE 1N4148	CONVERGENCE PS / ADAPTE
DV21	198589		DIODE 1N4148	CONVERGENCE PS / ADAPTE
DV22	198589		DIODE 1N4148	CONVERGENCE PS / ADAPTE
DV23	198589		DIODE 1N4148	CONVERGENCE PS / ADAPTE
DV24	198589		DIODE 1N4148	CONVERGENCE PS / ADAPTE
DV25	198589		DIODE 1N4148	CONVERGENCE PS / ADAPTE
DV270	259554		DIODE, ZENER(SMD): 3.9V 1/2W	SMALL SIGNAL BOARD
DV271	259550		DIODE	SMALL SIGNAL BOARD
DV276	259550		DIODE	SMALL SIGNAL BOARD
DV30	198589		DIODE 1N4148	CONVERGENCE PS / ADAPTE
DV50	198589		DIODE 1N4148	CONVERGENCE PS / ADAPTE
DV52	198589		DIODE 1N4148	CONVERGENCE PS / ADAPTE
DV520	206077		DIODE	SMALL SIGNAL BOARD
DV521	206077		DIODE	SMALL SIGNAL BOARD
DV523	206077		DIODE	SMALL SIGNAL BOARD
DV53	198589		DIODE 1N4148	CONVERGENCE PS / ADAPTE
DV530	259551		DIODE	SMALL SIGNAL BOARD
DV532	259551		DIODE	SMALL SIGNAL BOARD
DV533	206077		DIODE	SMALL SIGNAL BOARD
DV534	206077		DIODE	SMALL SIGNAL BOARD

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
DV535	206077		DIODE	SMALL SIGNAL BOARD
DV536	206077		DIODE	SMALL SIGNAL BOARD
DV70	237523		DIODE ZENER	CONVERGENCE PS / ADAPTE
DV80	198589		DIODE 1N4148	CONVERGENCE PS / ADAPTE
DV85	258728		DIODE	CONVERGENCE PS / ADAPTE
DV86	258728		DIODE	CONVERGENCE PS / ADAPTE
DV90	244870		DIODE	CONVERGENCE PS / ADAPTE
DV91	259955		DIODE, ZENER: 16V 1.3W	CONVERGENCE PS / ADAPTE
DV92	256971		DIODE	CONVERGENCE PS / ADAPTE
DV93	244870		DIODE	CONVERGENCE PS / ADAPTE
DVD	257124		MECHANISM DVD TVM502	DVD MECHANISM
DVD ASSY	258816		DVD ASY W/MPEG & A/V INT CBAS	DVD MODULE
DVD TOOL	258804		TOOL, DVD REMOVAL	INSTRUMENT ASSEMBLY
DVD TRIM	258805		FRONT TRIM FOR DVD TRAY	INSTRUMENT ASSEMBLY
DW12	232545		DIODE ZENER	CONVERGENCE AMP BOARD
DX002	198589		DIODE	FRONT PANEL 1
DX003	198589		DIODE	FRONT PANEL 1
DX004	198589		DIODE	FRONT PANEL 1
DX130	259555		DIODE, ZENER(SMD): 6.8V 1/2W	SMALL SIGNAL BOARD
DX131	259555		DIODE, ZENER(SMD): 6.8V 1/2W	SMALL SIGNAL BOARD
DX610	259555		DIODE, ZENER(SMD): 6.8V 1/2W	SMALL SIGNAL BOARD
DX611	259555		DIODE, ZENER(SMD): 6.8V 1/2W	SMALL SIGNAL BOARD
DX620	259555		DIODE, ZENER(SMD): 6.8V 1/2W	SMALL SIGNAL BOARD
DX621	259555		DIODE, ZENER(SMD): 6.8V 1/2W	SMALL SIGNAL BOARD
DX630	259555		DIODE, ZENER(SMD): 6.8V 1/2W	SMALL SIGNAL BOARD
DX631	259555		DIODE, ZENER(SMD): 6.8V 1/2W	SMALL SIGNAL BOARD
DX930	259555		DIODE, ZENER(SMD): 6.8V 1/2W	SMALL SIGNAL BOARD
DX940	259555		DIODE, ZENER(SMD): 6.8V 1/2W	SMALL SIGNAL BOARD
ENCLOSURE	258906		SPEAKER ENCLOSURE, RIGHT	INSTRUMENT ASSEMBLY
ENCLOSURE	259175		SPEAKER ENCLOSURE, LEFT	INSTRUMENT ASSEMBLY
END CAP	258673		END CAP, CONTROL PANEL: LEFT	INSTRUMENT ASSEMBLY
END CAP	258674		END CAP, CONTROL PANEL: RIGHT	INSTRUMENT ASSEMBLY
FA010	259492		CHOKE, QUAD (SMD)	SMALL SIGNAL BOARD
FA030	259492		CHOKE, QUAD (SMD)	SMALL SIGNAL BOARD
FA160	259492		CHOKE, QUAD (SMD)	SMALL SIGNAL BOARD
FA401	240152		FILTER	MPEG CBA
FB101	258699		DELAY LINE	KINE DRIVER RED W/SVM
FB201	258699		DELAY LINE	KINE DRIVER GREEN W/SVM
FB301	258699		DELAY LINE	KINE DRIVER BLUE W/SVM
FE216	240154		FILTER	MPEG CBA
FERRITE	245493		CORE FERRITE	INSTRUMENT ASSEMBLY
FERRITE	258922		FILTER, FERRITE CORE CLAMP	INSTRUMENT ASSEMBLY
FERRITE CORE	215696		CORE, FERRITE: 26MM DIAMETER	DVD CABLING & SUPPORT A
FERRITE CORE	258972		FERRITE CORE: 22.5MM DIAMETER	DVD CABLING & SUPPORT A
FERRITE CORE	258952		FERRITE CORE FOR RIBBON CABLE	DVD CABLING & SUPPORT A
FG161	240154		FILTER	MPEG CBA
FH122	240152		FILTER	MPEG CBA
FFI007	259256		FILTER, SIF	SMALL SIGNAL BOARD
FFI025	259257		FILTER, VIF	SMALL SIGNAL BOARD
FFI028	259621		FILTER, 91.5MHZ	SMALL SIGNAL BOARD
FFI525	259257		FILTER, VIF	SMALL SIGNAL BOARD
FFI528	259621		FILTER, 91.5MHZ	SMALL SIGNAL BOARD
FFL100	259212		FUSE, 250MA 125V	P-S/DEFLECTION
FFL221	259214		FUSE, 1.25A 125V	P-S/DEFLECTION
FFL231	259213		FUSE, 400MA 125V	P-S/DEFLECTION
FFL251	259214		FUSE, 1.25A 125V	P-S/DEFLECTION
FFLOOR	259170		CABINET FLOOR	INSTRUMENT ASSEMBLY
FFP360	259219		FUSE, 3.15A 125V	SMPS - DVD
FFP361	259217		FUSE, 1A 125V	SMPS - DVD
FFP362	259219		FUSE, 3.15A 125V	SMPS - DVD
FFP390	259218		FUSE, 2.5A 125V	SMPS - DVD
FFP400	259216		FUSE, 6A 125V	MAINS INPUT DOUBLER
FFP520	259214		FUSE, 1.25A 125V	SMALL SIGNAL BOARD
FFP521	259214		FUSE, 1.25A 125V	SMALL SIGNAL BOARD
FFP602	259211		FUSE, 1A 250V	MAINS INPUT DOUBLER
FFRAME	259206		INNER FRAME, LOWER	INSTRUMENT ASSEMBLY

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
FT201	259492		CHOKE, QUAD (SMD)	DIGITAL READY INTERFACE
FT202	259492		CHOKE, QUAD (SMD)	DIGITAL READY INTERFACE
FT400	259905		DELAY LINE	DIGITAL READY INTERFACE
FT940	259492		CHOKE, QUAD (SMD)	DIGITAL READY INTERFACE
FT960	259492		CHOKE, QUAD (SMD)	DIGITAL READY INTERFACE
FU001	259850		CRYSTAL, 24.576MHZ	SMALL SIGNAL BOARD
FU023	259850		CRYSTAL, 24.576MHZ	SMALL SIGNAL BOARD
FU030	259849		CRYSTAL, 27MHZ	SMALL SIGNAL BOARD
FV90	259213		FUSE, 400MA 125V	CONVERGENCE PS / ADAPTE
FX100	259492		CHOKE, QUAD (SMD)	SMALL SIGNAL BOARD
FX300	259492		CHOKE, QUAD (SMD)	SMALL SIGNAL BOARD
FX600	259492		CHOKE, QUAD (SMD)	SMALL SIGNAL BOARD
GK002	257862		LED, GREEN	FRONT PANEL 1
GK201	259938		IC, REMOTE PREAMP	IR PREAMP
GRILLE	263118		SPEAKER GRILLE W/ CLOTH	INSTRUMENT ASSEMBLY
HA130	259915		CABLE, 9-CONDUCTOR 420MM	CHASSIS ASSEMBLY
HA150	258780		CABLE, AC POWER CORD	INSTRUMENT ASSEMBLY
HA160	259887		CABLE, 1-CONDUCTOR 460MM	CHASSIS ASSEMBLY
HA180	259911		CABLE, 2-CONDUCTOR BL/BN 380MM	CHASSIS ASSEMBLY
HA200	259918		CABLE, 6-CONDUCTOR 580MM	CHASSIS ASSEMBLY
HA210	259919		CABLE, 5-CONDUCTOR 300MM	CHASSIS ASSEMBLY
HA220	259920		CABLE, 5-CONDUCTOR 260MM	CHASSIS ASSEMBLY
HA230	259880		CABLE, RIBBON: 25-CONDUCTOR	CHASSIS ASSEMBLY
HA240	259851		CABLE, RIBBON: 21-CONDUCTOR	CHASSIS ASSEMBLY
HA250	259942		CABLE, 7-CONDUCTOR 380MM	CHASSIS ASSEMBLY
HA260	263133		CABLE, 10-CONDUCTOR 1300MM	CHASSIS ASSEMBLY
HA280	263134		CABLE, 3-CONDUCTOR 1400MM	CHASSIS ASSEMBLY
HA290	259889		CABLE, RIBBON: 11-COND 160MM	CHASSIS ASSEMBLY
HA300	259890		CABLE, RIBBON: 21-COND 200MM	CHASSIS ASSEMBLY
HA310	259927		CABLE, 4-CONDUCTOR 180MM	CHASSIS ASSEMBLY
HA320	259912		CABLE, 6-CONDUCTOR 160MM	CHASSIS ASSEMBLY
HA380	259940		CABLE, 7-CONDUCTOR 140MM	CHASSIS ASSEMBLY
HA390	259941		CABLE, 6-CONDUCTOR 220MM	CHASSIS ASSEMBLY
HA400	258830		CABLE ASSY, 6-CONDUCTOR 260MM	CHASSIS ASSEMBLY
HA410	259145		CABLE, 2-CONDUCTOR 580MM	CHASSIS ASSEMBLY
HA420	263103		CABLE, 9-CONDUCTOR 1100MM	INSTRUMENT ASSEMBLY
HA430	263104		CABLE, 2-CONDUCTOR 1100MM	INSTRUMENT ASSEMBLY
HA440	263105		CABLE, 3-CONDUCTOR 1400MM	INSTRUMENT ASSEMBLY
HA450	263106		CABLE, 3-CONDUCTOR 720MM	INSTRUMENT ASSEMBLY
HA460	259150		CABLE, 8-CONDUCTOR 380MM	INSTRUMENT ASSEMBLY
HA470	258830		CABLE ASSY, 6-CONDUCTOR 260MM	CHASSIS ASSEMBLY
HA500	259151		CABLE, RIBBON: 11-COND 350MM	INSTRUMENT ASSEMBLY
HA510	259943		CABLE, 2-CONDUCTOR 740MM	CHASSIS ASSEMBLY
HA560	258632		CABLE ASSY, P11901/LEFT SPKR	INSTRUMENT ASSEMBLY
HA570	258633		CABLE ASSY, P11902/RIGHT SPKR	INSTRUMENT ASSEMBLY
HA600	259152		CABLE, 9-CONDUCTOR 500MM (RED)	INSTRUMENT ASSEMBLY
HA610	259153		CABLE, 9-CONDUCTOR 500MM (GRN)	INSTRUMENT ASSEMBLY
HA620	259154		CABLE, 9-CONDUCTOR 500MM (BLU)	INSTRUMENT ASSEMBLY
HA630	258939		CABLE, 7-CONDUCTOR 460MM	INSTRUMENT ASSEMBLY
HA640	258908		CABLE ASSY, 7-CONDUCTOR 340MM	INSTRUMENT ASSEMBLY
HA650	258915		CABLE ASSY, 7-CONDUCTOR 380MM	INSTRUMENT ASSEMBLY
HA660	259155		CABLE, FOC/SCRN CONTROL GROUND	OPTICS ASSEMBLY
HA665	258810		CABLE, 220MM	OPTICS ASSEMBLY
HA670	259931		CABLE, 10-CONDUCTOR 300MM	CHASSIS ASSEMBLY
HA680	259914		CABLE, 2-CONDUCTOR OR/GN 460MM	CHASSIS ASSEMBLY
HA690	259913		CABLE, 2-CONDUCTOR BL/BN 460MM	CHASSIS ASSEMBLY
HA700	260040		ANODE LEAD: IHVT-HV SPLITTER	P-S/DEFLECTION
HA710	259156		CABLE, FOC/SCRN CONTROL INPUT	OPTICS ASSEMBLY
HA720	258920		CABLE, FOC CONT-CONV ADP(BV18)	OPTICS ASSEMBLY
HA730	258919		CABLE, RED CRT DR-SCRN CONTROL	OPTICS ASSEMBLY
HA740	258918		CABLE, GRN CRT DR-SCRN CONTROL	OPTICS ASSEMBLY
HA750	258907		CABLE, BLU CRT DR-SCRN CONTROL	OPTICS ASSEMBLY
HA760	259157		CABLE, FOC CONT TO RED KINE DR	OPTICS ASSEMBLY
HA770	258845		CABLE, GRN CRT DR-FOC CONTROL	OPTICS ASSEMBLY
HA780	259158		CABLE, FOC CONT TO BLU KINE DR	OPTICS ASSEMBLY
HA790	259932		CABLE, 3-CONDUCTOR 300MM	CHASSIS ASSEMBLY

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
HA800	258941		CABLE, 7-CONDUCTOR 340MM	INSTRUMENT ASSEMBLY
HA810	259159		CABLE, 12-CONDUCTOR 300MM	INSTRUMENT ASSEMBLY
HA820	259160		CABLE, 8-CONDUCTOR 300MM	INSTRUMENT ASSEMBLY
HA830	259161		CABLE, 9-CONDUCTOR 500MM	INSTRUMENT ASSEMBLY
HA840	263086		CABLE, 1-CONDUCTOR 500MM	INSTRUMENT ASSEMBLY
HA850	258639		CABLE, HV SPLT GND/TECHBAR GND	INSTRUMENT ASSEMBLY
HA900	258636		CABLE, AUTO CONV W/ SOCKETS	INSTRUMENT ASSEMBLY
HA910	258640		CABLE, AUTO CONV ASY TO J19600	INSTRUMENT ASSEMBLY
HOLDER	259173		HOLDER, CONVERGENCE SIGNAL CBA	INSTRUMENT ASSEMBLY
HOLDER	259174		HOLDER, IR PREAMP CBA	OPTICS ASSEMBLY
HOLDER	259167		HOLDER, CONV AMP/PS/ADPT CBAS	CHASSIS ASSEMBLY
HOUSING	259186		HOUSING, FRONT A/V	INSTRUMENT ASSEMBLY
HV SPLITTER				
	263092		HIGH VOLTAGE SPLITTER	OPTICS ASSEMBLY
IA001	259287		IC, AUDIO PROCESSOR	SMALL SIGNAL BOARD
IA002	258736		IC, AUDIO POWER AMP	SMALL SIGNAL BOARD
IA003	259292		IC, HEADPHONE AMP	SMALL SIGNAL BOARD
IA10	259220		IC	CONVERGENCE AMP BOARD
IA180	259227		IC	SMALL SIGNAL BOARD
IA181	259227		IC	SMALL SIGNAL BOARD
IA405	248945		IC	MPEG CBA
IA500	256782		IC, OP AMP	MPEG CBA
IB101	249239		IC	KINE DRIVER RED W/SVM
IB12	259220		IC	CONVERGENCE AMP BOARD
IB201	249239		IC	KINE DRIVER GREEN W/SVM
IB301	249239		IC	KINE DRIVER BLUE W/SVM
IC500	259624		IC, SIGNAL PROCESSOR	SMALL SIGNAL BOARD
IC700	259624		IC, SIGNAL PROCESSOR	SMALL SIGNAL BOARD
ID100	259988		IC, MOTOR DRIVER	MPEG CBA
IE215	260026		IC, INVERTER	MPEG CBA
IE216	260026		IC, INVERTER	MPEG CBA
IF001	258738		IC, VERTICAL OUTPUT	P-S/DEFLECTION
IG100	260035		IC, MPEG DECODER	MPEG CBA
IG104	260028		IC, DRAM	MPEG CBA
IG11	259220		IC	CONVERGENCE AMP BOARD
IG128	258071		IC, EEPROM	MPEG CBA
IG501	243237		IC	MPEG CBA
IG502	260026		IC, INVERTER	MPEG CBA
IH106	260034		IC, FLASH MEMORY	MPEG CBA
IK001	259042		IC, MICROCONTROLLER	FRONT PANEL 1
IK01	248573		IC	CONVERGENCE SIGNAL BOAR
IK02	259239		IC	CONVERGENCE SIGNAL BOAR
IK03	259239		IC	CONVERGENCE SIGNAL BOAR
IK05	259225		IC, REGULATOR: +3.3V	CONVERGENCE SIGNAL BOAR
IK07	248601		INTEGRATED CKT	CONVERGENCE SIGNAL BOAR
IK08	260088		IC, EEPROM	CONVERGENCE SIGNAL BOAR
IK15	248602		INTEGRATED CKT	CONVERGENCE SIGNAL BOAR
IL140	257786		IC, PHOTOCOUPLER	P-S/DEFLECTION
INSULATOR	259962		INSULATOR, 35MM X 24MM	P-S/DEFLECTION
INSULATOR	258721		INSULATOR	P-S/DEFLECTION
IP020	259275		IC, SWITCHING REGULATOR	P-S/DEFLECTION
IP030	257786		IC, PHOTOCOUPLER	P-S/DEFLECTION
IP050	259273		IC	P-S/DEFLECTION
IP070	257786		IC, PHOTOCOUPLER	P-S/DEFLECTION
IP170	259273		IC	P-S/DEFLECTION
IP190	259273		IC	P-S/DEFLECTION
IP240	259281		IC, PRECISION REFERENCE	P-S/DEFLECTION
IP250	259862		IC, 5V REGULATOR	P-S/DEFLECTION
IP301	257786		IC, PHOTOCOUPLER	SMPS - DVD
IP302	259977		IC, REGULATOR	SMPS - DVD
IP305	257786		IC, PHOTOCOUPLER	SMPS - DVD
IP350	231525		IC, REFERENCE	SMPS - DVD
IP50	257786		IC, PHOTOCOUPLER	CONVERGENCE PS / ADAPTE
IP501	259827		IC	SMALL SIGNAL BOARD
IP510	259827		IC	SMALL SIGNAL BOARD
IP530	259864		IC, 3.3V REGULATOR	SMALL SIGNAL BOARD
IP540	259831		IC	SMALL SIGNAL BOARD

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
IP551	259863		IC, 1.8V REGULATOR	SMALL SIGNAL BOARD
IR001	259286		IC, MICROPROCESSOR	SMALL SIGNAL BOARD
IR005	260086		IC, EEPROM	SMALL SIGNAL BOARD
IR006	256781		IC, BUS EXPANDER	SMALL SIGNAL BOARD
IR040	259284		IC	SMALL SIGNAL BOARD
IR110	259277		IC, DRAM	SMALL SIGNAL BOARD
IR130	259324		IC	SMALL SIGNAL BOARD
IS01	258731		IC	CONVERGENCE SIGNAL BOAR
IS02	258731		IC	CONVERGENCE SIGNAL BOAR
IS03	258731		IC	CONVERGENCE SIGNAL BOAR
ISOLATOR	253458		ISOLATOR RING- SPKR MOUNTING	INSTRUMENT ASSEMBLY
IT001	259289		IC, +5V REGULATOR	DIGITAL READY INTERFACE
IT002	259864		IC, 3.3V REGULATOR	DIGITAL READY INTERFACE
IT003	259831		IC	DIGITAL READY INTERFACE
IT004	259864		IC, 3.3V REGULATOR	DIGITAL READY INTERFACE
IT200	259495		IC	DIGITAL READY INTERFACE
IT210	259221		IC	DIGITAL READY INTERFACE
IT220	259308		IC	DIGITAL READY INTERFACE
IT230	259310		IC	DIGITAL READY INTERFACE
IT240	259318		IC	DIGITAL READY INTERFACE
IT400	258741		IC, VIDEO PROCESSOR	DIGITAL READY INTERFACE
IT500	248541		IC	DIGITAL READY INTERFACE
IT510	248542		IC	DIGITAL READY INTERFACE
IT600	259507		IC, DIGITAL CRT CONTROLLER	DIGITAL READY INTERFACE
IT607	259505		DIODE ARRAY	DIGITAL READY INTERFACE
IT608	259505		DIODE ARRAY	DIGITAL READY INTERFACE
IT620	260087		IC, EEPROM(BLANK)	DIGITAL READY INTERFACE
IT900	259269		IC, AUDIO SWITCH	DIGITAL READY INTERFACE
IU001	259619		IC	SMALL SIGNAL BOARD
IU002	259267		IC	SMALL SIGNAL BOARD
IU003	259267		IC	SMALL SIGNAL BOARD
IU004	259282		IC, PRECISION REFERENCE	SMALL SIGNAL BOARD
IU030	259266		IC, DISPLAY PROCESSOR	SMALL SIGNAL BOARD
IU040	259311		IC	SMALL SIGNAL BOARD
IV10	259625		IC, 12V REGULATOR	CONVERGENCE PS / ADAPTE
IV100	259258		IC, VIDEO PROCESSOR	SMALL SIGNAL BOARD
IV200	259259		IC, VIDEO PROCESSOR	SMALL SIGNAL BOARD
IV520	259619		IC	SMALL SIGNAL BOARD
IV521	259619		IC	SMALL SIGNAL BOARD
IV90	257786		IC, PHOTOCOUPLER	CONVERGENCE PS / ADAPTE
IX600	258730		IC	SMALL SIGNAL BOARD
IX950	259309		IC	SMALL SIGNAL BOARD
IY502	260027		IC	MPEG CBA
IY504	260029		IC, VIDEO SWITCH	MPEG CBA
24J12101	249131		CONNECTOR 2 PIN	AUDIO CROSSOVER
24J12102	226499		CONNECTOR 4 PIN	AUDIO CROSSOVER
JA01	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA02	256783		RES CMF 0 OHM 0% 1/16W	FRONT PANEL 2
JA02	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA03	256783		RES CMF 0 OHM 0% 1/16W	FRONT PANEL 2
JA03	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA04	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA05	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA06	256783		RES CMF 0 OHM 0% 1/16W	FRONT PANEL 2
JA06	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA07	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA08	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA08	256783		RES CMF 0 OHM 0% 1/16W	FRONT PANEL 2
JA09	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA10	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA11	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA12	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA13	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA14	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA15	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA16	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
JA17	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA18	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA19	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA20	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA21	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA22	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA23	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA24	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA25	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA26	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA27	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA28	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA29	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA30	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA31	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA32	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA33	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA34	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA35	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA36	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA37	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA38	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA39	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA40	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA41	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA42	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA43	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA44	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA45	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA46	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA47	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA48	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA49	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA50	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA51	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA52	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA53	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA54	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA55	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA56	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA58	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA59	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA60	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA61	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA62	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA63	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA64	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA65	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA66	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA67	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA68	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA69	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA70	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA71	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA72	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA73	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA74	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA75	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA76	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA78	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JA79	NONSTK		WIREBARE 22	CONVERGENCE AMP BOARD
JB101	256783		RES CMF 0 OHM 0% 1/16W	KINE DRIVER RED W/SVM
JB111	NONSTK		WIREBARE 22	KINE DRIVER RED W/SVM
JB158	NONSTK		WIREBARE 22	KINE DRIVER RED W/SVM
JB201	256783		RES CMF 0 OHM 0% 1/16W	KINE DRIVER GREEN W/SVM
JB211	NONSTK		WIREBARE 22	KINE DRIVER GREEN W/SVM

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
JB258	NONSTK		WIREBARE 22	KINE DRIVER GREEN W/SVM
JB301	256783		RES CMF 0 OHM 0% 1/16W	KINE DRIVER BLUE W/SVM
JB311	NONSTK		WIREBARE 22	KINE DRIVER BLUE W/SVM
JB358	NONSTK		WIREBARE 22	KINE DRIVER BLUE W/SVM
JF001	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JF003	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JF006	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JF007	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JF010	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JG100	NONSTK		WIREBARE 22	KINE DRIVER RED W/SVM
JG200	NONSTK		WIREBARE 22	KINE DRIVER GREEN W/SVM
JG300	NONSTK		WIREBARE 22	KINE DRIVER BLUE W/SVM
JH501	256783		RES CMF 0 OHM 0% 1/16W	SMALL SIGNAL BOARD
JH503	256783		RES CMF 0 OHM 0% 1/16W	SMALL SIGNAL BOARD
NONJJ001	NONSTK		WIREBARE 22	FRONT A/V IN
NONJJ002	NONSTK		WIREBARE 22	FRONT A/V IN
JK001	NONSTK		WIRE JUMPER	FRONT PANEL 1
JK004	NONSTK		WIRE JUMPER	FRONT PANEL 1
JK005	NONSTK		WIRE JUMPER	FRONT PANEL 1
JK006	256783		RES CMF 0 OHM 0% 1/16W	FRONT PANEL 1
JK007	NONSTK		WIRE JUMPER	FRONT PANEL 1
JK008	NONSTK		WIRE JUMPER	FRONT PANEL 1
JK009	NONSTK		WIRE JUMPER	FRONT PANEL 1
JK010	NONSTK		WIRE JUMPER	FRONT PANEL 1
JK011	NONSTK		WIRE JUMPER	FRONT PANEL 1
JK012	NONSTK		WIRE JUMPER	FRONT PANEL 1
JK013	NONSTK		WIRE JUMPER	FRONT PANEL 1
JK014	NONSTK		WIRE JUMPER	FRONT PANEL 1
JK015	NONSTK		WIRE JUMPER	FRONT PANEL 1
JK016	NONSTK		WIRE JUMPER	FRONT PANEL 1
JK018	NONSTK		WIRE JUMPER	FRONT PANEL 1
JK019	NONSTK		WIRE JUMPER	FRONT PANEL 1
JK020	NONSTK		WIRE JUMPER	FRONT PANEL 1
JK021	NONSTK		WIRE JUMPER	FRONT PANEL 1
JK026	256783		RES CMF 0 OHM 0% 1/16W	FRONT PANEL 1
JK028	256783		RES CMF 0 OHM 0% 1/16W	FRONT PANEL 1
JK029	256783		RES CMF 0 OHM 0% 1/16W	FRONT PANEL 1
JK030	256783		RES CMF 0 OHM 0% 1/16W	FRONT PANEL 1
JK031	256783		RES CMF 0 OHM 0% 1/16W	FRONT PANEL 1
JK033	256783		RES CMF 0 OHM 0% 1/16W	FRONT PANEL 1
JK034	256783		RES CMF 0 OHM 0% 1/16W	FRONT PANEL 1
JK035	256783		RES CMF 0 OHM 0% 1/16W	FRONT PANEL 1
JK036	256783		RES CMF 0 OHM 0% 1/16W	FRONT PANEL 1
JK037	256783		RES CMF 0 OHM 0% 1/16W	FRONT PANEL 1
JK038	256783		RES CMF 0 OHM 0% 1/16W	FRONT PANEL 1
JK039	256783		RES CMF 0 OHM 0% 1/16W	FRONT PANEL 1
JK040	256783		RES CMF 0 OHM 0% 1/16W	FRONT PANEL 1
JK041	256783		RES CMF 0 OHM 0% 1/16W	FRONT PANEL 1
JK042	256783		RES CMF 0 OHM 0% 1/16W	FRONT PANEL 1
JK043	256783		RES CMF 0 OHM 0% 1/16W	FRONT PANEL 1
JK044	256783		RES CMF 1/16W 0% 0R	FRONT PANEL 1
JK045	256783		RES CMF 1/16W 0% 0R	FRONT PANEL 1
JK046	256783		RES CMF 1/16W 0% 0R	FRONT PANEL 1
JK047	256783		RES CMF 1/16W 0% 0R	FRONT PANEL 1
JK048	256783		RES CMF 1/16W 0% 0R	FRONT PANEL 1
JK049	256783		RES CMF 1/16W 0% 0R	FRONT PANEL 1
JK050	256783		RES CMF 1/16W 0% 0R	FRONT PANEL 1
JK051	256783		RES CMF 1/16W 0% 0R	FRONT PANEL 1
JK052	256783		RES CMF 1/16W 0% 0R	FRONT PANEL 1
JK055	NONSTK		WIRE JUMPER	FRONT PANEL 1
JK056	NONSTK		WIRE JUMPER	FRONT PANEL 1
JK057	NONSTK		WIRE JUMPER	FRONT PANEL 1
JK058	NONSTK		WIRE JUMPER	FRONT PANEL 1
JK059	NONSTK		WIRE JUMPER	FRONT PANEL 1
JK060	256783		RES CMF 1/16W 0% 0R	FRONT PANEL 1
JK061	256783		RES CMF 1/16W 0% 0R	FRONT PANEL 1

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
JK062	NONSTK		WIRE JUMPER	FRONT PANEL 2
JK063	256783		RES CMF 1/16W 0% 0R	FRONT PANEL 2
JK064	256783		RES CMF 1/16W 0% 0R	FRONT PANEL 2
JK065	256783		RES CMF 1/16W 0% 0R	FRONT PANEL 2
JK066	256783		RES CMF 1/16W 0% 0R	FRONT PANEL 1
JK067	256783		RES CMF 1/16W 0% 0R	FRONT PANEL 1
JK068	256783		RES CMF 1/16W 0% 0R	FRONT PANEL 1
JK069	256783		RES CMF 1/16W 0% 0R	FRONT PANEL 1
JK133	256783		RES CMF 1/16W 0% 0R	FRONT PANEL 1
JL002	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JL003	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JL007	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JL008	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JL009	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JL014	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JL020	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JL021	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JL024	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JL035	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JL036	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JL043	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JL120	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JL200	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JL220	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JL303	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JL304	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JL305	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JL500	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JL501	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JL901	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JL915	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JL917	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JL933	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JL934	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JL951	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JL960	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JL980	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP003	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP006	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP007	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP008	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP009	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP010	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP011	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP020	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP024	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP025	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP027	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP060	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP061	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP100	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP110	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP12	NONSTK		WIREBARE 22	CONVERGENCE PS / ADAPTE
JP120	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP121	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP122	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP126	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP128	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP129	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP135	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP138	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP139	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP150	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP151	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP152	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP160	NONSTK		WIRE JUMPER	P-S/DEFLECTION

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
JP170	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP175	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP200	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP240	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP242	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP243	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP244	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP245	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP250	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP301	NONSTK		WIRE JUMPER	SMPS - DVD
JP302	NONSTK		WIRE JUMPER	SMPS - DVD
JP303	NONSTK		WIRE JUMPER	SMPS - DVD
JP304	NONSTK		WIRE JUMPER	SMPS - DVD
JP305	NONSTK		WIRE JUMPER	SMPS - DVD
JP306	NONSTK		WIRE JUMPER	SMPS - DVD
JP307	NONSTK		WIRE JUMPER	SMPS - DVD
JP308	NONSTK		WIRE JUMPER	SMPS - DVD
JP315	NONSTK		WIRE JUMPER	SMPS - DVD
JP318	NONSTK		WIRE JUMPER	SMPS - DVD
JP319	NONSTK		WIRE JUMPER	SMPS - DVD
JP37	NONSTK		WIREBARE 22	CONVERGENCE PS / ADAPTE
JP371	NONSTK		WIRE JUMPER	SMPS - DVD
JP401	NONSTK		WIRE JUMPER	MAINS INPUT DOUBLER
JP402	NONSTK		WIRE JUMPER	MAINS INPUT DOUBLER
JP403	NONSTK		WIRE JUMPER	MAINS INPUT DOUBLER
JP404	NONSTK		WIRE JUMPER	MAINS INPUT DOUBLER
JP405	NONSTK		WIRE JUMPER	MAINS INPUT DOUBLER
JP406	NONSTK		WIRE JUMPER	MAINS INPUT DOUBLER
JP600	NONSTK		WIRE JUMPER	MAINS INPUT DOUBLER
JP601	NONSTK		WIRE JUMPER	MAINS INPUT DOUBLER
JP621	NONSTK		WIRE JUMPER	MAINS INPUT DOUBLER
JP622	NONSTK		WIRE JUMPER	MAINS INPUT DOUBLER
JP905	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP912	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JP961	NONSTK		WIRE JUMPER	P-S/DEFLECTION
JR041	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
JR046	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
JR132	249338		RES CMF 47K 62.5MW 5%	SMALL SIGNAL BOARD
JR135	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
JR136	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
JR140	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
JR210	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
JR302	181161		RES CMF 1/8W 0% 0R	SMALL SIGNAL BOARD
JR325	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
JR326	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
JT001	NONSTK		WIRE JUMPER	A/V INTERFACE
JT002	NONSTK		WIRE JUMPER	A/V INTERFACE
JT003	NONSTK		WIRE JUMPER	A/V INTERFACE
JT005	NONSTK		WIRE JUMPER	A/V INTERFACE
JT006	NONSTK		WIRE JUMPER	A/V INTERFACE
JT007	NONSTK		WIRE JUMPER	A/V INTERFACE
JT201	256783		RES CMF 1/16W 0% 0R	MPEG CBA
JT387	256783		RES CMF 1/16W 0% 0R	DIGITAL READY INTERFACE
JU001	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
JU002	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
JV001	NONSTK		WIRE JUMPER	A/V INTERFACE
JV002	NONSTK		WIRE JUMPER	A/V INTERFACE
JV003	NONSTK		WIRE JUMPER	A/V INTERFACE
JV01	NONSTK		WIREBARE 22	CONVERGENCE PS / ADAPTE
JV03	NONSTK		WIREBARE 22	CONVERGENCE PS / ADAPTE
JV04	NONSTK		WIREBARE 22	CONVERGENCE PS / ADAPTE
JV05	NONSTK		WIREBARE 22	CONVERGENCE PS / ADAPTE
JV06	NONSTK		WIREBARE 22	CONVERGENCE PS / ADAPTE
JV07	NONSTK		WIREBARE 22	CONVERGENCE PS / ADAPTE
JV08	NONSTK		WIREBARE 22	CONVERGENCE PS / ADAPTE
JV09	NONSTK		WIREBARE 22	CONVERGENCE PS / ADAPTE

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
JV10	NONSTK		WIREBARE 22	CONVERGENCE PS / ADAPTE
JV11	NONSTK		WIREBARE 22	CONVERGENCE PS / ADAPTE
JV12	NONSTK		WIREBARE 22	CONVERGENCE PS / ADAPTE
JV13	NONSTK		WIREBARE 22	CONVERGENCE PS / ADAPTE
JV14	NONSTK		WIREBARE 22	CONVERGENCE PS / ADAPTE
JV15	NONSTK		WIREBARE 22	CONVERGENCE PS / ADAPTE
JV16	NONSTK		WIREBARE 22	CONVERGENCE PS / ADAPTE
JV17	NONSTK		WIREBARE 22	CONVERGENCE PS / ADAPTE
JV18	NONSTK		WIREBARE 22	CONVERGENCE PS / ADAPTE
JV19	NONSTK		WIREBARE 22	CONVERGENCE PS / ADAPTE
JV20	NONSTK		WIREBARE 22	CONVERGENCE PS / ADAPTE
JV21	NONSTK		WIREBARE 22	CONVERGENCE PS / ADAPTE
JV24	NONSTK		WIREBARE 22	CONVERGENCE PS / ADAPTE
JV253	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
JV291	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
JV30	NONSTK		WIREBARE 22	CONVERGENCE PS / ADAPTE
JV300	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
JV310	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
JV320	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
LL12100	259496		COIL, 300UH 10%	AUDIO CROSSOVER
LA001	259620		COIL, 10UH 5%	SMALL SIGNAL BOARD
LA013	259861		LC FILTER	SMALL SIGNAL BOARD
LA014	259861		LC FILTER	SMALL SIGNAL BOARD
LA023	259861		LC FILTER	SMALL SIGNAL BOARD
LA024	259861		LC FILTER	SMALL SIGNAL BOARD
LA049	205408		RES CMF 1/10W 0% 0R	SMALL SIGNAL BOARD
LA05	258716		BEAD, FERRITE	CONVERGENCE AMP BOARD
LA050	259620		COIL, 10UH 5%	SMALL SIGNAL BOARD
LA051	259620		COIL, 10UH 5%	SMALL SIGNAL BOARD
LA06	258716		BEAD, FERRITE	CONVERGENCE AMP BOARD
LA063	259861		LC FILTER	SMALL SIGNAL BOARD
LA064	259861		LC FILTER	SMALL SIGNAL BOARD
LA065	205408		RES CMF 1/10W 0% 0R	SMALL SIGNAL BOARD
LA090	259373		COIL, 15UH 20% (SMD)	SMALL SIGNAL BOARD
LA091	259373		COIL, 15UH 20% (SMD)	SMALL SIGNAL BOARD
LA158	259861		LC FILTER	SMALL SIGNAL BOARD
LA162	259861		LC FILTER	SMALL SIGNAL BOARD
LA163	259861		LC FILTER	SMALL SIGNAL BOARD
LA501	259981		COIL, 10UH 10%	MPEG CBA
LA513	259981		COIL, 10UH 10%	MPEG CBA
LA53	258716		BEAD, FERRITE	CONVERGENCE AMP BOARD
LA58	258716		BEAD, FERRITE	CONVERGENCE AMP BOARD
LB05	258716		BEAD, FERRITE	CONVERGENCE AMP BOARD
LB06	258716		BEAD, FERRITE	CONVERGENCE AMP BOARD
LB123	259357		COIL, 68UH 10%	KINE DRIVER RED W/SVM
LB152	251881		LF 3U3H +5% 300MIO OHM 577MIOA	KINE DRIVER RED W/SVM
LB223	259357		COIL, 68UH 10%	KINE DRIVER GREEN W/SVM
LB252	251881		LF 3U3H +5% 300MIO OHM 577MIOA	KINE DRIVER GREEN W/SVM
LB323	259357		COIL, 68UH 10%	KINE DRIVER BLUE W/SVM
LB352	251881		LF 3U3H +5% 300MIO OHM 577MIOA	KINE DRIVER BLUE W/SVM
LB53	258716		BEAD, FERRITE	CONVERGENCE AMP BOARD
LB58	258716		BEAD, FERRITE	CONVERGENCE AMP BOARD
LD900	259981		COIL, 10UH 10%	SPDIF OUTPUT
LENS	256885		LENS, A-B: DELTA 260	OPTICS ASSEMBLY
LF022	258169		COIL, 60UH	P-S/DEFLECTION
LG05	258716		BEAD, FERRITE	CONVERGENCE AMP BOARD
LG06	258716		BEAD, FERRITE	CONVERGENCE AMP BOARD
LG114	259869		DUAL FERRITE CORE	KINE DRIVER RED W/SVM
LG161	223687		BEAD	MPEG CBA
LG162	259985		COIL, 47UH 10%	MPEG CBA
LG163	259985		COIL, 47UH 10%	MPEG CBA
LG214	259869		DUAL FERRITE CORE	KINE DRIVER GREEN W/SVM
LG314	259869		DUAL FERRITE CORE	KINE DRIVER BLUE W/SVM
LG53	258716		BEAD, FERRITE	CONVERGENCE AMP BOARD
LH001	259620		COIL, 10UH 5%	SMALL SIGNAL BOARD
LH500	259620		COIL, 10UH 5%	SMALL SIGNAL BOARD

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
LH501	259620		COIL, 10UH 5%	SMALL SIGNAL BOARD
LI027	263979		COIL, .27UH 10%	SMALL SIGNAL BOARD
LI033	259373		COIL, 15UH 20% (SMD)	SMALL SIGNAL BOARD
LI527	263979		COIL, .27UH 10%	SMALL SIGNAL BOARD
LI533	259373		COIL, 15UH 20% (SMD)	SMALL SIGNAL BOARD
LJ001	198656		RES CF 1/4W 5% 100R	FRONT A/V IN
LJ002	198656		RES CF 1/4W 5% 100R	FRONT A/V IN
LK001	214580		COIL 10UH	FRONT PANEL 1
LK002	258169		COIL, 60UH	FRONT PANEL 1
LK01	258719		COIL, 10UH 10%	CONVERGENCE SIGNAL BOAR
LK02	243496		COIL-SMD, 1UH	CONVERGENCE SIGNAL BOAR
LK03	243496		COIL-SMD, 1UH	CONVERGENCE SIGNAL BOAR
LK04	243496		COIL-SMD, 1UH	CONVERGENCE SIGNAL BOAR
LK05	243496		COIL-SMD, 1UH	CONVERGENCE SIGNAL BOAR
LK06	243496		COIL-SMD, 1UH	CONVERGENCE SIGNAL BOAR
LK07	243496		COIL-SMD, 1UH	CONVERGENCE SIGNAL BOAR
LK08	258719		COIL, 10UH 10%	CONVERGENCE SIGNAL BOAR
LK09	243496		COIL-SMD, 1UH	CONVERGENCE SIGNAL BOAR
LK10	243496		COIL-SMD, 1UH	CONVERGENCE SIGNAL BOAR
LK11	243496		COIL-SMD, 1UH	CONVERGENCE SIGNAL BOAR
LK12	243496		COIL-SMD, 1UH	CONVERGENCE SIGNAL BOAR
LK13	243496		COIL-SMD, 1UH	CONVERGENCE SIGNAL BOAR
LK14	243496		COIL-SMD, 1UH	CONVERGENCE SIGNAL BOAR
LK15	258719		COIL, 10UH 10%	CONVERGENCE SIGNAL BOAR
LK16	258719		COIL, 10UH 10%	CONVERGENCE SIGNAL BOAR
LK17	258719		COIL, 10UH 10%	CONVERGENCE SIGNAL BOAR
LK18	258719		COIL, 10UH 10%	CONVERGENCE SIGNAL BOAR
LK19	258719		COIL, 10UH 10%	CONVERGENCE SIGNAL BOAR
LL001	259293		TRANSFORMER, HORIZ DRIVE	P-S/DEFLECTION
LL005	235858		BEAD	P-S/DEFLECTION
LL008	259296		TRANSFORMER, IHVT	P-S/DEFLECTION
LL010	258716		BEAD, FERRITE	P-S/DEFLECTION
LL011	235858		BEAD	P-S/DEFLECTION
LL012	235858		BEAD	P-S/DEFLECTION
LL029	259261		COIL, 118UH 3%	P-S/DEFLECTION
LL030	259838		COIL, 560NH 20%	P-S/DEFLECTION
LL032	258716		BEAD, FERRITE	P-S/DEFLECTION
LL037	259244		COIL, HORIZ LINEARITY	P-S/DEFLECTION
LL100	244840		BEAD FERRITE	P-S/DEFLECTION
LL200	259936		COIL, 21.5UH 2%	P-S/DEFLECTION
LL201	253638		COIL, 22UH	P-S/DEFLECTION
LL211	235858		BEAD	P-S/DEFLECTION
LL212	253638		COIL, 22UH	P-S/DEFLECTION
LL221	NONSTK		WIRE JUMPER	P-S/DEFLECTION
LL231	258719		COIL, 10UH 10%	P-S/DEFLECTION
LL251	NONSTK		WIRE JUMPER	P-S/DEFLECTION
LP004	244840		BEAD FERRITE	P-S/DEFLECTION
LP020	259276		TRANSFORMER, STANDBY	P-S/DEFLECTION
LP050	259320		TRANSFORMER, SMT	P-S/DEFLECTION
LP051	259838		COIL, 560NH 20%	P-S/DEFLECTION
LP070	259279		TRANSFORMER	P-S/DEFLECTION
LP112	259854		COIL, 100UH 10%	P-S/DEFLECTION
LP113	258716		BEAD, FERRITE	P-S/DEFLECTION
LP140	259853		COIL, 47UH 10%	P-S/DEFLECTION
LP151	259853		COIL, 47UH 10%	P-S/DEFLECTION
LP301	259989		COIL, INPUT FILTER	SMPS - DVD
LP303	260030		TRANSFORMER, SMT	SMPS - DVD
LP320	244840		BEAD FERRITE	SMPS - DVD
LP325	235858		BEAD	SMPS - DVD
LP364	232428		COIL 50UH	SMPS - DVD
LP365	232428		COIL 50UH	SMPS - DVD
LP390	244840		BEAD FERRITE	SMPS - DVD
LP401	253697		COIL, LINE CHOKE	MAINS INPUT DOUBLER
LP50	259271		TRANSFORMER, SMT	CONVERGENCE PS / ADAPTE
LP60	258702		COIL, 68UH 10%	CONVERGENCE PS / ADAPTE
LP65	258702		COIL, 68UH 10%	CONVERGENCE PS / ADAPTE

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
LP70	258702		COIL, 68UH 10%	CONVERGENCE PS / ADAPTE
LP75	258702		COIL, 68UH 10%	CONVERGENCE PS / ADAPTE
LR001	259860		LC FILTER	SMALL SIGNAL BOARD
LR010	259648		LC FILTER	SMALL SIGNAL BOARD
LR011	259859		LC FILTER	SMALL SIGNAL BOARD
LR012	259859		LC FILTER	SMALL SIGNAL BOARD
LR015	259648		LC FILTER	SMALL SIGNAL BOARD
LR016	259859		LC FILTER	SMALL SIGNAL BOARD
LR017	259859		LC FILTER	SMALL SIGNAL BOARD
LR020	259648		LC FILTER	SMALL SIGNAL BOARD
LR021	259859		LC FILTER	SMALL SIGNAL BOARD
LR022	259859		LC FILTER	SMALL SIGNAL BOARD
LR025	259648		LC FILTER	SMALL SIGNAL BOARD
LR026	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
LR027	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
LR030	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
LR041	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
LR042	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
LR043	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
LR044	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
LR045	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
LR046	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
LR047	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
LR051	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
LR052	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
LR065	181161		RES CMF 1/8W 0% 0R	SMALL SIGNAL BOARD
LR066	181161		RES CMF 1/8W 0% 0R	SMALL SIGNAL BOARD
LR067	181161		RES CMF 1/8W 0% 0R	SMALL SIGNAL BOARD
LR110	259648		LC FILTER	SMALL SIGNAL BOARD
LR111	259859		LC FILTER	SMALL SIGNAL BOARD
LR115	259648		LC FILTER	SMALL SIGNAL BOARD
LR116	259859		LC FILTER	SMALL SIGNAL BOARD
LR130	259648		LC FILTER	SMALL SIGNAL BOARD
LR131	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
LS30	263911		LC FILTER(SMD)	CONVERGENCE SIGNAL BOAR
LS31	263911		LC FILTER(SMD)	CONVERGENCE SIGNAL BOAR
LT241	259644		COIL (SMD), 10UH 10%	DIGITAL READY INTERFACE
LT242	259644		COIL (SMD), 10UH 10%	DIGITAL READY INTERFACE
LT243	259644		COIL (SMD), 10UH 10%	DIGITAL READY INTERFACE
LT261	259250		FERRITE BEAD INDUCTOR	DIGITAL READY INTERFACE
LT262	256783		RES CMF 1/16W 0% 0R	DIGITAL READY INTERFACE
LT263	256783		RES CMF 1/16W 0% 0R	DIGITAL READY INTERFACE
LT264	256783		RES CMF 1/16W 0% 0R	DIGITAL READY INTERFACE
LT265	256783		RES CMF 1/16W 0% 0R	DIGITAL READY INTERFACE
LT415	205408		RES CMF 1/10W 0% 0R	DIGITAL READY INTERFACE
LT416	205408		RES CMF 1/10W 0% 0R	DIGITAL READY INTERFACE
LT501	238094		COIL, 15UH	DIGITAL READY INTERFACE
LT502	243892		COIL, 5.6UH	DIGITAL READY INTERFACE
LT503	243499		COIL, 12UH	DIGITAL READY INTERFACE
LT511	195713		COIL, 47UH	DIGITAL READY INTERFACE
LT513	215546		BEAD	DIGITAL READY INTERFACE
LT514	195713		COIL, 47UH	DIGITAL READY INTERFACE
LT516	215546		BEAD	DIGITAL READY INTERFACE
LT531	243675		COIL, 10UH	DIGITAL READY INTERFACE
LT532	243499		COIL, 12UH	DIGITAL READY INTERFACE
LT541	243675		COIL, 10UH	DIGITAL READY INTERFACE
LT542	243499		COIL, 12UH	DIGITAL READY INTERFACE
LT543	215546		BEAD	DIGITAL READY INTERFACE
LT545	195713		COIL, 47UH	DIGITAL READY INTERFACE
LT551	195713		COIL, 47UH	DIGITAL READY INTERFACE
LT553	215546		BEAD	DIGITAL READY INTERFACE
LT561	238094		COIL, 15UH	DIGITAL READY INTERFACE
LT571	226467		BEAD	DIGITAL READY INTERFACE
LT601	259323		COIL, .33UH 10% (SMD)	DIGITAL READY INTERFACE
LT611	259363		COIL, .33UH 10% (SMD)	DIGITAL READY INTERFACE
LT612	259363		COIL, .33UH 10% (SMD)	DIGITAL READY INTERFACE

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
LT613	259363		COIL, .33UH 10% (SMD)	DIGITAL READY INTERFACE
LT614	259363		COIL, .33UH 10% (SMD)	DIGITAL READY INTERFACE
LT621	247980		COIL	DIGITAL READY INTERFACE
LT622	247980		COIL	DIGITAL READY INTERFACE
LT623	247980		COIL	DIGITAL READY INTERFACE
LT641	259363		COIL, .33UH 10% (SMD)	DIGITAL READY INTERFACE
LT642	259363		COIL, .33UH 10% (SMD)	DIGITAL READY INTERFACE
LT643	259363		COIL, .33UH 10% (SMD)	DIGITAL READY INTERFACE
LT644	259363		COIL, .33UH 10% (SMD)	DIGITAL READY INTERFACE
LT691	259644		COIL (SMD), 10UH 10%	DIGITAL READY INTERFACE
LT754	215546		BEAD	DIGITAL READY INTERFACE
LU008	259644		COIL (SMD), 10UH 10%	SMALL SIGNAL BOARD
LU010	259644		COIL (SMD), 10UH 10%	SMALL SIGNAL BOARD
LU014	259860		LC FILTER	SMALL SIGNAL BOARD
LU015	259860		LC FILTER	SMALL SIGNAL BOARD
LV002	243496		COIL, 1UH	SMALL SIGNAL BOARD
LV004	239143		COIL, 2.2UH	SMALL SIGNAL BOARD
LV01	259237		COIL, 220UH 10%	CONVERGENCE PS / ADAPTE
LV011	259364		COIL, 3.9UH 10% (SMD)	SMALL SIGNAL BOARD
LV021	243892		COIL, 5.6UH	SMALL SIGNAL BOARD
LV041	243892		COIL, 5.6UH	SMALL SIGNAL BOARD
LV100	259620		COIL, 10UH 5%	SMALL SIGNAL BOARD
LV200	259620		COIL, 10UH 5%	SMALL SIGNAL BOARD
LV300	239143		COIL, 2.2UH	SMALL SIGNAL BOARD
LV310	239143		COIL, 2.2UH	SMALL SIGNAL BOARD
LV320	239143		COIL, 2.2UH	SMALL SIGNAL BOARD
LV513	243488		RES CM 4.7 OHM +5%	SMALL SIGNAL BOARD
LV80	259233		TRANSFORMER	CONVERGENCE PS / ADAPTE
LV90	258719		COIL, 10UH 10%	CONVERGENCE PS / ADAPTE
LW06	258719		COIL, 10UH 10%	CONVERGENCE AMP BOARD
LW07	258719		COIL, 10UH 10%	CONVERGENCE AMP BOARD
LX409	259250		FERRITE BEAD INDUCTOR	SMALL SIGNAL BOARD
LX410	259250		FERRITE BEAD INDUCTOR	SMALL SIGNAL BOARD
LX501	181161		RES CMF 1/8W 0% 0R	SMALL SIGNAL BOARD
LX502	181161		RES CMF 1/8W 0% 0R	SMALL SIGNAL BOARD
LX701	181161		RES CMF 1/8W 0% 0R	SMALL SIGNAL BOARD
LX702	181161		RES CMF 1/8W 0% 0R	SMALL SIGNAL BOARD
LY501	259981		COIL, 10UH 10%	MPEG CBA
LY502	259981		COIL, 10UH 10%	MPEG CBA
MASK	MK2553		MASK, SCREEN FRAME	INSTRUMENT ASSEMBLY
MIRROR	258520		MIRROR, PROJECTION	INSTRUMENT ASSEMBLY
NG104	242836		RES NETWORK 5% 10K X 4	MPEG CBA
NG105	242836		RES NETWORK 5% 10K X 4	MPEG CBA
NG106	242836		RES NETWORK 5% 10K X 4	MPEG CBA
NG203	240812		RES CMF 1/16W 5% 68R	MPEG CBA
NG204	240812		RES CMF 1/16W 5% 68R	MPEG CBA
NG205	240812		RES CMF 1/16W 5% 68R	MPEG CBA
NG206	240812		RES CMF 1/16W 5% 68R	MPEG CBA
NG207	240812		RES CMF 1/16W 5% 68R	MPEG CBA
NG208	240812		RES CMF 1/16W 5% 68R	MPEG CBA
NG209	240812		RES CMF 1/16W 5% 68R	MPEG CBA
NG210	240812		RES CMF 1/16W 5% 68R	MPEG CBA
NG211	240812		RES CMF 1/16W 5% 68R	MPEG CBA
NNH499	259606		CABLE, RF IN	SMALL SIGNAL BOARD
NNH500	259618		CIRCUIT, RF SPLITTER	SMALL SIGNAL BOARD
NNH501	259617		TUNER, CTF5805	SMALL SIGNAL BOARD
NNH503	259617		TUNER, CTF5805	SMALL SIGNAL BOARD
NT178	242836		RES NETWORK 5% 10K X 4	MPEG CBA
NT183	240812		RES CMF 1/16W 5% 68R	MPEG CBA
NU758	240812		RES CMF 1/16W 5% 68R	MPEG CBA
NU759	240812		RES CMF 1/16W 5% 68R	MPEG CBA
NU760	242836		RES NETWORK 5% 10K X 4	MPEG CBA
O-RING	265437		O-RING, PROJ PICTURE TUBE	OPTICS ASSEMBLY
OVERLAY	259946		OVERLAY FOR REAR JACK PANEL	CHASSIS ASSEMBLY
OVERLAY	259188		OVERLAY, A/V DOOR	INSTRUMENT ASSEMBLY
PANEL	258806		PANEL, REAR JACK	INSTRUMENT ASSEMBLY

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
PANEL	258811		CONTROL PANEL, OUTER(ALUMINUM)	INSTRUMENT ASSEMBLY
PANEL	258808		CONTROL PANEL, INNER(PLASTIC)	INSTRUMENT ASSEMBLY
PP180	230995		RES, CONTROL: 470 OHMS 33MW	P-S/DEFLECTION
QA001	258733		CRYSTAL, 18.432 MHZ	SMALL SIGNAL BOARD
QC536	259571		CRYSTAL, 3.58MHZ	SMALL SIGNAL BOARD
QC736	259571		CRYSTAL, 3.58MHZ	SMALL SIGNAL BOARD
QI033	198613		COIL	SMALL SIGNAL BOARD
QI533	198613		COIL	SMALL SIGNAL BOARD
QK001	263980		RESONATOR 8MHZ	FRONT PANEL 1
QR001	235882		FILTER	SMALL SIGNAL BOARD
QT231	242877		RESONATOR, CERAMIC	DIGITAL READY INTERFACE
QT260	259897		CRYSTAL, 20.25MHZ	DIGITAL READY INTERFACE
QT501	227894		CRYSTAL	DIGITAL READY INTERFACE
QV400	259636		CRYSTAL, 12MHZ	SMALL SIGNAL BOARD
RA005	243485		RES CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RA01	259476		RES MF 3.9K 1% .4W	CONVERGENCE AMP BOARD
RA011	206380		RES CMF 1/8W 5% 4.7K	SMALL SIGNAL BOARD
RA012	206380		RES CMF 1/8W 5% 4.7K	SMALL SIGNAL BOARD
RA013	253625		RES CMF 62.5MW 5% 150K	SMALL SIGNAL BOARD
RA014	253625		RES CMF 62.5MW 5% 150K	SMALL SIGNAL BOARD
RA015	192100		RES CMF 1/10W 5% 1K	SMALL SIGNAL BOARD
RA016	192100		RES CMF 1/10W 5% 1K	SMALL SIGNAL BOARD
RA02	258180		RES CF 1K 5% 1/4W	CONVERGENCE AMP BOARD
RA021	206380		RES CMF 1/8W 5% 4.7K	SMALL SIGNAL BOARD
RA022	206380		RES CMF 1/8W 5% 4.7K	SMALL SIGNAL BOARD
RA023	253625		RES CMF 62.5MW 5% 150K	SMALL SIGNAL BOARD
RA024	253625		RES CMF 62.5MW 5% 150K	SMALL SIGNAL BOARD
RA025	192100		RES CMF 1/10W 5% 1K	SMALL SIGNAL BOARD
RA026	192100		RES CMF 1/10W 5% 1K	SMALL SIGNAL BOARD
RA03	259472		RES MF 332 OHMS 1% 1/4W	CONVERGENCE AMP BOARD
RA031	206380		RES CMF 1/8W 5% 4.7K	SMALL SIGNAL BOARD
RA032	206380		RES CMF 1/8W 5% 4.7K	SMALL SIGNAL BOARD
RA033	253625		RES CMF 62.5MW 5% 150K	SMALL SIGNAL BOARD
RA034	253625		RES CMF 62.5MW 5% 150K	SMALL SIGNAL BOARD
RA035	192100		RES CMF 1/10W 5% 1K	SMALL SIGNAL BOARD
RA036	192100		RES CMF 1/10W 5% 1K	SMALL SIGNAL BOARD
RA04	259471		RES MF 2.43K 1% 1/4W	CONVERGENCE AMP BOARD
RA041	206380		RES CMF 1/8W 5% 4.7K	SMALL SIGNAL BOARD
RA042	206380		RES CMF 1/8W 5% 4.7K	SMALL SIGNAL BOARD
RA043	249338		RES CMF 47K 62.5MW 5%	SMALL SIGNAL BOARD
RA044	249338		RES CMF 47K 62.5MW 5%	SMALL SIGNAL BOARD
RA045	192100		RES CMF 1/10W 5% 1K	SMALL SIGNAL BOARD
RA046	192100		RES CMF 1/10W 5% 1K	SMALL SIGNAL BOARD
RA05	259465		RES MF 162 OHMS 1% 1/4W	CONVERGENCE AMP BOARD
RA050	256743		RES CMF 15K OHM 5% 1/16W	SMALL SIGNAL BOARD
RA051	235901		RES CFF 1/4W 5% 4.7 OHMS	SMALL SIGNAL BOARD
RA058	244074		RES CMF 47 OHM +5% 62.5MW	SMALL SIGNAL BOARD
RA06	259344		RES CF 12K 5% .7W	CONVERGENCE AMP BOARD
RA061	249338		RES CMF 47K 62.5MW 5%	SMALL SIGNAL BOARD
RA062	249338		RES CMF 47K 62.5MW 5%	SMALL SIGNAL BOARD
RA063	181492		RES CMF 1/8W 2% 220R	SMALL SIGNAL BOARD
RA064	181492		RES CMF 1/8W 2% 220R	SMALL SIGNAL BOARD
RA065	218508		RES CMF 1/10W 5% 100R	SMALL SIGNAL BOARD
RA066	218508		RES CMF 1/10W 5% 100R	SMALL SIGNAL BOARD
RA07	259485		RES MF 8.87K 1% 1/4W	CONVERGENCE AMP BOARD
RA08	258177		RES CF 4.7K 5% 1/4W	CONVERGENCE AMP BOARD
RA080	235901		RES CFF 1/4W 5% 4.7 OHMS	SMALL SIGNAL BOARD
RA09	259358		RES MF 1.8 OHMS 1% 1W	CONVERGENCE AMP BOARD
RA090	244056		RES CMF 470 OHM 5% 62.5MW	SMALL SIGNAL BOARD
RA091	244056		RES CMF 470 OHM 5% 62.5MW	SMALL SIGNAL BOARD
RA092	244074		RES CMF 47 OHM +5% 62.5MW	SMALL SIGNAL BOARD
RA094	244074		RES CMF 47 OHM +5% 62.5MW	SMALL SIGNAL BOARD
RA10	259475		RES MF 3.32K 1% 1/4W	CONVERGENCE AMP BOARD
RA110	243375		RES CMF 1/16W 5% 4.7K	SMALL SIGNAL BOARD
RA111	243375		RES CMF 1/16W 5% 4.7K	SMALL SIGNAL BOARD
RA112	256765		RES CMF 1/16W 5% 5.6K	SMALL SIGNAL BOARD

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
RA113	256765	RES	CMF 1/16W 5% 5.6K	SMALL SIGNAL BOARD
RA114	243485	RES	CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RA115	243485	RES	CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RA116	249038	RES	CMF 1/16W 5% 560R	SMALL SIGNAL BOARD
RA117	249038	RES	CMF 1/16W 5% 560R	SMALL SIGNAL BOARD
RA118	256746	RES	CMF 22K OHM +5% 62.5MW	SMALL SIGNAL BOARD
RA119	256746	RES	CMF 22K OHM +5% 62.5MW	SMALL SIGNAL BOARD
RA12	259486	RES	MFF .47 OHMS 10% .4W	CONVERGENCE AMP BOARD
RA120	235901	RES	CFF 1/4W 5% 4.7 OHMS	SMALL SIGNAL BOARD
RA121	235901	RES	CFF 1/4W 5% 4.7 OHMS	SMALL SIGNAL BOARD
RA122	256754	RES	CMF 100K OHM 5% 1/16W	SMALL SIGNAL BOARD
RA13	259469	RES	MF 267K 1% 1/4W	CONVERGENCE AMP BOARD
RA130	256746	RES	CMF 22K OHM +5% 62.5MW	SMALL SIGNAL BOARD
RA131	256746	RES	CMF 22K OHM +5% 62.5MW	SMALL SIGNAL BOARD
RA133	256748	RES	CMF 33K OHM 5% 1/16W	SMALL SIGNAL BOARD
RA134	256751	RES	CMF 68K OHM +5% 62.5MW	SMALL SIGNAL BOARD
RA135	253625	RES	CMF 62.5MW 5% 150K	SMALL SIGNAL BOARD
RA14	259486	RES	MFF .47 OHMS 10% .4W	CONVERGENCE AMP BOARD
RA145	256746	RES	CMF 22K OHM +5% 62.5MW	SMALL SIGNAL BOARD
RA148	256748	RES	CMF 33K OHM 5% 1/16W	SMALL SIGNAL BOARD
RA149	256783	RES	CMF 1/16W 0% 0R	MPEG CBA
RA15	258177	RES	CF 4.7K 5% 1/4W	CONVERGENCE AMP BOARD
RA150	243653	RES	CMF 1/16W 5% 100R	MPEG CBA
RA151	243653	RES	CMF 1/16W 5% 100R	MPEG CBA
RA152	243653	RES	CMF 1/16W 5% 100R	MPEG CBA
RA158	184056	RES	CF 1/4W 5% 470R	SMALL SIGNAL BOARD
RA159	256754	RES	CMF 100K OHM 5% 1/16W	SMALL SIGNAL BOARD
RA160	184056	RES	CF 1/4W 5% 470R	SMALL SIGNAL BOARD
RA161	184056	RES	CF 1/4W 5% 470R	SMALL SIGNAL BOARD
RA162	256754	RES	CMF 100K OHM 5% 1/16W	SMALL SIGNAL BOARD
RA163	256754	RES	CMF 100K OHM 5% 1/16W	SMALL SIGNAL BOARD
RA166	246960	RES	CMF 3.9K 5% 1/16W	SMALL SIGNAL BOARD
RA167	246960	RES	CMF 3.9K 5% 1/16W	SMALL SIGNAL BOARD
RA168	256744	RES	CMF 18K OHM +5% 62.5MW	SMALL SIGNAL BOARD
RA169	256744	RES	CMF 18K OHM +5% 62.5MW	SMALL SIGNAL BOARD
RA170	232646	RES	CMF 1/8W 5% 4.7R	SMALL SIGNAL BOARD
RA171	232646	RES	CMF 1/8W 5% 4.7R	SMALL SIGNAL BOARD
RA172	243653	RES	CMF 1/16W 5% 100R	MPEG CBA
RA172	242690	RES	CMF 1/16W 5% 10K	SMALL SIGNAL BOARD
RA173	242690	RES	CMF 1/16W 5% 10K	SMALL SIGNAL BOARD
RA174	257821	RES	MF 150 OHMS 5% 2W	SMALL SIGNAL BOARD
RA175	256754	RES	CMF 100K OHM 5% 1/16W	SMALL SIGNAL BOARD
RA176	256754	RES	CMF 100K OHM 5% 1/16W	SMALL SIGNAL BOARD
RA177	256764	RES	CMF 3.3K OHM 5% 1/16W	SMALL SIGNAL BOARD
RA178	256764	RES	CMF 3.3K OHM 5% 1/16W	SMALL SIGNAL BOARD
RA179	256764	RES	CMF 3.3K OHM 5% 1/16W	SMALL SIGNAL BOARD
RA180	256754	RES	CMF 100K OHM 5% 1/16W	SMALL SIGNAL BOARD
RA181	256754	RES	CMF 100K OHM 5% 1/16W	SMALL SIGNAL BOARD
RA182	256754	RES	CMF 100K OHM 5% 1/16W	SMALL SIGNAL BOARD
RA183	242690	RES	CMF 1/16W 5% 10K	SMALL SIGNAL BOARD
RA184	242690	RES	CMF 1/16W 5% 10K	SMALL SIGNAL BOARD
RA185	242690	RES	CMF 1/16W 5% 10K	SMALL SIGNAL BOARD
RA186	210190	RES	CF .43W 5% 1K	SMALL SIGNAL BOARD
RA187	210190	RES	CF .43W 5% 1K	SMALL SIGNAL BOARD
RA188	249338	RES	CMF 47K 62.5MW 5%	SMALL SIGNAL BOARD
RA191	218508	RES	CMF 1/10W 5% 100R	SMALL SIGNAL BOARD
RA192	218508	RES	CMF 1/10W 5% 100R	SMALL SIGNAL BOARD
RA193	218508	RES	CMF 1/10W 5% 100R	SMALL SIGNAL BOARD
RA194	218508	RES	CMF 1/10W 5% 100R	SMALL SIGNAL BOARD
RA195	218508	RES	CMF 1/10W 5% 100R	SMALL SIGNAL BOARD
RA20	259471	RES	MF 2.43K 1% 1/4W	CONVERGENCE AMP BOARD
RA200	258732	RES	WW .12 OHMS 5% 2.5W	SMALL SIGNAL BOARD
RA201	256765	RES	CMF 1/16W 5% 5.6K	SMALL SIGNAL BOARD
RA202	242690	RES	CMF 1/16W 5% 10K	SMALL SIGNAL BOARD
RA203	243375	RES	CMF 1/16W 5% 4.7K	SMALL SIGNAL BOARD
RA204	256765	RES	CMF 1/16W 5% 5.6K	SMALL SIGNAL BOARD

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
RA205	256746	RES	CMF 22K OHM +5% 62.5MW	SMALL SIGNAL BOARD
RA206	256761	RES	CMF 2.2K OHM 5% 1/16W	SMALL SIGNAL BOARD
RA207	256746	RES	CMF 22K OHM +5% 62.5MW	SMALL SIGNAL BOARD
RA208	243375	RES	CMF 1/16W 5% 4.7K	SMALL SIGNAL BOARD
RA209	256755	RES	CMF 120K OHM +5% 62.5MW	SMALL SIGNAL BOARD
RA210	242690	RES	CMF 1/16W 5% 10K	SMALL SIGNAL BOARD
RA211	174346	RES	CMF 470 OHMS 5% 1/8W	SMALL SIGNAL BOARD
RA212	174346	RES	CMF 470 OHMS 5% 1/8W	SMALL SIGNAL BOARD
RA400	256783	RES	CMF 1/16W 0% 0R	MPEG CBA
RA50	258180	RES	CF 1K 5% 1/4W	CONVERGENCE AMP BOARD
RA500	256754	RES	CMF 100K OHM 5% 1/16W	MPEG CBA
RA501	243485	RES	CMF 1/16W 5% 1K	MPEG CBA
RA502	256764	RES	CMF 3.3K OHM 5% 1/16W	MPEG CBA
RA503	256743	RES	CMF 15K OHM 5% 1/16W	MPEG CBA
RA504	242690	RES	CMF 1/16W 5% 10K	MPEG CBA
RA505	243485	RES	CMF 1/16W 5% 1K	MPEG CBA
RA51	259472	RES	MF 332 OHMS 1% 1/4W	CONVERGENCE AMP BOARD
RA510	256754	RES	CMF 100K OHM 5% 1/16W	MPEG CBA
RA511	243485	RES	CMF 1/16W 5% 1K	MPEG CBA
RA512	256764	RES	CMF 3.3K OHM 5% 1/16W	MPEG CBA
RA513	256743	RES	CMF 15K OHM 5% 1/16W	MPEG CBA
RA514	242690	RES	CMF 1/16W 5% 10K	MPEG CBA
RA515	243485	RES	CMF 1/16W 5% 1K	MPEG CBA
RA52	259471	RES	MF 2.43K 1% 1/4W	CONVERGENCE AMP BOARD
RA53	259465	RES	MF 162 OHMS 1% 1/4W	CONVERGENCE AMP BOARD
RA537	256783	RES	CMF 1/16W 0% 0R	MPEG CBA
RA539	256783	RES	CMF 1/16W 0% 0R	MPEG CBA
RA54	259342	RES	CF 10K 5% .7W	CONVERGENCE AMP BOARD
RA55	259469	RES	MF 267K 1% 1/4W	CONVERGENCE AMP BOARD
RA56	259475	RES	MF 3.32K 1% 1/4W	CONVERGENCE AMP BOARD
RA57	259358	RES	MF 1.8 OHMS 1% 1W	CONVERGENCE AMP BOARD
RA58	259486	RES	MFF .47 OHMS 10% .4W	CONVERGENCE AMP BOARD
RA59	259486	RES	MFF .47 OHMS 10% .4W	CONVERGENCE AMP BOARD
RA60	259485	RES	MF 8.87K 1% 1/4W	CONVERGENCE AMP BOARD
RA61	259476	RES	MF 3.9K 1% .4W	CONVERGENCE AMP BOARD
RA62	243375	RES	CMF 1/16W 5% 4.7K	CONVERGENCE AMP BOARD
RA64	259471	RES	MF 2.43K 1% 1/4W	CONVERGENCE AMP BOARD
RA66	243375	RES	CMF 1/16W 5% 4.7K	CONVERGENCE AMP BOARD
RB01	259476	RES	MF 3.9K 1% .4W	CONVERGENCE AMP BOARD
RB02	258180	RES	CF 1K 5% 1/4W	CONVERGENCE AMP BOARD
RB03	259472	RES	MF 332 OHMS 1% 1/4W	CONVERGENCE AMP BOARD
RB04	259471	RES	MF 2.43K 1% 1/4W	CONVERGENCE AMP BOARD
RB05	259465	RES	MF 162 OHMS 1% 1/4W	CONVERGENCE AMP BOARD
RB06	259342	RES	CF 10K 5% .7W	CONVERGENCE AMP BOARD
RB07	259485	RES	MF 8.87K 1% 1/4W	CONVERGENCE AMP BOARD
RB08	258177	RES	CF 4.7K 5% 1/4W	CONVERGENCE AMP BOARD
RB09	259358	RES	MF 1.8 OHMS 1% 1W	CONVERGENCE AMP BOARD
RB10	259475	RES	MF 3.32K 1% 1/4W	CONVERGENCE AMP BOARD
RB101	259443	RES	CF 33 OHMS 5% 1/4W	KINE DRIVER RED W/SVM
RB106	253719	RES	CMF 62.5MW 1% 475 OHM	KINE DRIVER RED W/SVM
RB107	253811	RES	CMF 62.5MW 1% 681 OHM	KINE DRIVER RED W/SVM
RB108	253719	RES	CMF 62.5MW 1% 475 OHM	KINE DRIVER RED W/SVM
RB109	253719	RES	CMF 62.5MW 1% 475 OHM	KINE DRIVER RED W/SVM
RB110	261152	RES	CMF 150 OHMS 5% 1/16W	KINE DRIVER RED W/SVM
RB111	253719	RES	CMF 62.5MW 1% 475 OHM	KINE DRIVER RED W/SVM
RB112	253719	RES	CMF 62.5MW 1% 475 OHM	KINE DRIVER RED W/SVM
RB114	253727	RES	CMF 62.5MW 1% 3.92K	KINE DRIVER RED W/SVM
RB12	259486	RES	MFF .47 OHMS 10% .4W	CONVERGENCE AMP BOARD
RB120	198672	RES	CF 1/4W 5% 1.5K	KINE DRIVER RED W/SVM
RB121	259443	RES	CF 33 OHMS 5% 1/4W	KINE DRIVER RED W/SVM
RB122	232249	RES	CFF 10 OHMS 5% 1/4W	KINE DRIVER RED W/SVM
RB125	232249	RES	CFF 10 OHMS 5% 1/4W	KINE DRIVER RED W/SVM
RB13	259469	RES	MF 267K 1% 1/4W	CONVERGENCE AMP BOARD
RB133	253722	RES	CMF 62.5MW 1% 2.21K	KINE DRIVER RED W/SVM
RB134	256735	RES	CMF 330 OHM 5% 1/16W	KINE DRIVER RED W/SVM
RB14	259486	RES	MFF .47 OHMS 10% .4W	CONVERGENCE AMP BOARD

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
RB140	258687	RES	CMF 18 OHM 5% 1/16W	KINE DRIVER RED W/SVM
RB141	259963	RES	MF 825 OHMS 1% 1/4W	KINE DRIVER RED W/SVM
RB142	245488	RES	MF 1/4W 1% 715 OHMS	KINE DRIVER RED W/SVM
RB143	243485	RES	CMF 1/16W 5% 1K	KINE DRIVER RED W/SVM
RB144	258704	RES	CFFP 470 OHMS 5% 1/2W	KINE DRIVER RED W/SVM
RB145	198717	RES	CF 1/4W 5% 470R	KINE DRIVER RED W/SVM
RB15	243375	RES	CMF 1/16W 5% 4.7K	CONVERGENCE AMP BOARD
RB150	258739	RES	MF 39K 2% 4W	KINE DRIVER RED W/SVM
RB153	259377	RES	CC 330 OHMS 10% 1/2W	KINE DRIVER RED W/SVM
RB154	259377	RES	CC 330 OHMS 10% 1/2W	KINE DRIVER RED W/SVM
RB155	263291	RES	CMF 1/10W 1% 10K	KINE DRIVER RED W/SVM
RB156	263291	RES	CMF 1/10W 1% 10K	KINE DRIVER RED W/SVM
RB157	243653	RES	CMF 1/16W 5% 100R	KINE DRIVER RED W/SVM
RB158	244865	RES	CC 1/2W 20% 47 OHMS	KINE DRIVER RED W/SVM
RB160	256754	RES	CMF 100K OHM 5% 1/16W	KINE DRIVER RED W/SVM
RB161	256754	RES	CMF 100K OHM 5% 1/16W	KINE DRIVER RED W/SVM
RB162	256754	RES	CMF 100K OHM 5% 1/16W	KINE DRIVER RED W/SVM
RB163	256746	RES	CMF 22K OHM 5% 1/16W	KINE DRIVER RED W/SVM
RB164	259339	RES	CF 100K 5% .7W	KINE DRIVER RED W/SVM
RB165	244871	RES	CC 1/2W 20% 1.5K	KINE DRIVER RED W/SVM
RB166	258708	RES	CF 3.3 MEGOHMS 5% .43W	KINE DRIVER RED W/SVM
RB167	258705	RES	CFFP 2.2KOHMS 5% 1/2W	KINE DRIVER RED W/SVM
RB169	244871	RES	CC 1/2W 20% 1.5K	KINE DRIVER RED W/SVM
RB171	244871	RES	CC 1/2W 20% 1.5K	KINE DRIVER RED W/SVM
RB182	NONSTK	WIREBARE	22	KINE DRIVER RED W/SVM
RB190	259423	RES	CF 100K 5% .14W	KINE DRIVER RED W/SVM
RB20	259471	RES	MF 2.43K 1% 1/4W	CONVERGENCE AMP BOARD
RB201	259443	RES	CF 33 OHMS 5% 1/4W	KINE DRIVER GREEN W/SVM
RB206	253719	RES	CMF 62.5MW 1% 475 OHM	KINE DRIVER GREEN W/SVM
RB207	253811	RES	CMF 62.5MW 1% 681 OHM	KINE DRIVER GREEN W/SVM
RB208	253719	RES	CMF 62.5MW 1% 475 OHM	KINE DRIVER GREEN W/SVM
RB209	253719	RES	CMF 62.5MW 1% 475 OHM	KINE DRIVER GREEN W/SVM
RB210	261152	RES	CMF 150 OHMS 5% 1/16W	KINE DRIVER GREEN W/SVM
RB211	253719	RES	CMF 62.5MW 1% 475 OHM	KINE DRIVER GREEN W/SVM
RB212	253719	RES	CMF 62.5MW 1% 475 OHM	KINE DRIVER GREEN W/SVM
RB214	253727	RES	CMF 62.5MW 1% 3.92K	KINE DRIVER GREEN W/SVM
RB220	198672	RES	CF 1/4W 5% 1.5K	KINE DRIVER GREEN W/SVM
RB221	259443	RES	CF 33 OHMS 5% 1/4W	KINE DRIVER GREEN W/SVM
RB222	232249	RES	CFF 10 OHMS 5% 1/4W	KINE DRIVER GREEN W/SVM
RB223	243653	RES	CMF 1/16W 5% 100R	KINE DRIVER GREEN W/SVM
RB225	232249	RES	CFF 10 OHMS 5% 1/4W	KINE DRIVER GREEN W/SVM
RB227	253727	RES	CMF 62.5MW 1% 3.92K	KINE DRIVER GREEN W/SVM
RB228	259767	RES	CMF 7.15K 1% 1/16	KINE DRIVER GREEN W/SVM
RB233	259843	RES	CMF 1.82K 1% 1/16W	KINE DRIVER GREEN W/SVM
RB234	256735	RES	CMF 330 OHM 5% 1/16W	KINE DRIVER GREEN W/SVM
RB235	263291	RES	CMF 1/10W 1% 10K	KINE DRIVER GREEN W/SVM
RB236	243653	RES	CMF 1/16W 5% 100R	KINE DRIVER GREEN W/SVM
RB237	253727	RES	CMF 62.5MW 1% 3.92K	KINE DRIVER GREEN W/SVM
RB238	256761	RES	CMF 2.2K OHM 5% 1/16W	KINE DRIVER GREEN W/SVM
RB240	258687	RES	CMF 18 OHM 5% 1/16W	KINE DRIVER GREEN W/SVM
RB241	259963	RES	MF 825 OHMS 1% 1/4W	KINE DRIVER GREEN W/SVM
RB242	245488	RES	MF 1/4W 1% 715 OHMS	KINE DRIVER GREEN W/SVM
RB243	243485	RES	CMF 1/16W 5% 1K	KINE DRIVER GREEN W/SVM
RB244	258704	RES	CFFP 470 OHMS 5% 1/2W	KINE DRIVER GREEN W/SVM
RB245	198717	RES	CF 1/4W 5% 470R	KINE DRIVER GREEN W/SVM
RB250	258739	RES	MF 39K 2% 4W	KINE DRIVER GREEN W/SVM
RB253	259377	RES	CC 330 OHMS 10% 1/2W	KINE DRIVER GREEN W/SVM
RB254	259377	RES	CC 330 OHMS 10% 1/2W	KINE DRIVER GREEN W/SVM
RB255	263291	RES	CMF 1/10W 1% 10K	KINE DRIVER GREEN W/SVM
RB256	263291	RES	CMF 1/10W 1% 10K	KINE DRIVER GREEN W/SVM
RB257	243653	RES	CMF 1/16W 5% 100R	KINE DRIVER GREEN W/SVM
RB258	244865	RES	CC 1/2W 20% 47 OHMS	KINE DRIVER GREEN W/SVM
RB260	256754	RES	CMF 100K OHM 5% 1/16W	KINE DRIVER GREEN W/SVM
RB261	256754	RES	CMF 100K OHM 5% 1/16W	KINE DRIVER GREEN W/SVM
RB262	256754	RES	CMF 100K OHM 5% 1/16W	KINE DRIVER GREEN W/SVM
RB263	256746	RES	CMF 22K OHM 5% 1/16W	KINE DRIVER GREEN W/SVM

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
RB264	259339		RES CF 100K 5% .7W	KINE DRIVER GREEN W/SVM
RB265	244871		RES CC 1/2W 20% 1.5K	KINE DRIVER GREEN W/SVM
RB266	258708		RES CF 3.3 MEGOHMS 5% .43W	KINE DRIVER GREEN W/SVM
RB267	258705		RES CFFP 2.2KOHMS 5% 1/2W	KINE DRIVER GREEN W/SVM
RB269	244871		RES CC 1/2W 20% 1.5K	KINE DRIVER GREEN W/SVM
RB271	244871		RES CC 1/2W 20% 1.5K	KINE DRIVER GREEN W/SVM
RB282	NONSTK		WIREBARE 22	KINE DRIVER GREEN W/SVM
RB290	259423		RES CF 100K 5% .14W	KINE DRIVER GREEN W/SVM
RB301	259443		RES CF 33 OHMS 5% 1/4W	KINE DRIVER BLUE W/SVM
RB306	253719		RES CMF 62.5MW 1% 475 OHM	KINE DRIVER BLUE W/SVM
RB307	253811		RES CMF 62.5MW 1% 681 OHM	KINE DRIVER BLUE W/SVM
RB308	253719		RES CMF 62.5MW 1% 475 OHM	KINE DRIVER BLUE W/SVM
RB309	253719		RES CMF 62.5MW 1% 475 OHM	KINE DRIVER BLUE W/SVM
RB310	261152		RES CMF 150 OHMS 5% 1/16W	KINE DRIVER BLUE W/SVM
RB311	253719		RES CMF 62.5MW 1% 475 OHM	KINE DRIVER BLUE W/SVM
RB312	253719		RES CMF 62.5MW 1% 475 OHM	KINE DRIVER BLUE W/SVM
RB314	253727		RES CMF 62.5MW 1% 3.92K	KINE DRIVER BLUE W/SVM
RB320	198672		RES CF 1/4W 5% 1.5K	KINE DRIVER BLUE W/SVM
RB321	259443		RES CF 33 OHMS 5% 1/4W	KINE DRIVER BLUE W/SVM
RB322	232249		RES CFF 10 OHMS 5% 1/4W	KINE DRIVER BLUE W/SVM
RB323	243653		RES CMF 1/16W 5% 100R	KINE DRIVER BLUE W/SVM
RB325	232249		RES CFF 10 OHMS 5% 1/4W	KINE DRIVER BLUE W/SVM
RB326	253718		RES CMF 62.5MW 1% 332 OHM	KINE DRIVER BLUE W/SVM
RB327	253722		RES CMF 62.5MW 1% 2.21K	KINE DRIVER BLUE W/SVM
RB328	259490		RES CMF 8.66K 1% 1/16W	KINE DRIVER BLUE W/SVM
RB330	259844		RES CMF 1.3K 1% 1/16W	KINE DRIVER BLUE W/SVM
RB331	259775		RES CMF 909 OHMS 1% 1/16W	KINE DRIVER BLUE W/SVM
RB332	243653		RES CMF 1/16W 5% 100R	KINE DRIVER BLUE W/SVM
RB333	253720		RES CMF 62.5MW 1% 1.5K	KINE DRIVER BLUE W/SVM
RB334	256735		RES CMF 330 OHM 5% 1/16W	KINE DRIVER BLUE W/SVM
RB335	263291		RES CMF 1/10W 1% 10K	KINE DRIVER BLUE W/SVM
RB336	243653		RES CMF 1/16W 5% 100R	KINE DRIVER BLUE W/SVM
RB337	253803		RES CMF 62.5MW 1% 1.21K	KINE DRIVER BLUE W/SVM
RB338	256761		RES CMF 2.2K OHM 5% 1/16W	KINE DRIVER BLUE W/SVM
RB339	253726		RES CMF 62.5MW 1% 2K	KINE DRIVER BLUE W/SVM
RB340	258687		RES CMF 18 OHM 5% 1/16W	KINE DRIVER BLUE W/SVM
RB341	259963		RES MF 825 OHMS 1% 1/4W	KINE DRIVER BLUE W/SVM
RB342	245488		RES MF 1/4W 1% 715 OHMS	KINE DRIVER BLUE W/SVM
RB343	243485		RES CMF 1/16W 5% 1K	KINE DRIVER BLUE W/SVM
RB344	258704		RES CFFP 470 OHMS 5% 1/2W	KINE DRIVER BLUE W/SVM
RB345	198717		RES CF 1/4W 5% 470R	KINE DRIVER BLUE W/SVM
RB350	258739		RES MF 39K 2% 4W	KINE DRIVER BLUE W/SVM
RB353	259377		RES CC 330 OHMS 10% 1/2W	KINE DRIVER BLUE W/SVM
RB354	259377		RES CC 330 OHMS 10% 1/2W	KINE DRIVER BLUE W/SVM
RB355	263291		RES CMF 1/10W 1% 10K	KINE DRIVER BLUE W/SVM
RB356	263291		RES CMF 1/10W 1% 10K	KINE DRIVER BLUE W/SVM
RB357	243653		RES CMF 1/16W 5% 100R	KINE DRIVER BLUE W/SVM
RB358	244865		RES CC 1/2W 20% 47 OHMS	KINE DRIVER BLUE W/SVM
RB360	256754		RES CMF 100K OHM 5% 1/16W	KINE DRIVER BLUE W/SVM
RB361	256754		RES CMF 100K OHM 5% 1/16W	KINE DRIVER BLUE W/SVM
RB362	256754		RES CMF 100K OHM 5% 1/16W	KINE DRIVER BLUE W/SVM
RB363	256746		RES CMF 22K OHM 5% 1/16W	KINE DRIVER BLUE W/SVM
RB364	259339		RES CF 100K 5% .7W	KINE DRIVER BLUE W/SVM
RB365	244871		RES CC 1/2W 20% 1.5K	KINE DRIVER BLUE W/SVM
RB366	258708		RES CF 3.3 MEGOHMS 5% .43W	KINE DRIVER BLUE W/SVM
RB367	258705		RES CFFP 2.2KOHMS 5% 1/2W	KINE DRIVER BLUE W/SVM
RB369	244871		RES CC 1/2W 20% 1.5K	KINE DRIVER BLUE W/SVM
RB371	244871		RES CC 1/2W 20% 1.5K	KINE DRIVER BLUE W/SVM
RB382	NONSTK		WIREBARE 22	KINE DRIVER BLUE W/SVM
RB390	259423		RES CF 100K 5% .14W	KINE DRIVER BLUE W/SVM
RB50	243485		RES CMF 1/16W 5% 1K	CONVERGENCE AMP BOARD
RB51	259472		RES MF 332 OHMS 1% 1/4W	CONVERGENCE AMP BOARD
RB52	259471		RES MF 2.43K 1% 1/4W	CONVERGENCE AMP BOARD
RB53	259465		RES MF 162 OHMS 1% 1/4W	CONVERGENCE AMP BOARD
RB54	259342		RES CF 10K 5% .7W	CONVERGENCE AMP BOARD
RB55	259469		RES MF 267K 1% 1/4W	CONVERGENCE AMP BOARD

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
RB56	259475		RES MF 3.32K 1% 1/4W	CONVERGENCE AMP BOARD
RB57	259358		RES MF 1.8 OHMS 1% 1W	CONVERGENCE AMP BOARD
RB58	259486		RES MFF .47 OHMS 10% .4W	CONVERGENCE AMP BOARD
RB59	259486		RES MFF .47 OHMS 10% .4W	CONVERGENCE AMP BOARD
RB60	259485		RES MF 8.87K 1% 1/4W	CONVERGENCE AMP BOARD
RB61	259476		RES MF 3.9K 1% .4W	CONVERGENCE AMP BOARD
RB62	243375		RES CMF 1/16W 5% 4.7K	CONVERGENCE AMP BOARD
RB64	259471		RES MF 2.43K 1% 1/4W	CONVERGENCE AMP BOARD
RB66	243375		RES CMF 1/16W 5% 4.7K	CONVERGENCE AMP BOARD
RRC546	243653		RES CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RRC547	243653		RES CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RRC552	249338		RES CMF 47K 62.5MW 5%	SMALL SIGNAL BOARD
RRC558	256743		RES CMF 15K OHM 5% 1/16W	SMALL SIGNAL BOARD
RRC746	243653		RES CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RRC747	243653		RES CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RRC748	243485		RES CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RRC752	249338		RES CMF 47K 62.5MW 5%	SMALL SIGNAL BOARD
RRC758	256743		RES CMF 15K OHM 5% 1/16W	SMALL SIGNAL BOARD
RRC921	243653		RES CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RRC950	260677		RES CMF 1/16W 5% 10R	SMALL SIGNAL BOARD
RRC952	242690		RES CMF 1/16W 5% 10K	SMALL SIGNAL BOARD
RRC953	243485		RES CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RRC954	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
RRC961	243653		RES CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RD100	259976		RES MF 10 OHMS 5% 1W	MPEG CBA
RD101	256762		RES CMF 2.7K +5% 62.5MW	MPEG CBA
RD102	256765		RES CMF 1/16W 5% 5.6K	MPEG CBA
RD103	242690		RES CMF 1/16W 5% 10K	MPEG CBA
RD104	243649		RES CMF 5.1K +5% 1/16W	MPEG CBA
RD105	242690		RES CMF 1/16W 5% 10K	MPEG CBA
RD106	256751		RES CMF 68K OHM +5% 62.5MW	MPEG CBA
RD107	244056		RES CMF 470 OHM 5% 62.5MW	MPEG CBA
RD108	244056		RES CMF 470 OHM 5% 62.5MW	MPEG CBA
RD109	249338		RES CMF 47K 62.5MW 5%	MPEG CBA
RD227	243375		RES CMF 1/16W 5% 4.7K	MPEG CBA
RD228	243375		RES CMF 1/16W 5% 4.7K	MPEG CBA
RD900	256783		RES CMF 1/16W 0% 0R	SPDIF OUTPUT
RE219	244078		RES CMF 1/16W 5% 1M	MPEG CBA
RE229	243653		RES CMF 1/16W 5% 100R	MPEG CBA
RE231	243222		RESCF 200 OHM +5%	MPEG CBA
REMOTE	257003		TRANSMITTER, REM: RCR160TALM1	INSTRUMENT ASSEMBLY
RRF002	259424		RES CF 12K 5% .14W	P-S/DEFLECTION
RRF003	259467		RES MF 1.3K 1% .4W	P-S/DEFLECTION
RRF004	259446		RES CF 3.3K 5% .14W	P-S/DEFLECTION
RRF005	259446		RES CF 3.3K 5% .14W	P-S/DEFLECTION
RRF006	259467		RES MF 1.3K 1% .4W	P-S/DEFLECTION
RRF008	259230		RES MF 1.5 OHMS 1% .7W	P-S/DEFLECTION
RRF009	259326		RES CF 2.2 OHMS 5% .43W	P-S/DEFLECTION
RRF011	259230		RES MF 1.5 OHMS 1% .7W	P-S/DEFLECTION
RRF012	259230		RES MF 1.5 OHMS 1% .7W	P-S/DEFLECTION
RRF020	259346		RES MF 330 OHMS 10% 1W	P-S/DEFLECTION
RRF022	259446		RES CF 3.3K 5% .14W	P-S/DEFLECTION
RRF040	216176		RES CF .14W 5% 1K	P-S/DEFLECTION
RRF041	259434		RES CF 22K 5% .14W	P-S/DEFLECTION
RG01	259476		RES MF 3.9K 1% .4W	CONVERGENCE AMP BOARD
RG02	258180		RES CF 1K 5% 1/4W	CONVERGENCE AMP BOARD
RG03	259472		RES MF 332 OHMS 1% 1/4W	CONVERGENCE AMP BOARD
RG04	259471		RES MF 2.43K 1% 1/4W	CONVERGENCE AMP BOARD
RG05	259465		RES MF 162 OHMS 1% 1/4W	CONVERGENCE AMP BOARD
RG06	259342		RES CF 10K 5% .7W	CONVERGENCE AMP BOARD
RG07	259485		RES MF 8.87K 1% 1/4W	CONVERGENCE AMP BOARD
RG08	243375		RES CMF 1/16W 5% 4.7K	CONVERGENCE AMP BOARD
RG09	259358		RES MF 1.8 OHMS 1% 1W	CONVERGENCE AMP BOARD
RG10	259475		RES MF 3.32K 1% 1/4W	CONVERGENCE AMP BOARD
RG101	259559		RES CMF 5.6 OHMS 5% 1/16W	KINE DRIVER RED W/SVM
RG102	259556		RES CF 2K 5% 1/4W	KINE DRIVER RED W/SVM

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
RG103	256942	RES	CMF 220 OHM 5% 1/16W	KINE DRIVER RED W/SVM
RG104	256740	RES	CMF 430 OHMS 5% 1/16W	KINE DRIVER RED W/SVM
RG105	253721	RES	CMF 62.5MW 1% 1.82K	KINE DRIVER RED W/SVM
RG106	256735	RES	CMF 330 OHM 5% 1/16W	KINE DRIVER RED W/SVM
RG108	256942	RES	CMF 220 OHM 5% 1/16W	KINE DRIVER RED W/SVM
RG110	256744	RES	CMF 18K OHM 5% 1/16W	KINE DRIVER RED W/SVM
RG112	244074	RES	CMF 47 OHM +5% 62.5MW	KINE DRIVER RED W/SVM
RG113	259568	RES	CMF 3.3 OHMS 5% 1/16W	KINE DRIVER RED W/SVM
RG119	258180	RES	CF 1K 5% 1/4W	KINE DRIVER RED W/SVM
RG12	259486	RES	MFF .47 OHMS 10% .4W	CONVERGENCE AMP BOARD
RG121	232443	RES	CF 1/4W 5% 82K	KINE DRIVER RED W/SVM
RG123	252359	RES	CF 1K 1% 1/10W	KINE DRIVER RED W/SVM
RG124	244041	RES	CMF 1/16W 5% 1.6K	MPEG CBA
RG125	244041	RES	CMF 1/16W 5% 1.6K	MPEG CBA
RG126	259643	RES	MF 3.3K 5% 3W	KINE DRIVER RED W/SVM
RG127	259643	RES	MF 3.3K 5% 3W	KINE DRIVER RED W/SVM
RG128	256754	RES	CMF 100K OHM 5% 1/16W	KINE DRIVER RED W/SVM
RG129	210190	RES	CF .43W 5% 1K	KINE DRIVER RED W/SVM
RG13	259469	RES	MF 267K 1% 1/4W	CONVERGENCE AMP BOARD
RG130	259459	RES	CFF 22 OHMS 5% 1/4W	KINE DRIVER RED W/SVM
RG132	232443	RES	CF 1/4W 5% 82K	KINE DRIVER RED W/SVM
RG134	258177	RES	CF 4.7K 5% 1/4W	KINE DRIVER RED W/SVM
RG135	243485	RES	CMF 1/16W 5% 1K	KINE DRIVER RED W/SVM
RG136	198728	RES	CF 1/4W 5% 100K	KINE DRIVER RED W/SVM
RG137	260677	RES	CMF 10 OHM +5% 1/16W	KINE DRIVER RED W/SVM
RG138	216176	RES	CF .14W 5% 1K	KINE DRIVER RED W/SVM
RG139	259424	RES	CF 12K 5% .14W	KINE DRIVER RED W/SVM
RG14	259486	RES	MFF .47 OHMS 10% .4W	CONVERGENCE AMP BOARD
RG140	253627	RES	CMF 62.5MW 5% 180K	KINE DRIVER RED W/SVM
RG141	244074	RES	CMF 47 OHM +5% 62.5MW	KINE DRIVER RED W/SVM
RG142	175769	RES	CF 1/2W 5% 390R	KINE DRIVER RED W/SVM
RG15	243375	RES	CMF 1/16W 5% 4.7K	CONVERGENCE AMP BOARD
RG161	260677	RES	CMF 1/16W 5% 10R	MPEG CBA
RG162	260677	RES	CMF 1/16W 5% 10R	MPEG CBA
RG163	256824	RES	CMF 16.5K OHM 1% 1/16W	MPEG CBA
RG164	256824	RES	CMF 16.5K OHM 1% 1/16W	MPEG CBA
RG173	243653	RES	CMF 1/16W 5% 100R	MPEG CBA
RG190	242690	RES	CMF 1/16W 5% 10K	MPEG CBA
RG191	242690	RES	CMF 1/16W 5% 10K	MPEG CBA
RG194	242690	RES	CMF 1/16W 5% 10K	MPEG CBA
RG20	259471	RES	MF 2.43K 1% 1/4W	CONVERGENCE AMP BOARD
RG201	259559	RES	CMF 5.6 OHMS 5% 1/16W	KINE DRIVER GREEN W/SVM
RG202	259556	RES	CF 2K 5% 1/4W	KINE DRIVER GREEN W/SVM
RG203	256942	RES	CMF 220 OHM 5% 1/16W	KINE DRIVER GREEN W/SVM
RG204	256740	RES	CMF 430 OHMS 5% 1/16W	KINE DRIVER GREEN W/SVM
RG205	253721	RES	CMF 62.5MW 1% 1.82K	KINE DRIVER GREEN W/SVM
RG206	256735	RES	CMF 330 OHM 5% 1/16W	KINE DRIVER GREEN W/SVM
RG208	256942	RES	CMF 220 OHM 5% 1/16W	KINE DRIVER GREEN W/SVM
RG210	256744	RES	CMF 18K OHM 5% 1/16W	KINE DRIVER GREEN W/SVM
RG212	244074	RES	CMF 47 OHM +5% 62.5MW	KINE DRIVER GREEN W/SVM
RG213	259568	RES	CMF 3.3 OHMS 5% 1/16W	KINE DRIVER GREEN W/SVM
RG219	258180	RES	CF 1K 5% 1/4W	KINE DRIVER GREEN W/SVM
RG221	232443	RES	CF 1/4W 5% 82K	KINE DRIVER GREEN W/SVM
RG223	252359	RES	CF 1K 1% 1/10W	KINE DRIVER GREEN W/SVM
RG225	242690	RES	CMF 1/16W 5% 10K	MPEG CBA
RG226	242690	RES	CMF 1/16W 5% 10K	MPEG CBA
RG226	259643	RES	MF 3.3K 5% 3W	KINE DRIVER GREEN W/SVM
RG227	259643	RES	MF 3.3K 5% 3W	KINE DRIVER GREEN W/SVM
RG228	256754	RES	CMF 100K OHM 5% 1/16W	KINE DRIVER GREEN W/SVM
RG229	210190	RES	CF .43W 5% 1K	KINE DRIVER GREEN W/SVM
RG230	259459	RES	CFF 22 OHMS 5% 1/4W	KINE DRIVER GREEN W/SVM
RG232	232443	RES	CF 1/4W 5% 82K	KINE DRIVER GREEN W/SVM
RG234	258177	RES	CF 4.7K 5% 1/4W	KINE DRIVER GREEN W/SVM
RG235	243485	RES	CMF 1/16W 5% 1K	KINE DRIVER GREEN W/SVM
RG236	198728	RES	CF 1/4W 5% 100K	KINE DRIVER GREEN W/SVM
RG237	260677	RES	CMF 10 OHM +5% 1/16W	KINE DRIVER GREEN W/SVM

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
RG238	216176	RES	CF .14W 5% 1K	KINE DRIVER GREEN W/SVM
RG239	259424	RES	CF 12K 5% .14W	KINE DRIVER GREEN W/SVM
RG240	243480	RES	MF 68 OHM +5%	MPEG CBA
RG240	253627	RES	CMF 62.5MW 5% 180K	KINE DRIVER GREEN W/SVM
RG241	244074	RES	CMF 47 OHM +5% 62.5MW	KINE DRIVER GREEN W/SVM
RG242	175769	RES	CF 1/2W 5% 390R	KINE DRIVER GREEN W/SVM
RG249	243653	RES	CMF 1/16W 5% 100R	MPEG CBA
RG301	259559	RES	CMF 5.6 OHMS 5% 1/16W	KINE DRIVER BLUE W/SVM
RG302	259556	RES	CF 2K 5% 1/4W	KINE DRIVER BLUE W/SVM
RG303	256942	RES	CMF 220 OHM 5% 1/16W	KINE DRIVER BLUE W/SVM
RG304	249038	RES	CMF 560 OHM 5% 1/16W	KINE DRIVER BLUE W/SVM
RG305	253721	RES	CMF 62.5MW 1% 1.82K	KINE DRIVER BLUE W/SVM
RG306	256735	RES	CMF 330 OHM 5% 1/16W	KINE DRIVER BLUE W/SVM
RG308	256942	RES	CMF 220 OHM 5% 1/16W	KINE DRIVER BLUE W/SVM
RG310	256744	RES	CMF 18K OHM 5% 1/16W	KINE DRIVER BLUE W/SVM
RG312	244074	RES	CMF 47 OHM +5% 62.5MW	KINE DRIVER BLUE W/SVM
RG313	259568	RES	CMF 3.3 OHMS 5% 1/16W	KINE DRIVER BLUE W/SVM
RG319	258180	RES	CF 1K 5% 1/4W	KINE DRIVER BLUE W/SVM
RG321	232443	RES	CF 1/4W 5% 82K	KINE DRIVER BLUE W/SVM
RG323	252359	RES	CF 1K 1% 1/10W	KINE DRIVER BLUE W/SVM
RG326	259643	RES	MF 3.3K 5% 3W	KINE DRIVER BLUE W/SVM
RG327	259643	RES	MF 3.3K 5% 3W	KINE DRIVER BLUE W/SVM
RG328	256754	RES	CMF 100K OHM 5% 1/16W	KINE DRIVER BLUE W/SVM
RG329	210190	RES	CF .43W 5% 1K	KINE DRIVER BLUE W/SVM
RG330	259459	RES	CFF 22 OHMS 5% 1/4W	KINE DRIVER BLUE W/SVM
RG332	232443	RES	CF 1/4W 5% 82K	KINE DRIVER BLUE W/SVM
RG334	258177	RES	CF 4.7K 5% 1/4W	KINE DRIVER BLUE W/SVM
RG335	243485	RES	CMF 1/16W 5% 1K	KINE DRIVER BLUE W/SVM
RG336	198728	RES	CF 1/4W 5% 100K	KINE DRIVER BLUE W/SVM
RG337	260677	RES	CMF 10 OHM +5% 1/16W	KINE DRIVER BLUE W/SVM
RG338	216176	RES	CF .14W 5% 1K	KINE DRIVER BLUE W/SVM
RG339	259424	RES	CF 12K 5% .14W	KINE DRIVER BLUE W/SVM
RG340	253627	RES	CMF 62.5MW 5% 180K	KINE DRIVER BLUE W/SVM
RG341	244074	RES	CMF 47 OHM +5% 62.5MW	KINE DRIVER BLUE W/SVM
RG342	175769	RES	CF 1/2W 5% 390R	KINE DRIVER BLUE W/SVM
RG50	258180	RES	CF 1K 5% 1/4W	CONVERGENCE AMP BOARD
RG500	259993	RES	CMF 24.9K 1% 1/16W	MPEG CBA
RG501	256761	RES	CMF 2.2K OHM 5% 1/16W	MPEG CBA
RG502	252357	RES	CF 1/10W 1% 20K	MPEG CBA
RG507	256761	RES	CMF 2.2K OHM 5% 1/16W	MPEG CBA
RG508	243480	RES	MF 68 OHM +5%	MPEG CBA
RG51	259472	RES	MF 332 OHMS 1% 1/4W	CONVERGENCE AMP BOARD
RG514	243480	RES	MF 68 OHM +5%	MPEG CBA
RG515	243480	RES	MF 68 OHM +5%	MPEG CBA
RG516	242690	RES	CMF 1/16W 5% 10K	MPEG CBA
RG517	242690	RES	CMF 1/16W 5% 10K	MPEG CBA
RG52	259607	RES	CMF 2.43K 1% 1/16W	CONVERGENCE AMP BOARD
RG520	242690	RES	CMF 1/16W 5% 10K	MPEG CBA
RG53	259465	RES	MF 162 OHMS 1% 1/4W	CONVERGENCE AMP BOARD
RG54	259342	RES	CF 10K 5% .7W	CONVERGENCE AMP BOARD
RG542	242690	RES	CMF 1/16W 5% 10K	MPEG CBA
RG543	256783	RES	CMF 1/16W 0% 0R	MPEG CBA
RG55	259469	RES	MF 267K 1% 1/4W	CONVERGENCE AMP BOARD
RG56	259475	RES	MF 3.32K 1% 1/4W	CONVERGENCE AMP BOARD
RG57	259358	RES	MF 1.8 OHMS 1% 1W	CONVERGENCE AMP BOARD
RG58	259486	RES	MFF .47 OHMS 10% .4W	CONVERGENCE AMP BOARD
RG59	259486	RES	MFF .47 OHMS 10% .4W	CONVERGENCE AMP BOARD
RG60	259485	RES	MF 8.87K 1% 1/4W	CONVERGENCE AMP BOARD
RG61	259476	RES	MF 3.9K 1% .4W	CONVERGENCE AMP BOARD
RG62	258177	RES	CF 4.7K 5% 1/4W	CONVERGENCE AMP BOARD
RG64	259471	RES	MF 2.43K 1% 1/4W	CONVERGENCE AMP BOARD
RRH020	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RRH021	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RRH030	256743	RES	CMF 15K OHM 5% 1/16W	SMALL SIGNAL BOARD
RRH031	246960	RES	CMF 3.9K 5% 1/16W	SMALL SIGNAL BOARD
RRH032	256739	RES	CMF 680 OHM 5% 1/16W	SMALL SIGNAL BOARD

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
RRH034	256754		RES CMF 100K OHM 5% 1/16W	SMALL SIGNAL BOARD
RRH126	242690		RES CMF 1/16W 5% 10K	MPEG CBA
RRH134	242690		RES CMF 1/16W 5% 10K	MPEG CBA
RRH135	243485		RES CMF 1/16W 5% 1K	MPEG CBA
RRH245	256783		RES CMF 1/16W 0% 0R	MPEG CBA
RRH246	243485		RES CMF 1/16W 5% 1K	MPEG CBA
RRH520	243653		RES CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RRH521	243653		RES CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RRH522	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
RRH530	256743		RES CMF 15K OHM 5% 1/16W	SMALL SIGNAL BOARD
RRH531	246960		RES CMF 3.9K 5% 1/16W	SMALL SIGNAL BOARD
RRH532	256739		RES CMF 680 OHM 5% 1/16W	SMALL SIGNAL BOARD
RRH533	256754		RES CMF 100K OHM 5% 1/16W	SMALL SIGNAL BOARD
RI002	256729		RES CMF 82 OHM 5% 1/16W	SMALL SIGNAL BOARD
RI007	256761		RES CMF 2.2K OHM 5% 1/16W	SMALL SIGNAL BOARD
RI008	256759		RES CMF 1/16W 5% 1.5K	SMALL SIGNAL BOARD
RI010	246964		RESCMF 6.8K OHM +5% 62.5W	SMALL SIGNAL BOARD
RI011	181491		RES CMF 1/8W 5% 180R	SMALL SIGNAL BOARD
RI012	244074		RES CMF 47 OHM +5% 62.5MW	SMALL SIGNAL BOARD
RI022	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
RI028	258691		RES CMF 1.2 MEG OHMS 5% 1/16W	SMALL SIGNAL BOARD
RI029	243486		RES CMF 390 OHMS 5% 1/16W	SMALL SIGNAL BOARD
RI030	243485		RES CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RI031	206379		RES CMF 1/8W 5% 330R	SMALL SIGNAL BOARD
RI032	256942		RES CMF 1/16W 5% 220R	SMALL SIGNAL BOARD
RI033	260677		RES CMF 1/16W 5% 10R	SMALL SIGNAL BOARD
RI034	260643		RES CMF 1/16W 5% 180R	SMALL SIGNAL BOARD
RI035	243485		RES CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RI036	206379		RES CMF 1/8W 5% 330R	SMALL SIGNAL BOARD
RI507	243375		RES CMF 1/16W 5% 4.7K	SMALL SIGNAL BOARD
RI522	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
RI527	256761		RES CMF 2.2K OHM 5% 1/16W	SMALL SIGNAL BOARD
RI528	258692		RES CMF 2.2 MEG OHMS 5% 1/16W	SMALL SIGNAL BOARD
RI529	243486		RES CMF 390 OHMS 5% 1/16W	SMALL SIGNAL BOARD
RI530	243485		RES CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RI531	206379		RES CMF 1/8W 5% 330R	SMALL SIGNAL BOARD
RI532	256942		RES CMF 1/16W 5% 220R	SMALL SIGNAL BOARD
RI533	260677		RES CMF 1/16W 5% 10R	SMALL SIGNAL BOARD
RI534	260643		RES CMF 1/16W 5% 180R	SMALL SIGNAL BOARD
RI535	243485		RES CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RI536	206379		RES CMF 1/8W 5% 330R	SMALL SIGNAL BOARD
RRK001	256743		RES CMF 15K OHM 5% 1/16W	FRONT PANEL 1
RRK002	243485		RES CMF 1/16W 5% 1K	FRONT PANEL 1
RRK003	253848		RES CMF 62.5MW 1% 39.2K	FRONT PANEL 1
RRK004	243485		RES CMF 1/16W 5% 1K	FRONT PANEL 1
RRK005	243485		RES CMF 1/16W 5% 1K	FRONT PANEL 1
RRK007	256942		RES CMF 1/16W 5% 220R	FRONT PANEL 1
RRK008	256942		RES CMF 1/16W 5% 220R	FRONT PANEL 1
RRK01	256743		RES CMF 15K OHM 5% 1/16W	CONVERGENCE SIGNAL BOAR
RRK010	243485		RES CMF 1/16W 5% 1K	FRONT PANEL 1
RRK012	256743		RES CMF 15K OHM 5% 1/16W	FRONT PANEL 1
RRK015	253848		RES CMF 62.5MW 1% 39.2K	FRONT PANEL 1
RRK016	256761		RES CMF 2.2K OHM 5% 1/16W	FRONT PANEL 1
RRK018	256761		RES CMF 2.2K OHM 5% 1/16W	FRONT PANEL 1
RRK019	256761		RES CMF 2.2K OHM 5% 1/16W	FRONT PANEL 1
RRK02	243375		RES CMF 1/16W 5% 4.7K	CONVERGENCE SIGNAL BOAR
RRK020	256761		RES CMF 2.2K OHM 5% 1/16W	FRONT PANEL 1
RRK021	256783		RES CMF 1/16W 0% 0R	FRONT PANEL 1
RRK022	259433		RES CF 1M 5% 1/4W	FRONT PANEL 1
RRK023	256761		RES CMF 2.2K OHM 5% 1/16W	FRONT PANEL 1
RRK024	246964		RES CMF 6.8K OHM +5% 62.5W	FRONT PANEL 1
RRK025	243485		RES CMF 1/16W 5% 1K	FRONT PANEL 1
RRK027	256761		RES CMF 2.2K OHM 5% 1/16W	FRONT PANEL 1
RRK03	243375		RES CMF 1/16W 5% 4.7K	CONVERGENCE SIGNAL BOAR
RRK031	242690		RES CMF 1/16W 5% 10K	FRONT PANEL 1
RRK032	258180		RES CF 1K 5% 1/4W	FRONT PANEL 1

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
RRK033	243375		RES CMF 1/16W 5% 4.7K	FRONT PANEL 1
RRK038	256754		RES CMF 100K OHM 5% 1/16W	FRONT PANEL 1
RRK039	256754		RES CMF 100K OHM 5% 1/16W	FRONT PANEL 1
RRK04	256743		RES CMF 15K OHM 5% 1/16W	CONVERGENCE SIGNAL BOAR
RRK040	256754		RES CMF 100K OHM 5% 1/16W	FRONT PANEL 1
RRK041	256754		RES CMF 100K OHM 5% 1/16W	FRONT PANEL 1
RRK042	256743		RES CMF 15K OHM 5% 1/16W	FRONT PANEL 1
RRK043	256743		RES CMF 15K OHM 5% 1/16W	FRONT PANEL 1
RRK044	243375		RES CMF 1/16W 5% 4.7K	FRONT PANEL 1
RRK046	243661		RES CMF 270 OHM +5%	FRONT PANEL 1
RRK050	220663		RES CF 1/4W 5% 22K	FRONT PANEL 1
RRK052	243485		RES CMF 1/16W 5% 1K	FRONT PANEL 1
RRK054	242690		RES CMF 1/16W 5% 10K	FRONT PANEL 1
RRK055	256754		RES CMF 100K OHM 5% 1/16W	FRONT PANEL 1
RRK056	241312		RES CF 1/4W 5% 10K	FRONT PANEL 1
RRK057	242690		RES CMF 1/16W 5% 10K	FRONT PANEL 1
RRK06	256737		RES CMF 430 OHMS 5% 1/16W	CONVERGENCE SIGNAL BOAR
RRK061	242690		RES CMF 1/16W 5% 10K	FRONT PANEL 1
RRK062	256783		RES CMF 1/16W 0% 0R	FRONT PANEL 1
RRK063	242690		RES CMF 1/16W 5% 10K	FRONT PANEL 1
RRK07	243653		RES CMF 1/16W 5% 100R	CONVERGENCE SIGNAL BOAR
RRK09	259840		RES CMF 374 OHMS 1% 1/16W	CONVERGENCE SIGNAL BOAR
RRK10	243485		RES CMF 1/16W 5% 1K	CONVERGENCE SIGNAL BOAR
RRK11	259840		RES CMF 374 OHMS 1% 1/16W	CONVERGENCE SIGNAL BOAR
RRK12	259840		RES CMF 374 OHMS 1% 1/16W	CONVERGENCE SIGNAL BOAR
RRK13	259840		RES CMF 374 OHMS 1% 1/16W	CONVERGENCE SIGNAL BOAR
RRK14	259840		RES CMF 374 OHMS 1% 1/16W	CONVERGENCE SIGNAL BOAR
RRK15	259840		RES CMF 374 OHMS 1% 1/16W	CONVERGENCE SIGNAL BOAR
RRK169	256754		RES CMF 100K OHM 5% 1/16W	MPEG CBA
RRK20	259840		RES CMF 374 OHMS 1% 1/16W	CONVERGENCE SIGNAL BOAR
RRK201	259430		RES CF 1K 2% 1/4W	IR PREAMP
RRK202	220648		RES CF 1/4W 5% 270R	IR PREAMP
RRK22	243653		RES CMF 1/16W 5% 100R	CONVERGENCE SIGNAL BOAR
RRK221	244056		RES CMF 470 OHM 5% 62.5MW	MPEG CBA
RRK222	256783		RES CMF 1/16W 0% 0R	MPEG CBA
RRK223	256783		RES CMF 1/16W 0% 0R	MPEG CBA
RRK224	256783		RES CMF 1/16W 0% 0R	MPEG CBA
RRK225	244056		RES CMF 470 OHM 5% 62.5MW	MPEG CBA
RRK24	256741		RES CMF 10K OHM 5% 1/16W	CONVERGENCE SIGNAL BOAR
RRK25	263913		RES CMF 1K 1% 1/16W	CONVERGENCE SIGNAL BOAR
RRK26	243653		RES CMF 1/16W 5% 100R	CONVERGENCE SIGNAL BOAR
RRK27	243653		RES CMF 1/16W 5% 100R	CONVERGENCE SIGNAL BOAR
RRK28	243653		RES CMF 1/16W 5% 100R	CONVERGENCE SIGNAL BOAR
RRK30	243485		RES CMF 1/16W 5% 1K	CONVERGENCE SIGNAL BOAR
RRK31	243485		RES CMF 1/16W 5% 1K	CONVERGENCE SIGNAL BOAR
RRK32	243485		RES CMF 1/16W 5% 1K	CONVERGENCE SIGNAL BOAR
RRK33	243485		RES CMF 1/16W 5% 1K	CONVERGENCE SIGNAL BOAR
RRK35	259839		RES CMF 324 OHMS 1% 1/16W	CONVERGENCE SIGNAL BOAR
RRK36	259839		RES CMF 324 OHMS 1% 1/16W	CONVERGENCE SIGNAL BOAR
RRK37	259839		RES CMF 324 OHMS 1% 1/16W	CONVERGENCE SIGNAL BOAR
RRK39	259839		RES CMF 324 OHMS 1% 1/16W	CONVERGENCE SIGNAL BOAR
RRK40	259839		RES CMF 324 OHMS 1% 1/16W	CONVERGENCE SIGNAL BOAR
RRK41	259839		RES CMF 324 OHMS 1% 1/16W	CONVERGENCE SIGNAL BOAR
RRK42	259839		RES CMF 324 OHMS 1% 1/16W	CONVERGENCE SIGNAL BOAR
RRK44	256761		RES CMF 2.2K OHM 5% 1/16W	CONVERGENCE SIGNAL BOAR
RRK45	243653		RES CMF 1/16W 5% 100R	CONVERGENCE SIGNAL BOAR
RRK46	243653		RES CMF 1/16W 5% 100R	CONVERGENCE SIGNAL BOAR
RRK47	243653		RES CMF 1/16W 5% 100R	CONVERGENCE SIGNAL BOAR
RRK48	243653		RES CMF 1/16W 5% 100R	CONVERGENCE SIGNAL BOAR
RRK50	256741		RES CMF 10K OHM 5% 1/16W	CONVERGENCE SIGNAL BOAR
RRK52	253624		RES CMF 62.5MW 5% 82K	CONVERGENCE SIGNAL BOAR
RRK53	256741		RES CMF 10K OHM 5% 1/16W	CONVERGENCE SIGNAL BOAR
RRK54	256741		RES CMF 10K OHM 5% 1/16W	CONVERGENCE SIGNAL BOAR
RRK56	256768		RES CMF 8.2K OHM 5% 1/16W	CONVERGENCE SIGNAL BOAR
RRK59	243485		RES CMF 1/16W 5% 1K	CONVERGENCE SIGNAL BOAR
RRK60	259841		RES CMF 2.43K 1% 1/16W	CONVERGENCE SIGNAL BOAR

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
RRK62	259841	RES	CMF 2.43K 1% 1/16W	CONVERGENCE SIGNAL BOAR
RRK64	259841	RES	CMF 2.43K 1% 1/16W	CONVERGENCE SIGNAL BOAR
RRK66	259841	RES	CMF 2.43K 1% 1/16W	CONVERGENCE SIGNAL BOAR
RRK68	259841	RES	CMF 2.43K 1% 1/16W	CONVERGENCE SIGNAL BOAR
RRK70	259841	RES	CMF 2.43K 1% 1/16W	CONVERGENCE SIGNAL BOAR
RRK72	256737	RES	CMF 430 OHMS 5% 1/16W	CONVERGENCE SIGNAL BOAR
RRK85	256762	RES	CMF 2.7K OHM 5% 1/16W	CONVERGENCE SIGNAL BOAR
RRK86	256737	RES	CMF 430 OHMS 5% 1/16W	CONVERGENCE SIGNAL BOAR
RRK87	256764	RES	CMF 3.3K OHM 5% 1/16W	CONVERGENCE SIGNAL BOAR
RRK88	256741	RES	CMF 10K OHM 5% 1/16W	CONVERGENCE SIGNAL BOAR
RRK90	243653	RES	CMF 1/16W 5% 100R	CONVERGENCE SIGNAL BOAR
RRK93	243485	RES	CMF 1/16W 5% 1K	CONVERGENCE SIGNAL BOAR
RRK95	256746	RES	CMF 22K OHM 5% 1/16W	CONVERGENCE SIGNAL BOAR
RRK99	243375	RES	CMF 1/16W 5% 4.7K	CONVERGENCE SIGNAL BOAR
RL001	258180	RES	CF 1K 5% 1/4W	P-S/DEFLECTION
RL002	211857	RES	CF 1/4W 5% 15R	P-S/DEFLECTION
RL003	203785	RES	CF .14W 5% 100R	P-S/DEFLECTION
RL004	259435	RES	CF 2.2K 5% .14W	P-S/DEFLECTION
RL005	184838	RES	CF .14W 5% 10K	P-S/DEFLECTION
RL006	259423	RES	CF 100K 5% .14W	P-S/DEFLECTION
RL007	263125	RES	CF .14W 5% 47K	P-S/DEFLECTION
RL008	259448	RES	CF 470K 5% .14W	P-S/DEFLECTION
RL009	259448	RES	CF 470K 5% .14W	P-S/DEFLECTION
RL010	259426	RES	CF 150K 5% .14W	P-S/DEFLECTION
RL014	210192	RES	CF .43W 5% 10 OHMS	P-S/DEFLECTION
RL015	259461	RES	CF 5.6 OHMS 5% 1/4W	P-S/DEFLECTION
RL016	259442	RES	CF 33 OHMS 5% .14W	P-S/DEFLECTION
RL021	259230	RES	MF 1.5 OHMS 1% .7W	P-S/DEFLECTION
RL022	179753	RES	MF 1/4W 1% 1K	P-S/DEFLECTION
RL023	259336	RES	MF 3.9M 2% .4W	P-S/DEFLECTION
RL024	259462	RES	MF 100K 1% 1/4W	P-S/DEFLECTION
RL025	259230	RES	MF 1.5 OHMS 1% .7W	P-S/DEFLECTION
RL026	216176	RES	CF .14W 5% 1K	P-S/DEFLECTION
RL027	258705	RES	CFFP 2.2KOHMS 5% 1/2W	P-S/DEFLECTION
RL028	256803	RES	CF 1/4W 5% 47K	P-S/DEFLECTION
RL029	263129	RES	CF .14W 5% 68K	P-S/DEFLECTION
RL030	259564	RES	WW 4.7 OHMS 5% 3W	P-S/DEFLECTION
RL032	256777	RES	CF 4.7 OHM 5% .43W	P-S/DEFLECTION
RL034	259330	RES	CF 6.8K 5% .43W	P-S/DEFLECTION
RL036	259330	RES	CF 6.8K 5% .43W	P-S/DEFLECTION
RL037	259377	RES	CC 330 OHMS 10% 1/2W	P-S/DEFLECTION
RL040	198672	RES	CF 1/4W 5% 1.5K	P-S/DEFLECTION
RL043	263126	RES	CF .14W 5% 47 OHMS	P-S/DEFLECTION
RL044	259466	RES	MF 191K 1% 1/4W	P-S/DEFLECTION
RL045	259478	RES	MF 511K 1% 1/4W	P-S/DEFLECTION
RL069	203782	RES	CF .14W 5% 4.7K	P-S/DEFLECTION
RL074	184838	RES	CF .14W 5% 10K	P-S/DEFLECTION
RL075	258179	RES	2.2K 5% 1/4W	P-S/DEFLECTION
RL100	203782	RES	CF .14W 5% 4.7K	P-S/DEFLECTION
RL101	184838	RES	CF .14W 5% 10K	P-S/DEFLECTION
RL102	203782	RES	CF .14W 5% 4.7K	P-S/DEFLECTION
RL103	259435	RES	CF 2.2K 5% .14W	P-S/DEFLECTION
RL105	259446	RES	CF 3.3K 5% .14W	P-S/DEFLECTION
RL106	263124	RES	CF .14W 5% 470 OHMS	P-S/DEFLECTION
RL107	216176	RES	CF .14W 5% 1K	P-S/DEFLECTION
RL109	259456	RES	CF 820 OHMS 5% .14W	P-S/DEFLECTION
RL110	259454	RES	CF 68 OHMS 5% .7W	P-S/DEFLECTION
RL112	216176	RES	CF .14W 5% 1K	P-S/DEFLECTION
RL120	261648	RES	CF .14W 5% 10R	P-S/DEFLECTION
RL121	263123	RES	CF .14W 5% 22 OHMS	P-S/DEFLECTION
RL140	216193	RES	CF .14W 5% 220K	P-S/DEFLECTION
RL141	259441	RES	CF 33K 5% .14W	P-S/DEFLECTION
RL221	259241	RES	WW .27 OHMS 5% 2.5W	P-S/DEFLECTION
RL230	259423	RES	CF 100K 5% .14W	P-S/DEFLECTION
RL231	259564	RES	WW 4.7 OHMS 5% 3W	P-S/DEFLECTION
RL251	259241	RES	WW .27 OHMS 5% 2.5W	P-S/DEFLECTION

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
RRL300	216193		RES CF .14W 5% 220K	P-S/DEFLECTION
RRL301	259436		RES CF 2.2M 5% .14W	P-S/DEFLECTION
RRL303	259473		RES MF 33.2K 1% 1/4W	P-S/DEFLECTION
RRL304	263131		RES CF .14W 5% 82K	P-S/DEFLECTION
RRL305	259438		RES CF 330K 5% .14W	P-S/DEFLECTION
RRL306	259359		RES CF 24K 5% .14W	P-S/DEFLECTION
RRL308	200447		RES MF 1/4W 1% 56.2K	P-S/DEFLECTION
RRL310	259228		RES MF 46.4K 1% .7W	P-S/DEFLECTION
RRL311	259470		RES MF 2.21K 1% 1/4W	P-S/DEFLECTION
RRL312	241312		RES CF 1/4W 5% 10K	P-S/DEFLECTION
RRL313	241312		RES CF 1/4W 5% 10K	P-S/DEFLECTION
RRL314	263125		RES CF .14W 5% 47K	P-S/DEFLECTION
RRL550	203785		RES CF .14W 5% 100R	P-S/DEFLECTION
RM140	242690		RES CMF 1/16W 5% 10K	MPEG CBA
RRP019	259328		RES CF 470K 5% .43W	P-S/DEFLECTION
RRP020	258703		RES WWF 100 OHMS 5% 3/4W	P-S/DEFLECTION
RRP021	241312		RES CF 1/4W 5% 10K	P-S/DEFLECTION
RRP022	248858		RES CF 1/4W 5% 47R	P-S/DEFLECTION
RRP023	261648		RES CF .14W 5% 10R	P-S/DEFLECTION
RRP024	216176		RES CF .14W 5% 1K	P-S/DEFLECTION
RRP025	259426		RES CF 150K 5% .14W	P-S/DEFLECTION
RRP026	263125		RES CF .14W 5% 47K	P-S/DEFLECTION
RRP027	263130		RES CF .14W 5% 6.8K	P-S/DEFLECTION
RRP028	263126		RES CF .14W 5% 47 OHMS	P-S/DEFLECTION
RRP029	263130		RES CF .14W 5% 6.8K	P-S/DEFLECTION
RRP030	203782		RES CF .14W 5% 4.7K	P-S/DEFLECTION
RRP031	259427		RES CF 150 OHMS 5% .14W	P-S/DEFLECTION
RRP032	203785		RES CF .14W 5% 100R	P-S/DEFLECTION
RRP033	216176		RES CF .14W 5% 1K	P-S/DEFLECTION
RRP034	203782		RES CF .14W 5% 4.7K	P-S/DEFLECTION
RRP035	216176		RES CF .14W 5% 1K	P-S/DEFLECTION
RRP049	179284		RES MFFP 2W 5% 10R	P-S/DEFLECTION
RRP050	259608		RES 10M 5% 1W	P-S/DEFLECTION
RRP051	259876		RES WW 100 OHMS 5% 4.5W	P-S/DEFLECTION
RRP052	258722		RES WW .1 OHM 5% 2.5W	P-S/DEFLECTION
RRP053	259442		RES CF 33 OHMS 5% .14W	P-S/DEFLECTION
RRP054	203785		RES CF .14W 5% 100R	P-S/DEFLECTION
RRP055	203782		RES CF .14W 5% 4.7K	P-S/DEFLECTION
RRP056	259437		RES CF 2.7 OHMS 5% 1/4W	P-S/DEFLECTION
RRP060	259440		RES CF 330 OHMS 5% .14W	P-S/DEFLECTION
RRP061	261648		RES CF .14W 5% 10R	P-S/DEFLECTION
RRP062	203782		RES CF .14W 5% 4.7K	P-S/DEFLECTION
RRP063	259423		RES CF 100K 5% .14W	P-S/DEFLECTION
RRP064	259451		RES CF 5.6K 5% .14W	P-S/DEFLECTION
RRP065	203785		RES CF .14W 5% 100R	P-S/DEFLECTION
RRP066	184838		RES CF .14W 5% 10K	P-S/DEFLECTION
RRP067	184838		RES CF .14W 5% 10K	P-S/DEFLECTION
RRP068	259423		RES CF 100K 5% .14W	P-S/DEFLECTION
RRP069	184838		RES CF .14W 5% 10K	P-S/DEFLECTION
RRP070	203782		RES CF .14W 5% 4.7K	P-S/DEFLECTION
RRP071	259435		RES CF 2.2K 5% .14W	P-S/DEFLECTION
RRP072	203782		RES CF .14W 5% 4.7K	P-S/DEFLECTION
RRP073	263122		RES CF .14W 5% 1.8K	P-S/DEFLECTION
RRP074	184838		RES CF .14W 5% 10K	P-S/DEFLECTION
RRP075	184838		RES CF .14W 5% 10K	P-S/DEFLECTION
RRP076	203782		RES CF .14W 5% 4.7K	P-S/DEFLECTION
RRP077	259435		RES CF 2.2K 5% .14W	P-S/DEFLECTION
RRP078	203782		RES CF .14W 5% 4.7K	P-S/DEFLECTION
RRP080	184838		RES CF .14W 5% 10K	P-S/DEFLECTION
RRP10	245057		RES CF 1/4W 5% 220K	CONVERGENCE PS / ADAPTE
RRP11	245057		RES CF 1/4W 5% 220K	CONVERGENCE PS / ADAPTE
RRP112	176656		RES MF 2W 5% 10K	P-S/DEFLECTION
RRP113	259329		RES CF 4.7K 5% .43W	P-S/DEFLECTION
RRP114	259329		RES CF 4.7K 5% .43W	P-S/DEFLECTION
RRP117	259329		RES CF 4.7K 5% .43W	P-S/DEFLECTION
RRP12	245057		RES CF 1/4W 5% 220K	CONVERGENCE PS / ADAPTE

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
RP120	259329		RES CF 4.7K 5% .43W	P-S/DEFLECTION
RP13	245057		RES CF 1/4W 5% 220K	CONVERGENCE PS / ADAPTE
RP130	184838		RES CF .14W 5% 10K	P-S/DEFLECTION
RP135	184838		RES CF .14W 5% 10K	P-S/DEFLECTION
RP137	203785		RES CF .14W 5% 100R	P-S/DEFLECTION
RP150	263126		RES CF .14W 5% 47 OHMS	P-S/DEFLECTION
RP151	216176		RES CF .14W 5% 1K	P-S/DEFLECTION
RP152	216176		RES CF .14W 5% 1K	P-S/DEFLECTION
RP153	203785		RES CF .14W 5% 100R	P-S/DEFLECTION
RP160	216176		RES CF .14W 5% 1K	P-S/DEFLECTION
RP161	232521		RES CF 1/4W 5% 220R	P-S/DEFLECTION
RP162	184838		RES CF .14W 5% 10K	P-S/DEFLECTION
RP163	263131		RES CF .14W 5% 82K	P-S/DEFLECTION
RP164	259435		RES CF 2.2K 5% .14W	P-S/DEFLECTION
RP165	216176		RES CF .14W 5% 1K	P-S/DEFLECTION
RP166	259423		RES CF 100K 5% .14W	P-S/DEFLECTION
RP170	259435		RES CF 2.2K 5% .14W	P-S/DEFLECTION
RP171	203785		RES CF .14W 5% 100R	P-S/DEFLECTION
RP172	203782		RES CF .14W 5% 4.7K	P-S/DEFLECTION
RP173	259434		RES CF 22K 5% .14W	P-S/DEFLECTION
RP174	259434		RES CF 22K 5% .14W	P-S/DEFLECTION
RP175	184838		RES CF .14W 5% 10K	P-S/DEFLECTION
RP176	261648		RES CF .14W 5% 10R	P-S/DEFLECTION
RP177	263131		RES CF .14W 5% 82K	P-S/DEFLECTION
RP178	203782		RES CF .14W 5% 4.7K	P-S/DEFLECTION
RP179	259424		RES CF 12K 5% .14W	P-S/DEFLECTION
RP180	259456		RES CF 820 OHMS 5% .14W	P-S/DEFLECTION
RP181	203782		RES CF .14W 5% 4.7K	P-S/DEFLECTION
RP182	216176		RES CF .14W 5% 1K	P-S/DEFLECTION
RP183	259345		RES MF 39K 1% 1/4W	P-S/DEFLECTION
RP184	214091		RES MF 1/4W 1% 4.75K	P-S/DEFLECTION
RP185	176801		RES CF 1/4W 2% 56K	P-S/DEFLECTION
RP186	184838		RES CF .14W 5% 10K	P-S/DEFLECTION
RP187	184838		RES CF .14W 5% 10K	P-S/DEFLECTION
RP188	216176		RES CF .14W 5% 1K	P-S/DEFLECTION
RP189	216176		RES CF .14W 5% 1K	P-S/DEFLECTION
RP190	184838		RES CF .14W 5% 10K	P-S/DEFLECTION
RP192	203785		RES CF .14W 5% 100R	P-S/DEFLECTION
RP193	263124		RES CF .14W 5% 470 OHMS	P-S/DEFLECTION
RP194	216176		RES CF .14W 5% 1K	P-S/DEFLECTION
RP195	216173		RES CF .14W 5% 1.2K	P-S/DEFLECTION
RP196	259434		RES CF 22K 5% .14W	P-S/DEFLECTION
RP197	259434		RES CF 22K 5% .14W	P-S/DEFLECTION
RP198	184838		RES CF .14W 5% 10K	P-S/DEFLECTION
RP199	259434		RES CF 22K 5% .14W	P-S/DEFLECTION
RP20	256741		RES CMF 10K OHM 5% 1/16W	CONVERGENCE PS / ADAPTE
RP200	263125		RES CF .14W 5% 47K	P-S/DEFLECTION
RP201	259446		RES CF 3.3K 5% .14W	P-S/DEFLECTION
RP202	184838		RES CF .14W 5% 10K	P-S/DEFLECTION
RP203	259471		RES MF 2.43K 1% 1/4W	P-S/DEFLECTION
RP204	214091		RES MF 1/4W 1% 4.75K	P-S/DEFLECTION
RP21	243375		RES CMF 1/16W 5% 4.7K	CONVERGENCE PS / ADAPTE
RP210	259435		RES CF 2.2K 5% .14W	P-S/DEFLECTION
RP212	184838		RES CF .14W 5% 10K	P-S/DEFLECTION
RP213	259435		RES CF 2.2K 5% .14W	P-S/DEFLECTION
RP22	263123		RES CF .14W 5% 22 OHMS	CONVERGENCE PS / ADAPTE
RP220	259423		RES CF 100K 5% .14W	P-S/DEFLECTION
RP221	203785		RES CF .14W 5% 100R	P-S/DEFLECTION
RP222	259424		RES CF 12K 5% .14W	P-S/DEFLECTION
RP223	259434		RES CF 22K 5% .14W	P-S/DEFLECTION
RP224	203785		RES CF .14W 5% 100R	P-S/DEFLECTION
RP225	259428		RES CF 15K 5% .14W	P-S/DEFLECTION
RP23	216190		RES CF .14W 5% 220R	CONVERGENCE PS / ADAPTE
RP230	216176		RES CF .14W 5% 1K	P-S/DEFLECTION
RP231	259445		RES CF 39K 5% .14W	P-S/DEFLECTION
RP239	248858		RES CF 1/4W 5% 47R	P-S/DEFLECTION

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
RP24	256741	RES	CMF 10K OHM 5% 1/16W	CONVERGENCE PS / ADAPTE
RP240	216176	RES	CF .14W 5% 1K	P-S/DEFLECTION
RP241	184838	RES	CF .14W 5% 10K	P-S/DEFLECTION
RP242	259474	RES	MF 392 OHMS 1% 1/4W	P-S/DEFLECTION
RP243	179753	RES	MF 1/4W 1% 1K	P-S/DEFLECTION
RP25	256746	RES	CMF 22K OHM 5% 1/16W	CONVERGENCE PS / ADAPTE
RP26	256737	RES	CMF 430 OHMS 5% 1/16W	CONVERGENCE PS / ADAPTE
RP27	256759	RES	CMF 1.5K OHM 5% 1/16W	CONVERGENCE PS / ADAPTE
RP28	263124	RES	CF .14W 5% 470 OHMS	CONVERGENCE PS / ADAPTE
RP29	243653	RES	CMF 1/16W 5% 100R	CONVERGENCE PS / ADAPTE
RP30	259442	RES	CF 33 OHMS 5% .14W	CONVERGENCE PS / ADAPTE
RP305	220644	RES	CF 1/4W 5% 120K	SMPS - DVD
RP306	220644	RES	CF 1/4W 5% 120K	SMPS - DVD
RP31	261648	RES	CF .14W 5% 10R	CONVERGENCE PS / ADAPTE
RP32	259564	RES	WW 4.7 OHMS 5% 3W	CONVERGENCE PS / ADAPTE
RP320	259980	RES	WW 1 OHM 5% 2.5W	SMPS - DVD
RP321	243090	RES	CF 1/4W 5% 22R	SMPS - DVD
RP327	184056	RES	CF 1/4W 5% 470R	SMPS - DVD
RP328	198644	RES	CF 1/4W 5% 2.7K	SMPS - DVD
RP33	249338	RES	CMF 47K 5% 1/16W	CONVERGENCE PS / ADAPTE
RP330	243090	RES	CF 1/4W 5% 22R	SMPS - DVD
RP331	220568	RES	CF 1/4W 5% 10R	SMPS - DVD
RP335	258180	RES	CF 1K 5% 1/4W	SMPS - DVD
RP34	256759	RES	CMF 1.5K OHM 5% 1/16W	CONVERGENCE PS / ADAPTE
RP353	198672	RES	CF 1/4W 5% 1.5K	SMPS - DVD
RP355	198699	RES	CF 1/4W 5% 18K	SMPS - DVD
RP368	241312	RES	CF 1/4W 5% 10K	SMPS - DVD
RP37	256743	RES	CMF 15K OHM 5% 1/16W	CONVERGENCE PS / ADAPTE
RP39	175325	RES	CF 1/4W 5% 100R	CONVERGENCE PS / ADAPTE
RP40	259435	RES	CF 2.2K 5% .14W	CONVERGENCE PS / ADAPTE
RP400	259288	RES	1.5M 5% 1W	MAINS INPUT DOUBLER
RP402	259872	RES	WW 1.5 OHMS 5% 4.5W	MAINS INPUT DOUBLER
RP403	259872	RES	WW 1.5 OHMS 5% 4.5W	MAINS INPUT DOUBLER
RP405	259512	MOV		MAINS INPUT DOUBLER
RP406	259512	MOV		MAINS INPUT DOUBLER
RP41	258179	RES	2.2K 5% 1/4W	CONVERGENCE PS / ADAPTE
RP42	259434	RES	CF 22K 5% .14W	CONVERGENCE PS / ADAPTE
RP43	216190	RES	CF .14W 5% 220R	CONVERGENCE PS / ADAPTE
RP44	259451	RES	CF 5.6K 5% .14W	CONVERGENCE PS / ADAPTE
RP45	256741	RES	CMF 10K OHM 5% 1/16W	CONVERGENCE PS / ADAPTE
RP46	198673	RES	CF 1/4W 5% 3.3K	CONVERGENCE PS / ADAPTE
RP47	256741	RES	CMF 10K OHM 5% 1/16W	CONVERGENCE PS / ADAPTE
RP48	259434	RES	CF 22K 5% .14W	CONVERGENCE PS / ADAPTE
RP49	175325	RES	CF 1/4W 5% 100R	CONVERGENCE PS / ADAPTE
RP50	259434	RES	CF 22K 5% .14W	CONVERGENCE PS / ADAPTE
RP520	243375	RES	CMF 1/16W 5% 4.7K	SMALL SIGNAL BOARD
RP521	243375	RES	CMF 1/16W 5% 4.7K	SMALL SIGNAL BOARD
RP522	259758	RES	CMF 470 OHMS 1% 1/16W	SMALL SIGNAL BOARD
RP523	252359	RES	CF 1/10W 1% 1K	SMALL SIGNAL BOARD
RP524	252359	RES	CF 1/10W 1% 1K	SMALL SIGNAL BOARD
RP525	252359	RES	CF 1/10W 1% 1K	SMALL SIGNAL BOARD
RP526	244056	RES	CMF 470 OHM 5% 62.5MW	SMALL SIGNAL BOARD
RP526	242690	RES	CMF 1/16W 5% 10K	SMPS - DVD
RP527	257028	RES	CMF 22 OHM 5% 1/16W	SMALL SIGNAL BOARD
RP529	256761	RES	CMF 2.2K OHM 5% 1/16W	SMPS - DVD
RP530	256764	RES	CMF 3.3K OHM 5% 1/16W	SMALL SIGNAL BOARD
RP531	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RP532	256746	RES	CMF 22K OHM +5% 62.5MW	SMPS - DVD
RP533	249338	RES	CMF 47K 62.5MW 5%	SMPS - DVD
RP534	256783	RES	CMF 1/16W 0% 0R	SMPS - DVD
RP537	243485	RES	CMF 1/16W 5% 1K	SMPS - DVD
RP538	256762	RES	CMF 2.7K +5% 62.5MW	SMPS - DVD
RP539	256762	RES	CMF 2.7K +5% 62.5MW	SMPS - DVD
RP540	242690	RES	CMF 1/16W 5% 10K	SMALL SIGNAL BOARD
RP541	244056	RES	CMF 470 OHM 5% 62.5MW	SMPS - DVD
RP542	256748	RES	CMF 33K OHM 5% 1/16W	SMPS - DVD

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
RP551	243485		RES CMF 1/16W 5% 1K	SMPS - DVD
RRP552	260038		RES CMF 2.26K 1% 1/16W	SMPS - DVD
RP554	257028		RES CMF 22 OHM 5% 1/16W	SMPS - DVD
RP555	256765		RES CMF 1/16W 5% 5.6K	SMPS - DVD
RP556	243485		RES CMF 1/16W 5% 1K	SMPS - DVD
RP557	242690		RES CMF 1/16W 5% 10K	SMPS - DVD
RP559	243653		RES CMF 1/16W 5% 100R	SMPS - DVD
RP571	249338		RES CMF 47K 62.5MW 5%	SMALL SIGNAL BOARD
RP601	216190		RES CF .14W 5% 220R	MAINS INPUT DOUBLER
RP602	NONSTK		WIRE JUMPER	MAINS INPUT DOUBLER
RP603	NONSTK		WIRE JUMPER	MAINS INPUT DOUBLER
RP605	184838		RES CF .14W 5% 10K	MAINS INPUT DOUBLER
RP606	203782		RES CF .14W 5% 4.7K	MAINS INPUT DOUBLER
RP607	203785		RES CF .14W 5% 100R	MAINS INPUT DOUBLER
RP608	263128		RES CF .14W 5% 680 OHMS	MAINS INPUT DOUBLER
RP610	259445		RES CF 39K 5% .14W	MAINS INPUT DOUBLER
RP611	259435		RES CF 2.2K 5% .14W	MAINS INPUT DOUBLER
RP612	259424		RES CF 12K 5% .14W	MAINS INPUT DOUBLER
RP613	259435		RES CF 2.2K 5% .14W	MAINS INPUT DOUBLER
RP614	259432		RES CF 1M 5% .14W	MAINS INPUT DOUBLER
RP621	NONSTK		WIRE JUMPER	MAINS INPUT DOUBLER
RP622	NONSTK		WIRE JUMPER	MAINS INPUT DOUBLER
RP624	NONSTK		WIRE JUMPER	MAINS INPUT DOUBLER
RP625	NONSTK		WIRE JUMPER	MAINS INPUT DOUBLER
RP87	198672		RES CF 1/4W 5% 1.5K	CONVERGENCE PS / ADAPTE
RP88	257028		RES CMF 22 OHM 5% 1/16W	CONVERGENCE PS / ADAPTE
RP900	259473		RES MF 33.2K 1% 1/4W	P-S/DEFLECTION
RP91	263124		RES CF .14W 5% 470 OHMS	CONVERGENCE PS / ADAPTE
RP92	259484		RES MF 825 OHMS 1% 1/4W	CONVERGENCE PS / ADAPTE
RP93	259468		RES MF 1.58K 1% 1/4W	CONVERGENCE PS / ADAPTE
RQ005	259449		RES CF 4.7 OHMS 5% 1/4W	FRONT A/V IN
RQ006	259449		RES CF 4.7 OHMS 5% 1/4W	FRONT A/V IN
RRR001	243653		RES CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RRR002	256729		RES CMF 82 OHM 5% 1/16W	SMALL SIGNAL BOARD
RRR004	243375		RES CMF 1/16W 5% 4.7K	SMALL SIGNAL BOARD
RRR005	253720		RES CMF 62.5MW 1% 1.5K	SMALL SIGNAL BOARD
RRR006	244078		RES CMF 1/16W 5% 1M	SMALL SIGNAL BOARD
RRR009	242690		RES CMF 1/16W 5% 10K	SMALL SIGNAL BOARD
RRR010	249338		RES CMF 47K 62.5MW 5%	SMALL SIGNAL BOARD
RRR011	249338		RES CMF 47K 62.5MW 5%	SMALL SIGNAL BOARD
RRR012	249338		RES CMF 47K 62.5MW 5%	SMALL SIGNAL BOARD
RRR013	249338		RES CMF 47K 62.5MW 5%	SMALL SIGNAL BOARD
RRR015	256759		RES CMF 1/16W 5% 1.5K	SMALL SIGNAL BOARD
RRR016	249338		RES CMF 47K 62.5MW 5%	SMALL SIGNAL BOARD
RRR017	253720		RES CMF 62.5MW 1% 1.5K	SMALL SIGNAL BOARD
RRR025	205278		RES CMF 1/8W 5% 27R	SMALL SIGNAL BOARD
RRR044	243375		RES CMF 1/16W 5% 4.7K	SMALL SIGNAL BOARD
RRR045	243375		RES CMF 1/16W 5% 4.7K	SMALL SIGNAL BOARD
RRR046	243375		RES CMF 1/16W 5% 4.7K	SMALL SIGNAL BOARD
RRR050	243485		RES CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RRR051	243485		RES CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RRR053	243375		RES CMF 1/16W 5% 4.7K	SMALL SIGNAL BOARD
RRR054	243375		RES CMF 1/16W 5% 4.7K	SMALL SIGNAL BOARD
RRR055	256754		RES CMF 100K OHM 5% 1/16W	SMALL SIGNAL BOARD
RRR056	242690		RES CMF 1/16W 5% 10K	SMALL SIGNAL BOARD
RRR061	243653		RES CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RRR062	243485		RES CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RRR063	244056		RES CMF 470 OHM 5% 62.5MW	SMALL SIGNAL BOARD
RRR064	242690		RES CMF 1/16W 5% 10K	SMALL SIGNAL BOARD
RRR065	256768		RES MF 8.2K +5%	SMALL SIGNAL BOARD
RRR066	243485		RES CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RRR067	243485		RES CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RRR068	256754		RES CMF 100K OHM 5% 1/16W	SMALL SIGNAL BOARD
RRR069	256759		RES CMF 1/16W 5% 1.5K	SMALL SIGNAL BOARD
RRR070	256764		RES CMF 3.3K OHM 5% 1/16W	SMALL SIGNAL BOARD
RRR071	256764		RES CMF 3.3K OHM 5% 1/16W	SMALL SIGNAL BOARD

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
RRR072	256942	RES	CMF 1/16W 5% 220R	SMALL SIGNAL BOARD
RRR073	243485	RES	CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RRR075	256942	RES	CMF 1/16W 5% 220R	SMALL SIGNAL BOARD
RRR080	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RRR081	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RRR082	242690	RES	CMF 1/16W 5% 10K	SMALL SIGNAL BOARD
RRR090	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RRR091	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RRR092	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RRR093	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RRR094	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RRR095	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RRR096	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RRR097	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RRR100	242690	RES	CMF 1/16W 5% 10K	SMALL SIGNAL BOARD
RRR101	242690	RES	CMF 1/16W 5% 10K	SMALL SIGNAL BOARD
RRR102	243375	RES	CMF 1/16W 5% 4.7K	SMALL SIGNAL BOARD
RRR104	242690	RES	CMF 1/16W 5% 10K	SMALL SIGNAL BOARD
RRR105	256764	RES	CMF 3.3K OHM 5% 1/16W	SMALL SIGNAL BOARD
RRR111	242690	RES	CMF 1/16W 5% 10K	SMALL SIGNAL BOARD
RRR112	243485	RES	CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RRR113	243485	RES	CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RRR114	243485	RES	CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RRR115	243485	RES	CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RRR116	243485	RES	CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RRR117	253720	RES	CMF 62.5MW 1% 1.5K	SMALL SIGNAL BOARD
RRR118	256744	RES	CMF 18K OHM +5% 62.5MW	SMALL SIGNAL BOARD
RRR130	244056	RES	CMF 470 OHM 5% 62.5MW	SMALL SIGNAL BOARD
RRR131	244056	RES	CMF 470 OHM 5% 62.5MW	SMALL SIGNAL BOARD
RRR134	244056	RES	CMF 470 OHM 5% 62.5MW	SMALL SIGNAL BOARD
RRR135	244056	RES	CMF 470 OHM 5% 62.5MW	SMALL SIGNAL BOARD
RRR136	244056	RES	CMF 470 OHM 5% 62.5MW	SMALL SIGNAL BOARD
RRR137	244056	RES	CMF 470 OHM 5% 62.5MW	SMALL SIGNAL BOARD
RRR138	244056	RES	CMF 470 OHM 5% 62.5MW	SMALL SIGNAL BOARD
RRR139	244056	RES	CMF 470 OHM 5% 62.5MW	SMALL SIGNAL BOARD
RRR140	246960	RES	CMF 3.9K 5% 1/16W	SMALL SIGNAL BOARD
RRR141	244056	RES	CMF 470 OHM 5% 62.5MW	SMALL SIGNAL BOARD
RRR142	260677	RES	CMF 1/16W 5% 10R	SMALL SIGNAL BOARD
RRR144	249041	RES	CMF 1/16W 5% 1.2K	SMALL SIGNAL BOARD
RRR145	244056	RES	CMF 470 OHM 5% 62.5MW	SMALL SIGNAL BOARD
RRR146	249041	RES	CMF 1/16W 5% 1.2K	SMALL SIGNAL BOARD
RRR147	244056	RES	CMF 470 OHM 5% 62.5MW	SMALL SIGNAL BOARD
RRR148	249041	RES	CMF 1/16W 5% 1.2K	SMALL SIGNAL BOARD
RRR149	244056	RES	CMF 470 OHM 5% 62.5MW	SMALL SIGNAL BOARD
RRR156	249338	RES	CMF 47K 62.5MW 5%	SMALL SIGNAL BOARD
RRR157	243375	RES	CMF 1/16W 5% 4.7K	SMALL SIGNAL BOARD
RRR158	242690	RES	CMF 1/16W 5% 10K	SMALL SIGNAL BOARD
RRR159	256764	RES	CMF 3.3K OHM 5% 1/16W	SMALL SIGNAL BOARD
RRR160	256764	RES	CMF 3.3K OHM 5% 1/16W	SMALL SIGNAL BOARD
RRR161	249338	RES	CMF 47K 62.5MW 5%	SMALL SIGNAL BOARD
RRR163	243375	RES	CMF 1/16W 5% 4.7K	SMALL SIGNAL BOARD
RRR170	249039	RES	CMF 1/16W 5% 1.8K	SMALL SIGNAL BOARD
RRR171	249039	RES	CMF 1/16W 5% 1.8K	SMALL SIGNAL BOARD
RRR172	249338	RES	CMF 47K 62.5MW 5%	SMALL SIGNAL BOARD
RRR175	256764	RES	CMF 3.3K OHM 5% 1/16W	SMALL SIGNAL BOARD
RRR180	243485	RES	CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RRR181	256764	RES	CMF 3.3K OHM 5% 1/16W	SMALL SIGNAL BOARD
RRR182	256764	RES	CMF 3.3K OHM 5% 1/16W	SMALL SIGNAL BOARD
RRR183	249338	RES	CMF 47K 62.5MW 5%	SMALL SIGNAL BOARD
RRR184	249338	RES	CMF 47K 62.5MW 5%	SMALL SIGNAL BOARD
RRR185	243375	RES	CMF 1/16W 5% 4.7K	SMALL SIGNAL BOARD
RRR187	243375	RES	CMF 1/16W 5% 4.7K	SMALL SIGNAL BOARD
RRR190	243485	RES	CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RRR191	243375	RES	CMF 1/16W 5% 4.7K	SMALL SIGNAL BOARD
RRR193	249338	RES	CMF 47K 62.5MW 5%	SMALL SIGNAL BOARD
RRR194	249338	RES	CMF 47K 62.5MW 5%	SMALL SIGNAL BOARD

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
RRR195	249338	RES	CMF 47K 62.5MW 5%	SMALL SIGNAL BOARD
RRR196	249338	RES	CMF 47K 62.5MW 5%	SMALL SIGNAL BOARD
RRR198	242690	RES	CMF 1/16W 5% 10K	SMALL SIGNAL BOARD
RRR199	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RRR250	258706	RES	CF 33 OHMS 5% .43W	SMALL SIGNAL BOARD
RRR300	259855	RES	NETWORK: 100 OHMS 1/16W X4	SMALL SIGNAL BOARD
RRR301	259855	RES	NETWORK: 100 OHMS 1/16W X4	SMALL SIGNAL BOARD
RRR302	259855	RES	NETWORK: 100 OHMS 1/16W X4	SMALL SIGNAL BOARD
RRR303	259855	RES	NETWORK: 100 OHMS 1/16W X4	SMALL SIGNAL BOARD
RRR304	259855	RES	NETWORK: 100 OHMS 1/16W X4	SMALL SIGNAL BOARD
RRR305	259855	RES	NETWORK: 100 OHMS 1/16W X4	SMALL SIGNAL BOARD
RRR306	259855	RES	NETWORK: 100 OHMS 1/16W X4	SMALL SIGNAL BOARD
RRR307	259855	RES	NETWORK: 100 OHMS 1/16W X4	SMALL SIGNAL BOARD
RRR308	259855	RES	NETWORK: 100 OHMS 1/16W X4	SMALL SIGNAL BOARD
RRR309	259855	RES	NETWORK: 100 OHMS 1/16W X4	SMALL SIGNAL BOARD
RRR310	259855	RES	NETWORK: 100 OHMS 1/16W X4	SMALL SIGNAL BOARD
RRR311	259855	RES	NETWORK: 100 OHMS 1/16W X4	SMALL SIGNAL BOARD
RRR312	259855	RES	NETWORK: 100 OHMS 1/16W X4	SMALL SIGNAL BOARD
RRR320	259855	RES	NETWORK: 100 OHMS 1/16W X4	SMALL SIGNAL BOARD
RRR321	259855	RES	NETWORK: 100 OHMS 1/16W X4	SMALL SIGNAL BOARD
RRR322	259855	RES	NETWORK: 100 OHMS 1/16W X4	SMALL SIGNAL BOARD
RRR323	259855	RES	NETWORK: 100 OHMS 1/16W X4	SMALL SIGNAL BOARD
RRR324	259855	RES	NETWORK: 100 OHMS 1/16W X4	SMALL SIGNAL BOARD
RRR325	259855	RES	NETWORK: 100 OHMS 1/16W X4	SMALL SIGNAL BOARD
RRR326	259855	RES	NETWORK: 100 OHMS 1/16W X4	SMALL SIGNAL BOARD
RRR327	259855	RES	NETWORK: 100 OHMS 1/16W X4	SMALL SIGNAL BOARD
RRR328	259855	RES	NETWORK: 100 OHMS 1/16W X4	SMALL SIGNAL BOARD
RRR329	259855	RES	NETWORK: 100 OHMS 1/16W X4	SMALL SIGNAL BOARD
RRR340	259855	RES	NETWORK: 100 OHMS 1/16W X4	SMALL SIGNAL BOARD
RRR341	259855	RES	NETWORK: 100 OHMS 1/16W X4	SMALL SIGNAL BOARD
RRS01	243485	RES	CMF 1/16W 5% 1K	CONVERGENCE SIGNAL BOAR
RRS02	243485	RES	CMF 1/16W 5% 1K	CONVERGENCE SIGNAL BOAR
RRS03	243485	RES	CMF 1/16W 5% 1K	CONVERGENCE SIGNAL BOAR
RRS04	243485	RES	CMF 1/16W 5% 1K	CONVERGENCE SIGNAL BOAR
RRS05	243485	RES	CMF 1/16W 5% 1K	CONVERGENCE SIGNAL BOAR
RRS06	243485	RES	CMF 1/16W 5% 1K	CONVERGENCE SIGNAL BOAR
RRS08	263914	RES	CMF 1.82K 1% 1/16W	CONVERGENCE SIGNAL BOAR
RRS09	263914	RES	CMF 1.82K 1% 1/16W	CONVERGENCE SIGNAL BOAR
RRS11	256741	RES	CMF 10K OHM 5% 1/16W	CONVERGENCE SIGNAL BOAR
RRS12	256741	RES	CMF 10K OHM 5% 1/16W	CONVERGENCE SIGNAL BOAR
RRS13	256741	RES	CMF 10K OHM 5% 1/16W	CONVERGENCE SIGNAL BOAR
RRS15	243653	RES	CMF 1/16W 5% 100R	CONVERGENCE SIGNAL BOAR
RRS30	256942	RES	CMF 220 OHM 5% 1/16W	CONVERGENCE SIGNAL BOAR
RRS31	256737	RES	CMF 430 OHMS 5% 1/16W	CONVERGENCE SIGNAL BOAR
RRS32	243485	RES	CMF 1/16W 5% 1K	CONVERGENCE SIGNAL BOAR
RRS33	243375	RES	CMF 1/16W 5% 4.7K	CONVERGENCE SIGNAL BOAR
RRS34	249338	RES	CMF 47K 5% 1/16W	CONVERGENCE SIGNAL BOAR
RRS36	243375	RES	CMF 1/16W 5% 4.7K	CONVERGENCE SIGNAL BOAR
RRS37	243653	RES	CMF 1/16W 5% 100R	CONVERGENCE SIGNAL BOAR
RRS39	256761	RES	CMF 2.2K OHM 5% 1/16W	CONVERGENCE SIGNAL BOAR
RRS40	244074	RES	CMF 47 OHM +5% 62.5MW	CONVERGENCE SIGNAL BOAR
RRS41	256942	RES	CMF 220 OHM 5% 1/16W	CONVERGENCE SIGNAL BOAR
RRS42	256764	RES	CMF 3.3K OHM 5% 1/16W	CONVERGENCE SIGNAL BOAR
RRS45	249038	RES	CMF 560 OHM 5% 1/16W	CONVERGENCE SIGNAL BOAR
RRS46	249038	RES	CMF 560 OHM 5% 1/16W	CONVERGENCE SIGNAL BOAR
RRS47	243485	RES	CMF 1/16W 5% 1K	CONVERGENCE SIGNAL BOAR
RRS48	256759	RES	CMF 1.5K OHM 5% 1/16W	CONVERGENCE SIGNAL BOAR
RRS50	256741	RES	CMF 10K OHM 5% 1/16W	CONVERGENCE SIGNAL BOAR
RRS51	256739	RES	CMF 680 OHMS 5% 1/16W	CONVERGENCE SIGNAL BOAR
RRS52	256762	RES	CMF 2.7K OHM 5% 1/16W	CONVERGENCE SIGNAL BOAR
RRS54	249338	RES	CMF 47K 5% 1/16W	CONVERGENCE SIGNAL BOAR
RT001	244056	RES	CMF 470 OHM 5% 62.5MW	DIGITAL READY INTERFACE
RT002	243485	RES	CMF 1/16W 5% 1K	DIGITAL READY INTERFACE
RT181	243485	RES	CMF 1/16W 5% 1K	MPEG CBA
RT182	243485	RES	CMF 1/16W 5% 1K	MPEG CBA
RT187	260677	RES	CMF 1/16W 5% 10R	MPEG CBA

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
RT201	242690		RES CMF 1/16W 5% 10K	MPEG CBA
RT201	259969		RES CMF 75 OHMS 1% 1/8W	DIGITAL READY INTERFACE
RT202	242690		RES CMF 1/16W 5% 10K	MPEG CBA
RT202	176818		RES CMF 1/8W 5% 100R	DIGITAL READY INTERFACE
RT203	259969		RES CMF 75 OHMS 1% 1/8W	DIGITAL READY INTERFACE
RT204	176818		RES CMF 1/8W 5% 100R	DIGITAL READY INTERFACE
RT205	259969		RES CMF 75 OHMS 1% 1/8W	DIGITAL READY INTERFACE
RT206	176818		RES CMF 1/8W 5% 100R	DIGITAL READY INTERFACE
RT207	259969		RES CMF 75 OHMS 1% 1/8W	DIGITAL READY INTERFACE
RT208	176818		RES CMF 1/8W 5% 100R	DIGITAL READY INTERFACE
RT209	259969		RES CMF 75 OHMS 1% 1/8W	DIGITAL READY INTERFACE
RT210	176818		RES CMF 1/8W 5% 100R	DIGITAL READY INTERFACE
RT211	259969		RES CMF 75 OHMS 1% 1/8W	DIGITAL READY INTERFACE
RT212	176818		RES CMF 1/8W 5% 100R	DIGITAL READY INTERFACE
RT213	259969		RES CMF 75 OHMS 1% 1/8W	DIGITAL READY INTERFACE
RT215	259969		RES CMF 75 OHMS 1% 1/8W	DIGITAL READY INTERFACE
RT221	259969		RES CMF 75 OHMS 1% 1/8W	DIGITAL READY INTERFACE
RT222	259969		RES CMF 75 OHMS 1% 1/8W	DIGITAL READY INTERFACE
RT223	162003		RES CMF 1/8W 5% 680R	DIGITAL READY INTERFACE
RT224	174348		RES CMF 1/8W 5% 1K	DIGITAL READY INTERFACE
RT225	259969		RES CMF 75 OHMS 1% 1/8W	DIGITAL READY INTERFACE
RT226	259969		RES CMF 75 OHMS 1% 1/8W	DIGITAL READY INTERFACE
RT227	259969		RES CMF 75 OHMS 1% 1/8W	DIGITAL READY INTERFACE
RT230	243653		RES CMF 1/16W 5% 100R	DIGITAL READY INTERFACE
RT231	259969		RES CMF 75 OHMS 1% 1/8W	DIGITAL READY INTERFACE
RT232	259969		RES CMF 75 OHMS 1% 1/8W	DIGITAL READY INTERFACE
RT233	259969		RES CMF 75 OHMS 1% 1/8W	DIGITAL READY INTERFACE
RT234	243653		RES CMF 1/16W 5% 100R	DIGITAL READY INTERFACE
RT235	243653		RES CMF 1/16W 5% 100R	DIGITAL READY INTERFACE
RT236	243653		RES CMF 1/16W 5% 100R	DIGITAL READY INTERFACE
RT237	243485		RES CMF 1/16W 5% 1K	DIGITAL READY INTERFACE
RT238	252355		RES MF 1/10W 1% 10K	DIGITAL READY INTERFACE
RT239	243485		RES CMF 1/16W 5% 1K	DIGITAL READY INTERFACE
RT240	256783		RES CMF 1/16W 0% 0R	DIGITAL READY INTERFACE
RT242	256783		RES CMF 1/16W 0% 0R	DIGITAL READY INTERFACE
RT243	256761		RES CMF 2.2K OHM 5% 1/16W	DIGITAL READY INTERFACE
RT244	259563		RES CMF 15K 1% 1/16W	DIGITAL READY INTERFACE
RT245	259953		RES CMF 84.5K 1% 1/16W	DIGITAL READY INTERFACE
RT247	244056		RES CMF 470 OHM 5% 62.5MW	DIGITAL READY INTERFACE
RT251	256783		RES CMF 1/16W 0% 0R	DIGITAL READY INTERFACE
RT252	256783		RES CMF 1/16W 0% 0R	DIGITAL READY INTERFACE
RT253	244095		RES CMF 1/16W 5% 820R	DIGITAL READY INTERFACE
RT254	256759		RES CMF 1/16W 5% 1.5K	DIGITAL READY INTERFACE
RT255	256783		RES CMF 1/16W 0% 0R	DIGITAL READY INTERFACE
RT256	243653		RES CMF 1/16W 5% 100R	DIGITAL READY INTERFACE
RT257	256759		RES CMF 1/16W 5% 1.5K	DIGITAL READY INTERFACE
RT258	256783		RES CMF 1/16W 0% 0R	DIGITAL READY INTERFACE
RT259	243653		RES CMF 1/16W 5% 100R	DIGITAL READY INTERFACE
RT260	256783		RES CMF 1/16W 0% 0R	DIGITAL READY INTERFACE
RT261	256759		RES CMF 1/16W 5% 1.5K	DIGITAL READY INTERFACE
RT262	243653		RES CMF 1/16W 5% 100R	DIGITAL READY INTERFACE
RT263	259343		RES CFF 10 OHMS 10% 1/4W	DIGITAL READY INTERFACE
RT272	256759		RES CMF 1/16W 5% 1.5K	DIGITAL READY INTERFACE
RT273	256759		RES CMF 1/16W 5% 1.5K	DIGITAL READY INTERFACE
RT274	244080		RES CCF 220K OHM +5% 62.5MW	DIGITAL READY INTERFACE
RT275	256759		RES CMF 1/16W 5% 1.5K	DIGITAL READY INTERFACE
RT276	243653		RES CMF 1/16W 5% 100R	DIGITAL READY INTERFACE
RT277	256759		RES CMF 1/16W 5% 1.5K	DIGITAL READY INTERFACE
RT278	243653		RES CMF 1/16W 5% 100R	DIGITAL READY INTERFACE
RT280	243485		RES CMF 1/16W 5% 1K	DIGITAL READY INTERFACE
RT281	243485		RES CMF 1/16W 5% 1K	DIGITAL READY INTERFACE
RT282	256783		RES CMF 1/16W 0% 0R	DIGITAL READY INTERFACE
RT283	256783		RES CMF 1/16W 0% 0R	DIGITAL READY INTERFACE
RT284	243485		RES CMF 1/16W 5% 1K	DIGITAL READY INTERFACE
RT286	260677		RES CMF 1/16W 5% 10R	DIGITAL READY INTERFACE
RT287	256739		RES CMF 680 OHM 5% 1/16W	DIGITAL READY INTERFACE

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
RT288	244078		RES CMF 1/16W 5% 1M	DIGITAL READY INTERFACE
RT289	256739		RES CMF 680 OHM 5% 1/16W	DIGITAL READY INTERFACE
RT290	243485		RES CMF 1/16W 5% 1K	DIGITAL READY INTERFACE
RT291	243485		RES CMF 1/16W 5% 1K	DIGITAL READY INTERFACE
RT293	243485		RES CMF 1/16W 5% 1K	DIGITAL READY INTERFACE
RT307	243653		RES CMF 1/16W 5% 100R	DIGITAL READY INTERFACE
RT308	243485		RES CMF 1/16W 5% 1K	DIGITAL READY INTERFACE
RT316	256759		RES CMF 1/16W 5% 1.5K	DIGITAL READY INTERFACE
RT317	243653		RES CMF 1/16W 5% 100R	DIGITAL READY INTERFACE
RT326	256759		RES CMF 1/16W 5% 1.5K	DIGITAL READY INTERFACE
RT327	243653		RES CMF 1/16W 5% 100R	DIGITAL READY INTERFACE
RT331	242690		RES CMF 1/16W 5% 10K	DIGITAL READY INTERFACE
RT332	243481		RES MF 27 OHM +5%	DIGITAL READY INTERFACE
RT333	256743		RES CMF 15K OHM 5% 1/16W	DIGITAL READY INTERFACE
RT334	256739		RES CMF 680 OHM 5% 1/16W	DIGITAL READY INTERFACE
RT335	259503		RES CMF 866 OHMS 1% 1/16W	DIGITAL READY INTERFACE
RT336	259640		RES CMF 2.15K 1% 1/16W	DIGITAL READY INTERFACE
RT337	259602		RES CMF 274 OHMS 1% 1/16W	DIGITAL READY INTERFACE
RT338	259562		RES CMF 5.62K 1% 1/16W	DIGITAL READY INTERFACE
RT339	252359		RES CF 1/10W 1% 1K	DIGITAL READY INTERFACE
RT340	242690		RES CMF 1/16W 5% 10K	DIGITAL READY INTERFACE
RT341	259969		RES CMF 75 OHMS 1% 1/8W	DIGITAL READY INTERFACE
RT342	259609		RES CMF 1.24K 1% 1/16W	DIGITAL READY INTERFACE
RT343	259343		RES CFF 10 OHMS 10% 1/4W	DIGITAL READY INTERFACE
RT348	256783		RES CMF 1/16W 0% 0R	DIGITAL READY INTERFACE
RT351	242690		RES CMF 1/16W 5% 10K	DIGITAL READY INTERFACE
RT352	243481		RES MF 27 OHM +5%	DIGITAL READY INTERFACE
RT353	256743		RES CMF 15K OHM 5% 1/16W	DIGITAL READY INTERFACE
RT354	243485		RES CMF 1/16W 5% 1K	DIGITAL READY INTERFACE
RT355	243485		RES CMF 1/16W 5% 1K	DIGITAL READY INTERFACE
RT356	256759		RES CMF 1/16W 5% 1.5K	DIGITAL READY INTERFACE
RT357	256759		RES CMF 1/16W 5% 1.5K	DIGITAL READY INTERFACE
RT358	259503		RES CMF 866 OHMS 1% 1/16W	DIGITAL READY INTERFACE
RT359	259604		RES CMF 6.34K 1% 1/16W	DIGITAL READY INTERFACE
RT360	259607		RES CMF 2.43K 1% 1/16W	DIGITAL READY INTERFACE
RT361	259640		RES CMF 2.15K 1% 1/16W	DIGITAL READY INTERFACE
RT362	259562		RES CMF 5.62K 1% 1/16W	DIGITAL READY INTERFACE
RT363	259602		RES CMF 274 OHMS 1% 1/16W	DIGITAL READY INTERFACE
RT364	252359		RES CF 1/10W 1% 1K	DIGITAL READY INTERFACE
RT365	242690		RES CMF 1/16W 5% 10K	DIGITAL READY INTERFACE
RT366	259969		RES CMF 75 OHMS 1% 1/8W	DIGITAL READY INTERFACE
RT367	256759		RES CMF 1/16W 5% 1.5K	DIGITAL READY INTERFACE
RT368	259343		RES CFF 10 OHMS 10% 1/4W	DIGITAL READY INTERFACE
RT371	242690		RES CMF 1/16W 5% 10K	DIGITAL READY INTERFACE
RT372	243481		RES MF 27 OHM +5%	DIGITAL READY INTERFACE
RT373	256743		RES CMF 15K OHM 5% 1/16W	DIGITAL READY INTERFACE
RT374	243485		RES CMF 1/16W 5% 1K	DIGITAL READY INTERFACE
RT375	243485		RES CMF 1/16W 5% 1K	DIGITAL READY INTERFACE
RT376	256759		RES CMF 1/16W 5% 1.5K	DIGITAL READY INTERFACE
RT377	256759		RES CMF 1/16W 5% 1.5K	DIGITAL READY INTERFACE
RT378	256759		RES CMF 1/16W 5% 1.5K	DIGITAL READY INTERFACE
RT379	259503		RES CMF 866 OHMS 1% 1/16W	DIGITAL READY INTERFACE
RT380	259609		RES CMF 1.24K 1% 1/16W	DIGITAL READY INTERFACE
RT381	259640		RES CMF 2.15K 1% 1/16W	DIGITAL READY INTERFACE
RT382	259562		RES CMF 5.62K 1% 1/16W	DIGITAL READY INTERFACE
RT383	259602		RES CMF 274 OHMS 1% 1/16W	DIGITAL READY INTERFACE
RT384	252359		RES CF 1/10W 1% 1K	DIGITAL READY INTERFACE
RT385	242690		RES CMF 1/16W 5% 10K	DIGITAL READY INTERFACE
RT386	259969		RES CMF 75 OHMS 1% 1/8W	DIGITAL READY INTERFACE
RT387	259343		RES CFF 10 OHMS 10% 1/4W	DIGITAL READY INTERFACE
RT401	243485		RES CMF 1/16W 5% 1K	DIGITAL READY INTERFACE
RT402	256758		RES CMF 240K OHM 5% 1/16W	DIGITAL READY INTERFACE
RT403	235901		RES CFF 1/4W 5% 4.7 OHMS	DIGITAL READY INTERFACE
RT412	243653		RES CMF 1/16W 5% 100R	DIGITAL READY INTERFACE
RT413	243375		RES CMF 1/16W 5% 4.7K	DIGITAL READY INTERFACE
RT414	261152		RES CMF 150R 5% 1/16W	DIGITAL READY INTERFACE

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
RT415	261152		RES CMF 150R 5% 1/16W	DIGITAL READY INTERFACE
RT421	256783		RES CMF 1/16W 0% 0R	DIGITAL READY INTERFACE
RT422	256783		RES CMF 1/16W 0% 0R	DIGITAL READY INTERFACE
RT501	261152		RES CMF 150R 5% 1/16W	DIGITAL READY INTERFACE
RT503	243658		RES CMF 510 OHM +5%	DIGITAL READY INTERFACE
RT504	256735		RESCF 330 OHM +5%	DIGITAL READY INTERFACE
RT505	249038		RES CMF 1/16W 5% 560R	DIGITAL READY INTERFACE
RT506	259840		RES CMF 374 OHMS 1% 1/16W	DIGITAL READY INTERFACE
RT507	253719		RES CMF 62.5MW 1% 475 OHM	DIGITAL READY INTERFACE
RT508	243375		RES CMF 1/16W 5% 4.7K	DIGITAL READY INTERFACE
RT510	249038		RES CMF 1/16W 5% 560R	DIGITAL READY INTERFACE
RT511	243653		RES CMF 1/16W 5% 100R	DIGITAL READY INTERFACE
RT512	243375		RES CMF 1/16W 5% 4.7K	DIGITAL READY INTERFACE
RT513	253717		RES CMF 62.5MW 1% 221 OHM	DIGITAL READY INTERFACE
RT514	244080		RES CCF 220K OHM +5% 62.5MW	DIGITAL READY INTERFACE
RT515	243485		RES CMF 1/16W 5% 1K	DIGITAL READY INTERFACE
RT516	256761		RES CMF 2.2K OHM 5% 1/16W	DIGITAL READY INTERFACE
RT517	253716		RES CMF 62.5MW 1% 47.5K	DIGITAL READY INTERFACE
RT518	244056		RES CMF 470 OHM 5% 62.5MW	DIGITAL READY INTERFACE
RT519	243375		RES CMF 1/16W 5% 4.7K	DIGITAL READY INTERFACE
RT521	244056		RES CMF 470 OHM 5% 62.5MW	DIGITAL READY INTERFACE
RT522	256783		RES CMF 1/16W 0% 0R	DIGITAL READY INTERFACE
RT523	256754		RES CMF 100K OHM 5% 1/16W	DIGITAL READY INTERFACE
RT526	243653		RES CMF 1/16W 5% 100R	DIGITAL READY INTERFACE
RT527	243653		RES CMF 1/16W 5% 100R	DIGITAL READY INTERFACE
RT531	243375		RES CMF 1/16W 5% 4.7K	DIGITAL READY INTERFACE
RT532	253668		RES CMF 62.5MW 1% 357 OHM	DIGITAL READY INTERFACE
RT533	243653		RES CMF 1/16W 5% 100R	DIGITAL READY INTERFACE
RT534	243375		RES CMF 1/16W 5% 4.7K	DIGITAL READY INTERFACE
RT535	244056		RES CMF 470 OHM 5% 62.5MW	DIGITAL READY INTERFACE
RT536	243653		RES CMF 1/16W 5% 100R	DIGITAL READY INTERFACE
RT537	260677		RES CMF 1/16W 5% 10R	DIGITAL READY INTERFACE
RT538	243653		RES CMF 1/16W 5% 100R	DIGITAL READY INTERFACE
RT541	243375		RES CMF 1/16W 5% 4.7K	DIGITAL READY INTERFACE
RT542	253668		RES CMF 62.5MW 1% 357 OHM	DIGITAL READY INTERFACE
RT543	243653		RES CMF 1/16W 5% 100R	DIGITAL READY INTERFACE
RT544	243375		RES CMF 1/16W 5% 4.7K	DIGITAL READY INTERFACE
RT545	244056		RES CMF 470 OHM 5% 62.5MW	DIGITAL READY INTERFACE
RT546	260643		RES CMF 1/16W 5% 180R	DIGITAL READY INTERFACE
RT547	260677		RES CMF 1/16W 5% 10R	DIGITAL READY INTERFACE
RT548	243653		RES CMF 1/16W 5% 100R	DIGITAL READY INTERFACE
RT551	243669		RESISTOR NETWORK	DIGITAL READY INTERFACE
RT552	243669		RESISTOR NETWORK	DIGITAL READY INTERFACE
RT553	243669		RESISTOR NETWORK	DIGITAL READY INTERFACE
RT554	243669		RESISTOR NETWORK	DIGITAL READY INTERFACE
RT561	256783		RES CMF 1/16W 0% 0R	DIGITAL READY INTERFACE
RT562	256783		RES CMF 1/16W 0% 0R	DIGITAL READY INTERFACE
RT563	256783		RES CMF 1/16W 0% 0R	DIGITAL READY INTERFACE
RT564	243485		RES CMF 1/16W 5% 1K	DIGITAL READY INTERFACE
RT565	244056		RES CMF 470 OHM 5% 62.5MW	DIGITAL READY INTERFACE
RT566	244056		RES CMF 470 OHM 5% 62.5MW	DIGITAL READY INTERFACE
RT571	259343		RES CFF 10 OHMS 10% 1/4W	DIGITAL READY INTERFACE
RT601	176818		RES CMF 1/8W 5% 100R	DIGITAL READY INTERFACE
RT602	176818		RES CMF 1/8W 5% 100R	DIGITAL READY INTERFACE
RT603	259493		RES NETWORK 4.7K X 4 1/16W	DIGITAL READY INTERFACE
RT604	256748		RES CMF 33K OHM 5% 1/16W	DIGITAL READY INTERFACE
RT605	243653		RES CMF 1/16W 5% 100R	DIGITAL READY INTERFACE
RT606	243653		RES CMF 1/16W 5% 100R	DIGITAL READY INTERFACE
RT609	256748		RES CMF 33K OHM 5% 1/16W	DIGITAL READY INTERFACE
RT610	256748		RES CMF 33K OHM 5% 1/16W	DIGITAL READY INTERFACE
RT611	259497		RES CMF 412 OHMS 1% 1/16W	DIGITAL READY INTERFACE
RT621	256764		RES CMF 3.3K OHM 5% 1/16W	DIGITAL READY INTERFACE
RT622	244056		RES CMF 470 OHM 5% 62.5MW	DIGITAL READY INTERFACE
RT623	244056		RES CMF 470 OHM 5% 62.5MW	DIGITAL READY INTERFACE
RT626	256728		RES CMF 75 OHM 5% 1/16W	DIGITAL READY INTERFACE
RT627	256728		RES CMF 75 OHM 5% 1/16W	DIGITAL READY INTERFACE

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
RT628	256728		RES CMF 75 OHM 5% 1/16W	DIGITAL READY INTERFACE
RT631	256734		RES CMF 300 OHM 5% 1/16W	DIGITAL READY INTERFACE
RT632	256734		RES CMF 300 OHM 5% 1/16W	DIGITAL READY INTERFACE
RT633	256734		RES CMF 300 OHM 5% 1/16W	DIGITAL READY INTERFACE
RT634	244056		RES CMF 470 OHM 5% 62.5MW	DIGITAL READY INTERFACE
RT635	256754		RES CMF 100K OHM 5% 1/16W	DIGITAL READY INTERFACE
RT636	244078		RES CMF 1/16W 5% 1M	DIGITAL READY INTERFACE
RT637	259499		RES CMF 143 OHMS 1% 1/16W	DIGITAL READY INTERFACE
RT709	256754		RES CMF 100K OHM 5% 1/16W	DIGITAL READY INTERFACE
RT724	243375		RES CMF 1/16W 5% 4.7K	DIGITAL READY INTERFACE
RT900	235901		RES CFF 1/4W 5% 4.7 OHMS	DIGITAL READY INTERFACE
RT910	243653		RES CMF 1/16W 5% 100R	DIGITAL READY INTERFACE
RT911	243653		RES CMF 1/16W 5% 100R	DIGITAL READY INTERFACE
RT940	206380		RES CMF 1/8W 5% 4.7K	DIGITAL READY INTERFACE
RT941	206380		RES CMF 1/8W 5% 4.7K	DIGITAL READY INTERFACE
RT942	256754		RES CMF 100K OHM 5% 1/16W	DIGITAL READY INTERFACE
RT943	256754		RES CMF 100K OHM 5% 1/16W	DIGITAL READY INTERFACE
RT950	206380		RES CMF 1/8W 5% 4.7K	DIGITAL READY INTERFACE
RT951	206380		RES CMF 1/8W 5% 4.7K	DIGITAL READY INTERFACE
RT952	256754		RES CMF 100K OHM 5% 1/16W	DIGITAL READY INTERFACE
RT953	256754		RES CMF 100K OHM 5% 1/16W	DIGITAL READY INTERFACE
RT960	206380		RES CMF 1/8W 5% 4.7K	DIGITAL READY INTERFACE
RT961	206380		RES CMF 1/8W 5% 4.7K	DIGITAL READY INTERFACE
RT962	256754		RES CMF 100K OHM 5% 1/16W	DIGITAL READY INTERFACE
RT963	256754		RES CMF 100K OHM 5% 1/16W	DIGITAL READY INTERFACE
RT970	206380		RES CMF 1/8W 5% 4.7K	DIGITAL READY INTERFACE
RT971	206380		RES CMF 1/8W 5% 4.7K	DIGITAL READY INTERFACE
RT990	176814		RES CMF 1/8W 5% 820R	DIGITAL READY INTERFACE
RT991	176814		RES CMF 1/8W 5% 820R	DIGITAL READY INTERFACE
RT992	176814		RES CMF 1/8W 5% 820R	DIGITAL READY INTERFACE
RT993	176814		RES CMF 1/8W 5% 820R	DIGITAL READY INTERFACE
RU002	244056		RES CMF 470 OHM 5% 62.5MW	SMALL SIGNAL BOARD
RU003	243485		RES CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RU004	259605		RES CMF 37.4K 1% 1/16W	SMALL SIGNAL BOARD
RU005	243485		RES CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RU006	243485		RES CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RU007	253724		RES CMF 62.5MW 1% 22.1K	SMALL SIGNAL BOARD
RU008	253719		RES CMF 62.5MW 1% 475 OHM	SMALL SIGNAL BOARD
RU010	259722		RES CMF 2.61K 1% 1/16W	SMALL SIGNAL BOARD
RU013	253719		RES CMF 62.5MW 1% 475 OHM	SMALL SIGNAL BOARD
RU018	253719		RES CMF 62.5MW 1% 475 OHM	SMALL SIGNAL BOARD
RU019	253719		RES CMF 62.5MW 1% 475 OHM	SMALL SIGNAL BOARD
RU020	243485		RES CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RU040	243375		RES CMF 1/16W 5% 4.7K	SMALL SIGNAL BOARD
RU060	243485		RES CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RU061	256744		RES CMF 18K OHM +5% 62.5MW	SMALL SIGNAL BOARD
RU062	253624		RES CMF 62.5MW 5% 82K	SMALL SIGNAL BOARD
RU705	243375		RES CMF 1/16W 5% 4.7K	MPEG CBA
RV001	261152		RES CMF 150R 5% 1/16W	SMALL SIGNAL BOARD
RV005	261152		RES CMF 150R 5% 1/16W	SMALL SIGNAL BOARD
RV007	259558		RES CMF 750 OHMS 1% 1/16W	SMALL SIGNAL BOARD
RV008	244056		RES CMF 470 OHM 5% 62.5MW	SMALL SIGNAL BOARD
RV009	249041		RES CMF 1/16W 5% 1.2K	SMALL SIGNAL BOARD
RV01	259564		RES WW 4.7 OHMS 5% 3W	CONVERGENCE PS / ADAPTE
RV010	253719		RES CMF 62.5MW 1% 475 OHM	SMALL SIGNAL BOARD
RV011	252361		RES CF 1/10W 1% 665R	SMALL SIGNAL BOARD
RV012	244056		RES CMF 470 OHM 5% 62.5MW	SMALL SIGNAL BOARD
RV013	253719		RES CMF 62.5MW 1% 475 OHM	SMALL SIGNAL BOARD
RV014	259641		RES CMF 825 OHMS 1% 1/16W	SMALL SIGNAL BOARD
RV016	244056		RES CMF 470 OHM 5% 62.5MW	SMALL SIGNAL BOARD
RV02	256762		RES CMF 2.7K OHM 5% 1/16W	CONVERGENCE PS / ADAPTE
RV021	243653		RES CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RV022	243653		RES CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RV023	256735		RESCF 330 OHM +5%	SMALL SIGNAL BOARD
RV024	244095		RES CMF 1/16W 5% 820R	SMALL SIGNAL BOARD
RV025	244056		RES CMF 470 OHM 5% 62.5MW	SMALL SIGNAL BOARD

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
RV026	244056		RES CMF 470 OHM 5% 62.5MW	SMALL SIGNAL BOARD
RV027	244095		RES CMF 1/16W 5% 820R	SMALL SIGNAL BOARD
RV03	259439		RES CF 330K 5% 1/4W	CONVERGENCE PS / ADAPTE
RV04	259439		RES CF 330K 5% 1/4W	CONVERGENCE PS / ADAPTE
RV041	243653		RES CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RV042	243653		RES CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RV043	243486		RES CMF 390 OHMS 5% 1/16W	SMALL SIGNAL BOARD
RV044	244095		RES CMF 1/16W 5% 820R	SMALL SIGNAL BOARD
RV045	244056		RES CMF 470 OHM 5% 62.5MW	SMALL SIGNAL BOARD
RV046	244056		RES CMF 470 OHM 5% 62.5MW	SMALL SIGNAL BOARD
RV047	260648		RES CMF 750R OHM +5% 1/16W	SMALL SIGNAL BOARD
RV05	244865		RES CC 1/2W 20% 47 OHMS	CONVERGENCE PS / ADAPTE
RV06	256764		RES CMF 3.3K OHM 5% 1/16W	CONVERGENCE PS / ADAPTE
RV07	258179		RES CF 2.2K 5% 1/4W	CONVERGENCE PS / ADAPTE
RV08	256746		RES CMF 22K OHM 5% 1/16W	CONVERGENCE PS / ADAPTE
RV09	259564		RES WW 4.7 OHMS 5% 3W	CONVERGENCE PS / ADAPTE
RV10	259425		RES CF 12K 5% 1/4W	CONVERGENCE PS / ADAPTE
RV11	259439		RES CF 330K 5% 1/4W	CONVERGENCE PS / ADAPTE
RV111	256754		RES CMF 100K OHM 5% 1/16W	SMALL SIGNAL BOARD
RV112	256754		RES CMF 100K OHM 5% 1/16W	SMALL SIGNAL BOARD
RV12	256761		RES CMF 2.2K OHM 5% 1/16W	CONVERGENCE PS / ADAPTE
RV120	243653		RES CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RV13	198656		RES CF 1/4W 5% 100R	CONVERGENCE PS / ADAPTE
RV130	243653		RES CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RV14	193334		RES CF 1/4W 5% 750K	CONVERGENCE PS / ADAPTE
RV15	198656		RES CF 1/4W 5% 100R	CONVERGENCE PS / ADAPTE
RV16	243653		RES CMF 1/16W 5% 100R	CONVERGENCE PS / ADAPTE
RV17	259482		RES 681 OHMS 1% .4W	CONVERGENCE PS / ADAPTE
RV19	256754		RES CMF 100K OHM 5% 1/16W	CONVERGENCE PS / ADAPTE
RV20	253625		RES CMF 62.5MW 5% 150K	CONVERGENCE PS / ADAPTE
RV21	263291		RES CMF 1/10W 1% 10K	CONVERGENCE PS / ADAPTE
RV22	259482		RES 681 OHMS 1% .4W	CONVERGENCE PS / ADAPTE
RV23	256762		RES CMF 2.7K OHM 5% 1/16W	CONVERGENCE PS / ADAPTE
RV230	243653		RES CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RV231	243653		RES CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RV24	263291		RES CMF 1/10W 1% 10K	CONVERGENCE PS / ADAPTE
RV240	243653		RES CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RV241	243653		RES CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RV25	259610		RES CMF 3.65K 1% 1/16W	CONVERGENCE PS / ADAPTE
RV250	259969		RES CMF 75 OHMS 1% 1/8W	SMALL SIGNAL BOARD
RV251	259969		RES CMF 75 OHMS 1% 1/8W	SMALL SIGNAL BOARD
RV252	259969		RES CMF 75 OHMS 1% 1/8W	SMALL SIGNAL BOARD
RV253	162001		RES CMF 1/8W 5% 1.5K	SMALL SIGNAL BOARD
RV26	259482		RES 681 OHMS 1% .4W	CONVERGENCE PS / ADAPTE
RV27	256746		RES CMF 22K OHM 5% 1/16W	CONVERGENCE PS / ADAPTE
RV270	206380		RES CMF 1/8W 5% 4.7K	SMALL SIGNAL BOARD
RV271	244080		RES CCF 220K OHM +5% 62.5MW	SMALL SIGNAL BOARD
RV275	155137		RES CMF 1/8W 5% 560R	SMALL SIGNAL BOARD
RV276	162006		RES CMF 1/8W 5% 3.9K	SMALL SIGNAL BOARD
RV277	256761		RES CMF 2.2K OHM 5% 1/16W	SMALL SIGNAL BOARD
RV28	160155		RES MF .4W 1% 10K	CONVERGENCE PS / ADAPTE
RV280	243485		RES CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RV281	242690		RES CMF 1/16W 5% 10K	SMALL SIGNAL BOARD
RV29	259349		RES MF 3.65K 1% .4W	CONVERGENCE PS / ADAPTE
RV30	253722		RES CMF 62.5MW 1% 2.21K	CONVERGENCE PS / ADAPTE
RV300	256735		RESCF 330 OHM +5%	SMALL SIGNAL BOARD
RV302	260677		RES CMF 1/16W 5% 10R	SMALL SIGNAL BOARD
RV303	155137		RES CMF 1/8W 5% 560R	SMALL SIGNAL BOARD
RV31	259479		RES MF 5.36K 1% .4W	CONVERGENCE PS / ADAPTE
RV310	256735		RESCF 330 OHM +5%	SMALL SIGNAL BOARD
RV312	260677		RES CMF 1/16W 5% 10R	SMALL SIGNAL BOARD
RV313	155137		RES CMF 1/8W 5% 560R	SMALL SIGNAL BOARD
RV32	253722		RES CMF 62.5MW 1% 2.21K	CONVERGENCE PS / ADAPTE
RV320	256735		RESCF 330 OHM +5%	SMALL SIGNAL BOARD
RV322	260677		RES CMF 1/16W 5% 10R	SMALL SIGNAL BOARD
RV323	155137		RES CMF 1/8W 5% 560R	SMALL SIGNAL BOARD

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
RV33	253722	RES	CMF 62.5MW 1% 2.21K	CONVERGENCE PS / ADAPTE
RV34	259558	RES	CMF 750 OHMS 1% 1/16W	CONVERGENCE PS / ADAPTE
RV340	256768	RES	MF 8.2K +5%	SMALL SIGNAL BOARD
RV341	243485	RES	CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RV35	220663	RES	CF 1/4W 5% 22K	CONVERGENCE PS / ADAPTE
RV36	256744	RES	CMF 18K OHM 5% 1/16W	CONVERGENCE PS / ADAPTE
RV37	244078	RES	CMF 1/16W 5% 1M	CONVERGENCE PS / ADAPTE
RV38	198656	RES	CF 1/4W 5% 100R	CONVERGENCE PS / ADAPTE
RV39	243485	RES	CMF 1/16W 5% 1K	CONVERGENCE PS / ADAPTE
RV40	258180	RES	CF 1K 5% 1/4W	CONVERGENCE PS / ADAPTE
RV41	249338	RES	CMF 47K 5% 1/16W	CONVERGENCE PS / ADAPTE
RV42	243485	RES	CMF 1/16W 5% 1K	CONVERGENCE PS / ADAPTE
RV44	243485	RES	CMF 1/16W 5% 1K	CONVERGENCE PS / ADAPTE
RV45	259490	RES	CMF 8.66K 1% 1/16W	CONVERGENCE PS / ADAPTE
RV47	243485	RES	CMF 1/16W 5% 1K	CONVERGENCE PS / ADAPTE
RV48	244078	RES	CMF 1/16W 5% 1M	CONVERGENCE PS / ADAPTE
RV49	249041	RES	CMF 1/16W 5% 1.2K	CONVERGENCE PS / ADAPTE
RV50	258179	RES	CF 2.2K 5% 1/4W	CONVERGENCE PS / ADAPTE
RV501	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RV502	244056	RES	CMF 470 OHM 5% 62.5MW	SMALL SIGNAL BOARD
RV505	244078	RES	CMF 1/16W 5% 1M	SMALL SIGNAL BOARD
RV507	256754	RES	CMF 100K OHM 5% 1/16W	SMALL SIGNAL BOARD
RV51	198672	RES	CF 1/4W 5% 1.5K	CONVERGENCE PS / ADAPTE
RV510	256764	RES	CMF 3.3K OHM 5% 1/16W	SMALL SIGNAL BOARD
RV511	256761	RES	CMF 2.2K OHM 5% 1/16W	SMALL SIGNAL BOARD
RV512	243485	RES	CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RV513	256761	RES	CMF 2.2K OHM 5% 1/16W	SMALL SIGNAL BOARD
RV52	259433	RES	CF 1M 5% 1/4W	CONVERGENCE PS / ADAPTE
RV520	174348	RES	CMF 1/8W 5% 1K	SMALL SIGNAL BOARD
RV521	259956	RES	CMF 127K 1% 1/8W	SMALL SIGNAL BOARD
RV522	242690	RES	CMF 1/16W 5% 10K	SMALL SIGNAL BOARD
RV523	256759	RES	CMF 1/16W 5% 1.5K	SMALL SIGNAL BOARD
RV524	259957	RES	CMF 470K 2% 1/8W	SMALL SIGNAL BOARD
RV525	256764	RES	CMF 3.3K OHM 5% 1/16W	SMALL SIGNAL BOARD
RV526	243485	RES	CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RV527	253807	RES	CMF 62.5MW 1% 18.2K	SMALL SIGNAL BOARD
RV528	259970	RES	CMF 17.8K 1% 1/8W	SMALL SIGNAL BOARD
RV529	259957	RES	CMF 470K 2% 1/8W	SMALL SIGNAL BOARD
RV53	244078	RES	CMF 1/16W 5% 1M	CONVERGENCE PS / ADAPTE
RV530	259603	RES	CMF 53.6K 1% 1/16W	SMALL SIGNAL BOARD
RV531	253625	RES	CMF 62.5MW 5% 150K	SMALL SIGNAL BOARD
RV532	220130	RES	CMF 1/8W 1% 10K	SMALL SIGNAL BOARD
RV533	243375	RES	CMF 1/16W 5% 4.7K	SMALL SIGNAL BOARD
RV534	248862	RES	CMF 330K OHM +5% 1/16W	SMALL SIGNAL BOARD
RV54	259433	RES	CF 1M 5% 1/4W	CONVERGENCE PS / ADAPTE
RV541	253848	RES	CMF 62.5MW 1% 39.2K	SMALL SIGNAL BOARD
RV542	256761	RES	CMF 2.2K OHM 5% 1/16W	SMALL SIGNAL BOARD
RV543	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RV544	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RV55	253625	RES	CMF 62.5MW 5% 150K	CONVERGENCE PS / ADAPTE
RV550	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RV555	243485	RES	CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RV556	205304	RES	CMF 1/8W 2% 330K	SMALL SIGNAL BOARD
RV56	249338	RES	CMF 47K 5% 1/16W	CONVERGENCE PS / ADAPTE
RV560	256764	RES	CMF 3.3K OHM 5% 1/16W	SMALL SIGNAL BOARD
RV57	256761	RES	CMF 2.2K OHM 5% 1/16W	CONVERGENCE PS / ADAPTE
RV58	256748	RES	CMF 33K OHM 5% 1/16W	CONVERGENCE PS / ADAPTE
RV59	249338	RES	CMF 47K 5% 1/16W	CONVERGENCE PS / ADAPTE
RV65	198656	RES	CF 1/4W 5% 100R	CONVERGENCE PS / ADAPTE
RV67	243653	RES	CMF 1/16W 5% 100R	CONVERGENCE PS / ADAPTE
RV70	243375	RES	CMF 1/16W 5% 4.7K	CONVERGENCE PS / ADAPTE
RV71	220663	RES	CF 1/4W 5% 22K	CONVERGENCE PS / ADAPTE
RV72	259339	RES	CF 100K 5% .7W	CONVERGENCE PS / ADAPTE
RV73	259339	RES	CF 100K 5% .7W	CONVERGENCE PS / ADAPTE
RV74	243375	RES	CMF 1/16W 5% 4.7K	CONVERGENCE PS / ADAPTE
RV80	244849	RES	CF 1/4W 5% 39K	CONVERGENCE PS / ADAPTE

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
RV81	198699		RES CF 1/4W 5% 18K	CONVERGENCE PS / ADAPTE
RV82	198673		RES CF 1/4W 5% 3.3K	CONVERGENCE PS / ADAPTE
RV83	259340		RES CF 270K 5% .7W	CONVERGENCE PS / ADAPTE
RV84	259340		RES CF 270K 5% .7W	CONVERGENCE PS / ADAPTE
RV85	210190		RES CF .43W 5% 1K	CONVERGENCE PS / ADAPTE
RV87	259342		RES CF 10K 5% .7W	CONVERGENCE PS / ADAPTE
RV88	258177		RES CF 4.7K 5% 1/4W	CONVERGENCE PS / ADAPTE
RV89	256741		RES CMF 10K OHM 5% 1/16W	CONVERGENCE PS / ADAPTE
RV91	263291		RES CMF 1/10W 1% 10K	CONVERGENCE PS / ADAPTE
RV92	263291		RES CMF 1/10W 1% 10K	CONVERGENCE PS / ADAPTE
RV94	258177		RES CF 4.7K 5% 1/4W	CONVERGENCE PS / ADAPTE
RV95	258177		RES CF 4.7K 5% 1/4W	CONVERGENCE PS / ADAPTE
RV96	256741		RES CMF 10K OHM 5% 1/16W	CONVERGENCE PS / ADAPTE
RV97	256803		RES CF 1/4W 5% 47K	CONVERGENCE PS / ADAPTE
RV98	259453		RES CF 680K 5% 1/4W	CONVERGENCE PS / ADAPTE
RW01	259446		RES CF 3.3K 5% .14W	CONVERGENCE AMP BOARD
RW02	259428		RES CF 15K 5% .14W	CONVERGENCE AMP BOARD
RW04	259450		RES CF 56K 5% .14W	CONVERGENCE AMP BOARD
RW05	259457		RES CF 8.2K 5% .14W	CONVERGENCE AMP BOARD
RW06	259446		RES CF 3.3K 5% .14W	CONVERGENCE AMP BOARD
RW09	216176		RES CF .14W 5% 1K	CONVERGENCE AMP BOARD
RW10	259457		RES CF 8.2K 5% .14W	CONVERGENCE AMP BOARD
RW11	203782		RES CF .14W 5% 4.7K	CONVERGENCE AMP BOARD
RW110	256783		RES CMF 1/16W 0% 0R	MPEG CBA
RW111	256783		RES CMF 1/16W 0% 0R	MPEG CBA
RW112	256783		RES CMF 1/16W 0% 0R	MPEG CBA
RW12	259424		RES CF 12K 5% .14W	CONVERGENCE AMP BOARD
RW13	259447		RES CF 3.9K 5% .14W	CONVERGENCE AMP BOARD
RW15	203782		RES CF .14W 5% 4.7K	CONVERGENCE AMP BOARD
RW18	184838		RES CF .14W 5% 10K	CONVERGENCE AMP BOARD
RW19	216176		RES CF .14W 5% 1K	CONVERGENCE AMP BOARD
RW20	248858		RES CF 1/4W 5% 47 OHMS	CONVERGENCE AMP BOARD
RX001	243661		RES CMF 270 OHM +5%	FRONT PANEL 1
RX001	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
RX002	243480		RES MF 68 OHM +5%	FRONT PANEL 1
RX004	243486		RES CMF 390 OHMS 5% 1/16W	FRONT PANEL 1
RX006	256783		RES CMF 1/16W 0% 0R	FRONT PANEL 1
RX010	181161		RES CMF 1/8W 0% 0R	SMALL SIGNAL BOARD
RX100	259969		RES CMF 75 OHMS 1% 1/8W	SMALL SIGNAL BOARD
RX101	206275		RES CMF 1/8W 5% 220R	SMALL SIGNAL BOARD
RX120	259969		RES CMF 75 OHMS 1% 1/8W	SMALL SIGNAL BOARD
RX121	206275		RES CMF 1/8W 5% 220R	SMALL SIGNAL BOARD
RX130	259969		RES CMF 75 OHMS 1% 1/8W	SMALL SIGNAL BOARD
RX133	243653		RES CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RX134	242690		RES CMF 1/16W 5% 10K	SMALL SIGNAL BOARD
RX135	174346		RES CMF 470 OHMS 5% 1/8W	SMALL SIGNAL BOARD
RX136	243485		RES CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RX137	174346		RES CMF 470 OHMS 5% 1/8W	SMALL SIGNAL BOARD
RX200	259969		RES CMF 75 OHMS 1% 1/8W	SMALL SIGNAL BOARD
RX201	206275		RES CMF 1/8W 5% 220R	SMALL SIGNAL BOARD
RX220	259969		RES CMF 75 OHMS 1% 1/8W	SMALL SIGNAL BOARD
RX221	206275		RES CMF 1/8W 5% 220R	SMALL SIGNAL BOARD
RX300	259969		RES CMF 75 OHMS 1% 1/8W	SMALL SIGNAL BOARD
RX301	206275		RES CMF 1/8W 5% 220R	SMALL SIGNAL BOARD
RX320	259969		RES CMF 75 OHMS 1% 1/8W	SMALL SIGNAL BOARD
RX321	206275		RES CMF 1/8W 5% 220R	SMALL SIGNAL BOARD
RX500	259968		RES CMF 169 OHMS 1% 1/8W	SMALL SIGNAL BOARD
RX501	190460		RES CMF 1/8W 2% 240R	SMALL SIGNAL BOARD
RX502	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
RX504	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
RX509	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
RX513	260677		RES CMF 1/16W 5% 10R	SMALL SIGNAL BOARD
RX514	256739		RES CMF 680 OHM 5% 1/16W	SMALL SIGNAL BOARD
RX520	243653		RES CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RX521	260677		RES CMF 1/16W 5% 10R	SMALL SIGNAL BOARD
RX522	256731		RES CMF 120 OHM 5% 1/16W	SMALL SIGNAL BOARD

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
RX523	258690	RES	CMF 910 OHMS 5% 1/16W	SMALL SIGNAL BOARD
RX530	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RX532	259670	RES	CMF 261 OHMS 1% 1/16W	SMALL SIGNAL BOARD
RX533	258689	RES	CMF 620 OHMS 5% 1/16W	SMALL SIGNAL BOARD
RX540	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RX542	243480	RES	MF 68 OHM +5%	SMALL SIGNAL BOARD
RX543	249038	RES	CMF 1/16W 5% 560R	SMALL SIGNAL BOARD
RX555	260677	RES	CMF 1/16W 5% 10R	SMALL SIGNAL BOARD
RX565	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RX566	260677	RES	CMF 1/16W 5% 10R	SMALL SIGNAL BOARD
RX567	243485	RES	CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RX571	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RX572	260677	RES	CMF 1/16W 5% 10R	SMALL SIGNAL BOARD
RX573	256942	RES	CMF 1/16W 5% 220R	SMALL SIGNAL BOARD
RX574	256739	RES	CMF 680 OHM 5% 1/16W	SMALL SIGNAL BOARD
RX580	259969	RES	CMF 75 OHMS 1% 1/8W	SMALL SIGNAL BOARD
RX581	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RX582	259969	RES	CMF 75 OHMS 1% 1/8W	SMALL SIGNAL BOARD
RX583	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RX584	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RX585	259969	RES	CMF 75 OHMS 1% 1/8W	SMALL SIGNAL BOARD
RX586	259969	RES	CMF 75 OHMS 1% 1/8W	SMALL SIGNAL BOARD
RX587	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RX590	243375	RES	CMF 1/16W 5% 4.7K	SMALL SIGNAL BOARD
RX591	242690	RES	CMF 1/16W 5% 10K	SMALL SIGNAL BOARD
RX592	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RX595	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RX596	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RX598	243375	RES	CMF 1/16W 5% 4.7K	SMALL SIGNAL BOARD
RX599	242690	RES	CMF 1/16W 5% 10K	SMALL SIGNAL BOARD
RX600	256783	RES	CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
RX606	256783	RES	CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
RX610	256754	RES	CMF 100K OHM 5% 1/16W	SMALL SIGNAL BOARD
RX611	256754	RES	CMF 100K OHM 5% 1/16W	SMALL SIGNAL BOARD
RX620	256754	RES	CMF 100K OHM 5% 1/16W	SMALL SIGNAL BOARD
RX621	256754	RES	CMF 100K OHM 5% 1/16W	SMALL SIGNAL BOARD
RX630	256754	RES	CMF 100K OHM 5% 1/16W	SMALL SIGNAL BOARD
RX631	256754	RES	CMF 100K OHM 5% 1/16W	SMALL SIGNAL BOARD
RX640	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RX641	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RX650	249041	RES	CMF 1/16W 5% 1.2K	SMALL SIGNAL BOARD
RX651	260677	RES	CMF 1/16W 5% 10R	SMALL SIGNAL BOARD
RX652	259607	RES	CMF 2.43K 1% 1/16W	SMALL SIGNAL BOARD
RX653	253722	RES	CMF 62.5MW 1% 2.21K	SMALL SIGNAL BOARD
RX655	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RX656	260677	RES	CMF 1/16W 5% 10R	SMALL SIGNAL BOARD
RX657	244056	RES	CMF 470 OHM 5% 62.5MW	SMALL SIGNAL BOARD
RX658	244056	RES	CMF 470 OHM 5% 62.5MW	SMALL SIGNAL BOARD
RX670	249041	RES	CMF 1/16W 5% 1.2K	SMALL SIGNAL BOARD
RX671	260677	RES	CMF 1/16W 5% 10R	SMALL SIGNAL BOARD
RX672	259607	RES	CMF 2.43K 1% 1/16W	SMALL SIGNAL BOARD
RX673	253722	RES	CMF 62.5MW 1% 2.21K	SMALL SIGNAL BOARD
RX675	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RX676	260677	RES	CMF 1/16W 5% 10R	SMALL SIGNAL BOARD
RX677	244056	RES	CMF 470 OHM 5% 62.5MW	SMALL SIGNAL BOARD
RX678	244056	RES	CMF 470 OHM 5% 62.5MW	SMALL SIGNAL BOARD
RX690	256783	RES	CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
RX700	259968	RES	CMF 169 OHMS 1% 1/8W	SMALL SIGNAL BOARD
RX701	190460	RES	CMF 1/8W 2% 240R	SMALL SIGNAL BOARD
RX703	181161	RES	CMF 1/8W 0% 0R	SMALL SIGNAL BOARD
RX704	256783	RES	CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
RX705	260677	RES	CMF 1/16W 5% 10R	SMALL SIGNAL BOARD
RX710	243375	RES	CMF 1/16W 5% 4.7K	SMALL SIGNAL BOARD
RX711	260677	RES	CMF 1/16W 5% 10R	SMALL SIGNAL BOARD
RX712	256739	RES	CMF 680 OHM 5% 1/16W	SMALL SIGNAL BOARD
RX720	243653	RES	CMF 1/16W 5% 100R	SMALL SIGNAL BOARD

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
RX721	260677		RES CMF 1/16W 5% 10R	SMALL SIGNAL BOARD
RX722	256731		RES CMF 120 OHM 5% 1/16W	SMALL SIGNAL BOARD
RX723	258690		RES CMF 910 OHMS 5% 1/16W	SMALL SIGNAL BOARD
RX730	243653		RES CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RX732	259670		RES CMF 261 OHMS 1% 1/16W	SMALL SIGNAL BOARD
RX733	258689		RES CMF 620 OHMS 5% 1/16W	SMALL SIGNAL BOARD
RX740	243653		RES CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RX742	243480		RES MF 68 OHM +5%	SMALL SIGNAL BOARD
RX743	249038		RES CMF 1/16W 5% 560R	SMALL SIGNAL BOARD
RX765	243653		RES CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RX766	260677		RES CMF 1/16W 5% 10R	SMALL SIGNAL BOARD
RX767	243485		RES CMF 1/16W 5% 1K	SMALL SIGNAL BOARD
RX771	243653		RES CMF 1/16W 5% 100R	SMALL SIGNAL BOARD
RX772	260677		RES CMF 1/16W 5% 10R	SMALL SIGNAL BOARD
RX773	244074		RES CMF 47 OHM +5% 62.5MW	SMALL SIGNAL BOARD
RX774	256739		RES CMF 680 OHM 5% 1/16W	SMALL SIGNAL BOARD
RX930	206275		RES CMF 1/8W 5% 220R	SMALL SIGNAL BOARD
RX940	206275		RES CMF 1/8W 5% 220R	SMALL SIGNAL BOARD
RX950	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
RX951	243375		RES CMF 1/16W 5% 4.7K	SMALL SIGNAL BOARD
RX952	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
RX960	256783		RES CMF 1/16W 0% 0R	SMALL SIGNAL BOARD
RY543	243661		RES CMF 270 OHM +5%	MPEG CBA
RY552	256783		RES CMF 1/16W 0% 0R	MPEG CBA
RY609	256783		RES CMF 1/16W 0% 0R	MPEG CBA
RY610	243485		RES CMF 1/16W 5% 1K	MPEG CBA
RY611	256783		RES CMF 1/16W 0% 0R	MPEG CBA
RY612	256783		RES CMF 1/16W 0% 0R	MPEG CBA
RY613	256783		RES CMF 1/16W 0% 0R	MPEG CBA
RY614	256783		RES CMF 1/16W 0% 0R	MPEG CBA
RY622	256728		RES CMF 75 OHM 5% 1/16W	MPEG CBA
RY624	256728		RES CMF 75 OHM 5% 1/16W	MPEG CBA
RY625	256728		RES CMF 75 OHM 5% 1/16W	MPEG CBA
RY628	256728		RES CMF 75 OHM 5% 1/16W	MPEG CBA
RY629	243661		RES CMF 270 OHM +5%	MPEG CBA
RY630	243661		RES CMF 270 OHM +5%	MPEG CBA
RY631	243661		RES CMF 270 OHM +5%	MPEG CBA
SCREEN	258518		SCREEN, PROJECTION: 61"(16X9)	INSTRUMENT ASSEMBLY
SCREW	258838		SCREW, TORX T10 L=.5" HD=.2"	CHASSIS ASSEMBLY
SCREW	259189		SCREW, TORX-T20 PANHD 4MMX16MM	INSTRUMENT ASSEMBLY
SCREW	259506		SCREW, DVI CABLE SECURING	DIGITAL READY INTERFACE
SCREW	259180		SCREW, TORX-T20 4MM X 20MM	INSTRUMENT ASSEMBLY
SCREW	259179		SCREW, TORX-T20 4MM X 16MM	INSTRUMENT ASSEMBLY
SCREW	257991		SCREW, TORX W/WSHR: 4MM X 25MM	INSTRUMENT ASSEMBLY
SCREW	259179		SCREW, TORX-T20 4MM X 16MM	CHASSIS ASSEMBLY
SCREW	258838		SCREW, TORX T10 L=.5" HD=.2"	INSTRUMENT ASSEMBLY
SENSOR	248432		TRANSISTOR, CONVERGENCE SENSOR	INSTRUMENT ASSEMBLY
SHIELD	259947		SHIELD FOR DVI-HDTV JACK	DIGITAL READY INTERFACE
SK001	257860		SWITCH	FRONT PANEL 1
SK002	257860		SWITCH	FRONT PANEL 2
SK004	257860		SWITCH	FRONT PANEL 2
SK005	257860		SWITCH	FRONT PANEL 2
SK015	257860		SWITCH	FRONT PANEL 1
SK016	257860		SWITCH	FRONT PANEL 1
SK020	257860		SWITCH	FRONT PANEL 1
SK021	257860		SWITCH	FRONT PANEL 1
SK022	257860		SWITCH	FRONT PANEL 1
SP402	259511		SPARK GAP	MAINS INPUT DOUBLER
SPACER	260033		SUPPORT, CBA SPACER	A/V INTERFACE
SPEAKER	258666		SPEAKER, 130MM 20W 8 OHMS	INSTRUMENT ASSEMBLY
SPEAKER	205260		SPEAKER 51MM 8 OHM 2W	INSTRUMENT ASSEMBLY
SPEAKER ENCLOSURE FACE PLATE	259176		SPEAKER ENCL FACE PLATE: LEFT	INSTRUMENT ASSEMBLY
SPEAKER ENCLOSURE FACE PLATE	258910		SPEAKER ENCL FACE PLATE: RIGHT	INSTRUMENT ASSEMBLY
SPRING	259191		SPRING, DVD DOOR	INSTRUMENT ASSEMBLY
SPRING	259190		SPRING FOR A/V DOOR	INSTRUMENT ASSEMBLY
ST980	259501		SWITCH, SPEAKER INT/EXT	DIGITAL READY INTERFACE

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
STRIKER	259178		BALLCATCH STRIKER	INSTRUMENT ASSEMBLY
SUPER SHIELD	258519		SUPER SHIELD, 61"(16 X 9)	INSTRUMENT ASSEMBLY
SUPPORT	259193		SUPPORT FOR SPDIF OUTPUT CBA	CHASSIS ASSEMBLY
SUPPORT	259882		SUPPORT FOR MID & SSB CBAS	CHASSIS ASSEMBLY
SUPPORT	259510		SUPPORT BRACKET FOR DRI MODULE	CHASSIS ASSEMBLY
SUPPORT	259207		SUPPORT, DVD MOUNTING	INSTRUMENT ASSEMBLY
SUPPORT	259181		SUPPORT RAIL FOR CHASSIS TRAY	INSTRUMENT ASSEMBLY
SVM COIL	258798		SVM COIL	OPTICS ASSEMBLY
TA01	259539		TRANSISTOR	CONVERGENCE AMP BOARD
TA02	259539		TRANSISTOR	CONVERGENCE AMP BOARD
TA03	259540		TRANSISTOR	CONVERGENCE AMP BOARD
TA04	259540		TRANSISTOR	CONVERGENCE AMP BOARD
TA05	259542		TRANSISTOR	CONVERGENCE AMP BOARD
TA06	259513		TRANSISTOR	CONVERGENCE AMP BOARD
TA130	259547		TRANSISTOR	SMALL SIGNAL BOARD
TA131	259547		TRANSISTOR	SMALL SIGNAL BOARD
TA145	259547		TRANSISTOR	SMALL SIGNAL BOARD
TA200	256808		TRANSISTOR	SMALL SIGNAL BOARD
TA201	259545		TRANSISTOR	SMALL SIGNAL BOARD
TA202	259545		TRANSISTOR	SMALL SIGNAL BOARD
TA50	259513		TRANSISTOR	CONVERGENCE AMP BOARD
TA51	259542		TRANSISTOR	CONVERGENCE AMP BOARD
TA52	259539		TRANSISTOR	CONVERGENCE AMP BOARD
TA53	259540		TRANSISTOR	CONVERGENCE AMP BOARD
TA54	259539		TRANSISTOR	CONVERGENCE AMP BOARD
TA55	259540		TRANSISTOR	CONVERGENCE AMP BOARD
TB01	259539		TRANSISTOR	CONVERGENCE AMP BOARD
TB02	259539		TRANSISTOR	CONVERGENCE AMP BOARD
TB03	259540		TRANSISTOR	CONVERGENCE AMP BOARD
TB04	259540		TRANSISTOR	CONVERGENCE AMP BOARD
TB05	259542		TRANSISTOR	CONVERGENCE AMP BOARD
TB06	259513		TRANSISTOR	CONVERGENCE AMP BOARD
TB101	259545		TRANSISTOR	KINE DRIVER RED W/SVM
TB111	256808		TRANSISTOR	KINE DRIVER RED W/SVM
TB120	256808		TRANSISTOR	KINE DRIVER RED W/SVM
TB140	259542		TRANSISTOR	KINE DRIVER RED W/SVM
TB155	259545		TRANSISTOR	KINE DRIVER RED W/SVM
TB161	259545		TRANSISTOR	KINE DRIVER RED W/SVM
TB166	259541		TRANSISTOR	KINE DRIVER RED W/SVM
TB201	259545		TRANSISTOR	KINE DRIVER GREEN W/SVM
TB211	256808		TRANSISTOR	KINE DRIVER GREEN W/SVM
TB212	256808		TRANSISTOR	KINE DRIVER GREEN W/SVM
TB220	256808		TRANSISTOR	KINE DRIVER GREEN W/SVM
TB235	259545		TRANSISTOR	KINE DRIVER GREEN W/SVM
TB237	256808		TRANSISTOR	KINE DRIVER GREEN W/SVM
TB240	259542		TRANSISTOR	KINE DRIVER GREEN W/SVM
TB255	259545		TRANSISTOR	KINE DRIVER GREEN W/SVM
TB261	259545		TRANSISTOR	KINE DRIVER GREEN W/SVM
TB266	259541		TRANSISTOR	KINE DRIVER GREEN W/SVM
TB301	259545		TRANSISTOR	KINE DRIVER BLUE W/SVM
TB311	256808		TRANSISTOR	KINE DRIVER BLUE W/SVM
TB312	256808		TRANSISTOR	KINE DRIVER BLUE W/SVM
TB320	256808		TRANSISTOR	KINE DRIVER BLUE W/SVM
TB331	256808		TRANSISTOR	KINE DRIVER BLUE W/SVM
TB332	256808		TRANSISTOR	KINE DRIVER BLUE W/SVM
TB333	259545		TRANSISTOR	KINE DRIVER BLUE W/SVM
TB335	259545		TRANSISTOR	KINE DRIVER BLUE W/SVM
TB337	256808		TRANSISTOR	KINE DRIVER BLUE W/SVM
TB340	259542		TRANSISTOR	KINE DRIVER BLUE W/SVM
TB355	259545		TRANSISTOR	KINE DRIVER BLUE W/SVM
TB361	259545		TRANSISTOR	KINE DRIVER BLUE W/SVM
TB366	259541		TRANSISTOR	KINE DRIVER BLUE W/SVM
TB50	259513		TRANSISTOR	CONVERGENCE AMP BOARD
TB51	259542		TRANSISTOR	CONVERGENCE AMP BOARD
TB52	259539		TRANSISTOR	CONVERGENCE AMP BOARD
TB53	259540		TRANSISTOR	CONVERGENCE AMP BOARD

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
TB54	259539		TRANSISTOR	CONVERGENCE AMP BOARD
TB55	259540		TRANSISTOR	CONVERGENCE AMP BOARD
TC950	259545		TRANSISTOR	SMALL SIGNAL BOARD
TD100	215496		TRANSISTOR	MPEG CBA
TD101	215495		TRANSISTOR	MPEG CBA
TF041	198749		TRANSISTOR	P-S/DEFLECTION
TG01	259539		TRANSISTOR	CONVERGENCE AMP BOARD
TG02	259539		TRANSISTOR	CONVERGENCE AMP BOARD
TG03	259540		TRANSISTOR	CONVERGENCE AMP BOARD
TG04	259540		TRANSISTOR	CONVERGENCE AMP BOARD
TG05	259542		TRANSISTOR	CONVERGENCE AMP BOARD
TG06	259513		TRANSISTOR	CONVERGENCE AMP BOARD
TG101	259513		TRANSISTOR	KINE DRIVER RED W/SVM
TG102	219354		TRANSISTOR	KINE DRIVER RED W/SVM
TG104	215977		TRANSISTOR	KINE DRIVER RED W/SVM
TG105	198749		TRANSISTOR	KINE DRIVER RED W/SVM
TG106	259639		TRANSISTOR	KINE DRIVER RED W/SVM
TG107	259995		TRANSISTOR	KINE DRIVER RED W/SVM
TG111	259545		TRANSISTOR	KINE DRIVER RED W/SVM
TG135	256808		TRANSISTOR	KINE DRIVER RED W/SVM
TG201	259513		TRANSISTOR	KINE DRIVER GREEN W/SVM
TG202	219354		TRANSISTOR	KINE DRIVER GREEN W/SVM
TG204	215977		TRANSISTOR	KINE DRIVER GREEN W/SVM
TG205	198749		TRANSISTOR	KINE DRIVER GREEN W/SVM
TG206	259639		TRANSISTOR	KINE DRIVER GREEN W/SVM
TG207	259995		TRANSISTOR	KINE DRIVER GREEN W/SVM
TG211	259545		TRANSISTOR	KINE DRIVER GREEN W/SVM
TG235	256808		TRANSISTOR	KINE DRIVER GREEN W/SVM
TG301	259513		TRANSISTOR	KINE DRIVER BLUE W/SVM
TG302	219354		TRANSISTOR	KINE DRIVER BLUE W/SVM
TG304	215977		TRANSISTOR	KINE DRIVER BLUE W/SVM
TG305	198749		TRANSISTOR	KINE DRIVER BLUE W/SVM
TG306	259639		TRANSISTOR	KINE DRIVER BLUE W/SVM
TG307	259995		TRANSISTOR	KINE DRIVER BLUE W/SVM
TG311	259545		TRANSISTOR	KINE DRIVER BLUE W/SVM
TG335	256808		TRANSISTOR	KINE DRIVER BLUE W/SVM
TG50	259513		TRANSISTOR	CONVERGENCE AMP BOARD
TG51	259542		TRANSISTOR	CONVERGENCE AMP BOARD
TG52	259539		TRANSISTOR	CONVERGENCE AMP BOARD
TG53	259540		TRANSISTOR	CONVERGENCE AMP BOARD
TG54	259539		TRANSISTOR	CONVERGENCE AMP BOARD
TTI010	259545		TRANSISTOR	SMALL SIGNAL BOARD
TTI030	259545		TRANSISTOR	SMALL SIGNAL BOARD
TTI530	259545		TRANSISTOR	SMALL SIGNAL BOARD
TK001	219349		TRANSISTOR	FRONT PANEL 1
TKK04	248805		TRANSISTOR	CONVERGENCE SIGNAL BOAR
TKK09	258661		TRANSISTOR	CONVERGENCE SIGNAL BOAR
TKK14	248805		TRANSISTOR	CONVERGENCE SIGNAL BOAR
TKK20	248805		TRANSISTOR	CONVERGENCE SIGNAL BOAR
TKK22	248805		TRANSISTOR	CONVERGENCE SIGNAL BOAR
TKK24	248805		TRANSISTOR	CONVERGENCE SIGNAL BOAR
TKK25	248805		TRANSISTOR	CONVERGENCE SIGNAL BOAR
TKK26	258661		TRANSISTOR	CONVERGENCE SIGNAL BOAR
TKK27	258661		TRANSISTOR	CONVERGENCE SIGNAL BOAR
TKK47	258729		TRANSISTOR	CONVERGENCE SIGNAL BOAR
TKK48	258729		TRANSISTOR	CONVERGENCE SIGNAL BOAR
TTL003	259513		TRANSISTOR	P-S/DEFLECTION
TTL004	177788		TRANSISTOR	P-S/DEFLECTION
TTL005	259533		TRANSISTOR	P-S/DEFLECTION
TTL010	259899		TRANSISTOR, HORIZONTAL OUTPUT	P-S/DEFLECTION
TTL029	256868		TRANSISTOR	P-S/DEFLECTION
TTL100	259513		TRANSISTOR	P-S/DEFLECTION
TTL104	259513		TRANSISTOR	P-S/DEFLECTION
TTL105	259622		TRANSISTOR	P-S/DEFLECTION
TTL111	219354		TRANSISTOR	P-S/DEFLECTION
TTL120	259871		TRANSISTOR	P-S/DEFLECTION

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
TL140	256868		TRANSISTOR	P-S/DEFLECTION
TL311	232549		TRANSISTOR	P-S/DEFLECTION
TL312	198749		TRANSISTOR	P-S/DEFLECTION
TOE RAIL	263117		TOE RAIL	INSTRUMENT ASSEMBLY
TP020	259856		TRANSISTOR	P-S/DEFLECTION
TP026	259513		TRANSISTOR	P-S/DEFLECTION
TP034	198749		TRANSISTOR	P-S/DEFLECTION
TP050	219354		TRANSISTOR	P-S/DEFLECTION
TP051	215977		TRANSISTOR	P-S/DEFLECTION
TP080	259513		TRANSISTOR	P-S/DEFLECTION
TP081	198749		TRANSISTOR	P-S/DEFLECTION
TP150	215977		TRANSISTOR	P-S/DEFLECTION
TP160	259513		TRANSISTOR	P-S/DEFLECTION
TP161	259513		TRANSISTOR	P-S/DEFLECTION
TP170	219354		TRANSISTOR	P-S/DEFLECTION
TP179	198749		TRANSISTOR	P-S/DEFLECTION
TP180	198749		TRANSISTOR	P-S/DEFLECTION
TP197	259513		TRANSISTOR	P-S/DEFLECTION
TP20	256808		TRANSISTOR	CONVERGENCE PS / ADAPTE
TP21	259545		TRANSISTOR	CONVERGENCE PS / ADAPTE
TP210	198749		TRANSISTOR	P-S/DEFLECTION
TP221	259513		TRANSISTOR	P-S/DEFLECTION
TP24	198749		TRANSISTOR	CONVERGENCE PS / ADAPTE
TP27	256808		TRANSISTOR	CONVERGENCE PS / ADAPTE
TP28	256808		TRANSISTOR	CONVERGENCE PS / ADAPTE
TP30	259630		TRANSISTOR	CONVERGENCE PS / ADAPTE
TP320	244844		TRANSISTOR	SMPS - DVD
TP321	259991		THYRISTOR	SMPS - DVD
TP322	198743		TRANSISTOR	SMPS - DVD
TP323	257827		TRANSISTOR	SMPS - DVD
TP325	230764		TRANSISTOR	SMPS - DVD
TP33	219354		TRANSISTOR	CONVERGENCE PS / ADAPTE
TP350	230764		TRANSISTOR	SMPS - DVD
TP45	198749		TRANSISTOR	CONVERGENCE PS / ADAPTE
TP520	259732		TRANSISTOR	SMALL SIGNAL BOARD
TP523	259650		TRANSISTOR, NPN DUAL	SMALL SIGNAL BOARD
TP605	198749		TRANSISTOR	MAINS INPUT DOUBLER
TP606	259513		TRANSISTOR	MAINS INPUT DOUBLER
TP610	259513		TRANSISTOR	MAINS INPUT DOUBLER
TP611	259513		TRANSISTOR	MAINS INPUT DOUBLER
TP90	259545		TRANSISTOR	CONVERGENCE PS / ADAPTE
TP91	259545		TRANSISTOR	CONVERGENCE PS / ADAPTE
TR015	256808		TRANSISTOR	SMALL SIGNAL BOARD
TR060	259547		TRANSISTOR	SMALL SIGNAL BOARD
TR061	256808		TRANSISTOR	SMALL SIGNAL BOARD
TR062	259545		TRANSISTOR	SMALL SIGNAL BOARD
TR140	256808		TRANSISTOR	SMALL SIGNAL BOARD
TR141	259545		TRANSISTOR	SMALL SIGNAL BOARD
TR144	256808		TRANSISTOR	SMALL SIGNAL BOARD
TR145	259545		TRANSISTOR	SMALL SIGNAL BOARD
TR146	256808		TRANSISTOR	SMALL SIGNAL BOARD
TR147	259545		TRANSISTOR	SMALL SIGNAL BOARD
TR148	256808		TRANSISTOR	SMALL SIGNAL BOARD
TR149	259545		TRANSISTOR	SMALL SIGNAL BOARD
TR198	259545		TRANSISTOR	SMALL SIGNAL BOARD
TRAY	259509		TRAY, CHASSIS SUPPORT	CHASSIS ASSEMBLY
TS36	248805		TRANSISTOR	CONVERGENCE SIGNAL BOAR
TS39	248805		TRANSISTOR	CONVERGENCE SIGNAL BOAR
TS41	248805		TRANSISTOR	CONVERGENCE SIGNAL BOAR
TS48	258661		TRANSISTOR	CONVERGENCE SIGNAL BOAR
TS50	248805		TRANSISTOR	CONVERGENCE SIGNAL BOAR
TT231	256808		TRANSISTOR	DIGITAL READY INTERFACE
TT251	256808		TRANSISTOR	DIGITAL READY INTERFACE
TT252	259545		TRANSISTOR	DIGITAL READY INTERFACE
TT253	259545		TRANSISTOR	DIGITAL READY INTERFACE
TT256	259545		TRANSISTOR	DIGITAL READY INTERFACE

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
TT257	259545		TRANSISTOR	DIGITAL READY INTERFACE
TT261	259545		TRANSISTOR	DIGITAL READY INTERFACE
TT303	256808		TRANSISTOR	DIGITAL READY INTERFACE
TT313	256808		TRANSISTOR	DIGITAL READY INTERFACE
TT323	256808		TRANSISTOR	DIGITAL READY INTERFACE
TT331	256808		TRANSISTOR	DIGITAL READY INTERFACE
TT332	259545		TRANSISTOR	DIGITAL READY INTERFACE
TT333	259545		TRANSISTOR	DIGITAL READY INTERFACE
TT351	259545		TRANSISTOR	DIGITAL READY INTERFACE
TT352	259545		TRANSISTOR	DIGITAL READY INTERFACE
TT353	256808		TRANSISTOR	DIGITAL READY INTERFACE
TT354	259545		TRANSISTOR	DIGITAL READY INTERFACE
TT355	259545		TRANSISTOR	DIGITAL READY INTERFACE
TT371	259545		TRANSISTOR	DIGITAL READY INTERFACE
TT372	259545		TRANSISTOR	DIGITAL READY INTERFACE
TT373	256808		TRANSISTOR	DIGITAL READY INTERFACE
TT374	259545		TRANSISTOR	DIGITAL READY INTERFACE
TT375	259545		TRANSISTOR	DIGITAL READY INTERFACE
TT401	259545		TRANSISTOR	DIGITAL READY INTERFACE
TT501	259545		TRANSISTOR	DIGITAL READY INTERFACE
TT502	259545		TRANSISTOR	DIGITAL READY INTERFACE
TT503	256808		TRANSISTOR	DIGITAL READY INTERFACE
TT511	256808		TRANSISTOR	DIGITAL READY INTERFACE
TT512	259545		TRANSISTOR	DIGITAL READY INTERFACE
TT513	256808		TRANSISTOR	DIGITAL READY INTERFACE
TT514	259545		TRANSISTOR	DIGITAL READY INTERFACE
TT531	256808		TRANSISTOR	DIGITAL READY INTERFACE
TT532	259545		TRANSISTOR	DIGITAL READY INTERFACE
TT533	256808		TRANSISTOR	DIGITAL READY INTERFACE
TT541	256808		TRANSISTOR	DIGITAL READY INTERFACE
TT542	259545		TRANSISTOR	DIGITAL READY INTERFACE
TT543	256808		TRANSISTOR	DIGITAL READY INTERFACE
TT561	259545		TRANSISTOR	DIGITAL READY INTERFACE
TT601	243577		TRANSISTOR	DIGITAL READY INTERFACE
TT602	243577		TRANSISTOR	DIGITAL READY INTERFACE
TT631	259545		TRANSISTOR	DIGITAL READY INTERFACE
TT632	256808		TRANSISTOR	DIGITAL READY INTERFACE
TU001	259544		TRANSISTOR	SMALL SIGNAL BOARD
TU004	258660		TRANSISTOR	SMALL SIGNAL BOARD
TU060	256808		TRANSISTOR	SMALL SIGNAL BOARD
TV006	256808		TRANSISTOR	SMALL SIGNAL BOARD
TV008	259545		TRANSISTOR	SMALL SIGNAL BOARD
TV01	259542		TRANSISTOR	CONVERGENCE PS / ADAPTE
TV012	259545		TRANSISTOR	SMALL SIGNAL BOARD
TV015	256808		TRANSISTOR	SMALL SIGNAL BOARD
TV02	256808		TRANSISTOR	CONVERGENCE PS / ADAPTE
TV023	256808		TRANSISTOR	SMALL SIGNAL BOARD
TV025	259545		TRANSISTOR	SMALL SIGNAL BOARD
TV028	256808		TRANSISTOR	SMALL SIGNAL BOARD
TV03	256808		TRANSISTOR	CONVERGENCE PS / ADAPTE
TV04	259545		TRANSISTOR	CONVERGENCE PS / ADAPTE
TV043	256808		TRANSISTOR	SMALL SIGNAL BOARD
TV045	259545		TRANSISTOR	SMALL SIGNAL BOARD
TV048	256808		TRANSISTOR	SMALL SIGNAL BOARD
TV20	256808		TRANSISTOR	CONVERGENCE PS / ADAPTE
TV21	259545		TRANSISTOR	CONVERGENCE PS / ADAPTE
TV22	259545		TRANSISTOR	CONVERGENCE PS / ADAPTE
TV277	215977		TRANSISTOR	SMALL SIGNAL BOARD
TV30	256808		TRANSISTOR	CONVERGENCE PS / ADAPTE
TV300	256808		TRANSISTOR	SMALL SIGNAL BOARD
TV31	259545		TRANSISTOR	CONVERGENCE PS / ADAPTE
TV310	256808		TRANSISTOR	SMALL SIGNAL BOARD
TV32	256808		TRANSISTOR	CONVERGENCE PS / ADAPTE
TV320	256808		TRANSISTOR	SMALL SIGNAL BOARD
TV33	259545		TRANSISTOR	CONVERGENCE PS / ADAPTE
TV34	259545		TRANSISTOR	CONVERGENCE PS / ADAPTE

<u>Symbol</u>	<u>Stock</u>	<u>Drawing</u>	<u>Description</u>	<u>Circuit</u>
TV35	256808		TRANSISTOR	CONVERGENCE PS / ADAPTE
TV40	259545		TRANSISTOR	CONVERGENCE PS / ADAPTE
TV50	259545		TRANSISTOR	CONVERGENCE PS / ADAPTE
TV51	259545		TRANSISTOR	CONVERGENCE PS / ADAPTE
TV513	259513		TRANSISTOR	SMALL SIGNAL BOARD
TV52	259545		TRANSISTOR	CONVERGENCE PS / ADAPTE
TV522	259249		TRANSISTOR	SMALL SIGNAL BOARD
TV523	259548		TRANSISTOR	SMALL SIGNAL BOARD
TV524	259547		TRANSISTOR	SMALL SIGNAL BOARD
TV53	259545		TRANSISTOR	CONVERGENCE PS / ADAPTE
TV80	259543		TRANSISTOR	CONVERGENCE PS / ADAPTE
TV90	259545		TRANSISTOR	CONVERGENCE PS / ADAPTE
TV91	259545		TRANSISTOR	CONVERGENCE PS / ADAPTE
TV92	259630		TRANSISTOR	CONVERGENCE PS / ADAPTE
TTW01	248805		TRANSISTOR	CONVERGENCE AMP BOARD
TTW02	248805		TRANSISTOR	CONVERGENCE AMP BOARD
TTW10	258661		TRANSISTOR	CONVERGENCE AMP BOARD
TTW13	248805		TRANSISTOR	CONVERGENCE AMP BOARD
TTW14	248805		TRANSISTOR	CONVERGENCE AMP BOARD
TTW19	258661		TRANSISTOR	CONVERGENCE AMP BOARD
TTX131	256808		TRANSISTOR	SMALL SIGNAL BOARD
TTX500	259545		TRANSISTOR	SMALL SIGNAL BOARD
TTX515	259545		TRANSISTOR	SMALL SIGNAL BOARD
TTX520	259545		TRANSISTOR	SMALL SIGNAL BOARD
TTX530	256808		TRANSISTOR	SMALL SIGNAL BOARD
TTX540	256808		TRANSISTOR	SMALL SIGNAL BOARD
TTX565	259545		TRANSISTOR	SMALL SIGNAL BOARD
TTX572	259545		TRANSISTOR	SMALL SIGNAL BOARD
TTX650	256808		TRANSISTOR	SMALL SIGNAL BOARD
TTX655	259545		TRANSISTOR	SMALL SIGNAL BOARD
TTX670	256808		TRANSISTOR	SMALL SIGNAL BOARD
TTX675	259545		TRANSISTOR	SMALL SIGNAL BOARD
TTX700	259545		TRANSISTOR	SMALL SIGNAL BOARD
TTX710	259545		TRANSISTOR	SMALL SIGNAL BOARD
TTX720	259545		TRANSISTOR	SMALL SIGNAL BOARD
TTX730	256808		TRANSISTOR	SMALL SIGNAL BOARD
TTX740	256808		TRANSISTOR	SMALL SIGNAL BOARD
TTX765	259545		TRANSISTOR	SMALL SIGNAL BOARD
TTX772	259545		TRANSISTOR	SMALL SIGNAL BOARD
UA505	260026		IC, INVERTER	MPEG CBA
UD910	242856		DIODE, LIGHT EMITTING	SPDIF OUTPUT
WIRE TIE	244011		WIRE TIE, 5.3 LG	INSTRUMENT ASSEMBLY
WIRE TIE	139301		WIRE TIE, BEAD CHAIN	INSTRUMENT ASSEMBLY
WIRE TIE	154385		WIRE TIE, TWIST END	INSTRUMENT ASSEMBLY
WIRE TIE	139301		WIRE TIE, BEAD CHAIN	CHASSIS ASSEMBLY
WIRE TIE	154385		WIRE TIE, TWIST END	CHASSIS ASSEMBLY
YE216	262430		CRYSTAL, 27MHZ	MPEG CBA
YOKE	258490		YOKE, DEFLECTION	OPTICS ASSEMBLY