

VR352

VOLTAGE CHARTS

POWER SUPPLY

MODE							
PIN No.	STOP	REC	PLAY	REW/ F.FWD	REV/FWD SEARCH	REC PAUSE	PLAY PAUSE
Q801							
E	0	0	0	0	0	0	0
C	144	144	144	144	144	144	144
B	0	-0.2	-0.2	-0.2	-0.2	-0.2	-0.2
Q802							
E	0	0	0	0	0	0	0
C	0	-0.2	-0.2	-0.2	-0.2	-0.2	-0.2
B	0.2	0	0	0	0	0	0
Q803							
E	5.2	5.2	5.2	5.2	5.2	5.2	5.2
C	5.9	5.9	5.9	5.9	5.9	5.9	5.9
B	5.9	5.9	5.9	5.9	5.9	5.9	5.9
Q804							
E	9.1	9.1	9.1	9.1	9.1	9.1	9.1
C	12.6	12.2	12.1	12.1	12.4	12.4	12.4
B	9.8	9.9	9.9	9.9	9.8	9.8	9.8
Q805							
E	12.6	12.3	12.2	12.2	12.4	12.4	12.4
C	12.6	12.2	12.1	12.2	12.4	12.4	12.4
B	11.8	11.5	11.4	11.5	11.6	11.6	11.6

MODE							
PIN No.	STOP	REC	PLAY	REW/ F.FWD	REV/FWD SEARCH	REC PAUSE	PLAY PAUSE
Q806							
E	5.2	5.2	5.2	5.2	5.2	5.2	5.2
C	5.9	5.9	5.9	5.9	5.9	5.9	5.9
B	5.9	5.9	5.9	5.9	5.9	5.9	5.9
Q807							
E	0	0	0	0	0	0	0
C	0	0	0	0	0	0	0
B	5	4.9	5	5	5	5	5
Q808							
E	0	0	0	0	0	0	0
C	5	4.9	5	5	5	5	5
B	0.1	0.1	0.1	0.1	0.1	0.1	0.1
Q809							
E	0	0	0	0	0	0	0
C	9.8	9.9	9.9	9.9	9.8	9.8	9.8
B	0.1	0.1	0.1	0.1	0.1	0.1	0.1

MODE	IC PHOTO COUPLER (IC801)						
PIN No.	STOP	REC	PLAY	REW/ F.FWD	REV/FWD SEARCH	REC PAUSE	PLAY PAUSE
1	5.8	5.8	5.8	5.8	5.8	5.8	5.8
2	4.7	4.7	4.7	4.7	4.7	4.7	4.7
3	0.2	0.2	0.2	0.2	0.2	0.2	0.2
4	2	2	2	2	2	2	2

MODE	IC REGULATOR (IC802)						
PIN No.	STOP	REC	PLAY	REW/ F.FWD	REV/FWD SEARCH	REC PAUSE	PLAY PAUSE
1	2.4	2.4	2.4	2.4	2.4	2.4	2.4
2	0	0	0	0	0	0	0
3	4.7	4.7	4.7	4.7	4.7	4.7	4.7